

POPULAR MECHANICS MAGAZINE

WRITTEN SO YOU CAN UNDERSTAND IT

REG'D. TRADE MARK, GREAT BRITAIN No. 410423

REG'D. U.S. PAT. OFF.



SEE PAGE 896

LUND/ACH

ATKINS

SILVER STEEL

SAWS

*To cut Wood
or Metal*

ATKINS SILVER
STEEL
MADE IN U.S.A.



Mr. Happy-Man Says—

“These Saws Save You Time, Labor and Money”

“SILVER STEEL”—backed by ATKINS exacting laboratory tests—tempered and proved to make every saw cut faster and longer—makes these ATKINS Mill Saws and Hack Saws save time, work and money for every user. It will pay you to learn why the ATKINS name on a saw means greater service and saving.



No matter what you saw—wood, metal, bone, stone or any material—you'll find a better saw with the ATKINS name as insurance of quality and value. Ask your Hardware Dealer or Mill Supply House, or send for folders on ATKINS SAWS for any use.

E. C. ATKINS & CO. Est. 1857 426 S. Ills. St., Indianapolis, Ind.

Leading Manufacturers of Highest Grade Saws for Every Use; Saw Tools, Saw Specialties, Plastering Trowels, Machine Knives, Grinding Wheels and Files

Organize a Band

Conn Makes it Easy



Dodge Brothers, Inc., Concert Band of Detroit, Mich., Eugene LaBarre, conductor. This is one of the famous industrial bands completely equipped with CONN instruments.

ONE interested person can start a band, and with Conn's help, carry it through to success. Our Band Service Department will help you organize a band or orchestra now, among your associates.

In industries, schools, scout troops, legion posts, lodges, communities, wherever there is a group of fellows, there is an opportunity for a band. Our easy payment plan provides complete equipment of instruments at a small outlay per month.

Summer time is band time. Get started now by writing the Conn Band Service Department for complete details—no obligation.

Exclusive Conn Features

The world's largest plant devoted to band instruments, with exclusive machinery and processes, enables Conn to produce the world's finest instruments; easiest to play, beautiful in tone, perfect in mechanism.

One Conn process, the famous hydraulic expansion of tapering tubes, called for an investment of a half million dollars. Unlimited resources in capital, machinery and expert skill are at the base of Conn quality.

FREE TRIAL, Easy Payments.

Send coupon now for free literature and details of trial offer on cornet, trumpet, trombone, saxophone, clarinet, flute, drums—any instrument for band or orchestra. No obligation, send TODAY.

CONN

BAND INSTRUMENTS
WORLD'S LARGEST MANUFACTURERS

Mail This

C. G. CONN, *Qtd.*
631 Conn Bldg., Elkhart, Ind.
Gentlemen: Please send literature and details of trial offer on the instrument I have indicated.

I am interested in organizing a ☐ band, or ☐ orchestra. Please have your Band Service Department advise me.

(Instrument) _____
Name _____
St. or R. F. D. _____
City, State _____
County _____



1091-044-WE1 P



You may "kid" the "cold-bath liar" *but you envy him one thing*

YOU know him—the "cold-bath liar." He brags, offensively, about bracing, stimulating, zestful feeling when he tumbles out of a nice warm bed and jumps under the icy shower. He gets by with a reputation for being sceptically clean.

How about you? Have you recently shoved your own familiar face up close to a truthful mirror for a good honest look? Try it. You are due for a surprise and a couple of shocks. You are going to discover that your face is really not quite clean.

That off-color, almost-but-not-quite-clean look about your skin is caused by ordinary, unpleasant dirt. It comes from the air. The

U. S. Weather Bureau estimates that there are 115,000 swirling bits of dust and grime in one cubic inch of city air. These invisible bits of smoky grime collect upon your face, in tiny wrinkles and open pores. Once there, they resist every effort of soap and water to get them out.

You can get clean—and stay clean. A Pompeian massage in your own home takes only seventy seconds—no more time than a hot towel and rinse. Use this invigorating massage cream after shaving, for that stimulating, zestful "feel." Use it to get clean, stay clean; then absorb some of the glory that gravitates to the cold-bath enthusiast.

Above all, use it for the grand and glorious feeling that, by gosh! you really are clean!

MAKE THIS CONVINCING TEST!

Wash your hands thoroughly. Rub a little Massage Cream into the back of your hand. Keep rubbing. The cream goes in pink and comes out black! The black is dirt you couldn't remove by washing. Make this simple but convincing test today. Get a jar of Massage Cream in any drug store—60c. Mail the coupon below for sample.



FREE—TO MEN ONLY

The Pompeian Company, Dept. 47A, Cleveland, Ohio. Please send me free, the sample tube of Massage Cream, with enough cream to make the hand test, and to give me several massages.

POMPEIAN MASSAGE CREAM

Increases Your Face Value

Name _____

Street _____

City _____ State _____

Popular Mechanics Magazine

200 E. Ontario Street, Chicago, U. S. A.

H. H. WINDSOR, Founder

H. H. WINDSOR, Jr., Editor and Publisher

London: Hachette & Cie.,
16-17 King William Street, Charing Cross, W. C. 2

Paris: Hachette & Cie.,
111 Rue Reaumur

Melbourne: Gordon & Goch
509-513 Little Collins St.

ISSUED MONTHLY

SUBSCRIPTION:

SINGLE COPY, 25 CENTS

In United States and its possessions, also Canada, Cuba, and Mexico, per year, postpaid - \$2.50

To all other countries in the Postal Union - 3.00

All subscriptions are discontinued at expiration. Please examine the date printed on your wrapper.

Entered as Second Class Matter Sept. 16, 1903, at the Post Office at Chicago, Illinois, under Act of March 3rd, 1879.

Entered as Second Class Matter at the Post Office Department, Canada.

Published monthly by POPULAR MECHANICS CO.

Copyright, 1927, by Popular Mechanics Co.

Copyright in Australia. Copyright in France

Vol. 47

Contents for June, 1927

No. 6

Acoustics—walls padded with paper disks to stop echoes	973
Advertising—imitation tree stump as real-estate sign	946
Airplanes	
from raw material to planes	903
rum chasing have machine guns	930
Airship	
dirigible combined with plane	914
flying Uncle Sam's gas bags	908
for trips across continent	929
Alarm Clock—memo pad for	893
Animals—sail lizard discovered	897
Army U. S.—soldier and his weapons	912
Astronomy—heaviest star "27" weighed at observatory	977
Automobiles	
electric eye to count	943
guard dropped over wheels protects pedestrian	967
tiny electric roadster	887
Automobiles—Driving—cause of auto mishaps is "human element"	984
Automobiles—Equipment and Supplies	
match and ash holder	915
seat for infant	924
Automobiles—Racing—flirting with death on garage ramp	888
Automobiles—Tires—branding torch marks	945
Automobiles—Windshields	
kept clear with chemical wiper	929
two blade wiper	943
Aviation—ground wire leads planes to safety in fog	1000
Bank—women in trained to shoot	914
Batteries—doll's head that lights up novelty	959
Beaver—wild life refuge in Alaska to protect	957
Boats and Boating—fishes' secret sought to add speed	900
Boys—taller today than fifty years ago	974
Bridge—sand boxes lift Carquinez in place	986
Building	
home built with wrench	904
home of concrete and glass	969
house on wedge-shaped lot	994
office of cement pipe	962
seventy-story labor temple proposed	985
Butter—treating cream with lime to improve	937
Cactus—Giant—home for screech owls	924
Cats—patrol capitol	959
Cement Gun—aids in building semicircular roof	959
Chalk Line—with plumb bob	989
Chalk Talk—invisible patterns make easy	996
China—spirit of ancient clings to soldiers with umbrella	898
Clarinet—metal will not crack	825
Clock—radio world time	1004
Concrete Bandstand—ice used to lower floor	931
Concrete	
lock strip in floor	942
mine hoist house	939
Cork—puller removes caps	940
Cowboy—roping gear	902
Dam—giant net protects penstocks	884
Deaf—sound amplifier for	936
Earth—task of weighing	904
Education	
electric questionnaire speeds study	931
pupils make own globe as geography aid	967
Electric Wiring—locator for	961
Elevator—up Mont Blanc	924
Fire—forest extinguisher worn like knapsack	977
Fire Towers—lofty guard Canada's forests	993

Fish	
ornamental raised at unique college	886
rescue work saves	975
Flashlight—electric in cane	999
Fog—lights carried by traffic police	908
Furnace—portable test set	939
Garbage—chimney fed incinerator	976
Gate—opened by auto bumper	968
Ghosts—the truth about	938
Glass—age of may follow steel	973
Gold—old days to return	881
Golf	
game played on table	916
hand strap holds club	957
where millions of balls go	970
Hair—structure of human clue to identity	951
Hair Cutting—ear guard while having hair bobbed	960
Hammer—drift takes its own power from gasoline	993
Heater—electric put on wall	923
Horticulture—gardens under glass bells	943
House Plan	105
Household Devices	814
Hydroelectric—Shannon river power plant	989
Idol—South sea mystery solved by finding lost	956
Illumination	
lights on theater tower rival those of streets	944
street lamps tested	901
Iron—making in African wilds	961
Kites—solve problem of tree seeds' flight	955
Knives—cutlery from old wire rope	923
Lamp Shade—ostrich feather	928
Life—value of human	972
Life Insurance—more risk in play than in work	952
Lighthouse—church spire as	913
Lions—the men-eaters	917
Log—fifty thousand year old found	924
Magnet—giant raises seventy-five tons	977
Medicine Man—of North Siberia wears odd garb	992
Metals—iridium hardest, thallium softest	946
Mint Growing—bringing a Japanese industry to U. S.	941
Mirror—for bus conductors	940
Models—castle of live trees for garden	995
Money—paper to be smaller	928
Motor Bus—like street car has two engines	913
Motor Truck	
serves as train	944
service recorder for	959
tank for trout	937
Motorboat—sets new record	958
Motorcycles—tilting bucket in race	952
Moving Pictures—films enlarged without cutting reel	985
Navy U. S.—underground storage for explosives	930
Nettles—fibers used for cloth in China	928
Occupations—more musicians in U. S. than lawyers	915
Omnibus—steam burns oil	927
Painting (Art)—rare found hidden on brick wall	896
Paints and Painting—weather wheel tests	961
Park—benches built for two	913
Pencil—adding is accurate	974
Phonograph—changes disks and plays for an hour	938
Plumbing and Steamfitting—truck carries supplies	945
Police—motor cops of the sea	947
Postage Stamps—printed by the mile	901
Pump	
electric drive for	696
for bottles simplifies oiling and spraying	992
run by Flettner rotor	937

[Continued on Page 4]

Barges, Mississippi
913

Brickly Bear

944

colored ink thing number 918

Radio Aerials	
directional effects from outdoor	1011
fishing poles as masts	1010
homemade decorative loop	1003
keep away from power lines	1009
simple lead-in arrangement	1011
Radio Apparatus—adjustable gridleak without pressure contacts	1004
Radio Application	
code for medical aid at sea	985
detects automobile noises	1014
"magic" locates buried riches	989
replaces St. Bernards in Alps	915
reproducing phonograph records through receiver	1014
Radio Batteries	
booster charger has high and low rate	1013
power unit eliminates all	1005
simplifies connections	1010
Radio Broadcasting—Japan's largest station	1012
Radio Coils	
convenient form for	1013
homemade low loss	1009
homemade R. F. choke	1010
new wire provides air spaced winding	1003
Radio Construction	
dull finish for panels	1013
improved method of shielding receiver	1004
mounting panel on baseboard	1004
shock absorbing tube mounting	1009
Radio Loud Speaker—repairing diaphragm	1009
Radio Receiver	
for blind	887
resembles cash register	1011
Radio Reception—weather in relation to DX	1001
Radio Repairing—binding frayed insulation	1004
Radio Tubes	
automatic tester	913
how to check r. f.	1012
new high MU increases volume	1010
use old for testing	1003
Railroad—to Lichtenstein castle	957
Rays—things made invisible by colored	968
Razor—sharp hints used for in New Zealand	974
Rifle Practice—shooting at moving pictures	958
Rivets—electric heater	995
Roads—truck for center-lining	1000
Rubber	
Edison joins hunt for rubber that can be raised here	916
lumber for aircraft	938
molded into dolls	901
Safety Devices and Measures	
steel cable in windy canyon protects pedestrians	951
train lights crossing sign	999
Saws—portable electric link	946
Sculpture—artist turns wood blocks into masterpieces	894
Seashells	
flowers and faces of	905
portrait carving on	951
Shaving Brush—removable bristle, easily dried	884
Ships—caring for the liner	902
Smoke—density of tested with chart	953
Smokers' Accessories	
cigar lighter quick action	945
trapdoor ash tray	931
Smokestacks—old ships' protect railroad roadbed	995
Sprinkler—spray watering outfit	960
Steeple—old without church Swedish landmark	973
Stool—adjustable locks with steel balls	1000
Street Car—window heater for	945
Street Cleaning—streets of old Rome swept with modern sweepers	953
Surfboard—air chamber in makes it unsinkable	969
Table—extension drafting	928
Tractor—runs sorghum mill unattended	972
Traffic—electric eye to count autos	943
Trees—saving uprooted shade	930
Tunnel	
Moffat completed	925
smoke bombs in test ventilation	897
Typewriter Supplies—carbon paper in cushion back	959
Umbrella—vanishing strap, easy to carry	885
Vacuum Cleaner—airing bag attached to	962
Ventilator—proof against draft and dust	988
Walnuts—cracker for black	972
War—secrets revealed	978
Waterways—Inland—how father of waters is coming back	963
Well—forecasts storms	923
Wine Cask—ancient German holds 50,000 gallons	988
Yoke—cut by Lincoln prized relic	895
Zoological Garden—"jungle" for zoo animals planned	956

AMATEUR MECHANICS

Automobile—converted into office	1028
Automobiles—Driving—adjusting carburetor for altitude	1035
Automobiles—Equipment and Supplies	
improving tonneau seat	1018
lock for Ford coupe	1017
Automobiles—Fuel—filling tank	1033
Automobiles—Tires—changing balloon	1036
Bathing—trolley for	1019
Battery—preserving carriers	1036
Boats and Boating—how to calk small boat	1018
Camping—how to make a baker for	1015
Canoe—how to pick your	1023
Children—concrete sand box for	1020
Chopper—food, grinding juicy substances	1033
Cleaning—removing scorch mark from linen	1021
Coaster—four wheel brake on	1017
Drain Pipe—simple repair for	1019
Fishing—digging worms with electricity	1016
Fuse Plug—homemade renewable	1036
Garage	
radiators automatically blanketed	1021
summer	1030
Gardening—novel method of growing strawberries	1033
Gasoline—saving tank gasket	1029
Gate—fastener for wire	1034
Lamp—combined with picture frame	1016
Lawn Sprayer—simple	1018
Manuscript—holder for speakers	1035
Paintbrushes—softener for	1036
Pantry—making more room in	1034
Phonograph—cleaning turntables	1036
Poultry—nests of concrete	1027
Putty—preventing marks on ground glass	1035
Quilts—locating knots on	1017
Ship Models	
making deadeyes for	1021
square-rigger for the boy	1031
Tent—heating a	1029
Washtub—ejector for emptying	1020
Window—wire rack holds open	1035
SHOP NOTES	
Air Compressor—portable made from junk pile parts	1052
Automobile	
sidetracking engine gases	1055
uses for old auto plate	1054
Automobiles—Engines—compression loss detected by air test	1043
Automobiles—Ignition	
overhead bracket for wiring	1054
placing brush over bands	1041
Automobiles—Radiators—air pressure test on	1051
Automobiles—Repairing	
creeper with adjustable headrest	1039
sill as guide for door	1052
Batteries—keeping cable in place	1053
Blowpipe—hot flame for the shop	1037
Decoration—Interior—easy ways to beautify home	1044
Draftsmen's Kinks	
holding ink bottle on drawing board	1051
substitute for quill	1052
Fence—convenient opening in farm	1040
Fire—automatic extinguisher	1040
Fishing—cane tube for fly rod tips	1055
Garage—gasoline pump extension	1053
Gate—removable protector for farm	1041
Glass—substitute for frosted	1039
Lawn Mower—repairing	1041
Loading and Unloading—conveyor loads lumber on flat cars	1039
Milk Can—release for cover	1053
Paints and Painting	
machine for painting siding	1042
painting over Keene's cement	1050
Photography—bellows substitute for focusing cloth	1038
Plaster—to prevent from cracking	1054
Plastering—stipple trowel for rough surfacing walls	1050
Sawmill—rails as guide for endless chain	1055
Shop Equipment—trash box under bench	1055
Signs—wheel for delivery trucks	1050
Stacker—for coins and washers	1049
Tapes—effect of temperature on steel	1050
Tools—flexible shaft for driving small	1040
Trees—protecting from mice and rabbits	1042
Trucks—brakes make hand truck safe	1049
Valves—repair for stripped valve stem thread	1051
Woodworking—how to turn small plugs	1053
Wrench—for bending small pipe	1043

marb. L Cote 1098


How Easy Way to Beautify 1044

DRAKE'S PRACTICAL MECHANICAL BOOKS

THEY WILL RAISE YOUR PAY—

ORDER ON 5-DAY TRIAL

The books listed below will perfect you in your chosen trade—pave the way to the big positions. Written in non-technical language—easy to read and understand. Every book covers its subject completely. An entire course of instruction condensed into one volume. Your choice sent postpaid—you benefit 5 days—money refunded in full if not entirely satisfactory. Order direct from this page.



Automobile Books

- Automobile Starting, Lighting and Ignition, by Manly... 700 pp. \$3.00
Brookes' Automobile Handbook... \$2.00
Ford Motor Car, Truck and Tractor, by Manly... Cloth \$1.50
Automobile Battery, Care and Repair, by Manly... Leatherette \$2.00
Motorcycle Handbook, by Manly... \$1.50



Shop Practice Books

- Practical Heating Systems, Trouble Jobs and Ventilation... \$4.00
Sheet Metal Workers' Manual... \$2.00
Oxy-Acetylene Welding and Cutting... Cloth \$1.25
Slide Rule and Logarithmic Tables... \$2.00
Handbook for Millwrights... Cloth \$2.00
Machine Shop Practice... Cloth \$2.00
Mechanical Drawing and Machine Design... Cloth \$2.00

ORDER DIRECT FROM THIS PAGE—ON OUR MONEY-BACK PLAN

The books listed above are only a few of the many in our catalogue, which you will receive promptly after filling out and mailing us the attached coupon. For quick action order direct from this page—cross name of each book wanted and send in with price quoted. We prepay postage and send the books on our money-back plan.


FREDERICK J. DRAKE & CO.

Publishers

1008 Michigan Ave.

CHICAGO


Drake Books Are For Sale at All Book Stores



Carpentry Books

Cloth Binding

- Modern Carpentry, 2 vols... \$3.00
The Steel Square, 2 vols... \$3.00
Modern Estimator... \$1.50
Timber Framing... \$2.00
Builders' Architectural Drawing... \$2.00
Concretes... \$1.50
Practical Bungalows... \$1.00
Roof Framing, by Van Gansbeek... \$1.50



Electrical Books

- Telephony, Including Automatic Switching, by Smith, 450 pp. Leatherette \$2.50
Practical Applied Electricity... \$2.00
Wiring Diagrams and Descriptions... \$1.50
Armature and Magnet Winding... \$1.50
Electric Motors, D. & A... \$1.50



Painting and Decorating

- Ross Crane Book of Home Furnishing and Decoration... Cloth \$3.00
Furniture, Furniture Finishing, Decoration and Patching... \$5.00
House Painting Methods with the Brush and Spray Gun, by Vanderwalker... Cloth \$2.00
Interior Wall Decoration, by Vanderwalker... Leatherette \$4.00
The Mixing of Colors and Paints, by Vanderwalker... Cloth \$2.00
Studio Handbook—Letter and Design... \$3.00
A Show at Show Cards... Cloth \$4.00
Sign Painting, by Atkinson... Cloth \$4.00
Strong's Book of Designs, Leatherette \$4.00
Modern Painters' Cyclopaedia... Cloth \$2.00
Automobile Painting... Cloth \$1.50
New Hardwood Finishing... Cloth \$1.50
Wood Finishing, Plain and Decorative... Cloth \$2.00
Owen's Paint Guide... Cloth \$1.00

Steam Engineering

- Swingle's Handbook for Steam Engineers and Electricians... Leatherette \$4.00
Examination Questions and Answers for Marine and Stationary Engineers... Leatherette \$2.00
Steam Boilers... Leatherette \$2.00
Swingle's Catechism of Steam, Gas and Electrical Engineering... Leatherette \$1.50

Modern Languages

- By Prof. P. S. Allen, U. of Chicago
French without a Teacher... Cloth \$1.25
Spanish without a Teacher... Cloth \$1.25
German without a Teacher... Cloth \$1.25
Everyday French... \$1.25
Everyday Spanish... \$1.25

FREDERICK J. DRAKE & CO.
1008 Michigan Avenue
Chicago, Ill.

GENTLEMEN:—Please send me free, postage paid, your illustrated catalogue which lists and describes 200 Practical Mechanical Books for Home Study.

My name is

and my address

Mail Coupon For Free Catalogue
Your Guide to Home Study

I Was a Bookkeeper Now General Sales Manager —Would Not Take \$10,000 for My Training

"When I first enrolled for LaSalle training," writes R. B. Cook, a Chicago man, "I was a bookkeeper. Before I was half way thru my training I was promoted to Collection Manager, with an increase of 50 per cent in salary. Later I became Credit Manager of another concern. This move was a very decided promotion.

"My next advancement was to the position of Office Manager. In each of these positions I was successful, and this fact paved the way to my present position. Two years ago I was offered the post of Assistant Credit Manager with my present concern, which I accepted. Within two years I was made General Sales Manager, which position I now hold.

"This, Mr. Chapline, is my five-year record as a LaSalle member, and this was made possible thru your splendid training and the various services which I have used with much profit. Furthermore, it accounts for my enrollment in a second LaSalle course.

"Two years ago I wrote you that I would not part with the knowledge LaSalle training had brought me, for \$10,000. Today I can say that I would not part with it for several times that amount."

Nothing extraordinary about Cook's achievement. During only six months' time as many as 1,248 LaSalle members reported definite salary-increases totalling \$1,399,507, *an average increase per man of 89 per cent.*

The records of these men are all set forth, in brief,

in a book entitled "A Geography of Success." It's a book well worth having, and it's yours for the asking. The following experiences are typical:

"Half way thru course—have had 3 promotions."

"Income increased from \$1,500 to \$6,000 a year."

"Promoted—salary increased 233 per cent."

Send for Salary-Doubling Plan

What's to prevent your equalling such

records—setting new records of your own? The coupon just below this text will bring you full particulars of the LaSalle *salary-doubling plan*—without the slightest obligation. Whether you adopt the plan or not, the basic information it will place in your hands, without cost, is of very real and definite value.

If a successful career is worth a 2c stamp and two minutes of your time, check the field of advancement that appeals to you, fill in your name and address, and place the coupon in the mail TODAY.



LASALLE EXTENSION UNIVERSITY

The World's Largest Business Training Institution

CLIP AND MAIL

LASALLE EXTENSION UNIVERSITY

Dept. 664-R

CHICAGO

I shall be glad to have details of your *salary-doubling plan*, together with complete information regarding the opportunities in the business field checked below. Also a copy of "Ten Years' Promotion in One," all without obligation.

☐ **Business Management:** Training for Official, Managerial, Sales and Departmental Executive positions.

☐ **Modern Salesmanship:** Training for position as Sales Executive, Salesman, Sales Coach or Trainer, Sales Promotion Manager, Manufacturer's Agent, Solicitor, and all positions in retail, wholesale, or specialty selling.

☐ **Higher Accountancy:** Training for position as Auditor, Comptroller, Certified Public Accountant, Cost Accountant, etc.

☐ **Law:** Training for Bar; LL.B. degree.

☐ **Commercial Law:** Reading, Reference and Consultation Service for Business Men.

☐ **Traffic Management—Foreign and Domestic:** Training for position as Railroad or Industrial Traffic Manager, Rate Expert, Freight Solicitor, etc.

☐ **Railway Station Management:** Training for position of Station Accountant, Cashier and Agent, Division Agent, etc.

☐ **Banking and Finance:** Training for executive positions in Banks and Financial Institutions.

☐ **Industrial Management:** Training for positions in Works Management, Production Control, Industrial Engineering, etc.

☐ **Modern Foremanship and Production Methods:** Training for positions in Shop Management, such as that of Superintendent, General Foreman, Foreman, Sub-Foreman, etc.

☐ **Personnel and Employment Management:** Training in the position of Personnel Manager, Industrial Relations Manager, Employment Manager, and positions relating to Employee Service.

☐ **Modern Business Correspondence and Practice:**

Training for position as Sales or Collection Correspondent, Sales Promotion Manager, Mail Sales Manager, Secretary, etc.

☐ **Business English:** Training for Business Correspondents and Copy Writers.

☐ **Effective Speaking:** Training in the art of forceful, effective speech, for Ministers, Salesmen, Fraternal Leaders, Politicians, Clubmen, etc.

☐ **Commercial Spanish.**

☐ **Expert Bookkeeping:** Training for position as Head Bookkeeper.

☐ **C. P. A. Coaching for Advanced Accountants.**



Name..... Present Position.....

Address.....

BUILDERS

TRADE GUIDES



4 Vols. \$6

AUDELS CARPENTERS AND BUILDERS GUIDES—4 VOLS. \$6

\$1 PER MO. Inside Information for Carpenters, Builders, Joiners, Building Mechanics—all Woodworkers. **1600 pages; 3700 diagrams; flexible; pocket size.** Short-cut instructions, new methods, ideas, solutions, plans, systems—money saving suggestions. An easy progressive course for the apprentice. A practical daily helper and Quick Reference for the master worker. A Helping Hand to Easier and Better Work and Better Pay. To get this aid for yourself, simply fill in and mail the FREE COUPON below.


INSIDE TRADE INFORMATION ON:

How to use steel square; How to file and set saws; How to build furniture; How to use mitre box; How to use chalk line; How to use rules; How to make joints; Carpenters' arithmetic; Mensuration problems; Estimat-

ing strength of timbers; How to set girders and sills; How to frame houses and roofs; How to estimate costs; How to build houses, barns, garages, bungalows, etc.; How to read and draw plans; Drawing up specifications; How

to excavate; How to use settings 12, 13 and 17 on the steel square; How to build bolsters and scaffolds—skylights; How to build stairs; How to put on interior trim; How to hang doors; How to lay floors; How to paint.

"Audels Guides worth four times their price—handy too as I carry them in pocket for reference." **W. J. Bates, Knoxville, Pa.**



4 Vols. \$6

AUDELS PLUMBERS AND STEAMFITTERS GUIDES—4 VOLS. \$6

\$1 PER MO. A new set—just out! A practical, illustrated, Reference Library and Study-Course for Master Plumbers, Journeymen and Apprentice Steamfitters, Gas Fitters and Helpers, Sheet Metal Workers, Draftsmen, Master Builders, Engineers and all Building Trade Students. **1670 pages; 3642 diagrams; flexible; pocket size.** Guides explain all the principles, advances and short cuts of the Plumbing and Heating trade. Contains instructions on how to figure and estimate jobs. Use FREE COUPON below to examine, without obligation, this valuable work.

INSIDE TRADE INFORMATION ON:

Soldering, tinning, joint wiping, bending, beating, Pipe—iron—steel, threading, Mathematics, tables, physics. Materials—iron, steel, copper, brass, lead, tin, antimony. Sheet metal—galvanized—plate. Sanita-

tion, syphonage, tanks. Drainage, sewage, purification. Fixtures—bath—kitchen. Pipe fittings, soil pipe, tools. Laying out work. Roughing. Screwed fittings, flanges, joints. Pipe bending, examples. Elbows. Heating, ven-

tilation, refrigeration. Water supply, mains, wells, tanks. Gas-fittings. Underwriters. Sheet metal work, problems, methods, brazing, heating, lead burning. Welding, various welds, methods. Blacksmithing, forges, tools.

"Audels Guides are practical, easy to understand, reliable. Cover the field in plain language." **W. F. Arminger, Annapolis, Md.**



4 Vols. \$6

AUDELS MASONS AND BUILDERS GUIDES—4 VOLS. \$6

\$1 PER MO. A new, complete, illustrated trade reference library, for Bricklayers, Cement Workers, Plasterers, Tile Setters and Stone Masons, including a practical outline of Steel Construction. **1100 pages; 2067 diagrams; flexible; pocket size.** A practical Trade Assistant explaining modern methods of masonry construction. Easy to understand and apply. A reliable and authentic reference work and study-course for Master Journeyman and Young Mechanic. Use FREE COUPON below and find out for yourself, without obligation, whether this set will benefit you.

INSIDE TRADE INFORMATION ON:

Bricklaying, tools, materials; Brick designs, patterns, bonds; Setting frames and foundations; Mortars, scaffolds, estimating; Mortars and mortar mixing; Tile setting, mosaic, hollow tile; Straight edge test, trow-

eling; How to figure brick work; Safe loads, piers, chimneys; Boiler settings, anchors, fire stops; Labor tables; Concrete, forms; How to figure concrete work; Stucco—on old and new buildings; Plastering—wood lath—metal;

Plasterers agreement; Plastering on various surfaces; Stonemasonry; Cutting, finishing, estimating stone; Derricks, rigging; Steel construction; Fire proof; How to read blue prints.


"Audels Masons Guides are the best books on the subject. Have laid brick 12 years and am able to judge." **H. A. Senneker, Corliss, Pa.**



PRACTICAL ELECTRICITY — 1 VOL. \$4

\$1 PER MO. Audels Handy Book of Practical Electricity is a simplified Ready Reference and Study Course in one pocket size, leather bound volume—for Engineers, Professional Electricians and Students. **1040 pages; 2500 diagrams; flexible red leather bound.** A reliable authority and handy helper for every electrical worker. Contains important and valuable wiring diagrams, calculations, machine sketches, helps on maintenance and repair. Use this FREE COUPON today and find out, without obligation, how this handy book will help you in your daily work.

Complete in one handy, red leather bound volume



INSIDE TRADE INFORMATION ON:

Electro-Therapeutics, X-Rays, Shocks, Welding, Brazing, Radio Hook-ups, Motion Pictures, Telephone, Telegraph, Cranes, Bells, Elevators, Pumps, Tools, Ship Drive, Railways, Vehicles, Automobile Electric Systems, Ignition, Generation, Lighting, Plant Management, Power

Plans, Armature Winding, Repairing, A. C. Motors and Apparatus, D. C. Motors and Apparatus, Alternator Construction, Dynamos, Wiring Diagrams, Sign Flashers, Cable Splicing, Power Wiring, Outside Wiring, Switches, Lighting, Rectifiers, Converters, Transformers, Fuses, Circuit Breakers, Rheostats, Electro Plating, Electrolysis, Storage Batteries, Magnetism, Electrical Energy, Conductors, Insulators, Static, Dynamic, Radio Electricity, Applications, Ready Reference and Index Covering the entire field of Modern Electricity.

Learn More and You Will Earn More!

Know your job and you'll never be without one. The skilled man is always in demand. Knowledge is power. Learn your trade thoroughly by easy reading. This coupon is your opportunity for advancement and better pay. You risk nothing in sending for Audels Guides for free examination. Send it NOW!

FREE EXAMINATION COUPON

THEO. AUDEL & CO.,

65 W. 23 ST., NEW YORK CITY

Please mail me for free examination the books marked (x) below. If I find them satisfactory, I agree to mail \$1 in 7 days, on each set ordered, and to further mail \$1 monthly on each set until I have paid the purchase price.

☐ 4 CARPENTERS GUIDES \$6 ☐ 4 PLUMBERS GUIDES \$6


☐ 4 MASONS GUIDES \$6 ☐ 1 ELECTRICIANS HANDY BOOK \$4

NAME

ADDRESS

OCCUPATION

EMPLOYED BY..... 6T30



Clip
Coupon
for
Free Auto
Book

BE AN
**AUTO
EXPERT**

— Earn up to
\$10,000
a year —

Go to School
AT HOME
the Cooke
**"JOB-
WAY"**

FREE Auto Book

PROOF!
See What I
Can Do For
YOU!

Send coupon for this amazing **FREE BOOK** right now.

See what it has done for others. See what it can do for you! Just think of this!

— Walter Mayville, Harold Lester, M. J. Morrison, Herbert Trask, Allen Pomeroy and dozens of others without previous auto experience—**in only a few months** after enrolling—were in business for themselves, making **big money**. My Free Book tells you all about their wonderful, **QUICK** successes. Send for it.

**Start to
Make Money Quick!**

You don't have to wait to finish to make real money with Cooke "Job-Way" training. Many of my students make money right in the very first few weeks.

\$215 in a Single Week!

Only 15 weeks after enrolling, Ernest B. Tucker, Cotton, Miss., wrote me he was making as much as \$215 in a single week! That's the kind of **QUICK RESULTS** you want! Find out what you can do today!

**Raises His Salary Almost
300% in 7 Short Months**

Cooke "Job-Way" boosted the salary of Gust Ahrens, Box 172, Parkerton, Wyo., a foreman with little education, from \$18 a week to \$50 a week in only 7 months and he gives my training full credit.

GET THE FACTS!

Send for this remarkable **FREE Auto Book**. Get all the facts about this amazing "quick results" Training Method. See what others did. Find out what you can do.

ACT NOW!

MAIL "JOB-WAY" COUPON

B. W. COOKE, Directing Engineer
CHICAGO MOTOR TRAINING CORPORATION
1916 Sunnyside Avenue, Dept. A-16, CHICAGO, ILL.

Send me **FREE Auto Book** and proof that you will show me the **QUICK WAY** toward a **BIG JOB** and a **RAISE IN PAY**. Also send your 4 Outfits Offer. It is understood that this obligates me in no way.

Tools, Test Bench, All equipment included **Free** of Extra Cost. Also \$33 wiring diagram charts. Wonderful Offer Now. Act quick. Clip coupon for full details.

Name

Address

My training includes ALL Electrical work—Ignition, Starting, Lighting—All Mechanical and Welding, Brazing, Vulcanizing—also Business Course, Salesmanship, Advertising, Buying, How to Keep Simple Books—also Auto Magazine, also 4 Outfits. Nowhere else I know of, can get you ALL this training.

Common Schooling All You Need

Men between 15 and 60 and with little education quickly and easily finish my training. Many become Garage Owners, Managers, Superintendents, Foremen, Auto Experts, in the class with BIG PAY executives. I back you up with the entire resources of this great Institution. Employment service for your whole life. Also Lifetime Consultation service. Notice on this page what a few of my students have done—then send for my **Free Auto Book** right away! Address me personally.

**B. W. COOKE DIRECTING
ENGINEER**
CHICAGO MOTOR TRAINING CORPORATION
1916 Sunnyside Avenue Dept. A-16 CHICAGO

**The World's
Biggest Business
Needs You!**

If you're earning a cent less than \$50 a week, clip coupon now. Get my Free Book. Let me show you how Five Thousand Million Dollars are spent every year for Auto Upkeep alone. Let me show you how salaries are raised—doubled—tripled in such **quick time** it's **positively amazing!** Look at this—from \$33 a week to **\$225 IN A SINGLE WEEK** is what Cooke "Job-Way" did for Bernard Rumpel, 365 Edison Place, Glendale, N. Y., only 10 months after enrolling!

No other business offers you so many wonderful opportunities. Job way is the training that is bringing such marvelous quick results. Get all the facts. Send for my Free Book Today!

Earn Up to \$150 a Week!

Don't sell your time for low pay. Raise your Pay **QUICK**. Be a Big Pay man. My book will show you the way.

Learn Right at Home!

Keep your present job. Get started for Big Pay **QUICK** as an Auto Expert, through Cooke "Job-Way," quickly, easily, right in your own home. Send for my free book: it shows you how successful I've been and how successful I am. Being a practical Directing Engineer Owner and Head of this Institution, I know what practical money making training you need to become a **BIG PAY MAN** and to get **QUICK RESULTS** and that training I give you.

The Only "Job-Way" Training on Earth!

B. W. Cooke is in no way connected with any other person or training of similar name. Nowhere else can you get the original, genuine copyrighted Cooke "JOB-WAY" training. I train you with tools which I give you and illustrated **JOBS—not books**. Find out how "Job-Way" fits you for Big Pay. Learn what it has done for others, see what it can do for you. Mail coupon to me right now.

FORMER PLASTERER NOW MAKING \$12,000 A YEAR




Worked for Small Salary

Henry J. Bellman had little education and little opportunity to get ahead, but he refused to give up. Deep within him was the longing to make something of his life before it was too late—to build a building some day instead of tinkering around it as a plasterer or bricklayer.



Resolves to Earn More Money

"If spare time study can help other men to get out of the rut," he said, "it can help me. I'm going to take up a course with the International Correspondence Schools and study at home. It's the only way I can ever hope to put myself on a par with technically trained men."



Gets Offer from Contractor

Bellman's friends laughed at him and said he was wasting his time, but he kept right on studying, for he could see how the course was helping him in his work. Soon one of the leading contractors heard about "this bright young man" and made him superintendent at a fine increase in salary.



Secures Big Contract

Bellman went ahead so rapidly that he decided to start a business of his own. He met with unusual success from the very start and today his income is "more than \$12,000 a year." Recently he handled the contracting work of the new \$200,000 Chamber of Commerce building in Scranton.



Glad He Studied at Home

"I give the International Correspondence Schools full credit for my success," Mr. Bellman writes: "there is nothing better for the man who has been deprived of the advantages of a college education. Many of my friends also give the I. C. S. full credit for their ability to do their work efficiently and well."



The Secret of His Success

Henry J. Bellman is a successful man today because he had vision—ambition—and perseverance. He realized that he had to learn more before he could earn more. Instead of just drifting along, he picked a definite goal and then worked and strived until he made his dreams come true.

MAIL THIS COUPON FOR FREE BOOKLET

INTERNATIONAL CORRESPONDENCE SCHOOLS, Box 5651-E, Scranton, Penna.

Without cost or obligation, please send me one of your booklets and tell me how I can qualify for the position or in the subject before which I have marked an X:

BUSINESS TRAINING COURSES

- ☐ Business Management
- ☐ Industrial Management
- ☐ Personnel Organization
- ☐ Traffic Management
- ☐ Business Law
- ☐ Banking and Banking Law

- ☐ Accountancy (including C.P.A.)
- ☐ Nicholson Cost Accounting
- ☐ Bookkeeping
- ☐ Private Secretary
- ☐ Spanish
- ☐ French

- ☐ Salesmanship
- ☐ Advertising
- ☐ Business Correspondence
- ☐ Show Card Lettering
- ☐ Stenography and Typing
- ☐ Good English

- ☐ Civil Service
- ☐ Railway Mail Clerk
- ☐ Common School Subjects
- ☐ High School Subjects
- ☐ Illustrating
- ☐ Cartooning

TECHNICAL AND INDUSTRIAL COURSES

- ☐ Electrical Engineering
- ☐ Electric Lighting
- ☐ Mechanical Engineer
- ☐ Mechanical Draftsman
- ☐ Machine Shop Practice
- ☐ Railroad Positions

- ☐ Gas Engine Operating
- ☐ Civil Engineer
- ☐ Surveying and Mapping
- ☐ Metallurgy
- ☐ Steam Engineering
- ☐ Radio


- ☐ Architect
- ☐ Blueprint Reading
- ☐ Contractor and Builder
- ☐ Architectural Draftsman
- ☐ Concrete Builder
- ☐ Structural Engineer

- ☐ Chemistry
- ☐ Automobile Work
- ☐ Airplane Engines
- ☐ Navigation
- ☐ Agriculture and Poultry
- ☐ Mathematics
- ☐ Pharmacy

Name

Address

Canadian address—International Correspondence Schools Canadian, Limited, Montreal



Are You Hungry For... Adventure... Popularity. Big Pay?

THEN CHOOSE AVIATION!

Are you eager for a life of constant thrills, constant excitement and fascinating events? Do you crave adventure, popularity, admiration, and the applause of great crowds? Then why not get into the Aviation Industry—the greatest adventure since time began—the greatest thrill ever offered to man?

Think what Aviation offers you. Thrills such as you never had before! The praise and plaudits of the multitude. Ordinary salaries from \$75 to better than \$400 a week! And a chance to get in on the ground floor where rewards will be unlimited!

Aviation is growing so swiftly that one can hardly keep track of all the astonishing new developments. Air-mail routes have just been extended to form a vast aerial network over the entire U. S. Airlines and airplane factories are springing up all over the country. Men like Henry Ford are investing millions in the future of commercial Aeronautics in America! The possibilities are so tremendous that they stagger imagination!

Everything is set for the greatest boom in history. The fortunes that came out of the automobile industry and out of motion pictures will be nothing compared to the fortunes that will come out of Aviation! There is just one thing holding it up:—lack of trained men! Even in the beginning thousands will be needed—and generously paid. The opportunities open to them cannot be over-estimated. Those who qualify quickly will find themselves on the road to undreamed of money—success—popularity—and prominence!

ARE you a red-blooded, daring he-man?

Easy to Become an Aviation Expert

\$50 to \$100 a Week

Get into this thrilling profession at once while the field is new and uncrowded. Now—by a unique new plan—you can quickly secure the basic training for one of these wonderful high salaried jobs, at home, in spare time. Experts will teach you the secrets—give you all the inside facts that are essential to your success. And, the study of Aviation is almost as fascinating as the actual work itself. Every lesson is chock-full of interest—and so absorbing that you actually forget you are studying. But best of all are the ultimate rewards you are fitting yourself to gain!

Pick Your Job!

Airplane Instructor
Airplane Engineer
Airplane Repairman
Airplane Assembler
Airplane Mechanician
Airplane Inspector
Airplane Builder
Airplane Salesman
Exhibition Manager
Airplane Contractor
Airplane Motor Expert
Airplane Designer

Send for FREE Book

Send the coupon for our new, free book, just out—"Opportunities in the Airplane Industry".

It is vitally interesting, reads like a romance and tells you things about this astonishing profession you never even dreamed of. This book is so fascinating it could easily sell for a dollar. We offer a limited number FREE. Write for yours today.



American School of Aviation
Dept. 135-A, 3601 Michigan Ave., Chicago, Ill.

AMERICAN SCHOOL OF AVIATION,
Dept. 135-A, 3601 Michigan Ave., Chicago, Ill.


Without any obligation please send me FREE book "Opportunities in the Airplane Industry." Also information about your course in Practical Aeronautics.

Age.....

Name.....

Address.....

City.....State.....



Amazingly Easy Way to get into **ELECTRICITY**

Don't spend your life waiting for \$5 raises in a dull, hopeless job. Now . . . and forever . . . say goodbye to 25 and 35 dollars a week. Let me teach you how to prepare for positions that lead to \$50, \$60 and on up to \$200 a week in Electricity—NOT by correspondence, but by an amazing way to teach that makes you a Real Electrician in 90 days! Getting into electricity is far easier than you imagine!

Learn Without Lessons in **90 DAYS**

LACK of experience—age, or advanced education bars no one. I don't care if you don't know an armature from an air brake—I don't expect you to! It makes no difference! Don't let lack of money stop you. Most of the men at Coyne have no more money than you have. That's why I have worked out my astonishing offers.

I PAY

Your Railroad Fare When You Enroll

I pay your railroad fare to Chicago, and assist you to part time work while training. Then, in 12 brief weeks, in the great roaring shops of Coyne, I train you as you never dreamed you could be trained . . . on one of the greatest outlays of electrical apparatus ever assembled . . . real dynamos, engines, power plants, autos, switchboards, transmitting stations . . . everything from doorbells to farm power and lighting . . . full-sized . . . in full operation every day!

No Books—No Printed Lessons

No dull books, no baffling charts . . . all real actual work . . . building real batteries . . . winding real armatures, operating real motors, dynamos and generators, wiring houses, etc., etc. That's a glimpse of how we help to make you a master electrician, teaching you far more than the average ordinary elec-



JOBS OPEN

Here are a few of hundreds of positions open to Coyne-trained men. Our free employment bureau puts you in touch with openings to choose from.

Armature Expert	\$100 a Week
Substation Operator	\$65 a Week
Auto Electrician	\$110 a Week
Inventor	Unlimited
Maintenance Engineer	\$150 a Week
Service Station Owner	\$200 a Week
Radio Expert	\$100 a Week

trician ever knows and fitting you to hold big jobs after graduation.

Jobs, Pay, Future

Don't worry about a job. Coyne training settles the job question for life. Big demand for Coyne trained men. Our employment bureau secures dozens of positions weekly. Two weeks after graduation, Clyde F. Hart got a position as electrician with the Great Western Railroad at over \$100 a week. That's not unusual. We can point to many Coyne men making up to \$800 a month. \$60 a week is only the beginning of your opportunity. You can go into radio, battery or automotive electrical business for yourself and make up to \$15,000 a year.

Get the Facts

Coyne is your one great chance to get into electricity. Every obstacle is removed. This school is 28 years old—Coyne training is tested—proven beyond all doubt—endorsed by electrical industry. You can find out everything absolutely free. Simply mail the coupon and let me send you the big, free Coyne book of 150 photographs . . . facts . . . jobs . . . salaries . . . opportunities. Tells you how many earn expenses while training and how we assist our graduates in the field. This does not obligate you. So act at once. Just mail coupon.

Get
this
FREE
Book



COYNE ELECTRICAL SCHOOL

H. C. LEWIS, Pres.
Dept. A7-72

1300 W. Harrison St., Chicago, Ill.
Founded 1899

Mr. H. C. Lewis, Pres.,
COYNE ELECTRICAL SCHOOL, Dept. A7-72
1300 W. Harrison St., Chicago, Ill.

Dear Mr. Lewis:
Without obligation send me your big free catalog and all details of your Railroad Fare to Chicago offer. Free Employment service. Radio and Automotive Courses without extra cost, and how I can "earn while learning." I understand I will not be bothered by any salesman.

Name.....
Address.....
City.....State.....



\$2500 Reward!

For the Capture of an Unknown Man

Twice he had entered the St. Clair Mansion. What was he after? Who? What was in danger?

Berteau, the famous detective, had warned St. Clair that *the mysterious marauder would come again*. And now—a noise in the passage! The creak of an opening door. A shot in the dark! A capture!

Is this wounded stranger the mysterious intruder? Who could tell? Yet Berteau identified the man without hesitation and won the \$2500 reward.

How did he do it? Easy enough for the Finger Print Expert. He is the specialist, the leader, the *cream* of detectives. Every day's paper tells their wonderful exploits in solving mysterious crimes and convicting dangerous criminals.

More Trained Men Needed

The demand for trained men by governments, states, cities, detective agencies, corporations, and private bureaus is becoming greater every day. Here is a real opportunity for YOU. Can you imagine a more fascinating line of work than this? Often life and death depend upon finger print evidence—and big rewards go to the expert. Many experts can earn regularly from \$3,000 to \$10,000 per year.

Learn at Home in Spare Time

And now you can learn the secrets of this science at home in your spare time. Any man with common school education and average ability can become a Finger Print Detective in a surprisingly short time.

Course in Secret Service

FREE

UNIVERSITY OF APPLIED SCIENCE

Dept. A-135—1920 Sunnyside Ave., Chicago, Illinois

Gentlemen:—Without any obligation whatever, send me your *new, fully illustrated, FREE book on Finger Prints* and your offer of a *FREE course in Secret Service Intelligence* and the *Free Professional Finger Print Outfit*.

Name

Street Address

City and State

For a limited time we are making a special offer of a *professional Finger Print Outfit, absolutely Free, and Free Course in Secret Service Intelligence*. Mastery of these two kindred professions will open a brilliant career for you.

Write quickly for fully illustrated free book on Finger Prints which explains this wonderful training in detail. Don't wait until this offer has expired—mail the coupon now. You may never see this announcement again! You assume no obligation—you have everything to gain and nothing to lose. Write at once—address

University of Applied Science

Dept. A-135

1920 Sunnyside Avenue, Chicago, Illinois

They Thought I Was Trying to be Funny—



Until I Started to Play — Then I Gave Them the Surprise of Their Lives

THE crowd sat spellbound. Harry had just played the violin—beautifully. With mock dignity I arose. "With your kind permission," I announced, "I shall now charm you with a piano recital."

Everyone snickered. They were sure I couldn't play a note. "Does he really play?" one girl asked. "Yes," Phil laughed, "he plays the Victrola—beautifully!"

With studied clumsiness, I fell over the piano stool. Then I proceeded to pick out "Chop Sticks" with one finger! The crowd laughed. This was the dramatic moment for my surprise. Dropping the mask of the clown, I struck the first sweet chords of Wagner's lovely "The Evening Star" from "Tannhauser."

The laughter died on their lips. The magic of my music cast a spell over everyone. As I played on with complete confidence, I forgot the room—the people—everything. I was alone—lost in the sheer beauty of the immortal master's tender melodies.

The Thrill of My Life

When the last notes had faded away, there was a roar of applause. Then came questions and congratulations from my dumbfounded friends — "How long have you been playing?"—"Who was your teacher?"—"Where did you learn?"

"I know it is hard to believe," I replied, "but I learned at home—and without a teacher!"

Then I told them the whole story.

"I have always wanted to play the piano. But I never had a chance to take lessons. Then one day I saw an interesting ad. It told about a new, easy way of learning music—right at home—without a teacher. I sent for the Free Demonstration Lesson and Book-let.

"When they arrived, I was amazed to see how easy playing the piano really

was. I decided that I would send for the course and practice secretly. Then I could surprise you all.

Just a Few Minutes a Day

"The course was as fascinating as a new game. I enjoyed every minute of it. I was playing real tunes from the start, by note. Reading music was as easy as A-B-C! No weary scales, no monotonous exercises, no tiresome hours of practicing. Soon I could play jazz, ballads, classical music—all with equal ease."

You, too, can learn to play your favorite instrument by this easy "at home" method that has taught almost half a million people. There's nothing marvelous about it. It's just a common sense practical method—so simple you don't have to know the slightest thing about music. You find your progress amazingly rapid because every step is clear and easy to understand. Just pick out the instrument you want to play. The U. S. School of Music does the rest. And its cost averages just a few cents a day!

Free Book and Demonstration Lesson

Our illustrated free book and free demonstration lesson explain all about this remarkable method. They prove how anyone can learn to play his favorite instrument in almost no time.

If you really want to learn to play, take this opportunity to make your dreams come true. Sign the coupon below. Instruments supplied when needed, cash or credit. U. S. School of Music, 76 Brunswick Bldg., New York.

U. S. SCHOOL OF MUSIC,
76 Brunswick Bldg., New York City

Please send me your free book, "Music Lessons in Your Own Home," with Introduction by Dr. Frank Crane. Demonstration Lesson and particulars of your Special Offer. I am interested in the following course:

Have you above instrument?


Name

Address

City State

Pick Your Instrument

Piano	Cello
Organ	Harmony and
Violin	Composition
Drums &	Sight Singing
Traps	Ukulele
Guitar	Hawaiian Steel
Mandolin	Guitar
Harp	Clarinet
Cornet	Flute
Piccolo	Saxophone
	Trombone
Voice and Speech Culture	
Automatic Finger Control	
Piano Accordion	
Banjo (5-String, Plectrum	
and Tenor)	



EARLE E. LIEDERMAN, *The Muscle Builder*
Author of "Science of Wrestling," "Muscle Building," "Secrets of Strength," "Here's Health," "Endurance," etc.

Kill This Man!

THERE'S a devil inside of you. He's trying to kill you. Look out for him! He tells you not to work so hard. What's the use? the boss only piles more work on you. He tells you not to bother with your body. If you're weak—you always will be weak. Exercise is just a lot of rot. Do you recognize him? Of course you do. He's in us all. He's a murderer of ambition. He's a liar and a fool. *Kill him!* If you don't, he will kill you.

Saved


Thank your lucky stars you have another man inside of you. He's the human dynamo. He fills you full of pep and ambition. He keeps you alive—on fire. He urges you on in your daily tasks. He makes you strive for bigger and better things to do. He makes you crave for life and strength. He teaches you that the weak fall by the wayside, but the strong succeed. He shows you that exercise builds live tissue—live tissue is muscle—muscle means strength—strength is power. Power brings success! That's what you want, and gosh darn your old hide! you're going to get it.

Which Man Will It Be?

It's up to you. Set your own future. You want to be the Human Dynamo? Fine! Well, let's get busy. That's where I come in. That's my job. Here's what I'll do for you:

In just 30 days I'll increase your arm one full inch with real live, animated muscle. Yes, and I'll add two inches to your chest in the same time. Pretty good, eh? That's nothing. Now come the works. I'll build up your shoulders. I'll deepen your chest. I'll strengthen your whole body. I'll give you arms and legs like pillars. I'll literally pack muscle up your stomach and down your back. Meanwhile I'll work on those inner muscles surrounding your vital organs. You'll feel the thrill of life shooting up your old backbone and throughout your entire system. You'll feel so full of life you will shout to the world, "I'm a man and I can prove it!"

Sounds good, what? But listen! That isn't all. I'm not just promising these things. *I guarantee them!* It's a sure bet. Oh, boy! Let's ride.



Send For My New
64 Page Book
"Muscular Development"
IT IS FREE

What do you think of that? I don't ask one cent. And it's the peppiest piece of reading you ever laid your eyes on. I swear you'll never blink an eyelash till you've turned the last cover. And there's 48 full-page photos of myself and some of my prize-winning pupils. This is the finest art gallery of strong men ever assembled. And every last one of them is shouting my praises. Look them over. If you don't get a kick out of this book, you had better roll over—you're dead. Come on, then. Take out the old pen or pencil and sign your name and address to the coupon. If you haven't a stamp, a postal will do. But snap into it. Do it *now*. Tomorrow you may forget. Remember, it's something for nothing and no strings attached, no obligation. *Grab it!*

EARLE E. LIEDERMAN

Dept. 2006, 305 Broadway, New York City

**It
Is
F
R
E
E**

**DON'T
SEND ONE
PENNY
—
YOUR
NAME AND
ADDRESS
ON A
POSTAL
WILL DO**

EARLE E. LIEDERMAN

Dept. 2006, 305 Broadway, New York City


Dear Sir: Please send me, absolutely **FREE** and without any obligation on my part whatever, a copy of your latest book, "Muscular Development."

Name.....

Street.....

City..... State.....

(Please write or print plainly.)



This Dental Laboratory Expert earns UP TO \$20 a day!

What's the use of training for the old, overcrowded trades? If you're going to prepare for big-salaried jobs or a profitable business of your own GET INTO THE FASTEST GROWING PROFESSION—"Laboratory Dentistry." Biggest opportunity for success of the century, because there are many more jobs than there are experts to fill them, because there are a dozen cities crying for Laboratories for each EXPERT capable of operating one!

Easiest, pleasantest work you ever saw! Your own boss, money and success yours from the very beginning. You can start with a "shoe-string." We prepare you in a few months to run a business of your own, to do any job. Common schooling, ability to use your fingers ALL YOU NEED! R. R. Fare to Chicago, Cleveland, Detroit, Boston or Philadelphia deducted from cost of course for a limited time!

Jobs Up to \$125 a Week!

In a business where there are many times as many jobs as Experts, salaries are high, hours are easy, opportunities are everywhere! Dentists recognize the high-standing of our graduates. No books here—learn with tools and instruments. Start quick—get ready in a few months for your big opportunity! Mail Coupon today!

Rubber Plates

Learn to make partial upper or lower plates with soldered, cast or wire clasps, with palatal bars; with lingual bars. McCarrie-trained Students learn to make full rubber plates of every type, including Vulcanite base-plates, butted gums, carved gums, etc.

CROWNS

Here's only a small part of your practical training in Crown-work: Two-piece, seamless, open-face, Richmond, cast-base porcelain, Carmichael, split-pin, carved (swaged) cusp, cast cusp, etc.

BRIDGE WORK

Complete training in both fixed and removable bridgework. Interchangeable teeth, gold dummy, Sanitary porcelain dummy jobs—Roach, Gilmore, Bischoff and all forms of cast-clip work is taught—not with books but in actual Laboratory.

METAL BASE DENTURES

Cast bases of Aluminum, Watt's metal, etc., are included in your training. Both centrifugal and air pressure casting machines are used. Free Book contains complete list of subjects in course.



R-R-FARE TO Chicago Cleveland Detroit Boston or Phila. DEDUCTED from TUITION

64,000 DENTISTS NEED LABORATORY WORK!

Only a few hundred Laboratories in all the U. S.—most of them in the larger cities. Dentists can't afford to do their own mechanical jobs. They can buy the services of a Laboratory Expert at about \$3.00 an hour and sell their own time at \$6 to \$15 an hour. Dentists will encourage you to learn mechanical Dentistry, start a "Lab" of your own, give them quicker service than sending their work to other cities. Dentists can't wait and keep their patients waiting. Ask your Dentist.

WE HELP YOU OPEN A LABORATORY OF YOUR OWN!

Many of our graduates open a Laboratory of their own. To encourage more men to go into this wonderful Mechanical profession, we will help you find a good location for your Laboratory, and help you towards success. Write for complete information on how you can find yourself in a profitable business of your own after you become a Dental Laboratory Expert.

INTERESTING BOOK—FREE!

Right this minute there are openings for 150 Dental Laboratory Experts in locations where they can do a business of \$5,000 to \$20,000 a year. But you can't cash in, take advantage of these OPPORTUNITIES until you're Trained. Catalog tells you how quickly and easily you can get ready, how hundreds of others have SUCCEEDED! Tells you how you learn in a few months BY DOING ACTUAL LABORATORY JOBS in our famous Dental Laboratory Schools. Brings you R. R. Fare offer and other big inducements. Write for free Book today!

McCarrie School of Mechanical Dentistry

1338 S. Michigan Ave.
Dept. 126 Chicago, Ill.

EARN while you LEARN!
Day students make all or part cost of course by part-time night work. Night students can find plenty of good jobs to see them thru.
We'll help you!

McCarrie School of Mechanical Dentistry
1338 S. Michigan Ave., Dept. 126, Chicago, Ill.

Without obligation, please send me your R. R. fare offer and free Book with complete information about how I may become a Mechanical Dentist. How you will help me open a Laboratory, how you will help me find a job while I take my training, etc.

Name.....
St. No. or R. F. D.....
City.....State.....

**NOW!
FREE!**

Raised My Pay 700%

This Amazing Book Showed Me How

This is Perhaps the Most Remarkable Book Ever Printed. It Has Proved the Turning Point in the Careers of Thousands Who Were Ambitious for Bigger Pay! If You Ever Aspired to Earn \$10,000 a Year or More—Read it Without Fail!

CAN you imagine how a man feels when his earning capacity quickly jumps 700% in a few months? Can you imagine how you would feel if your salary suddenly became *seven times* greater than ever before?

That is exactly what happened to O. A. Jones of Missouri, after reading the amazing book pictured above. Between its covers, he discovered something he had never even dreamed of before—a certain force that lifted him out of the routine rut and set him on the road to \$10,000 a year!

Unusual? Not at all. This surprising book has done the same for hundreds of others. For example: C. W. Birmingham of Ohio read it and jumped from \$15 a week to \$7,500 a year. Wm. Shore of California, read it and commenced earning as high as \$525 a week. C. V. Champion of Illinois read it and became President of his company at a salary exceeding \$10,000 a year!

THE SECRET OF BIG EARNINGS

How did they do it? What did the book show them? Just this: Every one of these men realized that a knowledge of salesmanship and the *ability to sell* brings bigger rewards than anything else in modern business today! But until they saw the contents of this book—"Modern Salesmanship"—they had no idea that they, *too*, could win quick success through salesmanship. They believed that this golden field of endeavor was forever barred to them. But they were wrong—and this unusual book opened the way to the success that they had formerly despaired of attaining!

SALESMEN ARE MADE—NOT BORN!

Yes! Any man of ordinary intelligence can become a successful salesman! Just as you learned the alphabet, you can master the secrets of selling as taught by the National Salesmen's Training Association.

Reason it out for yourself. Salesmanship is governed by rules and laws. There are certain ways of saying and doing things to make men act as you want them to: certain ways of getting exactly what you go after! Once you have mastered these fundamental rules, your success is governed only by your energy and ambition!

BIG DEMAND FOR TRAINED SALESMEN

City and traveling sales positions are open in every line all over the country. For years, thousands of leading firms have

called on the N. S. T. A. to supply them with salesmen. Employment service is free to both employers and members and thousands have secured positions through this service.

FREE TO EVERY MAN

If we were asking two or three dollars a copy for "Modern Salesmanship," you might hesitate. But it is now FREE. We cannot urge you too strongly to take advantage of this opportunity to see for yourself what salesmanship has done for others—and what the National Salesmen's Training Association stands ready and willing to do for you. No matter what your opinion is now, "Modern Salesmanship" will give you a new insight into this fascinating and highly-paid profession.

Mail the coupon now!



Dept. G-12, N. S. T. A. Bldg.
Chicago, Ill.

National Salesmen's Training Association

Dept. G-12, N. S. T. A. Bldg., Chicago, Ill., U. S.

Please mail me FREE your illustrated book, "Modern Salesmanship," and particulars of membership in your association and its Free Employment Service.

Name.....

Address.....

City.....State.....

Age.....Occupation.....



G. King Franklin
Famous Auto
Painting Authority

Whether You want a Job or a Business of Your Own Be an Auto Painter!

A Paint Shop of Your Own in Sight!

Little capital needed to start a small shop when you know how to do a professional job of painting and spraying. As profits roll in you can buy spraying equipment, employ helpers and branch out. Hundreds of the largest paint shops in the U. S. started with half a dozen brushes and a few cans of material. My 13 outfits illustrated below include sufficient tools to make a start in a shop of your own.

Learn in a Few Months at Home!

13 Outfits of Tools and You Don't Need a Car to Learn by My System

I send you panels of metal and wood to prime, surface, paint, varnish, stripe, etc. I supply sandpaper, chamois, all kinds of brushes, scrapers and other tools—all without extra charge. I start you off by doing actual painting jobs. I guarantee that you can learn quickly and easily. Satisfaction or money refunded is my method. My course includes shop-tickets, shop-lectures, work-tickets, etc. And I tell you how to go out and get the business, how to run it, how to keep order and cost records, etc. It would take many years of actual experience and twice the time and three times the cost at a trade school to learn all branches of the work as I give it to you AT HOME in your spare time.

G. King Franklin, Supt.
American Auto Painting School
Dept. 301—421 S. Ashland Ave., Chicago

Send sample shop-tickets free and information on how I may learn auto painting and Duco at home in spare time.

Name.....

Street No.....

City.....

State.....

Earn \$75 a Week and Up!

Paint and Duco experts are always sure of a well-paid job. That's one branch of auto work never crowded. Twenty million autos, trucks, tractors, busses and taxis need repainting every couple of years.

Paint and Duco experts earn big salaries. Finishers earn \$75 to \$125 a week. Painters and sprayers earn \$50 to \$90 a week.

Plenty of jobs—everywhere—all the time in auto painting, and the work's easy and pleasant.

Here is an uncrowded field that assures your success.

Materials Included Sample Shop-Tickets FREE

Mail coupon for complete information and get sample shop-tickets FREE. I want you to see how easy, rapid and practical I have made the learning of auto painting and Duco. Low tuition for this instruction and very small monthly payments. Rush coupon today.

G. King Franklin, Supt.

American Auto Painting School
Dept. 301, 421 South Ashland Avenue, CHICAGO

Would You Sign This CONTRACT?

I HEREBY agree and bind myself to stay at my present job for the term of *ten years from this date*, at the same salary I am now drawing.

Signed: _____



Ask Yourself This Vital Question:

In ten years will you still be meeting the same competition on the same ground, with the only difference that you yourself are older, more discouraged?

If you wouldn't sign a contract to "stay put" for the next ten years, what are you doing to get hold of a better place? If you aren't doing anything, you might as well sign the contract as not—you'll be there anyway.

In the last few years a vast new industry has opened up, offering thousands of new opportunities to all sorts of men. If you will train yourself to hold its good jobs you can find a better future here. This industry still needs men—many of them—in more than twenty different lines of work. The work is more than interesting, it's fascinating—so much so that thousands dabble with it just for the pleasure it gives them. This industry is RADIO.

Here's a real opportunity for men who are stuck in the rut to train themselves for a new, fascinating line of work which offers a big opportunity both at present and for the future. Radio needs **trained experts** for its good jobs. You can get the necessary training, in a short time at home, to enable you to get into the Radio game and learn how it feels to make **REAL MONEY**—in a wide-awake, prosperous new profession.

Send for Free Book That Gives All Facts

A 64-page book, full of facts, photos, and general information on the opportunities in this new field, will be sent to you free on request. Previous experience in Radio is not necessary—when we prepare you for the Radio profession we do the job thoroughly



J. E. SMITH

J. E. Smith, President, National Radio Institute—for 14 years the leading educator in the Radio field. He has trained thousands of men (more than any other educator in the world) to enter the Radio profession. National Radio Institute, the oldest and largest Radio home-study school in the world, today has students or graduates in almost every Radio business of consequence.

from the beginning. While the necessary training can be obtained in a space of a few months, it is absolutely complete and thorough. It is also clear and easily-learned—men of practically no education often take it up and master it.

You owe to yourself and to your future to look into this opportunity, and see exactly what it offers you. The book will be sent free—absolutely no obligation.

Would you sign **your** name in the contract above, and hand the contract to your employer? If you wouldn't, then look around for something better. Fill in the coupon below and take a look at Radio's offer.

J. E. SMITH, President,
National Radio Institute, Dept. F-85, Washington, D. C.
Dear Mr. Smith: Kindly send me your free 64-page book on Radio opportunities, also full information on your home-study Radio training. I understand no salesman will call on me, and that this places me under absolutely no obligation.

Name.....

Address.....

Town.....State.....

Learn
Magic at
Home



Startling New MAGIC TRICK FREE

A most mysterious effect! Absolutely new. A trick you never knew or saw performed. One of the many original and surprising illusions created by the famous Dr. Harlan Tarbell. Sent to you without one penny's cost or obligation. Includes full directions that will enable YOU to perform it with expert skill with fifteen minutes practice. All you need to do is mail the coupon below.

Astonish Your Friends

Nothing like Magic to give you that magnetic popularity that means everything to a man in social and business life. We offer you this free trick to show you the marvelous possibilities open to you through Dr. Tarbell's complete Magic Course.

Make BIG Money

Magic is like a golden key that opens all doors to success. As a professional, a semi-professional, or as a help in your present business life, Magic will add tremendously to your income. Mail the coupon. Get started. See for yourself.

Just
Mail Coupon
for **FREE
TRICK**

That's all. No cost. No obligation. Trick is complete with full instructions. Yours to keep. Mail the coupon right NOW!

Tarbell System, Inc.
Dept. A-135
1926 Sunnyside Ave., Chicago

Tarbell System, Inc., Dept. A-135 1926 Sunnyside Ave., Chicago
Please send me your mysterious Vanishing Card Trick and full information as to how I can learn Magic and make big money. I understand this trick is FREE, prepaid, and sent me without obligation.

Name

Address

Age

CAMERA GIVEN

Without Extra Charge

Your Choice—\$100 Professional
MOTION PICTURE Camera or
Professional VIEW Camera



BE a Motion Picture Cameraman, Portrait, News or Commercial Photographer. Earn a handsome salary or own a studio and set your own prices! No experience needed. Spare time work. Big money to be made while you are learning!

Learn Photography

A few minutes a day at home fits you for a big paying position and you get your choice of these standard professional cameras. Instruction also given in our great New York studios.

Cameramen and photographers are always in demand. You can quickly qualify for this easy, fascinating work.

Earn \$75 to \$250 a week

Big money in all branches. Hundreds of positions now open pay \$75 to \$250 a week and more! The most interesting profession in the world.

Send name and address for big, new, illustrated book on Professional Photography. Explains amazing opportunities. Write for your copy tonight!



NEW YORK INSTITUTE OF PHOTOGRAPHY

Dept. 49, 10 West 33rd St., NEW YORK CITY

Write NOW for FREE BOOK

HEALTHY
GOV'T
JOBS

MEN-WOMEN, 18-50,
wanting Forest Ranger,
Railway Mail Clerk, Border
Patrol Guard, Mail
Carrier, P. O. Clerk,
Matron, and other Gov't
Positions, local or traveling.
For particulars write
Mr. Osmont, Dept. 111
St. Louis, Mo.

IN OR
OUTSIDE
WORK
\$140-\$300
MONTHLY

LAW

High-Grade Instruction

By Correspondence
Prepares You for
the Bar—Est. 1892

University Methods. Standard Text-Books.
Approved by Bench and Bar. Graduates practicing
in every state. Send today for Free
Catalog and Rules for Admission to the Bar.
CHICAGO SCHOOL OF LAW, 802 Reaper Block, Chicago, Ill.



"BECOME A LIGHTNING TRICK CARTOONIST"

Send \$1.00 for Lanch Producing Program of 23 Trick Drawings with Instructions. Catalog of Chalk Talk Supplies Free.
BALDA ART SERVICE, Dept. 1, Oshkosh, Wis.

IF YOU **STAMMER**

Write for my free book "Millard's Advanced Natural Corrective Course" and a free copy of my speech magazine. 10,000 cases successfully treated. Est. 24 years. Largest school for stammerers in world. Millard Inst. of Normal Speech, 2317 Millard Bldg., Milwaukee, Wis.



Wonderful, new device, guides your hand; correct your writing in few days. Big improvement in three hours. No failures. Complete outline FREE. Write C. J. Osmont, D-34, St. Louis, Mo.

The Man Who is Astounding America!

What is the mysterious power wielded by this man—a power he also shows others how to use? What is this new method which has started thousands of despairing persons on the road to health, happiness and prosperity?

THOUSANDS upon thousands have been turned away from the great theatres and auditoriums in Chicago, New York, San Francisco, Seattle, Denver, Boston, and practically every great city in America where Dr. Bush has been lecturing! These vast halls could not accommodate half of those who heard of his wonderful powers and had heard how he disclosed the secret of his powers to others!

Those who were ill had been shown how to become well and strong by a method to which other mental science movements were as the first step in a mammoth, far-reaching stairway.

The worried and the nervous had been shown how to rise above their mental and nervous troubles in a single evening and how to attack and solve their problems with a keener mind unhampered by despair.

An Astounding New Power

But that wasn't all. As wonderful as it is to have the secret of mental and physical health in one's grasp—there is a still greater force at work in the universe. This force can be harnessed in such a way as to bring us the MATERIAL things we want—money, power, influence, no matter what it is. And Dr. Bush has harnessed this force; has proved its value in his own case; and has proved time and again that he can show others how to use this power.

Long before the lectures were over the reports began to come in showing how quickly his audiences had been taught to use this wonderful power.

"By your method of visualization I secured the funds to build my home," writes one of Dr. Bush's Chicago listeners. Mrs. Mary Roberts of Denver writes, "My salary was increased

40% in one week by following your psychological method—and my powers of salesmanship were DOUBLED." "TEN Thousand Dollars would not pay for the benefits I have received," James C. Smith of Somerville, Mass. writes him. Another says, "I was making no money, my health was bad and I was heavily in debt. Now I have a store of my own and am doing a good business. My family and myself enjoy the best of health." A man who learned of this power in Pittsburgh—he had never earned more than \$25 per week—stepped out the first month and made over \$1000. Dr. Bush has thousands of letters like these. They are his proudest possessions.

His Teachings Now in Book Form

Dr. Bush's sole idea in giving these lectures is the same idea that actuated him in his earlier days before he had discovered this amazing new force. Then as an earnest and brilliant young minister of the Gospel he had refused honors and financial returns in order to apply his efforts where they would do good to the greatest number. His lectures given are



David V. Bush
*America's Foremost
Author-Lecturer on
Practical Psychology*

for the same reason—to teach this new force to everyone who will learn. And to reach still more people he has incorporated his lectures in an absorbingly interesting book, "Applied Psychology and Scientific Living," which will be sent, on FREE TRIAL, to any earnest seeker after knowledge. Luther Burbank said, "Applied Psychology appears to me the most practical and useful work which has been published on these and similar subjects."


When You Need This Book

Are you nervous or depressed? Do you feel old? Have you lost your grip? Have you a worrying disposition? Have you a personality that fails to attract others? Are you timid? Are you misunderstood? Do others seem inclined to give you always the worst of everything? Do you lack the aggressiveness necessary to bring you position and power? Are you in ill health? Have you any chronic disease? Is anyone in your family or among your friends so affected? Are your children wilful and disobedient?

Examine It Free!

But no description can begin to give you even an idea of the startling truths explained and proved in this wonderful book of over 500 pages. The very first page will be a revelation to you just as Dr. Bush's lectures have been a revelation to keen thinking, analytical minds in every city. One enthusiast says: "It can be understood by everyone. And if everyone would read it and then use this new force, humanity would advance 5,000 years overnight."

But you will be the sole judge of this wonderful value. Mail the coupon. This remarkable book will be sent at once. Read it for 5 days. Practice this new force yourself. At the end of that time if you find it the most inspiring, the most valuable means to obtain health, wealth and happiness send us only \$3.50 which, as you will realize, pays only for the cost of printing, advertising and distributing the 500-page book. Otherwise return the book itself within 5 days and you will not owe a penny. But begin to enjoy the benefit of this new force at once. Mail the coupon today. **DAVID V. BUSH, Publisher, Dept. 1056, 225 N. Michigan Ave., Chicago, Ill.**



Partial List of Contents Psycho-Analysis and the Sub-conscious

How to Have Amazing Memory
How to Destroy Fear—Man's Worst Enemy—The Unseen World

What is Love and How to Keep It

How to Be Popular
How to Overcome Failure and Adverse Environment

How to Be Beautiful Through Mysterious Force

Vibration—How to Win Success
How to Develop Personality

How to Conquer Illness
Poverty a Disease—How to Overcome It

How to Double Your Efficiency
Visualization—How to Make Your Dreams Come True

The Mastery of Fate
How to Use Suggestion for Health, Success and Happiness

The Greatest Law in the Universe, Just Lately Discovered, and How to Use It

What the World Owes You and How to Get It

After This Life What?—What is God?

Smile, Smile, Smile
Psychology of Health—Building the Body Beautiful

Long Life and Full of Pep

**DAVID V. BUSH, Publisher, Dept. 1056
225 N. Michigan Ave., Chicago, Ill.**

Please send me a copy of "Applied Psychology and Scientific Living" for approval. I agree to remit \$3.50 or return the book in five days.

Name.....

Address.....

City.....State.....

(Remittance from Foreign countries and U. S. possessions must accompany all orders)



Automobile Experts in Demand

Study with the same school that helped to train many leading men in the automobile industry

THE best proof of the value of the home-study courses of the International Correspondence Schools is the success of I. C. S. students. This success is especially apparent in the automobile industry.

Jesse G. Vincent, Vice-president of the Packard Motor Car Co., is a former I. C. S. student. So is Walter P. Chrysler, President of the Chrysler Corporation. E. V. ("Eddie") Rickenbacker, Vice-president and Director of Sales of the Rickenbacker Motor Car Co.; Hiram Walker, Chief Engineer of the Chandler Motor Car Co., and John Moore, designer of the famous Ansted Motor, are also former I. C. S. students.

The first step they took was to mark and mail an I. C. S. coupon similar to the one printed below. Make your start the same way and make it right now. We'll gladly send you complete information about the I. C. S. Automobile Courses or any other course in which you are interested.

INTERNATIONAL CORRESPONDENCE SCHOOLS Box 565B-E, Scranton, Penna.

Oldest and largest correspondence schools in the world
Without cost or obligation on my part, please tell me how I can qualify for the position or in the subject before which I have marked an X:

- | | |
|---|--|
| <input type="checkbox"/> Complete Automobile Course | <input type="checkbox"/> Gas Engine Operating |
| <input type="checkbox"/> Automobile Electric Equipment | <input type="checkbox"/> Complete Gas Engine Course |
| <input type="checkbox"/> Electrical Engineering | <input type="checkbox"/> Architect |
| <input type="checkbox"/> Electric Lighting | <input type="checkbox"/> Architects' Blueprints |
| <input type="checkbox"/> Mechanical Engineer | <input type="checkbox"/> Contractor and Builder |
| <input type="checkbox"/> Mechanical Draftsman | <input type="checkbox"/> Architectural Draftsman |
| <input type="checkbox"/> Machine Shop Practice | <input type="checkbox"/> Concrete Builder |
| <input type="checkbox"/> Railroad Positions | <input type="checkbox"/> Structural Engineer |
| <input type="checkbox"/> Civil Engineer | <input type="checkbox"/> Chemistry <input type="checkbox"/> Pharmacy |
| <input type="checkbox"/> Surveying and Mapping | <input type="checkbox"/> Airplane Engines |
| <input type="checkbox"/> Metallurgy <input type="checkbox"/> Mining | <input type="checkbox"/> Agriculture and Poultry |
| <input type="checkbox"/> Steam Engineering <input type="checkbox"/> Radio | <input type="checkbox"/> Mathematics |

BUSINESS TRAINING COURSES

- | | |
|--|---|
| <input type="checkbox"/> Business Management | <input type="checkbox"/> Salesmanship |
| <input type="checkbox"/> Industrial Management | <input type="checkbox"/> Advertising |
| <input type="checkbox"/> Personnel Organization | <input type="checkbox"/> Better Letters |
| <input type="checkbox"/> Traffic Management | <input type="checkbox"/> Show Card Lettering |
| <input type="checkbox"/> Business Law | <input type="checkbox"/> Stenography and Typing |
| <input type="checkbox"/> Banking and Banking Law | <input type="checkbox"/> Business English |
| <input type="checkbox"/> Accountancy (including C.F.A.) | <input type="checkbox"/> Civil Service |
| <input type="checkbox"/> Nicholson Cost Accounting | <input type="checkbox"/> Railway Mail Clerk |
| <input type="checkbox"/> Bookkeeping | <input type="checkbox"/> Common School Subjects |
| <input type="checkbox"/> Private Secretary | <input type="checkbox"/> High School Subjects |
| <input type="checkbox"/> Spanish <input type="checkbox"/> French | <input type="checkbox"/> Illustrating |

Name.....

Street.....
Address.....

City.....State.....

Occupation.....

If you reside in Canada, send this coupon to the International Correspondence Schools Canadian, Limited, Montreal

Hundreds More
Needed Now



Three Months
Training

THE OPPORTUNITY OF A LIFETIME For Men Who Naturally LIKE TO USE TOOLS

Without a cent of cost to you or any obligation whatever, we will send you complete details of how to enter this profitable trade and earn steady up to

\$125 A WEEK

making Crowns, Plates, Bridges, etc., for Dentists—many experts earn far more. Don't let lack of money stop you—we have a regular arrangement for part time positions to help you pay expenses. R. R. Fare to our nearest school included.

Write Today for Free Bulletin 2

BODEE DENTAL INSTITUTE

Established over 35 years

The Pioneer in this Field

New York Philadelphia
1756 Broadway 1302 N. Broad St.
Brooklyn
85 Court St.



ONLY \$2.00 Giant Chest Expander and Progressive Exerciser

Use This
Money
Saving
Coupon

Be a muscular Marvel. Have the muscles of a superman. Become strong for your health's sake or to astound your friends with extraordinary feats which only men of giant strength can do.

Free Instructions.

The Giant Chest Expander and Progressive Exerciser is made with new, two springy rubber so as to give it long wear and great resisting qualities. Sold with a guarantee to give entire satisfaction or money back. Made two ways, either

5 Cables or double strength 10 Cables
for **\$2** The double strength exerciser has resistance of over 200 lbs. for **\$4**

Send No. Money Send at once and get your Giant Exerciser at the present low introductory price. Deal with a long established, reliable firm. Don't pay more—order from us—get the most for your money. Use coupon now.

PROGRESSIVE EXERCISER CO.,
4006 Langdon Bldg.,
Broadway and Duane Street, New York

Please send ☐ your 10 cables ☐ Progressive
☐ your 5 cable ☐ Exerciser.
(Check the Exerciser you want.) It is understood that if I am not satisfied with this Exerciser, I will return it within 5 days and get my money back.

Name.....

Address.....

City.....State.....

These Real Blue Prints **and two Books** Sent **FREE**



**Just
mail the
coupon below!
Send no money!**

Every builder can get these real blue print plans and our book "How to Read Blue Prints" without sending us a penny. Just send the coupon. Lots of valuable and interesting information—all *free*. Yes, and we'll send along another book on building; it tells why "the big money goes to the man who *knows*." It explains the practical Chicago Tech. easy method of home-training for men in the building trades. Learn how to get the jobs that pay most money or how to get into your own business as a building contractor.

Plan Reading—Estimating—Superintending, etc.

Train at Home to **MAKE MORE MONEY** **No Schooling Necessary**

Learn how to read plans, lay out work and run jobs. Your spare time is enough. Wherever you may be—whatever your job—we can help you quickly to fill a higher place and have a bigger income. Age does not matter. Previous school

training is not needed. This is a practical course for practical men, prepared by practical instructors who have been through every branch of the building game themselves. You owe it to yourself to find out how to make more money.

To Builders Living in or Near Chicago

Visit our Day or Evening School for builders and see with your own eyes the work we do. 1000 builders attend each year. You can get the same training *at home*. Same lessons—same blue prints—same practical instructors—same successful results.

Get the Facts Find out how little time it takes to make more money—much more money—in building. Write today. The coupon brings all *Free*.

**Chicago Technical
SCHOOL for BUILDERS**

Dept. G-140, 118 East 26th St., Chicago, Ill.

Mail the Coupon—NOW

**Chicago Technical
SCHOOL for BUILDERS**

Dept. G-140, 118 East 26th St., Chicago, Ill.

Please send me without obligation. Free and Postpaid, your two Books and Blue Prints for Builders. It is understood that no salesman will call on me.

(Please Write or Print Name Plainly)

Name.....

Address.....

City.....State.....

Age.....Occupation.....

Discovered!

The Scientific Secret of Caruso's

Amazing Vocal Power



A post mortem of Caruso's throat showed superb development of his Hyo-Glossus muscle—again proving the soundness of Eugene Feuchtinger's theories of voice production.

Eugene Feuchtinger, A. M., Musician-Scientist, who discovered this scientific method for developing the voice.

The arrow points to the all-important Hyo-Glossus muscle, the "keynote" of the Physical Voice Culture method.

The Great Discovery

Professor Feuchtinger, A. M.—famous in the music centers of Europe—discovered the secret of the Hyo-Glossus muscle. He devoted years of his life to scientific research and finally perfected a system of voice training that will develop your Hyo-Glossus muscle by simple, silent exercises right in your own home.

Since the Professor brought his discovery to America—over 10,000 happy pupils have received his wonderful training.

100% Improvement Guaranteed

The Perfect Voice Institute guarantees that Physical Voice Culture will improve your Voice 100%. You are to be your own judge—take this training—if your voice is not improved 100% in your own opinion, your entire tuition will be refunded.

Inspiring Book FREE Send the coupon below and we'll send you FREE this valuable work, "Physical Voice Culture". You assume no obligation. It may be the first step in your career. Do not delay.

Perfect Voice Institute

1922 Sunnyside Ave., Studio A-135 Chicago


Perfect Voice Institute 1922 Sunnyside Ave. Studio A-135 Chicago
Please send me a copy of your new book, "Physical Voice Culture", FREE. I understand that it is mine to keep and there is no obligation on my part. I am interested in

☐ Singing ☐ Speaking ☐ Stammering ☐ Weak Voice

Name

Address

Age



LEARN BY DOING

Every phase of all branches of

ELECTRICITY

taught by

Actual Practice

In one of America's foremost institutions for trade training

ESTABLISHED 1902

No Books Used

Individual Instruction
Start Any Day

Write for FREE 64-page catalog

THE NEW YORK ELECTRICAL SCHOOL

44 West 17th St., New York City

LEARN WATCH REPAIRING

Be a watchmaker—you can learn this profitable trade by correspondence in a few weeks in your own home by the DeSelms Chart System. After you complete the course you will know a watch from A to Z. You will know just what the matter is and how to repair one. When you graduate you will be a general watchmaker and repairer and competent to fill any position. Positions for our graduates. Ask for our Free Book. It explains our system and terms.

THE DeSELMS WATCH SCHOOL
LOGANSFORT, INDIANA



Cheapest Way to Go

to work or school and recreation is on a Mead bicycle. You can have your choice of 44 Styles, colors and sizes, 30 DAYS FREE TRIAL.

Factory to Rider Do business direct with the makers. We ship on approval. Save time and money. Prices from \$21.00.

Tires Best quality, factory prices. Save big money on lamps, wheels and equipment, low prices. Send No Money, do business direct with makers.

Mead CYCLE COMPANY
DEPT. H-110 CHICAGO

Write today for free Catalog, factory prices and marvelous new offer.



Learn to PAINT SIGNS and SHOW CARDS

We quickly teach you by mail, or at school, in spare time. Enormous demand. Big future, interesting work. Oldest, foremost school.

EARN \$50 TO \$200 WEEKLY

John Vasson, N. Y., gets \$25 for single show card.

Greenville, S. C., says: "Earned \$200 while taking course."

Send today for free information, samples and guarantee.

DETROIT SCHOOL OF LETTERING

154 Stinson Ave. Est. 1899 Detroit, Mich.



LEARN PIANO TUNING AT HOME

DURING SPARE TIME AND EARN \$50 TO \$100 A WEEK.

Our Tune-A-Phone Makes It Easy. With it any one who has ordinary hearing can acquire the knack quickly and accurately. Esmy Long Beach, Cal., says: "never dreamed there was so much money in Piano Tuning. I earned \$265 in ten days." He is but one of many. Write for Free copy of our book "Winning Independence" and Guarantee Plan.

BRYANT SCHOOL, 71 BRYANT BLDG., AUGUSTA, MICH.



They Thought I Was A Weak Sister -But I Took Their Breath Away!

ALL of a sudden the office was very quiet, as sometimes happens for an instant or two, and a few words reached me. "Oh, he won't dare kick," the manager was saying, "he's a pretty weak sister."

Mechanically I went on with my work, wondering vaguely who the weak sister could be. A new man had just been hired for our department and desks were being moved to make room for him. A minute later I looked up and saw the chief clerk standing at my side. "Bob," he crisply ordered, "move your desk back in that corner. I want this space for the new assistant I've hired." Then he turned and strode away.

I gulped and wilted down into my chair. I was the weak sister! And I was actually being demoted! The new man was being hired for my place! This was my reward for all my hard work—this was how I won out by waiting patiently for my turn to be promoted. I had even congratulated myself on my close-lipped, reserved manner—I thought I was showing strength of character by sticking to my work and not trying to push myself—to show off.

And that was the whole trouble. I had plenty of steel in my makeup, but I had no ability to express myself. I was timid, self-conscious, and actually afraid of my own voice. I would study out the office problems and find solutions for our difficulties, but I didn't know how to present these ideas to the man up ahead. Several of the boys who had started at the time I did were now department managers—because they had the knack of forceful speech, self-confidence and personality—the very qualities I lacked. It made me good and mad—and I resolved to show them—to get rid, once and for all of my timidity and shyness—my bashfulness and lack of poise.

In Fifteen Minutes a Day

And then suddenly I discovered a new easy method which made me into a good talker—a forceful and powerful speaker—almost overnight. I learned how to say just the right words at the right time, how to win and hold the attention of those around me, how to bend others to my

will, how to dominate one man or an audience of thousands. My self-consciousness began to vanish. One morning I got up my courage and presented the manager and the chief clerks with a complete plan for rearranging our department—stating it simply and clearly, but in a pleasing, interesting and forceful way. I actually took their breath away—they were so amazed that they gave me full power to carry out my ideas!

Soon I had won salary increases, promotion, popularity, power. And I accomplished all this by developing the natural power of speech possessed by everyone, but cultivated by so few—by simply spending 15 minutes a day in the privacy of my own home on this most fascinating subject.


Send for This Amazing Book

This new method of training is fully described in a very interesting and informative booklet which is now being sent to everyone mailing the coupon below. This book is called, *How to Work Wonders With Words*. In it you are shown how to conquer stage fright, self-consciousness, timidity, bashfulness and fear—those things that keep you silent while men of lesser ability get what they want by the sheer power of convincing speech. Not only men who have made millions, but thousands have sent for this book—and are unstinting in their praise of it. You are told how to bring out and develop your priceless "hidden knack"—the natural gift within you—which will win for you advancement in position and salary, popularity, social standing, power and real success. You can obtain your copy absolutely free by sending the coupon.

What 15 Minutes a Day Will Show You

How to talk before your club or lodge
How to propose and respond to toasts
How to address board meetings
How to make a political speech
How to tell entertaining stories
How to make after-dinner speeches
How to converse interestingly
How to write letters
How to sell more goods
How to train your memory
How to enlarge your vocabulary
How to develop self-confidence
How to acquire a winning personality
How to strengthen your will-power and ambition
How to become a clear, accurate thinker
How to develop your power of concentration
How to be the master of any situation

**NOW SENT
FREE**



North American Institute

3601 Michigan Ave., Dept. 135-A, CHICAGO, ILL.

NORTH AMERICAN INSTITUTE.
3601 Michigan Ave., Dept. 135-A
Chicago, Ill.

Please send me FREE and without obligation my copy of your inspiring booklet, *How to Work Wonders With Words* and full information regarding your Course in Effective Speaking.


Name.....

Address.....

City.....State.....

Make That Dream Come True!

Haven't you often pictured yourself playing the Hawaiian Guitar, a happy crowd around you, everybody enjoying and admiring your playing? Now you can reach your goal—and play all the latest hits just as the Hawaiians do!



You can play the **HAWAIIAN GUITAR** just like the Hawaiians!

\$15
HAWAIIAN GUITAR
with Genuine Seal Grain
Fabrikoid Cover
GIVEN
when you enroll

Complete Conservatory Course

52 complete lessons. Pictures explain every move. Our method is simple, practical and interesting—only 4 motions to learn. No tiresome scales and exercises—you play a real piece your very first lesson.

Expert Instruction by Native Hawaiians

Get the advantage of expert instruction by Kolomoku, Kalaiki, Perera and Seville—every one famous as both player and teacher. Even if you never touched a musical instrument in your life, under their direction you make rapid headway—you will be astonished when you see how easy it is!

This Sweet Toned Hawaiian Guitar

in genuine Fabrikoid Case—and complete playing outfit including picks, steel playing bar, etc.; given you when you enroll. Retailers ask \$15.00 or more for a similar outfit without the case. Remember, there are no extra—we furnish everything with the course.

Learn in Spare Time

Pick up your guitar at any time and play. Your lessons are always ready—you can always refer to them. You are never hurried or forced. And no waiting for a class to form—start now—go ahead as fast as you like.

Pay as You Play

Small first payment starts you. And the entire 52-lesson course comes to just a few cents a lesson! Begin now.

We Guarantee

in writing to teach you. And after graduation we coach and advise you without charge. Over 45,000 successful graduates.

Tenor Banjo and other courses—Violin, Tiple, Tenor Guitar, Banjo Ukulele, Ukulele—under well-known instructors. Write for information.

FIRST HAWAIIAN CONSERVATORY OF MUSIC, INC.

9th Fl., Woolworth Bldg., Dept. 348, New York, N. Y.

Approved as a Correspondence School Under the Laws of the State of New York

SEND THIS COUPON FOR LIBERAL OFFER!

First Hawaiian Conservatory of Music, Inc.
9th Fl., Woolworth Bldg., Dept. 348, New York, N. Y.

Please mail full information about your 52-lesson Hawaiian Guitar Course. I am not obliged to enroll unless I want to.

Name _____
Address _____
City _____ State _____



BLISS ELECTRICAL SCHOOL

Condensed Course in Theoretical and Practical Electricity

A special technical school, with comprehensive course.

ELECTRICAL

men with training are in demand. Since 1893 this school has been training men of ambition and limited time for the electrical industries. Condensed course in Electrical

ENGINEERING

enables graduates to secure good positions and promotions. Mathematics and Mechanical Drawing. Students construct motors, install wiring and test electrical machinery. Regular course designed to be completed in one college year. Over 5000 men trained. Thoroughly equipped fire-proof dormitories, dining hall, laboratories, shops. Prepare for your profession in the most interesting city in the world. Catalog on request.



BLISS ELECTRICAL SCHOOL
116 Takoma Ave., Washington, D. C.


LEARN WATCH REPAIRING



You can learn by our modern and original system of instruction every part of the **Watch Repairing Trade** at home as good or better than at a shop. You can earn money while learning and secure a well paying position or start in business after completing our course of instruction. Good watch repairers are always in demand and earn from \$50 to \$75 per week. For particulars apply to the **Wisconsin School of Watch Repairing**
166 Mason St., MILWAUKEE, WIS.

Anyone CAN LEARN

No talent or experience necessary. Fascinating work. Pays big money. Complete instruction book tells about: Alphabets, Colors, How to Mix Paints, Snow Cards, Window Boards and Wall Signs, Ready made letters, Gliding, Tricks of the Trade, also gives 100 Alphabets and Designs. Book bound in flexible imt. leather-gold edges, and four ball bearing Show Card. Penn. Sent postpaid \$3.00, C.O.D. \$1.00 ex. Bellis Pub. Co., 57 Rosa St., Dept. 20, N. Y. City



EARN MONEY IMMEDIATELY—WE FURNISH EQUIPMENT TO START!!

"STAMMERING Its Cause and Cure"

You can be quickly cured if you stammer. Send 10 cents, coin or stamps, for 288 page cloth bound book on Stammering and Stuttering. It tells how I cured myself after Stammering and Stuttering for 20 years. **BENJAMIN N. BOGUE**
6944 Bogue Building, 1147 N. 11th St. Indianapolis

FOREST RANGERS

Men wanting forest ranger, mail clerk, or other government positions, write for particulars.
MOKANE, 236, DENVER, COLO.

Become an Artist

LEARN AT HOME

You can learn to draw pictures that sell through a remarkable simple home-study method. Earn money while learning and secure a well-paying position after completing course. Good artists are always in demand and earn from \$100 to \$250 a week. Write today for free book. No obligation.

Washington School of Art
Room 306-E 1115-15th St., N. W. Washington, D. C.




Learn How to BOX

JIMMY DeFOREST BOXING COURSE

DEVELOPS CHAMPIONS BY MAIL

DeForest Boys are on the Road to Fame and Fortune!

The World's Most Famous Trainer Will Make You a Finished Boxer!



Since you wrote me last I won the Welterweight Championship of the Maritime Provinces (Eastern Canada). It was a whole of a fight, but the things I learned from your course just made McKenna look bewildered and foolish. Your course is worth its weight in gold. Everything I know today I got from it. I am deeply indebted to you for all I know and I wish to thank you ever so much for your attention and kindness to me. Within two years I will be in New York fighting the topnotchers.—Johnny Nemis, New Waterford, N. S., Canada.

Think of being made a thoroughbred boxer under the System of the World's Leading Trainer and Developer of Champions—Jimmy DeForest—the greatest Boxing Genius of all time! You can have that priceless knowledge which has made so many World Champions, and started hundreds to Fame and Fortune! Read what Johnny Nemis, Welterweight Champion of Eastern Canada, says about it, at the left.

NO EXPERIENCE NECESSARY

You start right from the very beginning. Jimmy DeForest teaches you his way. Step by step you go along. Every blow, every attack, every defense, every trick and every bit of ring strategy and generalship that was taught Jack Dempsey, Kid McCoy, George Dixon, Luis Firpo, Joe Gans and a host of other champions and great contenders that DeForest trained.

Everything that the Master Trainer—Jimmy DeForest—knows about boxing has been set down in one Complete Course that you can master just as thousands of others have, without stepping outside your home, or interfering with your work.

20 WEEKS—AND YOU ARE READY

20 weeks will make you a finished DeForest-trained boxer—ready to take your place along with the best of the lads who are real drawing cards for bouts at big fights. Soon thereafter, by applying the principles you have been taught, your name will rank as one of the clever boxers in your locality. DeForest-trained boys

who were unheard of a year ago, are now fast approaching championship titles, and several of them are actual contenders. Novices in the beginning, they are top-notchers now!

GOLDEN OPPORTUNITIES WITHOUT NUMBER

Now is the time to cash in on this marvelous opportunity. From Coast to Coast, the demand for boxing talent far exceeds the supply. Big Boxing Promoters are scouting everywhere for talent—paying \$100 and \$200 a fight. They are constantly writing us to recommend Jimmy DeForest-trained boys to them.

Weaklings have been made strong and men physically rebuilt, energy, strength and courage developed. Prominent men and leaders in all walks of life, including Prof. T. W. Seeley, famous Physical Culturist, box regularly to keep themselves fit. It will be a revelation to you.

Send for This Gripping Book Send today for this new famous book, "The Golden Age of Boxing," the most remarkable volume of its kind ever written, full of valuable information, photos of great boxers and pupils who became successes overnight. It contains a complete outline of the DeForest Course, week by week, with special picture charts used in most of the lessons. This book will thrill you and open your eyes to the marvelous opportunity that lies before you. Enclose 10c to cover cost of mailing, etc. Do it NOW and mail it AT ONCE, to

Jimmy DeForest Boxing Course
347 Madison Ave., New York City



Jimmy DeForest Boxing Course,
347 Madison Ave., Box 619, New York City
Without cost or obligation on my part, please send me your book, "The Golden Age of Boxing."

Name

Street No.

City State

LAW

Personal Instruction
By Mail Be a lawyer or law trained businessman. Qualify to earn \$2,500.00 to \$15,000.00 a year.

University Methods. TUITION LOW. EASY TERMS. Textbooks furnished. Practical and authoritative non-resident course. Endorsed by bench and bar. Prepares for bar or business. Over 60,000 students. PERSONAL INSTRUCTION. Guarantee to coach free any graduate failing to pass bar exams. Write today for particulars of low tuition offer now in force and book on law FREE. No obligation.

AMERICAN CORRESPONDENCE SCHOOL OF LAW
3601 Michigan Avenue, Dept. 135-A CHICAGO, ILL.

MEN WANTED TO LEARN

Motion Picture Projection

\$2,000 to \$4,000 a Year

Quickly learned. Short hours, big pay. Best equipped school in Michigan. Projectionists for Movie Houses and Road Shows.

MOVIE OPERATORS SCHOOL

61 Sprout Street, DETROIT, MICHIGAN

AT HOME LEARN TELEGRAPHY AT HOME



TEACH YOURSELF

In half usual time, at trifling cost, with the wonderful Automatic Transmitter, **THE OMNIGRAPH**. Sends unlimited Morse or Continental messages, at any speed, just as an expert operator would. Adopted by U. S. Government, and leading Universities, Colleges and Telegraph Schools. Catalog 6 cents.

OMNIGRAPH MFG. CO., 13-19 Hudson St., NEW YORK

EARN UP TO \$250 PER MO. SALARY as a Railway Traffic Inspector

I will help place as many men as I can qualify in this dignified, interesting profession where you are practically your own boss, see new sights and places each minute. It's outdoor, healthy work near home or in more distant cities. Promotions are rapid and opportunities numerous.

No Previous Experience Necessary

For eight years I have trained men for Traffic Inspection and upon completion of 3 months' spare time home study, I helped them get good positions. Any man of normal intelligence can qualify regardless of previous training. I will train you on the same basis and upon completion assist you to a position paying at least \$120 per month salary plus expenses—or refund your money.

Let me show you how Traffic Inspection will increase your income and give you a permanent profession. Send coupon today.

JAMES T. JARRELL
PRES. DIV. 2

Standard Business Training Inst.
BUFFALO, N. Y.

Standard Business Training Inst.
Div. No. 2
Buffalo, N. Y.

Yes, I'd like to know more about Traffic Inspection. Send me your free booklet "A Profession of Protection."

Name

Address



BIG WAGES

\$75 to \$150 Weekly—\$10 to \$25 Daily

Become a
McSWEENEY
Trained
AUTO MECHANIC

McSweeney graduates are earning up to \$10,000 a year. Learn in only a few weeks. Your money back if you are not perfectly satisfied. No schooling required. No book study. Mac's SHOP WAY Means Bigger Pay. You learn with real tools on real equipment. Only McSweeney operates three great schools for training auto and tractor mechanics. Choose either school.

Learn the ONE great "Open Shop" trade, get the kind of training that you can sell anywhere for BIG PAY. Become a trained Auto, Tractor and Electrical mechanic. No scabbing because no union to join. No strikes. No Apprenticeship. Steady work in America's greatest industry.

100,000 Men Wanted

—trained men who know how to keep America's 22,000,000 cars and tractors repaired. No other business offers such opportunities to men and boys.

SPECIAL!

Limited Reduced Price Tuition Offer Includes

Your Board and Railroad Fare

to Cincinnati, Cleveland or Chicago
No Extra Charges of Any Kind

The greatest, most liberal offer I have ever made. This offer will be withdrawn without notice. Don't miss it. Write quick for full particulars and my big 68-page book. Mail this coupon to my nearest school TODAY SURE.

McSWEENEY

AUTO, TRACTOR and ELECTRICAL SHOPS

Dept. 14TF, Cleveland, O., Chicago, Ill., Cincinnati, O.

Name.....

Address.....

City.....State.....



DRAWING IS A WAY TO FORTUNE

All Hated, a Persian farmer, sold his acres to go out and seek his fortune. He who bought the farm found it contained a diamond mine which made him fabulously rich. All Hated overlooked the great opportunity at his door to go far afield in search of wealth—which illustrates a great truth.

EARN \$200 TO \$500 A MONTH

If you like to draw, develop your talent. Your fortune lies in your hand.

Present opportunities for both men and women to illustrate magazines, newspapers, etc., have never been exceeded. Publishers are buying millions of dollars' worth of illustrations each year. The Federal Home Study Course has been prepared by such famous artists as Neysa McMein, Norman Rockwell, Charles Livingston Bull, Clare Briggs, Sidney Smith, Fontaine Fox and fifty others. Each student gets individual personal attention. No previous training is necessary. Every step is clear and simple.

FREE illustrated catalog on request. Shows work of students and testimonial letters. Complete outline of course with all the details. Just write your name and address in the margin and send it to us.

Federal School of Illustrating

6137 Federal School Bldg.

MINNEAPOLIS, MINN.



1,000 Hotel Positions Open!

HOTELS, restaurants, clubs, apartments, hospitals, institutions, schools and colleges everywhere need trained men and women. Over 70,000 high-class positions paying \$2,500 to \$10,000 a year open annually in the hotels of the United States. Nearly one and three-quarter billions of dollars' worth of NEW HOTELS, CLUBS AND INSTITUTIONS, being built this year will need over 200,000 trained men and women. Hotels start you at salaries up to \$3,500 a year, with living usually included. At any time there are over 1,000 hotel positions open.

Previous Experience Unnecessary

You can have one of these fascinating, big-pay positions. The Lewis Schools guarantee to give you the valuable knowledge that it has taken some of the most successful hotel men years to obtain. Age is no obstacle—young and old alike have equal chance for success. Past experience absolutely unnecessary. A common school education is all you need.

We train you in your spare time with the Lewis Simplified Study Plan and put you in touch with big opportunities. All of your training under the personal supervision of Clifford Lewis, Managing Consultant for over 225 hotels throughout the United States. Our students employed by leading hotels everywhere. Send today for Free Book, "Your Big Opportunity," showing how we can train you for one of these splendid positions, and explaining our Money-Back Agreement.

FREE BOOK COUPON

**LEWIS HOTEL TRAINING SCHOOLS,
Room AG-365, Washington, D. C.**


Send me without obligation the Free Book "Your Big Opportunity."

Name.....

Address.....

City.....State.....

At Last The Perfect Automobile Trouble Lamp!



Sells On Sight!!

SHAFFER MADE \$67 IN ONE DAY

**MAGNETIC
BASE...**

**STICKS
JUST
WHERE
YOU WANT
IT!!**

READ!

**What Other Men Are Doing
\$106.95 in 4 Days**

"Please ship by express 100 more lights. I have seven lights left out of the 100 received last Monday."
—Hicks.

22 Sales in 15 Minutes

Freeman writes: "The lights go like hot cakes. I sold 22 in 15 minutes the first day. Every car owner tells another."

Orders 1500 at a Time

"Please tell us when we can expect the balance of 1500 ordered. We can sell 1000 in 1500 per week, as your light is one of the most attractive specialties we have run across."
—C. J. Lewis.

**Emergency Makes a
Booster**

"I sold a light to one man who used it as a headlight last night when his burned out. Everything was fixed, and he had to drive 150 miles, 100 through mud and ruts, with only the BURNS MAGNETIC LIGHT to guide him. He is now a real booster for me now. Rush the order enclosed."—C. R. Seaman, Minnesota.

NO more fumbling in the dark to change a tire or adjust a balky motor. No more juggling feats with flashlights or dangerous matches! A clever new invention known as the BURNS MAGNETIC LIGHT now makes night repairs easy. Also useful as an emergency spot-light, tail lamp, etc. Salesmen report it the fastest selling device ever conceived for motorists. One of our men, Shaffer, actually made \$67 in one day selling to car owners! Willingham sold 23 in 3 hours—Dupon a dozen in 45 minutes. And no wonder—

Lightning Demonstration Makes Quick Sales

A powerful electro-magnet in the base of this beautiful light causes it to stick like glue to any iron or steel part of your car—right through paint, enamel, grease or oil. Throws its brilliant beam just where you want it, and leaves both hands free

to work with. Plug connection fits any car. More cord than you'll ever need. The magnetic feature permits a quick, convincing demonstration. Franko says under date of Feb. 3, 1927: "The lights sell themselves before I can complete my demonstration." Think what this will mean to you, with 22,300,000 cars on the highways this Spring, and every owner a live prospect!

\$75—\$150 a Week

Remember, the car owner is just one of your big markets. Dealers buy in big quantities, and your profits mount steadily upwards. Unusually large discounts to agents now in effect. Mail the coupon and let us tell you how you can test this amazing device without risking a penny. See how your friends and fellow-employees will enthuse over it—how easy it will be to take any number of orders right off the bat. The coupon brings full details and an illustrated description. Mail it today!

**Consolidated Specialties Corp.,
Dept. G-14, 21 W. Elm Street,
Chicago, Illinois.**


Yes, send me full details of your no-risk offer to test the BURNS MAGNETIC LIGHT, with special agents' prices and your Two-Way Selling Plan. This does not obligate me in any way.


Name.....

Address.....

City..... State.....

**Consolidated
Specialties Corp.
Dept. G-14, 21 W. Elm St.
CHICAGO, ILL.**





Here's **FUN** and **SPENDING MONEY**

How'd you like to have a pocketful of spending money all the time—\$5 or \$10 or even \$15 every week—all your own—and a lot of real fun at the same time? It would be great, wouldn't it? Well, you can have it! Hundreds of boys still in school are getting it! And they're no different from you except that they are "Cooke" Trained—they know how to do little electrical jobs in their spare time, after school hours, for which they get real money. I showed them how. And I'll show you, too, just as easily!

I Will Train You at Home

With my easily learned, fascinating Electrical Course, I'll train you at home like I've trained hundreds of other boys who are now successful men with jobs paying \$70 to \$200 a week! It's all done after school hours, without interfering with your school work or with your regular job if you're working. And it's more like play than study. But it's practical. It's sound. It's up-to-the-minute. It fits you thoroughly to land a Big-Pay job when school days are over. And it pays for itself as you learn and gives you plenty spending money, besides, through the spare-time work I tell you how to get, how to do and what to charge for.

Tools, Apparatus and Radio Course— Given Without Extra Charge

You'll need tools to do Electrical work with, so I give them to you—six big outfits of instruments and apparatus, and a real electric motor—a dandy layout that you can do any kind of spare-time work with—and it'll all yours for "keep." And not only that, but I also give you a brand new Course in Radio! All without extra cost!

Makes \$200 a Month

"Dear Mr. Cooke: When I began with you I was a sophomore in High School. Was making \$40 a month as grocery clerk. Now I am a \$200 a month electrician. Not so bad for a 17 year old boy, eh? Oliver P. Cooper 1131 Middle St. Ashland, Pa."

Mail Coupon Now!

You want lots of spending money! You want a Big-Pay job when you're through school! Sure, you do! Then don't wait a minute—don't hesitate a second—don't right this instant to get into this Big-Pay field where you can make \$2 or \$3 or more spare-time money every day while learning. Mail coupon at once and I'll send you my big 72-page book and a sample lesson, too—All FREE. See for yourself how easy it is. Fill in and mail coupon this minute!

**6 BIG
WORKING
OUTFITS
NO EXTRA
CHARGE**

Use this **FREE BOOK COUPON**

L. L. COOKE, Chief Instruction Engineer,
L. L. COOKE School of Electricity,
Dept. 01-A, 2150 Lawrence Ave., Chicago, Ill.

Send me your big Electrical Book, Sample Lesson and particulars about your Electrical Course and extra Radio Course. This does not obligate me in any way.

Name.....

Address.....

(This Coupon only for boys 15 years old or more)

I Teach by Mail

I CAN make a good penman of you at your home during spare time, no matter where you live or how poorly you now write. My simplified system has shown thousands of others the way to good penmanship during the past twenty years—it can and will do the same for YOU!

Beautifully Illustrated Book
"How to Become a Good Penman"
 It contains general information, with testimonials and beautiful specimens of penmanship showing what others have accomplished by the Tambllyn System. (Your name elegantly written on a card if you enclose stamp for postage) **FREE!**
F. W. TAMBLYN
 418 Ridge Bldg., Kansas City, Mo., U. S. A.

LAW

Become a lawyer. Legally trained men win high positions and big success in business and public life. Be independent. Greater opportunities now than ever before. Big corporations are headed by men with legal training. Earn \$5,000 to \$10,000 Annually.

We guide you step by step. You can train at home during spare time. Degree of LL.B. conferred. LaSalle students found among practicing attorneys of every state. We furnish all text material, including fourteen-volume Law Library. Low cost, easy terms. Get our valuable 108-page Law Guide and "Evidence" books FREE. Send for them NOW. LaSalle Extension University, Dept. 664-L, Chicago. The World's Largest Business Training Institution

Learn Photography at HOME

Earn \$3000 to \$10,000 a year. Prepare quickly during spare time. Also earn while you learn. New easy method. Nothing else like it. Send at once for free book "Opportunities in Modern Photography" and full particulars. Special offer open now.

AMERICAN SCHOOL OF PHOTOGRAPHY
 Dept. 135-A 3601 Michigan Ave. Chicago, U. S. A.

LEARN WATCHMAKING AND ENGRAVING

BY OUR PROFIT-SHARING PLAN
OUR GRADUATES SUCCEED

One of our Iowa students started in a very small way—now doing over \$30,000 a year. Another in Wisconsin, over \$10,000 the first year. Day or night classes. Call or write for FREE BOOK

Chicago School of Watchmaking, Dept. 2301, 4844 Lincoln Avenue, CHICAGO

Learn Advertising at HOME

Many of the highest paid men in the world are advertising men. You can learn easily and quickly at home during your spare time. We guarantee satisfaction. Bigger opportunities now in advertising than ever before. Constant demand for our graduates at splendid pay.

Send for FREE Book. Giving interesting information and vital facts—just what you want to know about advertising. Write today.

PAGE-DAVIS SCHOOL OF ADVERTISING
 Dept. 135A 3601 S. Michigan Ave., Chicago, U. S. A.



"GET ON" Uncle Sam's PAYROLL

Post Office Clerks
City Mail Carriers
Rural Mail Carriers

Railway Postal Clerks

Bookkeepers Stenographers
Income Tax Auditors
Clerks in Government Offices


at WASHINGTON, D. C., and ELSEWHERE

**\$1140⁰⁰
to \$3300⁰⁰ a Year**

These are steady positions. Strikes, poor business conditions, lockouts or politics will not affect them. U. S. Government employees get their pay for full twelve months every year. There is no such thing as "HARD TIMES" in the U. S. Government Service.

RAILWAY POSTAL CLERKS

Railway Postal Clerks now get \$1850 the first year, being paid on the first and fifteenth of each month. \$77.00 each pay day. Their pay is quickly increased, \$100 and \$150 a year, the maximum being \$2700 a year. \$112.50 each pay day. They get extra allowance for hotel expenses when away from home.



PAID VACATIONS

Railway Postal Clerks, like all Government employees, are given a yearly vacation of 15 working days (about 18 days). On runs they usually work three days and have three days off duty, or in the same proportion. During this off duty and vacation, their pay continues just as though they were working. When they grow old they are retired with a pension. As Railway Postal Clerks are continually traveling, they have an excellent chance to see the country. They are furnished with a railroad pass.

CITY MAIL CARRIERS—POST OFFICE CLERKS

Clerks and Carriers get \$1700 the first year regular, and automatically increase \$100 a year to \$2100 with further increase to \$2300. They also have 15 days vacation. Examinations are frequently held. City residence is unnecessary.

GENERAL CLERK

(Open to men or women 18 or over)

Salary \$1140 to \$1860 a year. Pleasant clerical work in the various departments and offices at Washington, D. C., and elsewhere throughout country.

WHAT WILL YOU EARN 5 YEARS FROM NOW?

Compare these conditions with your present or prospective condition, perhaps changing positions frequently, kicking around from post to pillar, no chance in sight for PERMANENT employment; frequently out of a position and the year's average salary very low. DO YOU EARN \$1000 EVERY YEAR? HAVE YOU ANY ASSURANCE THAT A FEW YEARS FROM NOW YOU WILL GET \$2700 OR MORE A YEAR, EVERY YEAR?

GET FREE LIST OF POSITIONS

Fill out the coupon. Tear it off and mail it today—now, at once. DO IT NOW—This investment of two cents for a postage stamp may result in you getting a U. S. Government Job.

**FRANKLIN
INSTITUTE
Dept. K-173
ROCHESTER,
N. Y.**

MAIL COUPON TODAY

Rush to me, entirely free of charge (1) a full description of the position checked below; (2) Send particulars telling how to get appointment; (3) Free copy of 32-page illustrated book, "U. S. Government Positions and How to Get Them," with list of positions now obtainable.

Railway Postal Clerk.....(\$1850-\$2700)
Post Office Clerk.....(\$1700-\$2300)
City Mail Carrier.....(\$1700-\$2100)
Rural Mail Carrier.....(\$2100-\$3300)
Clerk in Government Offices.....(\$1140-\$1860)
Bookkeeper.....(\$1320-\$2040)

Name.....

Address.....

Use This Coupon Before You Mislaid It—Write or Print Plainly



Go to High School at Home

You can secure a high school education right at home by studying the splendid new courses recently prepared by the International Correspondence Schools.

These courses are equivalent to the courses given in residential high schools. They have been specially arranged for men and women who wish to meet college entrance examinations, to qualify for a business position, or to make up the education they missed when forced to leave school too soon.

The College Preparatory Course, the High School Commercial Course and the High School English Course include English, algebra, ancient, medieval, modern and U. S. History, history, physiology, literature, geography, Latin, bookkeeping, drawing, geometry, shorthand, physics, chemistry, salesmanship, advertising, civics, trigonometry, economics, American business law, corporation finance, money and banking, business and trade economics, etc. A diploma is given at graduation.

The lessons are easy to understand and you will make rapid progress because you will be in a class by yourself and you will study under the guidance of instructors who are sincerely interested in helping you to get ahead and achieve the bigger things of life.

Just mark and mail the coupon and we will gladly send you interesting free booklets describing the High School Courses of the International Correspondence Schools or any other subject in which you are interested.

INTERNATIONAL CORRESPONDENCE SCHOOLS Box 5854-E, Scranton, Penna.

Without cost or obligation, please tell me how I can qualify for the position or in the subject before which I have marked an X:

- ☐ College Preparatory Course
- ☐ High School Commercial Course
- ☐ High School English Course
- ☐ High School Vocational Course
- ☐ High School Agricultural Course

- ☐ Business Management
- ☐ Industrial Management
- ☐ Traffic Management
- ☐ Business Law
- ☐ Banking and Banking Law
- ☐ Accountancy (including C.P.A.)
- ☐ Nicholson Cost Accounting
- ☐ Bookkeeping
- ☐ Private Secretary
- ☐ Spanish ☐ French

- ☐ Salesmanship
- ☐ Advertising
- ☐ Better Letters
- ☐ Show Card Lettering
- ☐ Stenography and Typing
- ☐ Business English
- ☐ Civil Service
- ☐ Railway Mail Clerk
- ☐ Common School Subjects
- ☐ Illustrating ☐ Cartooning

TECHNICAL AND INDUSTRIAL COURSES

- ☐ Electrical Engineering
- ☐ Electric Lighting
- ☐ Mechanical Engineer
- ☐ Mechanical Draftsman
- ☐ Machine Shop Practice
- ☐ Railroad Positions
- ☐ Gas Engine Operating
- ☐ Civil Engineer
- ☐ Surveying and Mapping
- ☐ Metallurgy
- ☐ Steam Engineering
- ☐ Radio

- ☐ Architect
- ☐ Architects' Blueprints
- ☐ Contractor and Builder
- ☐ Architectural Draftsman
- ☐ Concrete Builder
- ☐ Structural Engineer
- ☐ Chemistry ☐ Pharmacy
- ☐ Automobile Work
- ☐ Airplane Engines
- ☐ Navigation
- ☐ Agriculture and Poultry
- ☐ Mathematics

Name.....
Street.....
Address.....
City..... State.....

PREPARE FOR AN ART CAREER

—thru the only school operated as a department of a large art organization. Commercial Artists trained the "Meyer Both Way" earn as high as \$10,000 per year. We today have hundreds of students who had previously studied art elsewhere. Why? Because your instruction is based upon our everyday experience in meeting the art needs of leading advertisers. Home study instruction. Write for illustrated book telling of the success of our students.

MEYER BOTH COMPANY

Michigan Ave. at 20th St., Dept. 16, Chicago, Ill.

Don't Envy The Plumber BE ONE!

\$11.00-\$16.00 PER DAY and work **EVERY day**, is the Plumber's wage.

Every skilled workman will tell you that Plumbers have the best of it. WINTER and SUMMER the Plumber is busy at top wages. No skilled Plumber is ever out of a job—compare his opportunities with any trade, plus the opportunities of having your own shop.

We teach you Plumbing with **TOOLS** (not books) under Licensed Master **PLUMBERS** in one of the finest equipped schools in America. We make you a Plumber, every branch is taught thoroughly—Lead Work—Blue Print for plan reading—all other tricks.

LEARN IN 8 to 12 WEEKS without previous experience. If you are making less than \$60.00 a week you owe it to yourself to investigate. Get FREE catalog that tells in pictures and words how we teach this trade. Special rates now.

UNIVERSAL PLUMBING SCHOOL
2030 Troost Ave. KANSAS CITY, MO.

YMCA

Learn Auto Mechanic, Auto Electrical, Battery, Machine, Electrical, Radio Mechanic, Tiling, Bricklaying, Plastering, Plumbing, Welding, Drawing, Estimating, Show Card, Sign Painting, Window Dressing. Write for Catalog 50.

BROOKLYN ENGINEERING INSTITUTE
(Operated by Bedford Br. Y.M.C.A.)

1125 Bedford Ave., Brooklyn, New York City.

LEARN WATCHMAKING

and become independent. We help you secure a position.

Easy to learn. Send for **FREE CATALOG**.
ST. LOUIS WATCHMAKING SCHOOL, Dept. 5, ST. LOUIS, MO.

FOREST RANGERS

MEN, GET FOREST RANGER JOB; \$125-\$300 MO. AND HOME FURNISHED; PERMANENT; HUNT, FISH, TRAP.

FOR DETAILS, WRITE
NORTON, 226-B, McMANIS BUILDING, DENVER, COLORADO



WHY NOT spend Spring, Summer and Fall gathering butterflies, insects? I buy hundreds of kinds for collections. Some worth \$1 to \$7 each. Simple outdoor work with my instructions, pictures, price-list. Send 10 cents (not stamps) for my illustrated Prospectus before sending butterflies.

MR. SINCLAIR, DEALER IN INSECTS.
Dept. 6, Box 1424, San Diego, Calif.

Skin Troubles

Cleared up—often in 24 hours. To prove you can be rid of Pimples, Blackheads, Acne Eruptions on the face or body, Barbers' Itch, Eczema, Enlarged Pores, Oily or Shiny Skin, simply send me your name and address today—no cost—no obligation. **CLEAR-TONE** tried and tested in over 100,000 cases—used like toilet water—is simply magical in prompt results. You can repay the favor by telling your friends; if not, the loss is mine. **WRITE TODAY.**
E. S. GIVENS, 428 Chemical Bldg., Kansas City, Mo.

Men Wanted

Get This New 74-Page Book Today. It's FREE. The First Step to a Big Pay Job.



Garage	\$150 to \$400
Tractor	\$10 a day
Electrician	\$225
Mechanics	\$10 a day
Chauffeurs	\$90 to \$150
Truck Drivers	\$125
Tire	\$100 to \$200
Welder	\$140 to \$200
Battery	\$150 to \$200

You, Too, Can Have Money in Bank \$5,000 Home



E. J. Sweeney

The SWEENEY SCHOOL

with over 65,000 graduates, trains you in a good trade. What appeals to you? Auto repairing—bus line driving—garage—repair shop—tire shop—welding—radio broadcasting—auto painting? Write me today—GET THE FACTS—about wages—profits—opportunities and HOW THE SWEENEY SYSTEM is equipped to give you successful training. Auto Mechanics make \$50 to \$100 a week. Learning is easy by the Sweeney System of Practical Training. Use tools not books. Be an auto mechanic—driver—truck driver—repair man—tire man—demonstrator. Own your garage or repair shop. Run a welding and vulcanizing shop. You can learn these trades separately or in a combined course.

Sweeney System "Learn by Doing"

If you are mechanically inclined, if you like to work with tools, you will learn under the "SWEENEY SYSTEM" by actually doing the work on the most complete gas engine and electrical equipment. Over \$200,000 invested. \$50,000 Radio Station WHB. You'll get dirty and greasy, but you'll learn through the SWEENEY SYSTEM OF PRACTICAL TRAINING that fits you for the big pay jobs waiting for Sweeney Trained Men.

World's Greatest Business

in all my years of teaching with tools, not books, and of training men for high paid jobs, there has never been a time when it was so easy for the trained man to cash in immediately on his work. Over 20 million cars and trucks now running, and annually 4 million new cars poured into the market; good roads everywhere; bus lines, city and country; repair shops, garages, battery and tire stations needed; electrical workers, painters, welders, mechanics, drivers find openings at high pay every place with certainty of sure continued employment. The Automobile industry has taken the world by storm, and the man who knows his job need never worry about assured success. Coming to the Sweeney School means that in a few short weeks you learn from the ground up in the shortest time, at less expense, by proven methods, and under the best surroundings.

Will You Work for \$10 a Day?

A tremendous demand for welders has sprung up over the country, both in automotive lines and also in Oklahoma where they can't get pipe welders for love or money. These jobs pay \$10 up and the trade is easily and quickly learned. I have taken our welding department and enlarged it into a special course so if you want a GOOD TRADE QUICK and a sure fire big pay job, here's your chance. All practical work and when you've finished, jobs are hunting the men—particularly in the booming southwest.

LEARN A TRADE
Sweeney
AUTOMOTIVE & ELECTRICAL SCHOOL
3831 SWEENEY BLDG. KANSAS CITY, MO.

Listen man: Do you want money? Do you want independence? Do you want a sure trade that pays \$50 a week up? Do you want to travel and see the world? How would you like a good driving job? Or a place in a repair shop? Or your own service, tire or battery station?

Here's a letter that shows what you can do. \$10,000 CASH says it is true and genuine. Why man—I can show you \$500 or a thousand dollars just as good. YOU may not have to go broke to pay for your training. But even if you do, what's the odds? See how well it paid Hawkins to go broke.


Dear E. J.: All I can say is I was broke when I left Kansas City—had only 25 cents over my ticket to Meridian; came here—went to work in the Dodge Service Station. Then in N. East Service Station—then opened up a service place of my own. Now moved in a larger place—4 block square. Keeping six mechanics busy. Just built a nice home over \$5000. Own my own car, and wife has hers—sedan. Owe no one, have a good stock on hand and money in the bank. I can honestly say—it was Sweeney's wonderful training that did it. Before I went to Sweeney's I worked in a dry goods store as clerk—drawing one of top salaries, \$22.50 a week. Now the expenses of my three kids in boarding school are more than the \$22.50 a week I used to make.

I am still with you in the air at night—using an eight tube set, Western Electric amplifier. A. J. Hawkins, Meridian, Miss.

COME RIGHT NOW

Never Before Have I Made Such an Amazing Offer. I now make it possible for you to come to this Million Dollar Sweeney School Right Now.

FREE CATALOG AND SPECIAL OFFER



Get my big FREE 74-page catalog. It shows hundreds of actual photographs of men at work in my magnificent new school. Tells all about wages, profits, opportunities in auto business. Explains step by step how you learn. Interesting letters from graduates telling how they made good. Shows how men come from all over the world to this big school. Makes you want to join the crowd. Tells everything you want to know. I will gladly send you a copy beautifully illustrated. I'll tell you how to get into business for yourself. No colored students accepted.

E. J. Sweeney, President

EMORY J. SWEENEY, President
3831 Sweeney Building, Kansas City, Mo.

Send me free, without any obligation, your catalog and Special Offer!

NAME.....

P. O.

STATE..... AGE.....

WOW! SEE Those Muscles GROW!

TALK about putting on muscle! Look at those two pictures at the right. That's just one of the boys I've made over. Yes, sir, changed him almost overnight from a puny weakling into a powerful, two-fisted HE MAN.

Want me to do the same for you? Just give me a few minutes a day in your own home. In 30 days I'll cover your body from head to foot with the finest set of muscles you ever saw! Don't take my word for it, I GUARANTEE you big muscles.

Come on, friend, don't go plugging along with half your spark plugs dead and your engine missing. I'll make you hit on ALL SIX. Say, I'll give you so much speed and

pep that when you start to mix it with the other boys you'll look like the "Mystery S" racing a steam roller.

My amazing secrets of muscle-building have built champions and strong men all over the world. I don't care where you live—how old you are—whether you're big or little. Just follow my personal directions for a few minutes a day, and you'll fairly SEE your muscles grow! I'll load your arms with muscle—I'll deepen your chest, broaden your shoulders, give you the legs of a six-day bike racer. Boy, you'll be proud to put on a bathing suit!

FREE "BETTER BUILT BODIES"

My Amazing New Big Book—Check Full of Muscle-Building Facts

I want every reader of Popular Mechanics to have this great book. It's crammed with actual photographs showing MIRACLES WORKED IN MUSCLE—and Titus' own wonderful secrets of MAN-BUILDING. Also details of my \$2,000 Muscle-Building Contest. Let me send YOU a copy FREE. The most valuable book you ever read. No obligation. Just shoot me your name and address on the coupon.

The One and Only **TITUS** 105 E. 13th St. New York City



BEFORE



AFTER 30 DAYS OF TITUS TRAINING

He looked like a mosquito when he first read a Titus ad. The boys in his town called him "Sparrow" and he was the butt of every joke they could think of. He was too weak to defend himself and had to take it all. But they don't play jokes on him any more. He took the TITUS course at home without letting anyone know. Some big bruiser started one of the old jokes, "Smash!!" That's a thrill that comes once in a lifetime. Let me give it to YOU!

TITUS (Dept. P-115),
105 E. 13th St., New York, N. Y.

Please send me FREE your wonderful new Book, "Better Built Bodies." Also details of your \$2,000 Muscle-Building Contest.

Name.....

Address.....

Town.....State.....

What Is Holding You Back?

Pelmanism increases the earning power of the mind as physical training develops muscle. Doubled salaries in six months not at all unusual. Strengthens your weak links; awakens sleeping powers.

Scientific Mind Training—FREE

If you are not increasing your earnings \$1,000 every year, send today for free book "Scientific Mind Training," showing how Pelmanism has helped 600,000 people.

THE PELMAN INSTITUTE OF AMERICA
Dept. 66, 19 West 44th St., New York

Music Lessons UNDER MASTER TEACHERS At Home

Complete Conservatory Course by Mail
Wonderful home study music lessons under great American and European teachers. Endorsed by Paderewski. Master teachers guide and coach you. Lessons a marvel of simplicity and completeness.

Any Instrument Written name of course you are interested in: Piano, Harmony, Voice, Public School Music, Violin, Cornet, Mandolin, Guitar, Banjo or Reed Organ—and we will send FREE CATALOG—SEND for it NOW!
University Extension Conservatory, 393 S. Dearborn St., Chicago

YOU CAN OIL PAINT

Amazing new method teaches men or women to earn after first lesson. OIL PAINT photos—portraits, landscapes or art subjects. Earn \$18 to \$30 and more a week. OIL PAINT OUT-FIT GIVEN. Send now for free illustrated book. PICTORIAL ART STUDIOS Inc. Dept. MP, 2026 No. Clark St., Chicago

STAMMERERS
Learn to speak correctly, increase earning power! Our methods invariably successful. Booklet Free
SAMUEL A. ROBBINS, 419 Boylston St., Boston, Mass.

LEARN CARTOONING




Successful cartoonists earn big salaries. Many of the most popular cartoonists of today learned to draw in their spare time, at home through the Landon Course of Cartooning and now earn \$75 to \$200 or more per week. The Landon Picture Chart Method of teaching ORIGINAL drawing makes cartooning easy to learn. Hundreds of sketches like the above explain every step in creating ORIGINAL heads, figures, animals, and every detail of cartoon drawing. Send 6c in stamps today for sample Picture Chart and full description of this widely known course, also long list of successful Landon students. Complete information showing possibilities for you will be forwarded. Please state your age.

Address C. N. Landon, Director The Landon School, 738 National Building, Cleveland, Ohio

Former Students Who Are Now Successful Comic Strip Artists

- BLOSSER—Now drawing "Freckles and His Friends."
- BYRNES—Now drawing "Reg'lar Fellers."
- BRANNER—Now drawing "Winnie Winkle."
- LOCHER—Now drawing "Cicero Sapp."
- TAYLOR—Now drawing "Mom'n Pop."
- EDWINA—Now drawing "'Cap' Stubbs."
- CRANE—Now drawing "Washington Tubbs II."
- ETHEL HAYS—Now drawing "Flapper Fanny."
- PAUL FUNG—Now drawing "Gus & Gussie."

5 ELECTRICAL Job Tickets actually FREE!



Training Built by 29 Noted Engineers

This is not a one-man, one-idea school. 29 famous Engineers and Executives of the following corporations and universities helped me make Dunlap-training complete and up-to-date.

1. General Electric Co.
2. Commonwealth Edison
3. Crocker-Wheeler Co.
4. Cutler-Hammer
5. American Tel. & Tel. Co.
6. Westingh. El. & Mfg. Co.
7. Western Electric Co.
8. Underwriters Lab., Inc.
9. Columbia University
10. Dartmouth College
11. Massachusetts Inst.
12. Lehigh University
13. University of Vermont

AND MANY OTHERS

to prove this home-training will prepare you for a good job and a raise in pay!

Get these five job-tickets. Look them over. Test your own ability to master Electricity at home in spare time. See for yourself how every fact has been simplified. See what thousands of men have paid millions of dollars for, to help them earn BIGGER PAY. Uncover some of the mysteries of Electricity, and see why millions of men are so fascinated by it. Don't send a penny, don't enroll—just mail the coupon.

Go Into ELECTRICITY!

Thousands of jobs open at \$60 to \$125 a week. My training prepares you to fill them. Superintendents of Power Plants Wanted. Chief Electricians Wanted. Electrical Experts Wanted in Radio, Electrical factories, Auto Plants, Telephone and Telegraph Systems, etc.

I Will make this Contract with You!

Read it. This million dollar institution stands back of this agreement to PREPARE you to fill a well-paid Electrical Job, and then to help you FIND the job—or to refund the small amount charged for your training!

7 Costly Electrical Outfits Given!

I send you absolutely without extra cost, as a part of this training, 7 costly outfits of standard size tools and materials, so you learn Electricity BY DOING actual Electrical jobs. One of these outfits is a \$10 Electric Motor—a real motor and generator, the same type as the big fellows in a power plant. I send it to you "knockdown" and have you wind the field and armature and assemble it. That's the way I teach every branch of Electricity! House-wiring, Electric Light, Radio, and Motor outfits included.




\$10 Motor Given

Your name here.....
When you enroll for my home-training in ELECTRICITY I agree to give you:

1. Complete training, including Electrical Engineering, Ignition, Radio, etc.
2. Seven outfits of standard tools and materials, including a \$10 motor.

3. I WILL HELP YOU GET A GOOD JOB AND A RAISE IN PAY.
4. —or I will refund every cent of your money.

By *Chief Engineer Dunlap*



AMERICAN SCHOOL
—the Million Dollar Educational Institution



Free Job Service!

for STUDENTS and GRADUATES. This JOB SERVICE keeps in touch with great Electrical employers all over America. The day you enroll, this Job-Service Department registers you, finds out what kind of job you want, where you want to work, etc. And when you apply for the job you want, we back you with our recommendation and help you make good in it after you get it.

WRITE Me Immediately!

If you have reached the point where you realize YOU MUST train and specialize to get anywhere, write me immediately! I will show you the wonderful opportunities, the enormous salaries, the many openings waiting in this billion dollar industry. I'll tell you about our sensational combination TRAINING-AND-JOB offer which practically assures your success. Mail coupon and get 5 Free Electrical Job-Tickets and complete information.

CHIEF ENGINEER DUNLAP, Electrical Division

AMERICAN SCHOOL Drexel Avenue and 58th Street
Dept. EA-74 CHICAGO

5 Job Tickets actually FREE!

Chief Engineer Dunlap, Electrical Division

AMERICAN SCHOOL

Drexel Ave. & 58th St., Dept. EA-74 CHICAGO

Send me your combination TRAINING-AND-JOB offer, 5 Free Job-Tickets, facts about opportunities in Electricity, etc.

Name _____

Address _____

Occupation _____ Age _____

Sensational Typewriter Offer



The World's Only Ball Bearing Typewriter

NEVER has there been such a typewriter bargain on as easy terms! A genuine Silent Ball Bearing L. C. Smith at a 40% savings!

Only the L. C. Smith has all these features:

Ball bearings (936 of them) at all points of wear. All the writing visible all the time. Non-shift carriage. 2-color ribbon. All the latest operating conveniences. Beautiful—renewed.

If you decide to keep it only **\$3.00** DOWN BALANCE EASY TERMS

Guaranteed 5 Years

Money cannot buy a better typewriter. U. S. Government bought 50,000. The choice of railroads, big corporations like the Standard Oil Co., etc., because of its exclusive ball bearing feature. Easiest running, longest wearing of typewriters.

Send No Money!

Just mail coupon. Without delay or red tape, typewriter will be shipped you. Use it 10 days. See how speedy and easy it runs—the perfect work it turns out. If not delighted, return at our expense. You'll want to keep it. You can, for \$3 down and \$5 monthly. Now is the time to buy. \$3 worth of extras free. Send coupon now before offer is withdrawn.

40% SAVED by Using this Coupon

SMITH TYPEWRITER SALES CORP.
116-360 E. Grand Ave., Chicago

Ship me the L. C. Smith, P. O. B. Chicago. On arrival I'll deposit \$3 with express agent. If I keep machine, I'll send you \$5 a month until the \$25.00 balance of \$28.75 price is paid; the \$3 to remain with you until then. I am to have 10 days to try the typewriter. If I decide not to keep it, I will repack and return to express agent, who will return my \$3. You are to give your standard 5-year guarantee.

Name

Address

City State

Employed by

WRITE for big book on wrestling. Tells secrets you've always wanted to know.



Learn How to WRESTLE

In Your Own Home By Mail

Yes, learn to become an expert wrestler right in your own home, by mail, from the greatest wrestler the world has ever known. Be an athlete, be strong, be healthy. Learn how to throw and handle big men with ease. Learn to defend yourself. Learn from the World's Champions.

Farmer Burns and Frank Gotch Secrets

Farmer Burns, who taught Frank Gotch—trainer of SEVEN World's Champions, will teach you Scientific Wrestling—Physical Culture—Jiu-Jitsu and Self-Defense. Write today for big wrestling book, illustrated with many fine pictures—shows holds and secret tricks used by champions. Tells how easy it is to learn the marvelous breaks, falls and holds that make you an expert. Send today for this wonderful book. Enclose only 10c to help cover cost of wrapping and postage. Be sure to state age. No obligation.

Farmer Burns, A-177 Ry. Exch. Bldg., Omaha, Neb.

Send Now for Farmer Burns' Book



PLAY PIANO BY EAR

Master Jazz or Ragtime in 90 days by famous Niagara Method. \$5,000 pupils. Big, established school. Certificate given on graduation. Send dime today for booklets: "Entertaining at Piano" and "The Niagara Secret." Niagara School of Music, Dept. B, Niagara Falls, N.Y.



From \$1,800 to \$10,000 in Four Years

Thanks to Higher Accountancy

"LaSalle training in Higher Accountancy has enabled me in four years to increase my business income more than 600%." So writes John H. Lansing, Public Accountant, Income Tax Specialist, and prominent citizen of Amsterdam, New York. "When you stop to consider that the average bookkeeper does not receive more than \$40 a week," he continues, "it is obvious that \$10,000 a year has advantages well worth the consideration of any ambitious man or woman. I shall always be grateful to LaSalle for the help it has given me in building a greater income." Mr. Lansing was 43 when he enrolled with LaSalle, and at the time was earning less than \$2,000 a year.

Send for This Book—It's Free

Are you ambitious to make a real success in business—to fit yourself for positions paying \$3,000, \$5,000, \$10,000 a year and even better? Then you will find LaSalle's 64-page book, "Accountancy, the Profession that Pays," of the greatest help and inspiration—and—LaSalle will send it to you FREE. For the sake of a brighter future, clip and mail the coupon NOW.

—Find Yourself Thru LaSalle!

LaSALLE EXTENSION UNIVERSITY

The World's Largest Business Training Institution

Dept. 664-HR

Chicago

I should be glad to have details of your salary-doubling plan as applied to my advancement in the business field checked below. Also a copy of "Ten Years' Promotion in One," all without obligation.

Higher Accountancy


- ☐ Business Management
- ☐ Modern Salesmanship
- ☐ Traffic Management
- ☐ Railway Station Management
- ☐ Law—Degree of LL.B.
- ☐ Commercial Law
- ☐ Industrial Management
- ☐ Factory Management
- ☐ Banking and Finance

- ☐ Modern Business Correspondence and Practice
- ☐ Modern Foremanship and Production Methods
- ☐ Personnel and Employment Management
- ☐ Expert Bookkeeping
- ☐ C. P. A. Coaching
- ☐ Business English
- ☐ Commercial Spanish
- ☐ Effective Speaking

Name

Present Position

Address



WHY YOU SHOULD LEARN MODERN BARBERING

Barbering will enable you to travel and see the World. A job in every town.

Barbering can be used as a stepping stone to higher professions. It will make your living—while studying Medicine, Law, etc.

Barbering coupled with Beauty Culture has a wonderful future—protected—professionalized.

Barbering will soon be harder to get into on account of Education and Restrictions.

Barbering in addition to a good salary—pays in commission and tips more than most men earn.

Address Branch nearest you. (Street address not needed.) For Booklet B-6.

The Moler System of Colleges

Chicago, Ill.	Milwaukee, Wis.	Denver, Colo.
St. Louis, Mo.	Memphis, Tenn.	Omaha, Nebr.
Cincinnati, Ohio	New York, N. Y.	Atlanta, Ga.
Detroit, Mich.	Kansas City, Mo.	Dallas, Texas
New Orleans, La.	Cleveland, Ohio	


LEARN TO Mount Birds

We teach you At Home by Mail to mount Birds, Animals, Heads, Tax Furs and Make Rugs. Be a taxidermy artist. Easily, quickly learned by men, women and boys. Tremendously interesting and fascinating. Decorate home and den with beautiful art. Make big profits from Spare Time Selling Specimens and Mounting for Others.

Free Book—Yes absolutely Free—beautiful book telling all about how to learn taxidermy. Send Today. You will be delighted. Don't Delay! Northwestern School of Taxidermy, A-177 Elwood Bldg., OMAHA, NEB.



MUSIC LESSONS IN YOUR HOME



Write today for our **FREE** booklet. It tells how to learn to play Piano, Organ, Violin, Mandolin, Guitar, Banjo, etc. Beginners or advanced players. Your only expense about 2c per day for music and postage used. **American School of Music, 51 Manhattan Bldg., Chicago**

LAST CALL

Your Last Chance

You Must Act Now to Save \$4.00

Get your Croft **LIBRARY OF PRACTICAL ELECTRICITY** now before the price is raised. Increased costs are making it necessary to raise the price of this famous library to \$23.50. If you act now instead of waiting, you save \$4.00. Act today! Mail the coupon now!

The Croft Library of Practical Electricity

A combined reference library and home study course, 8 volumes, 3000 pages, 2100 illustrations, flexible binding, \$1.50 in ten days and \$2.00 monthly for nine months—only 7 cents a day.

The man who gets anywhere in any line of endeavor is the man who **KNOWS**. And generally the more he knows the more he earns. For the man who wants to know, there is nothing better than these eight volumes packed to the covers with sound, helpful information on every phase of electricity from first principles to central station work.



SEE IT FREE—

No obligation to Purchase


By just filling out and returning the coupon below you will have, at no cost to you whatsoever, a practical, useful set of books for 10 days' Free Examination. We take all the risk—pay all charges. You assume no obligation—unless you decide to keep the books. Send the coupon **NOW** and see the books for yourself.

FREE EXAMINATION COUPON

McGraw-Hill Book Co., Inc., 370 Seventh Ave., New York
Send me for 10 days' free examination the Croft Library of Practical Electricity. If satisfactory I will send you \$1.50 in 10 days and \$2.00 monthly until the special price of \$19.50 is paid. If not wanted, I will return the books at your expense.

Signed.....
Address.....
City and State.....
Position.....
Employer..... P. M. 6-127

10 DAYS' TRIAL
SEND NO
MONEY



NO
NEED
FOR A
NEW
PHONOGRAPH

New PHONIC Reproducer

makes an up-
to-the-minute **\$3⁸⁵**
Phonograph out
of your old one!

Direct
from
Factory

Now at last you can say goodbye to the squeaky, nasal, rasping metallic tone of your phonograph. Now you can have the beautiful, natural, full-rounded tone of the expensive new machines which are startling the world. Yet you need not buy a new phonograph if you have an old one. The reproducer is the **HEART** of any phonograph—and the New PHONIC reproducer makes your old phonograph like an entirely new one. Based on the new PHONIC principle. Makes you think the orchestra or artist is in the same room.

Gives the New Tone and Volume of Latest New Phonographs

Tones never before heard are clearly distinguished when the new PHONIC reproducer is used. Test it on an old record. Hear the difference yourself. Listen to the deep low notes and the delicate high notes. Hear how plainly and clearly the voice sounds. Note the natural tone of the violin and the piano, and the absence of "tinny" music. You will be amazed. The new PHONIC reproducer is ideal for dancing or for home entertainments. Its volume is almost double that of the ordinary reproducer.

10 Days' Trial—Send No Money

You cannot realize how wonderful the New PHONIC is until you hear it. That is why we want to send it to you on 10 days' trial. Send no money now—just the coupon. Pay the postman only \$3.85 plus a few pennies postage when the New PHONIC arrives. Then if you are not delighted, send it back within 10 days and your money will be refunded. If sold in stores the price would be at least \$7.50. Our price only \$3.85. Over 350,000 people have dealt with us by mail. You take no risk. Mail the coupon now for 10 days' trial. **BE SURE TO STATE THE NAME OF PHONOGRAPH YOU OWN.**

NATIONAL MUSIC LOVERS, Inc., Dept. 586
327 West 36th Street, New York

Please send me a New PHONIC reproducer for.....

I will pay the postman \$3.85 plus few cents postage. If I am not satisfied after trial, I will return your reproducer within 10 days and you guarantee to refund my money. *Outside U. S. \$4.10, cash with order.*

Name.....

Address.....

City..... State.....



Can You Fix It?

Repair any auto fault, learn how NOW. You can do it easily in this new simple way.

These FIVE Big Books are up to the minute on automobile engineering subjects; chock full of little known facts about construction, operation and repairs. Electric wiring treated in complete detail—illustrations and diagrams make everything clear and easily understood by anybody. The most interesting and most practical set of books ever written on modern automobile engineering. Whether you want to fit yourself for garage owner, repair expert or merely wish to know more about your car, you will realize the value of these splendidly bound volumes. This is the new 1927 Edition with 70 new and up-to-date wiring diagrams.

"NO MONEY" OFFER

An amazing new plan of distribution brings these books to you for examination without one cent of payment to us. We don't ask a penny of you, but ship the books to you FREE. Look them over—read them as much as you want to; note the splendid photographs and drawings and then if you decide you want them, send us \$2.00 and then only \$3.00 a month until only \$24.80 is paid. That is all; nothing more to pay us. If you send NOW we will include

Consulting Membership—FREE

Yes, we actually give you a certificate of membership in the AMERICAN TECHNICAL SOCIETY which entitles you to free consultation on any subject related to Automobile Engineering. Eighteen specialized experts are at your disposal—ready at any time to help you. With this library and this membership you ought to be able soon to know all there is to be known about autos. Note:—In addition to all this, those who send now will be entitled to the services of our EMPLOYMENT DEPARTMENT without charge. We are in daily contact with firms all over the country who need good men and are willing to pay big. This service costs you nothing. Don't miss this special offer. Send now.

American Technical Society,
Automobile Division, AA-19A, Chicago, Illinois

You may send me your new complete Automobile Engineering library (1927 edition) 5 big volumes bound in flexo covers for ten days' Free Examination. If satisfied, I will send you \$2.00 then and \$3.00 per month until the special low price of only \$24.80 is paid, otherwise I will return them and owe you nothing. Include membership certificate and free employment service offer.

Name.....
Address.....
City.....State.....
Reference.....

MEN INTERESTED IN RADIO Big money for your spare or full time. Give a service to radio owners and autoists. No machines, no equipment; something all need once a month anyhow. EVENINGS ALONE PAY YOU SEVERAL DOLLARS EACH—full time much better. No technical knowledge required—we teach everything.

Enclose 25c for sample to try and full details.

ARVED COMPANY, Dept. 10, GROSSE ISL., MICH.

Why Good Dancers Are Popular

EVERYONE admires and wants to dance with the person who knows the latest steps. There is no need of being a wallflower! By my remarkable new easy method **anyone** can learn the newest dances at home in a few hours. Much less expensive than from a personal teacher. No music or partner needed. So simple even a child can learn quickly. **Almost one half million have learned dancing by mail.** Your own success is guaranteed.



Posed by
Edna
Murphy
and
Arthur
Murray

To prove I can quickly and easily make you an accomplished dancer, I will send you **FREE** my 32 page book and **TEST LESSON**. To pay the cost of mailing, handling, etc., send 10c. Learn in private—surprise your friends. Act now and be a good dancer soon!
ARTHUR MURRAY, Studio 717, 7 East 43rd St., NEW YORK

AGENTS CAN OPENERS MUST GO!

\$4.50 AN HOUR

Just Showing New DEVICE.

NEW invention now makes old style can openers obsolete. Flips entire top out of any size can, round, square or oval, at turn of crank. Simple. Absolutely safe. Lasts a lifetime. Housewives wild about it. Agents cleaning up fortunes.

FREE OUTFIT Big Free Offer now ready for first 300 men. Territories being snapped up fast. Send quick for details. Address

CENTRAL STATES MFG. CO.,
4500 Mary Ave., Dept. 5-700, St. Louis, Mo.

Win a Buick
or \$1500.00 In Cash



SOLVE THIS PUZZLE

2	21	9	3	11	7	9	22	5	14
---	----	---	---	----	---	---	----	---	----

The numbers in the squares above spell two words. A is 1, B is 2, C is 3, etc. Can you make out what they are? Send me your answer right away and I will immediately award you 25,000 votes and tell you how to win, absolutely free, a latest model Buick Sedan worth \$1,195.00. We are also giving away a Chevrolet Coupe worth \$625 and many other valuable prizes and hundreds of dollars in cash. In case of ties duplicate prizes will be awarded each one tying.

\$305 Extra for Promptness

In addition to many Grand Prizes a special prize of \$305 in cash will be given for promptness. Winners may have cash instead of prize won, if preferred. First prize winner can have \$1,500 cash or a Buick Sedan worth \$1,195 and \$305 in cash. Hurry! Solve the puzzle, clip this ad and send it to me right away with your name and address plainly written. Everybody rewarded.

Address: **WILLIAM LEROY**
Dept. A-177, 315 S. Peoria St., Chicago, Ill.

NOW YOU CAN STUDY MUSIC AT HOME

earn
\$75.00
to
\$200.00
each week

With a nationally famous artist as your teacher you can learn to play classical or popular music on your favorite instrument. We guarantee our personal teaching method. Both advanced and elementary courses.

Write for catalogue
CONN NATIONAL SCHOOL OF MUSIC, INC.
506 S. Wabash Ave., Dept. 516, Chicago



"They say me \$300 a month."
John Savadge
Dobe Trained Draftsman



"I received \$2000.00 a month."
Carl Dupree
Dobe Trained Draftsman



"I make \$130.00 a week."
C.E. Cermack
Dobe Trained Draftsman



"I earn \$7000 to \$8000 per year."
A.H. Hamner
Dobe Trained Draftsman

\$50,000
They earn a year!




"I am averaging over \$400 a month."
Arthur Edwards
Dobe Trained Draftsman



"I make \$475 a month."
J.C. Stoops
Dobe Trained Draftsman



"I make \$1000 a month."
O.V. Bowen
Dobe Trained Draftsman



"I am now earning \$300 a month and I haven't finished course yet."
L.V. Broughton
Dobe Trained Draftsman

They Learned Drafting at Home from Dobe ~ So Can You!

Here are eight successful Dobe-trained draftsmen. The total yearly earnings of these eight men are \$50,000. All of them took Dobe's Simple, Easy, Quickly-learned Drafting Course. All became successful draftsmen because Dobe trained them in the actual execution of real drafting work. Only Dobe uses the practical, simple, easily-mastered Dobe method. Dobe teaches drafting by giving his students the day in and day out work which they are compelled to do when they become draftsmen.

And you learn all this at home. You don't travel a long way to a distant city. You don't give up your present job. You learn drafting the Dobe way by using your spare time only. No matter what your job is now, you should write for Dobe's great book, "Successful Draftsmanship" and the names and addresses of many other big-earning Dobe trained men. Before the men pictured above began to earn the real money Dobe trained them for, they were making from \$12 to \$25 a week. Think that over. How much are you making today?

Maybe you can't do as well as these men have done—but you've got to admit that it is worth a try. Don't you think so?



Here Are the Tools You Get

Everything you need to learn and work as a draftsman. These are the same tools that Savadge, Dupree, Cermack and all the others got. Dobe has trained more than 10,000 men. There are Dobe trained draftsmen in every state and in every big city.



Write for Free Book "Successful Draftsmanship"

Send a postcard or a letter or mail the coupon for the Free Book, "Successful Draftsmanship", which Dobe has written for the benefit of all men who are interested in drafting. It's a great book about a great profession—and you ought to read it. These eight men are certainly glad they read it and took Dobe's word that he could make real draftsmen out of them. No matter who you are, where you are, or what your job is you should send for this book NOW. You should send for it unless you are making all the money you want already.

DOBE EASY DRAFTING

Established 1900

1951 Lawrence Ave., Div. A-135 Chicago

Dobe Easy Drafting,
1951 Lawrence Ave., Div. A-135, Chicago

Please send me free your book, "Successful Draftsmanship", and names of other big money earning draftsmen you have trained.

Name _____ Age _____

Address _____

Post Office _____ State _____



High School Course in Two Years!

You Want to Earn Big Money!

And you will not be satisfied unless you earn steady promotion. But are you prepared for the job ahead of you? Do you measure up to the standard that insures success? For a more responsible position a fairly good education is necessary. To write a sensible business letter, to prepare estimates, to figure cost and to compute interest, you must have a certain amount of preparation. All this you must be able to do before you will earn promotion. Many business houses hire no men whose general knowledge is not equal to a high school course. Why? Because big business refuses to burden itself with men who are barred from promotion by the lack of elementary education.

Can You Qualify for a Better Position

We have a plan whereby you can. We can give you a complete but simplified high school course in two years, giving you all the essentials that form the foundation of practical business. It will prepare you to hold your own where competition is keen and exacting. Do not doubt your ability, but make up your mind to it and you will soon have the requirements that will bring you success and big money. **YOU CAN DO IT.**

Let us show you how to get on the road to success. It will not cost you a single working hour. Write today. It costs you nothing but a stamp.

American School

Dept. HA-74, Drexel Ave. and 58th St., Chicago

American School

Dept. HA-74, Drexel Ave. and 58th St., Chicago

Send me full information on the subject checked and how you will help me win success.

- | | |
|-----------------------------|---------------------------|
|Architect |Business Law |
|Building Contractor |Lawyer |
|Automobile Engineer |Machine Shop Practice |
|Automobile Repairman |Mechanical Engineer |
|Civil Engineer |Shop Superintendent |
|Structural Engineer |Employment Manager |
|Business Manager |Steam Engineer |
|Cert. Public Accountant |Foremanship |
|Accountant and Auditor |Sanitary Engineer |
|Bookkeeper |Surveyor (& Mapping) |
|Draftsman and Designer |Telephone Engineer |
|Electrical Engineer |Telegraph Engineer |
|Electric Light & Power |High School Graduate |
|General Education |Wireless Radio |
|Vocational Guidance |Undecided |

Name.....

Address.....

23rd Year



CHICAGO TECHNICAL COLLEGE

LEARN DRAFTING IN 4 MONTHS

Trained Draftsmen earn \$80 to \$100 a week. 4 months' interesting study at Chicago Tech. fits you to earn big money in drafting's effective field. Common schooling all you need. Expert instructors. Opportunities for self-support while studying. Free Employment Service. Day or Evening Classes. Athletics. Enter any Building. Write for free 72-page "Blue Book" and facts about how to qualify for a high-pay drafting job in 4 months. Dept. G-400 118 East 28th St. Chicago Technical College Chicago

If you can't come to Chicago, study at home. Write for Free Trial Lesson in Drafting.



Your School Problem

Solved the Red Book Way

Every year thousands of boys and girls choose a better private school through the assistance of The Red Book Magazine Educational Department. After an intensive seven year study which includes yearly visits to over 800 private schools in every part of the country, this department has a wealth of school facts and information at your immediate disposal.

Write in detail, giving past schooling, individual characteristics and kind of school wanted. No obligation. Address The Director, Educational Dept.

The Red Book Magazine A-420 Lexington Ave. NEW YORK CITY



Don't Let Anybody BULLY YOU

Learn Scientific Tricks of Physical Mastery

By a few simple tricks you can have any assailant at your mercy quick as a flash. The astounding secrets of self-defense, used by the New York Police, are revealed in the marvelous, officially recognized system—

Captain Wallander's Course

All Complete In

Physical Training Manual

By Capt. A. W. Wallander

Commander Physical Training, New York Police

A complete course in physical culture. Scores of gripping action photos showing just how to throw a bigger man and overpower him—disarm a hold-up thug—build up muscle—keep in fighting trim. Hundreds of health hints, too: care of the feet, prevention of colds, correct posture, walk without fatigue. This is the genuine book used by the New York Police, now available TO YOU.

Easy to Learn Let Capt. Wallander give you his great secrets and detective tricks. You'll hardly believe that such valuable knowledge could be learned so easily.

ALL YOURS IN WORLD'S MOST AMAZING COURSE

In Physical Culture and Police circles this volume is world famous. Send immediately for your copy. **DON'T SEND MONEY NOW.** Send coupon today. When volume arrives, pay the postman \$1.97, plus few cents postage. If you are not satisfied return volume and get money back. **\$1.97**

SIEBEL PRESS, 34-H.W. 20th St., New York.

Send me Capt. Wallander's Physical Mastery Course as contained in the "Physical Training Manual."

Name.....

Address.....

City.....State.....

(\$2.25 U. S. Cash with order outside the U. S. A.)



30 Miles of BATHING BEACHES in CHICAGO

Learn **ELECTRICITY** Here at GREER COLLEGE


Railroad fare allowed—no extra cost

Why not enjoy life while you train for life's biggest job? Learn Electricity. Learn it now. Learn it here—at Greer College—in Chicago, the world's greatest vacation city.

Thirty miles of bathing beaches to take the edge off your day's electrical work among our hundreds of motors, rotary converters, generators, telephone and radio equipments. Combine pleasure with educational profit. Leave here after twelve weeks equipped to start after the \$1 per hour to \$25,000 per year that electricity pays trained men.

We take mighty good care of you—help you find a place to live—help find a part-time job if you need one—and in other ways keep you from feeling like a stranger in a big city. Hundreds of fine men, all ages, already enrolled. You'll find them excellent companions, and perhaps lifetime friends or business associates.

Act fast if you want to get full information in time to enroll for new summer class. Your



A 25 H. P. Motor for student practice

FREE Employment Service

Our employment department is ready to help you—while in training and for life. Day and evening classes. Low cost. Easy terms.

name on coupon brings a big Free Book that answers all questions. Tells how to get an allowance of railroad fare—how to save 37½% of regular cost by taking our Automobile Course along with Electricity. Greer Shops have trained over 60,000 men for better jobs. Come here for good training and fair treatment. And while you learn, enjoy life at Chicago's many summer playgrounds. Mail the coupon and learn all about our School, courses and Greer opportunity Now.

If unable to come to Chicago now for resident course, write for information about Home Study Course!

GREER

College of Electrical Engineering

Dept. 601

2024 S. Wabash Avenue

CHICAGO, ILLINOIS

ERWIN GREER, President, Greer College—
Dept. 601, 2024 S. Wabash Ave., CHICAGO.

Please send me your FREE BOOK and offer for
It is understood I am not obligated in any way

Electrical ☐ course
Automotive ☐


Name

Address



"I Made \$1,000 a Month

from the New Food Sensation Greaseless Doughnuts"



That's what Thomas Minch did with Brown Bobby. You, too, can cash in big on this sensational new food product. Think of it! Actually a Greaseless Doughnut!

Mrs. Nelson, Rockford, Ill., makes Brown Bobbys at home. "Sold 90 doz. last week. Will sell 3 times that many this week. Wonderfully easy." Fair Store, Chicago.

says: "It's a great money-making device." "The demand for Brown Bobby is beyond my wildest expectations," writes Jas. O'Connor, Chicago. So it goes everywhere. Investigate!

Big Profits for YOU!

Millions of greasy doughnuts are sold daily, hard as they are to digest. What a mammoth market for Brown Bobby! Cooked without a trace of grease to a golden brown—crisped to a feathery lightness—Brown Bobby is positively the food sensation of the age. No one thought a doughnut could be made without grease. But WE did it. And YOU can get in on the first easy profits.

Simple, Easy and Sure

Get this! With one simple, inexpensive, electrically operated machine, you can turn out a full dozen Brown Bobbys every 3 minutes—cost, less than 1c each. No baking skill required. Just add water to our patented "Mix." No bother. No boiling grease. No odor. A child can do it. Big money for women making Brown Bobbys at home. Tremendous opportunities in every town for a thriving business on a surprisingly small investment. Wherever there are hungry people, Brown Bobby is a sure hit. In lunch rooms, drug stores, wherever food is sold Brown Bobby offers a chance for amazing profits. Special openings for Brown Bobby Specialty Doughnut Shops in every town.

Write Quick! Be the first in your locality to get the first easy profits. Whatever your present line-up, let us present you a plan that will be feasible and full of opportunity for a steady, paying business. Just mail the coupon! Get the facts now. Profits are waiting.

FOOD DISPLAY MACHINE CORP.

350 W. Huron St., Dept. A-135, CHICAGO, ILL.

Food Display Machine Corp., Dept. A-135
350 W. Huron St., Chicago, Ill.

Gentlemen: Please send me the plan by which I can cash in on Brown Bobby, the Greaseless Doughnut. It is understood that this obligates me in no way whatever.

Name.....

Street.....

City..... State.....

ELECTRICITY

Practical-Technical TRAINING

Great demand for practical-technical electricians and engineers. A brilliant future awaits you! A high salaried position or a profitable business of your own; these may be yours through our PRACTICAL-TECHNICAL courses. Opportunities unlimited.

Finlay condensed method now in 25th successful year trains head and hand. Thousands of high salaried graduates throughout the world testify to the success of Finlay training. Extensively equipped laboratories and shops. Faculty of recognized experts. One and Two Year courses in Electrical Engineering open in September; 12 Weeks courses in Practical Electricity and Power Plant Operation open at any time. Degrees, diplomas and certificates of efficiency awarded. Students assisted to positions.

SEND
FOR
FREE
CATALOG

FINLAY ENGINEERING COLLEGE Fall term starts September 15th.
120 Finlay Bldg. Kansas City, Mo.

LAW Free Book

Write today for FREE 128-page book, "THE LAW TRAINED MAN," which shows how to learn law in your spare time and earn more money. Qualify for a high salaried executive position or prepare to enter the practice of law. Study at home through the Blackstone Course prepared by 80 prominent legal authorities including CHIEF JUSTICE WILLIAM HOWARD TAFT. Blackstone graduates practicing law everywhere. LL. B. degree conferred. Magnificent 25 volume law library furnished immediately upon enrollment. Moderate tuition fee. Low monthly terms. Money Back Guarantee. Write for book today.

Blackstone Institute, Inc. 4753 Grand Blvd. Dept. 30-A Chicago
America's Foremost Non-Resident Law School

GIVEN



\$20 Musical Instruments

Your choice of a Violin, Tenor Banjo, Hawaiian Guitar, Banjo, Cornet, Ukulele, Banjo Ukulele, Guitar, Mandolin or Banjo Mandolin. You will be proud to own any one of these instruments and we will give you one without cost. A few cents a day for lessons is your only expense. Our system of teaching is so easy that you can play several pieces by note with the first four lessons. We guarantee success or no charge. Instrument and lessons sent on one week's free trial. Write for booklet today, no obligation. Over 200,000 satisfied pupils.

CHICAGO CORRESPONDENCE SCHOOL OF MUSIC, INC.
1632 North Halsted Street, Dept. 345, Chicago, Illinois.

No Joke to STAMMER

Successful, Master perfect speech. Win happiness. Send for full information and special phonograph record. Discovers cause. 153 Stinson, The Lewis Institute, Detroit

LEARN PHOTO-ENGRAVING!


Earn \$200 to \$500 monthly. Photography and Photo-Engraving taught in few months by largest college of its kind. Established 1893. Big demand for graduates.

Write for free book. Illinois College of Photography, Box 467, Effingham, Ill.

Write and Speak MASTERLY ENGLISH



Learn correct English with Sherwin Cody's new invention. No rules to memorize. Like a fascinating game. Spare time study, 15 minutes each day, quickly gives you masterly command of English. Interesting booklet sent free. Write today. Sherwin Cody School of English, 56 Searle Building, Rochester, N. Y.



HOW I Discovered the Secret of Making \$7500 a Year and More!

Here are Some Amazing Inside Facts About Success—As Discovered by a Man Who Has **TRIPLED** His Former Earnings in 3 Short Months! Read This Interesting Message Without Fail!

By N. C. Paige—Star Salesman After 3 Months' Experience

\$104 in 3 days! \$80 an hour! \$7,500 to \$10,000 a year!

Those are figures I was only dreaming about a few months ago. But today they are chalked up in black and white on my sales record, and, what is more important, in my bank book! And yet, to be frank, only a small part of the credit is due me. Anybody with average ability can do exactly the same.

Where the Big Money Is

Take my own case for example. Before I "came to," I tried nine different ways of earning money. They all sounded good, solid, substantial and difficult. The harder they looked, the bigger I thought the possibilities must be. None of my propositions panned out and I hardly made enough to keep going. Then I discovered KRISS-KROSS.

The day I read about this amazing shaving device in Liberty Magazine was certainly a red-letter day for me! Here's what I saw:

I'll Guarantee to Keep You in Razor Blades for Life

"Think of it! 365 keen, cool shaves a year from the same blade. That's what KRISS-KROSS is doing for American shavers everywhere!

"This amazing invention marks such a radical advance in shaving comfort and economy that it deserves to be called a blade rejuvenator.

"KRISS-KROSS strops your blade (any make) on the diagonal just like a master barber. Pressure decreases automati-

cally. Nickel jig flies up to notify you when your blade is ready.

"And now for my smashing offer! To introduce KRISS-KROSS stropper I will give you an amazing new kind of razor free. Really 3 razors in one. Can be made straight or T-shape in a jiffy. Comes with 5 special blades."

Naturally, I was vitally interested because cool, slick painless shaves are what every man tries to get and usually can't! And then at the bottom of the ad, I saw a little square:

"Agents: Make big money as a KRISS-KROSS representative—\$75 to \$225 a week. H. King made \$66 in one day. J. C. Kellogg made \$200 in 7 days."

First Step to Success!

At first I was skeptical about the money-making part of it. But the stropper sounded so extraordinary that I sent for it. When it came, I saw it was even more astonishing than I had imagined. I took it over to show a friend and in less than 5 minutes he asked me to get him one. While we were talking, two more friends dropped in and made the same request that I get them each a KRISS-KROSS outfit! When I left, I had nearly \$5 cash profit in my pocket—money I had not made one single effort to get!

I saw my chance and grabbed it! The KRISS-KROSS people gave me exclusive territory, a wonderful lot of sales helps and a big, illustrated salesmanship course book that contained selling secrets worth \$100 cold cash to me! My first week I made \$180! The next 3 days I made \$104. Just think of it! It didn't


seem to take any effort. The orders rolled in like water over a waterfall!

Mr. Paige's experience is typical of that of hundreds of KRISS-KROSS representatives. Practically every man who takes up this astonishing proposition writes us that he is making money faster and easier than he ever dreamed possible. Right now more KRISS-KROSS representatives and agents are wanted—to earn \$30 a day and up. Find out about it today! Clip the coupon and mail it at once! You'll never regret it. Paige didn't! So act at once!

Rhodes Manufacturing Co.

Makers of KRISS-KROSS

1418 Pendleton Ave. St. Louis, Mo.
Dept. G-371



**Rhodes Mfg. Co.,
Dept. G-371**

1418 Pendleton Ave.,
St. Louis, Mo.

Please send me full details of your amazing KRISS-KROSS Stropper with list of generous commissions, and tell me how I can make big profits with it in my full or spare time.


Name.....

Address.....

City..... State.....

CHEMISTRY

Learn
at
Home



The Chemical Industry now ranks fourth among the industries of the United States and it offers a splendid opportunity for ambitious men.

Arthur D. Little emphasized this very point in his speech before the American Institute of Chemical Engineers when he said: "Industrial developments along new lines are everywhere in progress and they call upon the chemical engineer for new equipment and new methods of production and control."

One of the best ways for you to prepare for a good position in this fascinating field is through the home-study courses in Chemistry offered by the International Correspondence Schools.

These courses are complete and practical because they were prepared by some of the best-known chemists in this country, including:

ALLEN ROGERS, B.S., M.S., Ph.D.—Head of Department of Industrial Chemistry, Pratt Institute.

ANDREW M. FAIRLIE, B.S.—Consulting Chemical Engineer for the Tennessee Copper and Chemical Corporation; American Zinc, Lead and Smelting Co.; American Zinc Oxide Co., and the Bugh Chemical Co.

L. M. TOLMAN, Ph.D.—Formerly Chief Chemist, Wilson & Co. Now Vice-president, United Chemical and Organic Products Co.

BRADLEY STOUTCHON, B.S.—Head of the Department of Metallurgy, Lehigh University.

OWEN L. SHINN, Ph.D.—Professor of Applied Chemistry, University of Pennsylvania.

Qualitative and Quantitative Analyses Outfits are supplied with these I. C. S. Courses at special prices for your laboratory work at home, and the courses are so arranged that you get just the help you need to secure a good position in the work you like best.

Just mark and mail the coupon and we'll gladly send you Free Booklets describing the I. C. S. CHEMISTRY Courses or any other course in which you are interested.

Mail the Coupon for Free Booklet

INTERNATIONAL CORRESPONDENCE SCHOOLS

Box 5652-E, Scranton, Penna.

Without cost or obligation, please send me one of your booklets, and tell me how I can qualify for the position or in the subject before which I have marked an X:

- | | |
|--|--|
| <input type="checkbox"/> Analytical Chemistry | <input type="checkbox"/> Analytical and Industrial Chemistry |
| <input type="checkbox"/> Chemical Engineering | <input type="checkbox"/> Chemistry |
| <input type="checkbox"/> Industrial Chemistry | <input type="checkbox"/> Short Chemistry Course |
| <input type="checkbox"/> Metallurgical Chemistry | <input type="checkbox"/> Pharmacy |

Also courses specializing in the Chemistry of the following industries

- | | |
|---|--|
| <input type="checkbox"/> Manufacture of Leather | <input type="checkbox"/> Manufacture of Iron |
| <input type="checkbox"/> Manufacture of Cottonseed Oil | <input type="checkbox"/> Manufacture of Steel |
| <input type="checkbox"/> Manufacture of Petroleum | <input type="checkbox"/> Manufacture of Sugar |
| <input type="checkbox"/> Manufacture of Sulphuric Acid and Hydrochloric Acids | <input type="checkbox"/> Manufacture of Soap |
| <input type="checkbox"/> Manufacture of Cement | |
| <input type="checkbox"/> Electrical Engineering | <input type="checkbox"/> Steam Engineering |
| <input type="checkbox"/> Electric Lighting | <input type="checkbox"/> Architect |
| <input type="checkbox"/> Mechanical Engineer | <input type="checkbox"/> Architects' Blueprints |
| <input type="checkbox"/> Mechanical Draftsman | <input type="checkbox"/> Contractor and Builder |
| <input type="checkbox"/> Machine Shop Practices | <input type="checkbox"/> Architectural Draftsman |
| <input type="checkbox"/> Railroad Positions | <input type="checkbox"/> Concrete Builder |
| <input type="checkbox"/> Civil Engineer | <input type="checkbox"/> Structural Engineer |
| <input type="checkbox"/> Surveying and Mapping | <input type="checkbox"/> Airplane Engines |
| <input type="checkbox"/> Metallurgy | <input type="checkbox"/> Mathematics |
| <input type="checkbox"/> Mining | |

Name.....

Street Address.....

City.....State.....


The Poultry Business PAYS BIG

Those who know how, find it easy to make incomes of \$3,000 a year and more even on very small acreage. There is big money in poultry if you follow the right plan. Start as small as you like—grow fast.

Write for FREE BOOK

Free Book, "How to Raise Poultry for Profit," by Harry Lamont, former Government Poultry Expert, tells all about his course. Shows you how to get started and how to succeed. Success positively guaranteed if you follow his methods. Send for your copy TODAY.

National Poultry Institute
Dept. 411, Washington, D. C.



Learn to PAINT SIGNS and SHOW CARDS

We quickly teach you by mail, or at school, in spare time. Enormous demand. Big future. Interesting work. Oldest, foremost school.

EARN \$50 TO \$200 WEEKLY

John Vassco, N. Y., gets \$25 for single show card. Crawford, B. C., says: "Earned \$200 while taking course."

Send today for free information, samples and guarantee.

DETROIT SCHOOL OF LETTERING

150 Stinson Ave. Est. 1899 Detroit, Mich.



PIANO JAZZ

By Note or Ear. With or without music. Short Course. Adult beginners taught by mail. No teacher required. Self-instruction Course for Advanced Pianists. Learn 259 styles of Bass, 684 Syncopated Effects, Blue Harmony, Oriental, Chime, Movie and Café Jazz, Trick Endings, Clever Breaks, Space Fillers, Sax Shurs, Triple Bass, Wicked Harmony, Blue Obligato, and 247 other Subjects, including Ear Playing. 133 pages of REAL Jazz, 25,000 words. A Postal brings our FREE Special Offer.

Waterman Piano School, 1826 W. Adams St. Los Angeles, Cal.

Big Money for You as an Automobile Mechanic

These four practical books, written by five well known teachers of automobile practice, will teach you right in your own home during your leisure time just what you need to know about automobile troubles and repair. They will teach you automobile construction, maintenance and repair as experts know them and will help you to earn an expert's pay.

Practical Automobile Library: Four Books—\$1.50 in 10 days and \$2 monthly for 6 months—only \$13.50 in all!

Hundreds of question-answering diagrams—hundreds of clearly-marked illustrations—make the books plain and readily understandable. All the explanations and descriptions are clear, simple, direct. Every chapter is packed with definite, step-by-step, how-to-do-it information. Here is your opportunity to enter a big-pay field.

Sent FREE

Send No Money
Mail the Coupon



FREE EXAMINATION COUPON

McGraw-Hill Book Co., Inc., 370 Seventh Ave., New York

Send me for 10 days' free examination the New Practical Automobile Library. If satisfactory, I will send you \$1.50 in 10 days and \$2.00 monthly until the special price of \$13.50 is paid. If not wanted, I will return the Books at your expense.

Signed.....

Address.....

City and State.....

Position.....

Employer..... F. M. 6-1-27

Guaranteed Twin Service for Ambitious Men!



O. C. MILLER
Director Extension Work

The American School is the first in the home-study field to recognize the need of guaranteeing its courses with a money-back contract, if the training fails to accomplish the benefits you expect. Thus all risk and doubt are eliminated—either the training will help you to a better job and a raise in pay or it will cost you nothing. To better carry out this important service, we maintain a National employment department which keeps in touch with the employers of Draftsmen all over the U. S. All this without extra charge to our students and graduates.

Professional Outfit Given!

You will naturally expect the American School to give you the best kind of instruments and tools with the best kind of training. This outfit is good enough to use professionally after you finish your training. Mail coupon for description.



T
Training
Preparing
you for a
better job
and a Raise
in Pay - - -

E
Employment
—then help-
ing you get it,
or money
refunded!

Come into Drafting!

Learn drafting—how to make and read plans, and the doors of opportunity in all mechanical, building, and engineering lines swing open for you! There are more well-paid Drafting jobs open today than in any other one profession or trade. There's a variety, a fascination to Drafting that will grip you. No other work is so interesting, so well paid—no other field offers equal opportunities for quick promotion.

The Draftsman is the Boss of the Works!

Destroy blue-prints and plans, and the wheels of all Industry will stop until new ones can be made. Every move of every workman on the job is controlled by the Draftsman through his plans. Railroads, public works, buildings of a hundred sorts, machinery, electricity, automobiles—all manufacturing and construction start on the Drafting table! That's the kind of work to get into, friend. Where you have the same chance as anybody else to make a quick success!

**If You Are
Now Earn-
ing \$40 a
Week or Less**

I guarantee to prepare you for a fine drafting position, right in your home, in your spare time; then I guarantee to help you find such a position paying at least 50% more than you earn today, within 60 days after you complete this training, or I will refund small amount you pay for tuition. We make this agreement to prove this instruction will make you a real Draftsman. Back of this guarantee are the entire resources and reputation of this million dollar institution.

O. C. Miller

O. C. MILLER
Director Extension Work

3 DRAFTING Lessons FREE!
—to prove you can learn at home in spare time!

You'll be surprised how quickly you can learn Drafting by our new one-step-at-a-time method. We start you off by doing actual Drafting room jobs from the very beginning. Before you know it, you are battling out professional plans like a veteran. Get the first three lessons—the coupon brings them. Do them. Test your ability to master Drafting at home. Without cost or obligation.

The American School

Dept. DA-74, Drexel Ave. and 58th, Chicago


O. C. MILLER, Director Extension Work
American School, Dept. DA-74, Drexel Ave. and 58th St., Chicago.

Your offer to send me three lessons free and facts about the opportunities in Drafting and about your course, looks good to me. It is understood I am not obligated in any way in making this request.

Name _____

Address _____

Occupation _____ Age _____



PAIN and DISEASE

Quickly Conquered by
VIOLET RAY



Let us tell you how thousands of men and women suffering from rheumatism, neuritis, paralysis, nervousness, skin diseases, headaches, constipation, sprains, prostate trouble, goitre and many other ailments, even hay fever and asthma, have found quick relief—new health and vitality with this marvelous, scientific invention. Pains vanish almost instantly.

Violetta

Ten Days FREE Trial


For Health—Beauty—Vigor

Endorsed and used by hospitals, sanitariums and physicians. Every home can now have one. Saves hours, days, months of suffering. No medicine. Painless, pleasant treatment. Only the violet ray can penetrate to every nerve affected. Simple, safe, painless—anyone can use VIOLETTA. Why suffer pain and poor health when you can try VIOLETTA 10 days FREE.

This Book FREE

Tells all about violet rays—how this marvelous discovery by Nikola Tesla, the electrical wizard, now brings this mysterious curative power to all. Contains many astounding testimonials from our thousands of satisfied users. Send for the facts and our liberal trial offer today. Mail the coupon now.

VI-REX CO., Dept. 631
2304 Warren Avenue, Chicago



VI-REX CO., 2304 Warren Ave., Dept. 631 Chicago

Please send me your free book on Violet Rays and details of your 10 days' free trial offer.

Name.....

Address.....

City.....State.....

Ailment.....

Electrical Trades/ Need Men



LEARN Automobile Starting, Lighting, Ignition; Storage Batteries, Armature Winding, House Wiring, Farm Lighting, Electric Welding, Electric Refrigeration, A. C. and D. C. Motors, Power and Light Switchboards, Radio.

EARN \$200 to \$400 monthly. \$320,000.-000 paid in wages to electrical workers in U. S. last year. Get your name on the payroll this year. Easy to learn by actual work on real equipment.

FREE BOOK—Write today for book which explains the Coleman System of ten week courses.

WM. H. COLEMAN, President

Coleman Electrical School
1628 C MAIN ST., KANSAS CITY, MO.

BE AN ARTIST

WE CAN TEACH YOU DRAWING in your own home during your spare time. Twenty-five years of successful teaching proves our ability. Artists receive large salaries. Write Today for Art Year Book

SCHOOL OF APPLIED ART
ROOM NO. 2 BATTLE CREEK MICH.



Factory to Rider

Saves \$10 to \$25 on the Mead Bicycle you select. You can have your choice of 44 Styles, colors and sizes. Delivered free on approval. \$21.50 up.

30 Days' Free Trial on the bicycle you select from the big free catalog. Ride it a month to be sure you like it. Return it if not satisfied.

Tires—best quality, factory prices. Save big money on lamps, wheels and equipment, low prices. Send No Money, do business direct with makers.

Mead CYCLE COMPANY
DEPT. 110 CHICAGO

Write today for free catalog, factory prices and marvelous new offer.



Genuine HAWAIIAN RADIO TONE GUITAR

GIVEN

When You Enroll

New Short Easy-to-Play Course

One of the most efficient methods of instruction ever invented is now offered you.

**You will understand it, instantly—
Play Popular Music in Half an Hour**

Your lessons come from lovely Hollywood, where the Stars learn to play the Hawaiian Radio-Tone Guitar. This fascinating instrument, brings you echoes of a far-off, dreamy, tropical isle.

You may now hear, clear, ringing, quivering one you have heard on the Radio.

When you tune in on Hawaiian programs, it thrills you, makes you long to hear it again and again.

The Hawaiian-Radio Tone Guitar produces that wonderful, singing-humming tone you love. (It comes to you from Filmland, where it is redoubtably night.)

Our Easy-to-Play Lessons teach you to produce the tone you desire so much to hear.

Native Hawaiian Teachers have worked out these simple lessons which reveal the secrets of their art.



SEND THIS COUPON NOW

Hawaiian Teachers of Hollywood, Studio (A)—Hollywood, California
Please send me full information about your Free Hawaiian Radio-Tone Guitar

Name.....

Address.....

You Can Set the Pace —BUT IT MAY COST YOUR LIFE!



STRONGFORT
Builder of Men

I have been conspicuous in the field of physical culture and muscular development for over 25 years. I am known on both hemispheres. I first made my impress on the public mind by developing myself to marvelous symmetrical proportions—my bodily perfection being the subject of wide comment wherever I exhibited—and performing, in Europe and America, incredible feats of strength. I had "the goods" and I delivered them.

—Lionel Strongfort

STRONGFORT INSTITUTE
LIONEL STRONGFORT, DIRECTOR

Physical and Health Specialist for over 25 Years
DEPT. 345 NEWARK, NEW JERSEY, U. S. A.

You, young fellow, may be one of those chaps who thought you could set the world on fire and fiddle while it burned. Nero tried that—you know what happened to Nero? You thought you were different from most young fellows. You could hit on all eight cylinders and get away with it. You could carouse, dissipate, stay up all hours and make up for your excesses by taking poison booze or drugs and dope to brace you up. You had a strong constitution—nothing worried you. Wild parties couldn't be too fast for you—you were a real roaring lion with the girls—the life of the party—whoopee!

But, now, you see what's happening to young fellows who saw no limit to life—who had "vitality to burn!" They're slumping—they're slipping—they're despondent! Read the papers. Ask yourself what is at the bottom of these frequent cases of despondency. If the truth were told, you'd learn that these poor devils had laid the foundation for their tragedy in their youth. Added excesses—speed, carousing, boozing, doping, associating with degenerates—piled up a burden Nature could not stand for—collapse followed.

Are you going to go on until you find yourself in the same physically broken condition? Are you going to keep on tapping the reservoir of energy Nature gave you? Don't do it, boy. I sound this warning as a friend, a protector. I have seen so many go down to physical and mental disaster that I must warn you to stop right where you are—NOW.

Heed the Danger Signals

You're tearing down a whole lot faster than you are building up and the longer you keep going as you have the worse you're going to get. Now is the time to take yourself in hand—before it's too late. And you can do it.

STRONGFORTISM will show you how, but you must act now. Each day you wait, each day you delay makes it just that much harder to bring you back. Let **STRONGFORTISM** help you. Let it restore in you those vital powers that you know you are losing and losing fast.

STRONGFORTISM will build up that body of yours in such a way as to make a brand new fellow out of you. It will make you fit for any physical task—give you pep, vigor and punch. You will radiate health and good cheer. Confidence will fill you so that you won't be afraid of anything or anybody.

STRONGFORTISM WILL BRING YOU BACK

—not with medicine or dope—but with the aid of Nature. You cast Nature aside in those days of early, frivolous youth. I will show you how to work with Nature. I will build you up inch by inch—internally and externally—until you are a robust, powerful fellow—a real He-man who will command respect and admiration wherever you go. I have done this for thousands of others and I will do it for you through my original and unailing methods.

Send for My FREE Book

The experience and research of a lifetime are contained in my wonderfully instructive book,

"PROMOTION AND CONSERVATION OF HEALTH, STRENGTH AND MENTAL ENERGY." It will tell you frankly how you can make yourself over into a vigorous specimen of vital manhood. Just mark the subjects on the free consultation coupon on which you want special confidential information and send to me with a ten-cent piece (one dime) to help pay postage, etc. It's a man-builder and life-saver. Send for my free book RIGHT NOW—TODAY.

Send this FREE Consultation Coupon ABSOLUTELY CONFIDENTIAL

Mr. Lionel Strongfort, Strongfort Institute, Dept. 345, Newark, N. J.—Please send me absolutely free my copy of your book, "PROMOTION AND CONSERVATION OF HEALTH, STRENGTH AND MENTAL ENERGY." I am enclosing 10c (one dime) to help cover mailing expense, etc., and have marked (X) before the subjects in which I am most interested.

- | | | |
|-----------------------------------|---------------------------------------|---|
| <input type="checkbox"/> Catarrh | <input type="checkbox"/> Overweight | <input type="checkbox"/> Great Strength |
| <input type="checkbox"/> Colds | <input type="checkbox"/> Constipation | <input type="checkbox"/> Lung Troubles |
| <input type="checkbox"/> Asthma | <input type="checkbox"/> Weak Back | <input type="checkbox"/> Round Shoulders |
| <input type="checkbox"/> Headache | <input type="checkbox"/> Weak Eyes | <input type="checkbox"/> Stomach Disorders |
| <input type="checkbox"/> Rupture | <input type="checkbox"/> Rheumatism | <input type="checkbox"/> Increased Height |
| <input type="checkbox"/> Thinness | <input type="checkbox"/> Nervousness | <input type="checkbox"/> Muscular Development |
| <input type="checkbox"/> Pimples | <input type="checkbox"/> Short Breath | |
| <input type="checkbox"/> Insomnia | <input type="checkbox"/> Weak Heart | |

Other Ailments.....

Name.....

Age..... Occupation.....

Street.....

City..... State.....

L. L. COOKE

—the man who has trained and helped many thousands of other men into Big-Pay electrical jobs in all parts of the world.

**\$30 A DAY!**

"Dear Mr. Cooke: I was making \$25 a week, when I enrolled. Now with my own Electrical Shop I make as high as \$30 a day."

A. J. Daigneault
226 Worcester
Southbridge, Mass.

**\$3,500 A YEAR!**

"Dear Mr. Cooke: When I began with you I was just a common laborer. Now my salary is \$3,500 a year."

C. O. Beckett
108 Maple Heights
New Lexington, Ohio

**I
WILL
TRAIN
you
at
HOME**

Learn to Make It in the big pay field Electricity

DON'T be a wage slave all your life—don't spend your best days in a miserable \$25 to \$35 a week job—pinching the pennies and barely making ends meet—when thousands of men, no smarter nor luckier than you, are drawing down \$70 to \$200 every Saturday as "Cooke" Trained Electrical Men. It's your own fault if you don't do the same. Blame yourself if your pay is small when I've made it so easy for you to learn to earn \$3,500 to \$10,000 a year in electricity!

Be a "Cooke" Trained Man

I'll show you how—in your spare time—in the quiet of your own home—without losing a minute from your regular job! I'll train you in a clear, simple, quickly-grasped unforgettable way with my famous "Work Sheet" and "Job Ticket" Method—the same method that has landed more than 10,000 fellows like you in \$3,500 to \$10,000 a year jobs—the same method that Electrical men are praising and great Electrical concerns recommend to their employees.

"Schooling" Not Necessary

Don't think for a minute that you need a college education or a high school diploma to become a "Cooke" Trained Big-Pay Man. You don't! Mighty few of my "boys" ever went farther than grade school. But that was no drawback. With the Six Big Outfits of tools and apparatus that I furnish without extra charge, they got

simplified, practical training along work shop lines. They learned by doing—they learned thoroughly—just as if I was constantly at their elbow. And in no time at all they were experts—commanding, and getting, Big-Pay!

Make Money While Learning

Another amazing thing about "Cooke" Training is that it pays for itself as you go along. Yes, Sir! You'll hardly have begun the Course when I'll show you how to make your spare hours count for cash! I'll show you how to get jobs—how to do the work—what to charge! And all while you're still learning! Afterwards comes the Big Job—the Big Pay—the great opportunities that will make you independent the rest of your days.

Investigate—Mail Coupon

Don't delay! Get started! Mail coupon right now for my Big Book—the same book that has raised the pay of thousands of men—the book that will show you—yes, prove to you—why "The COOKE Trained Man is The BIG-PAY Man"—always and everywhere! It's FREE—just mail coupon—at once!

L. L. COOKE, Chief Instruction Eng.

L. L. COOKE SCHOOL OF ELECTRICITY


Dept. 1-A

2150 Lawrence Ave., Chicago, Ill.

**There are
Thousands of
Big Pay Jobs
to be had!**

**6 BIG
OUTFITS
at**

no extra cost



MAIL THE COUPON · Get this book free

**L. L. COOKE, Chief Instruction Engineer,
Dept. 1-A, 2150 Lawrence Ave., Chicago, Illinois**

You may send me, FREE and fully prepaid, your book "Secrets of Success in Electricity," with all particulars about your Home Study Course in Electricity.

Name.....

Address.....

City..... State.....

Residents of Canada send coupon to R. A. Farrow, Special Representative, 7 Medbury Lane, East, Windsor, Ont., Canada.

The "Cooke" Trained Man is the "Big Pay" Man

Classified Advertisements

WORLD'S BEST WANT AD MEDIUM

Advertisements in this section, 30 cents per word, each insertion, minimum 10 words, payable in advance. To be inserted under proper classification in July issue, copy should be in our office May 18th

ADVERTISING AGENCIES

ADVERTISERS: Amazing growth made by one of our clients, who started last May with \$1.20 weekly. Now spending \$500.00 weekly. Name furnished on request. We'll help you put your proposition over. Cash in on our thirty years of experience. Copy and literature composing service free. Your 24 word ad inserted in the following ten leading Sunday papers for only \$10.00: Age-Herald, Birmingham; Gazette, Little Rock; Star, Indianapolis; Journal, Minneapolis; Star, Kansas City; World-Herald, Omaha; Courier, Buffalo; Enquirer, Cincinnati; Gazette-Times, Pittsburgh; Banner, Nashville. Proof of insertion guaranteed or money refunded. 52 page rate book sent free. Frank W. Lenhoff Advertising Agency (Established 1897), 608 North Michigan Blvd., Chicago. Chicago's most progressive agency.

A TEN Dollar Ad may put your proposition over. \$10 pays for a 4 line 24 word classified ad one Sunday in 9 of the largest newspapers. Reach over 6 million readers. Minneapolis Tribune, Buffalo Courier, St. Louis Post-Dispatch, Pittsburgh Press, Indianapolis Star, Atlanta Journal, Birmingham News, Cincinnati Enquirer, Little Rock Gazette. Free catalogue showing other lists of newspapers and magazines sent on request. Ankrum Advertising Agency, 22 West Jackson Blvd., Chicago. Largest classified advertising agency in the world.

ADVERTISE in the classified section of newspapers and magazines, to secure help, money, or to sell. 24-word advertisement in nine big Metropolitan papers \$10.00. Nearly two million circulation. Many other bargain lists. Write for Free 58-page Directory No. 26. Brinkerhoff Advertising Agency, 37 W. VanBuren, Chicago.

ADVERTISE in 24 Big Sunday Newspapers. 24 words \$15.00. Excellent for securing Agents, Salesmen, and Business Opportunities. Catalog listing 1,000 leading Dailies, Weeklies, Mail Order Magazines, Everything. Free. Wade Advertising, Baltimore Bldg., Chicago.

NEWSPAPER—Magazine advertising—Classified, mailorder, Catalog. Martin, 278B West 43rd, New York.

SIX Word Line—355 rural weeklies \$3.55. Admeyer, 4112-M Hartford, St. Louis.

FOR ADVERTISERS

YOUR 25-word advertisement in "The Winner" 75c; sample copy 10c. Witts Sales Co., Rush Springs, Okla.

40 WORDS insert 40 magazines \$2.00. Empire Agency, Shawano, Wis.

ADVERTISERS' Manual, summer edition, inside information, postpaid 50c. Economes Co., 1475P Broadway, New York.

ADVERTISE in 275 country newspapers, 28 words, \$10. Keator, Hartford Bldg., Chicago.

CUTS, Drawings \$1.50. Window Cartoons, 6, \$1.50. GPO, Box 471, New York.

SALES PROMOTION

\$50 TO \$50,000 Daily Sales Developed During 28 years for clients by our direct mail plans, copy, campaigns. One product, 1923, an idea; this year \$100,000 orders booked. Fifty year old concern desired 50 national representatives in 1925; we produced 40 in three months. 700 dealers in 10 months at \$3 each, for another. Ten years Sales Promotion Manager Larkin Co. Submit sales problems for free diagnosis. James C. Johnson, 118A Woodbridge Ave., Buffalo.

BLACKBOARDS for all purposes; plain, or ruled and lettered. Wm. Planno, 4049 Fifth Ave., Chicago, Ill.

AUTOMOBILE SUPPLIES

FREE trial of new spring lubricator. Stops squeaks. Needed by every car owner. Great money saver. Write for details without obligation. Turner Manufacturing Co., Kokomo, Ind.

YOU are wanted to resilver mirrors at home. Immense profits, plating autopaets, headlights, tableware, stoves, etc. Outfits furnished. Write for information. Sprinkle, Plater, 77, Marion, Ind.

SAVE money on repair parts. 50 to 75% off list prices. Parts guaranteed satisfactory. Gears, axles, drive shafts, wheels, bearings, motor and transmission parts for old and late model cars. Cylinder blocks for Ford, \$8; Dodge, \$12; Chevrolet, \$10; Overland 4, \$15; Lycoming K, \$15; Continental 7W, \$15, 7R, \$18; Hudson, \$20; Buick 6, \$18; Studebaker, \$20. Special prices on quantity orders. Prompt service. Price list free. Century Parts Co., 1725 S. 18th St., St. Louis, Mo.

SAVE 40-80%. New and Used Automotive Parts, 2,000 models, also truck parts, 5,000 bargains. Bankrupt supplies, tires, generators, \$10 up; carburetors \$3.50 up. Complete Khaki roadster tops \$10; Khaki touring, fit most 5-passenger, \$15. Wheels, gears, radiators. Brightman Auto Parts Co., 321 Windsor Ave., Hartford, Conn.

CARBURETOR Supplement to famous Dyke's Auto Encyclopedia. Just out. Deals with every make of carburetor. Just what every auto service man has long been in need of. 106 pages, 246 illus. Price \$2.00. Send for your copy today. C. O. D. if you prefer. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

SY-LENT Paws—rubber heels for the motor—will kill that vibration period. \$1.75 set. Vapor Vent, the perfect crankcase ventilator, permits changing motor oil only every four thousand miles. \$3.50 complete. Both sent postpaid \$5.00. Mark Anton Mfg. Company, Belleville, N. J.

AUTO Tires—represent us. Buy them at wholesale. Big saving. Send for prices. Federated Motor, 250 W. 54th St., New York, N. Y.

BUY a 17-battery capacity Scioto Battery Charger for \$50. Complete Battery Shop equipment for \$129.74. Get catalog. Adams-Barr, Columbus, Ohio.

CHEVROLET Parts. I can save you from 35 to 50% off on all used Chevrolet parts, all models from 1921 to 1924. Write me for your wants on Chevrolet parts. Mr. A. Mayer, 2101 McNair Ave., St. Louis, Mo.

VULCANIZING Auto Tires is a Paying Business. We have Plants near you from \$50 up. Catalog Free. Instruction Book \$1. Equipment Exchange, 108 East 11th, Los Angeles, Calif.

MAGNETOS, Starters, Generators, Ignition systems, spark plugs, part, timing chains, repairing. Melner Magneto Co., 1739 E. 21st St., Cleveland, Ohio.

1 AUTO Gas Saver Free. To introduce. All makes. Amazing mileage increase. Critchlow, CI-805, Wheaton, Ill.

DYKE'S Automobile Encyclopedia. Latest 14th edition. Information on repairing and adjusting every part of all motor cars. How to find trouble and fix it. Send no money. Pay postman the postage and \$6. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

WE make over 300 new, artistic radiator ornaments. One of them was designed especially for your car. Catalogue free if you mention Popular Mechanics. Irving Florman Company, 153 Lafayette Street, New York City.

AT Last! Reasonably priced Auto Emblems for every Lodge. Sells for only \$1.25. Write for attractive selling proposition and free Sample Case offer. North Central Distributors, Dept. 9, Ashland, Ohio.

OUR Improved Vibrator Points make Ford engines start easy. Complete set postpaid \$1. S. D. Brown, 198 South St., Newburgh, N. Y.

AUTOMOBILES

AUTO TOURISTS—Here are 133 practical plans for making touring easier, less expensive and more enjoyable. With these we supply a Touring Atlas of the U. S. showing road maps of every state. All this information for the small price of 98 cents plus the postage. Pay postman when he delivers the package. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

753 TIME, Labor and Money Saving Ideas for all who own, drive or repair autos. These practical hints are based upon the actual experiences of hundreds of owners and repairmen. Three books, Auto Owners, Auto Repairman's and Auto Tourists Handbooks, regular \$1.50 value from Popular Mechanics Press will be supplied at 98c, plus the postage C. O. D. for a limited time only. Send your order today to Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

AUTOMOBILE—Make your own motor car, toy size, operated with motorcycle engine. Any boy can make it. Costs little aside from engine. Full directions with drawings and dimensions in The Boy Mechanic. Book 3. Send no money. Pay postman postage and \$2. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

AUTOMOBILE SERVICE EQUIPMENT

CONSTANT Potential One-Day Battery Charger, HB Make, first-class condition, priced for quick sale, terms if desired. A bargain. Write to W. E. Jordan, Box M671, Troy, Ohio.

HB Universal Test Bench practically new at a big saving. A bargain for any Auto Repair or Electric shop. Will take small payment down—balance monthly. E. C. Galbreath, Box M673, Troy, Ohio.

3/4 HP Twin Cylinder Air Compressor. Fine for Tire Service Shop or Auto Repair Shop. Used only a few weeks. Better than a new one, priced to sell. Latest model beltless Upright 11H. Terms and guarantee. D. C. Jenkins, Box M672, Troy, Ohio.

NESTLER Rubber Fusing Outfit, with shop tools, instructions, etc. This plant will repair or retread any size tire. Will sell reasonable. Roy B. Hutchason, Olney, Ill.

FOR FORD OWNERS

SHIMMY and Road Shock Eliminated from your steering wheel with Shimco Steering Stabilizer. Make your steering gear irreversible like large cars. State whether balloon or hard tire model. \$2.00—Guaranteed. Agents wanted. Steering Improvement Co., Portsmouth, N. H.

UNDERSLUNG with "RKO" Swing Lo Irons. See "Red-i-Kut" ad page 138.

PUT a "Bingo" Timer on your Ford. "More Pep—More Power." Money-Back Guarantee. \$1.50 delivered with simple instructions to install. Write for exclusive Agency—fine proposition. United Machinery Company, Cincinnati, U. S. A.

FORD Brake and Reverse Bands adjusted easily without opening transmission case when Tuttle External Adjusters are installed. Set, \$2.50. Barker Factory, 5 Crescent Street, Norwalk, Conn.

SIMPLEX Mechanical Starter (Ford's without electric), \$7.50. American Simplex Co., Anderson, Ind.

SIMPLE One Piece Valve Adjuster and Silencer quickly installed without tools. Saves gas, time and nut adjusting. Stops click; takes up wear. Thousands satisfied. Send dollar for complete set. C. W. Young, 2121 New York Ave., N. W., Washington, D. C.

FORD Electrical Equipment Troubles—Locate and remedy them easily yourself with the aid of our book "Ford Standard Electrical Equipment." Why pay big garage bills? Battery, ignition, starting and lighting covered. Order today. When postman hands you the package pay him \$1.98 and the postage. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

1 AUTO Gas Saver Free. To introduce. All makes. Amazing mileage increase. Critchlow, C2-805, Waukegan, Ill.

MOTORCYCLES, BICYCLES AND SUPPLIES

MONEY Saving Motorcycle Bargains—Large stock of Used Harley-Davidson—\$50 and up. Send for Free bargain bulletin—New! Motorcycle Parts, accessories, repairs for all makes. Knuth's Harley-Davidson Agency, 2525 Fond Du Lac Ave., Milwaukee, Wis.

MOTORCYCLE Bargains. Used, rebuilt. Guaranteed. Shipped on approval. Catalog free. Floyd Clymer, 810 Broadway, Denver, Colo.

SEND stamp for Bargain Bulletin. All makes rebuilt motorcycles at lowest prices. Used parts half price. Ash Motor Corporation, Rochester, N. Y.

REBUILT Indian Motorcycles, lowest prices. Used motorcycle parts. Hurck Indian Co., 2127 Locust, St. Louis, Mo.

INDIAN motorcycles \$50. Standard models \$10. Deposit with order, balance C. O. D. Stern Bros., 1790 1st Ave., New York City.

DON'T buy a Bicycle Motor Attachment until you get our prices. Shaw Mfg. Co., Dept. 27, Galesburg, Kans.

AVIATION

LEARN to Fly: \$100.00 including Solo. We guarantee to solo you regardless of the number of flying hours required. Our instructors are ex-army aviators and air-mail pilots with wide experience. Our training equipment is the best obtainable. Our course requires about two weeks, depending on the individual. No bond required, no charge for breakage. Eight years without an accident, 76 students graduated in 1925. Commercial aviation is a rapid growing industry. Don't delay! Enroll now in one of the oldest and best known flying schools in America. Write for booklet. Robertson Aircraft Corporation, operators of the United States Air Mail, St. Louis-Chicago, Lambert-St. Louis Airport, St. Louis, Mo.

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

TEN Lesson in the air of twenty minutes each will make you a pilot by our advanced method of training. This, together with our five weeks shop course, at \$100.00, makes America's oldest aircraft factory the most popular flying school. Work after class hours guaranteed. Special summer evening course, including shop work, field and flying, \$185.00. Employment assistance on jobs paying \$18.00 to \$40.00 per week. Heath Airplane Company, Chicago, Ill.

AERONAUTICS! "Aeroplane engines in Theory and Practice," by Rathbun, describes engines fully. Includes all makes. For mechanician, builder and flyer. Send no money. Just order on a postal. When postman hands you book, pay him \$2.50 and postage charges. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

AVIATION positions pay \$2,000 to \$10,000 a year. Prepare for flying and ground positions thru thorough and complete home study training. Write Dept. K-6, Western Airplane Corp., Monadnock Bldg., Chicago.

TO liquidate affairs of an aero company I will sacrifice following: Thomas Morse fuselage \$25.00, Curtiss \$40.00, Lawrence Motor with propeller \$75.00, Gnome motor \$32.50, LeRhone \$25.00, Propellers \$5.00 up. Photographs furnished with complete description if you mean business. L. E. Waldron, Box 283, St. Paul, Minn.

EVERYTHING for the Airplane Builder. Complete fuselage fittings \$37.00. Southern Airways, Inc., 210 College, San Antonio, Tex.

\$188.00 BUYS all parts, including assembled wings, to build the new Heath "Parasol" sport plane, using motorcycle engine. Simplest to construct. Safest to fly. \$75.00 ready to fly away. Send 5c for circular. Heath Airplane Company, Chicago, Ill.

BLUEPRINTS. Prices reduced. "Aeroplane" boats, sleds. Blueprints only 50c each. Ostergaard Aircraft, 4303 No. Narragansett, Chicago.

LEARN to fly by "Club Plan." Least expensive of all. Registered U. S. pilots instruct and have best equipment. Chicago Flying Club (Incorporated not for profit), 330 S. Dearborn St., Chicago.

PREPARE in Your Spare Time to Fly and Build Airplanes. Flying and Evening Shop Course \$150.00. Shop Course only, \$15.00. Wallace Aircraft Co., 4710 Irving Pk. Blvd., Chicago, Ill.

THE American School of Aviation announces a new correspondence course in Mechanics of Aviation. A thorough training in Practical Aeronautics. American School of Aviation, Dept. 1361, 3601 Michigan Ave., Chicago, Ill.

SEND dime for 12 inch mounted propeller and circulars on free three foot model airplane. No selling. Aero Shop, 3050 Hurbit Ave., Detroit, Mich.

BIGGEST, Best Catalog Model Airplanes, Parts Supplies; 5c postpaid. Ideal Company, 165 1/2 Spring Street, New York.

DICTIONARY of Aviation, \$3.00. Languages Publishing Company, 15 W. 18th Street, New York.

THE Age of the Air is Here. For reliable information on both airplane building and flying we recommend "Aeroplane Construction and Operation," by Rathbun. All features of construction treated. Send no money. Pay postman \$2.50 and postage. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

AIRPLANE Supplies wholesale prices; genuine leather helmets \$1.95 up; aviator goggles 70c to \$7.50; new propellers, 8' \$3.50; flying suits with insignia, \$9.50; new TM Wings, \$15.00. Air Transport, Carlo Place, New York.

BOOKS AND PERIODICALS

HYPNOTISM wins Health, Wealth, Fame, etc. 25 Easy Lessons and 248-page illustrated reference guide \$2.00. Popular Institute, 430-NJ Milwaukee Ave., Chicago.

"WHERE'D Cain Get Willy?" \$7.00 words, 20c. Jabe Studio, G. D., Kansas City, Mo.

SEND for our unique catalog of 5000 books listed alphabetically under subject headings. Free on request. Popular Mechanics Press, 200 E. Ontario St., Chicago.

HYPNOTISM easily learned. Lessons guaranteed. Postpaid, \$1.10. Smith Pub. Co., Dept. 3, Springfield, Mass.

ANSWERS to mathematical problems of office, store, shop, bank, farm, or factory. Explains and simplifies every principle of arithmetic, mechanics and mensuration. Send No Money. Just ask for Ropp's Calculator." Pay postman \$1.00 and postage. Popular Mechanics Press, 200 E. Ontario St., Room 906, Chicago, Ill.

NEW Book, Batteries, How to Make and Repair Them, \$1.00. Information Bureau, 94 Bonham St., Paris, Texas.

PUZZLES! If you like them we recommend an illustrated book containing 122 of the best Mechanical Puzzles. You can have loads of fun working out the solutions as enough hints are given in the text matter to enable one to do so. Pay postman \$1.00 and postage when he hands you the package. Address Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

SHOP Notes for 1927. Get your copy now. Only a limited edition. Contains all the articles published in the Shop Notes department of Popular Mechanics Magazine during 1926. Send no money. Just write a postal and we'll send 1927 Shop Notes and any one of the other following numbers, 1908, 1912, 1913, 1914, 1915, 1916, 1917, 1919, 1920, 1921, 1922, 1923, 1924, 1925, 1926. Pay the postman 98 cents and the postage when he hands you the two books. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

WHAT Subjects Interest You? Select from this list of helpful worth while books. Social Letters Made Easy, Spelling Made Easy, How to Develop Your Will Power, Tricks and Magic Made Easy, Bookkeeping Made Easy, Chemistry for Beginners, How to Work Your Way Through College, Confidential Chats with Boys. Price \$1.25 per volume. Pay postman price and postage when he hands you the package. Address Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

PICTURES AND POSTCARDS

JOIN Live Postcard club. Membership Lists including Catalog 10c. Harvey Teeple, Decatur, Ind.

VIEWS in natural colors. Thirty views. City of Detroit; twenty-two views of Belle Isle Park; twenty views, Ford plant, world's largest; twenty views of Detroit's largest industries and hotels. Each folder size 4x6 in. Mention views wanted. Price each folder 10c. Atlas View Co., Dept. A, Box 631, Detroit, Mich.

ART Pictures, Books and Novelties. Catalog 10c. Howard Sales Co., Dept. 15, 1188 Folsom St., San Francisco, Calif.

100 PHOTO Postcards from any picture, \$3.00. Gillespie, Photographer, 11 Portland St., Boston, Mass.

20 CEYLONESE Girl Models. Dollar bill. Art Photo Galleries, 10 Temple Road, Colombo, Ceylon.

FREE, True-Blue Book. Exchange postcards, stamps. Ericson, Elroy, Wis.

KOMIC jollying Cards free. Insetose stamp. Address Home Products Co., Turlock, Calif.

GAMES, ENTERTAINMENTS AND PLAYS

WORLD History Game describes 1,000 titles. \$1. Blounting, Campbell, Calif.

VENTRILLOQUISM taught almost anyone at home. Small cost. Send 2c stamp today for particulars and proof. George W. Smith, Room S-172, 125 N. Jefferson Ave., Peoria, Ill.

QUESTION and Answer had sweeps country. Send for a copy of the best book on this popular pastime "Ask Me Another," 2000 Questions and Answers, forty information tests with the scores of 69 people you know from all walks of life. Pay postman \$1.00 and the postage when he hands you the package. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

100 LIGHTNING Chalk Talk Stunts \$2.00. Cartoonist, 2925 Euclid, Kansas City, Mo.

CHALK-TALK your way to popularity. Audiences at your feet if you learn how to entertain with a few simple pictures. Little artistic ability needed. "How to Chalk Talk" tells what to say and what to draw. Profusely illustrated. Make \$1 and more a night. Send no money. Just order on a postal. Pay postman \$1.00 and postage. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

MAGIC TRICKS, BOOKS AND JOKER NOVELTIES

MAGIC—Tricks, Books and Supplies. For Amateurs as well as the great professionals. Anyone can learn through our instructions. Feature Acts in Mind-Reading, Spiritualism, Rope Ties, etc. Large illustrated Professional Catalog, 20c. Chicago Magic Co., 140 So. Dearborn St., Dept. B, Chicago, Ill.

FOR something different, send 10c for "Fun-Magic-Mystery." New 80-page Book of 500 Tricks. Also contains Catalog largest line Magic Tricks and Supplies in South, at lowest prices. Send 10c today! Lyle Douglas, Station A, Dallas, Texas.

SEVEN Magical Delusions and Catalogs—25c. Glimagico, Morgan Park, Ill.

MAGIC Trick Cards That Are Absolutely guaranteed. Free samples. Write me today. C. D. Blankenship, Adrian, W. Va.

FREE with \$25 order die box. Send 20c for our large catalogue of tricks, wigs, sensational escapes. Oaks Magical Co., Dept. 518, Oshkosh, Wis.

ELECTRIC Fun! Seventy stunts, 110 volts, \$1. Tawutting, Campbell, Calif.

FORTUNE-TELLING and Dream Books—Gypsy Madge's big 66-page size, 25c. Gypsy Oracle (smaller), 10c. G. Elsea, Bowling Green, Ohio.

CARD tricks. Coin tricks. Hypnotism. Ventriloquism. 64-page books. Complete guides 10c each. Geo. Fenner, 2401 Jefferson, Louisville, Ky.

BECOME a Handcuff King! Fool friends! Mystifying! Absolutely new! Full instructions 25c. Price, Harleysville, Pa.

FREE: Catalog of Amazing Tricks, Wonderful Novelties, Funniest Jokes. Theodore King, 566 Main, Worcester, Mass.

READ Sealed Messages in Dark; messages retained by audience; burned message appears on blank slate; spirit message appears on slate in sitter's presence; spirit rappings; spirits appear in the dark; answer questions written on folded papers while blindfolded. All this you can do with directions in "Behind the Scenes with The Mediums." 80 best secrets of mediums fully exposed. The best because most baffling, yet all easy to do. Send no money. Just write a postal. Pay postman \$1.50 and postal charges. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

COMPLETE Book on Magic. 563 pages, 318 illustrations. Hundreds of tricks. The standard book for years. Make money giving magic entertainments. Send no money. Just ask for Prof. Hoffman's "Modern Magic." Pay postman postal charges and \$2.00. Popular Mechanics Press, Room 900, 200 E. Ontario St., Chicago, Ill.

NOVELTIES, CURIOS, ETC.

EGYPTIAN Jewelry. Antique designs—brooches, earrings, bracelets, cuff links, neckties, each \$1. Novelty Tut-Ankh-Amen necklaces \$2; ladies' silver shawl, needle work, \$7.50; scarf pins, letter openers, each 50 cents; spoons, powder-boxes, cigarette holders, each 75 cents; mummy pencil, \$1.50; scarab gems, pair \$1.50; fan, \$1.25; 24 picture postcards, 50 cents. Cushion Pharaonic ornament, \$1. Fly whisk hair, ivory handle, \$1. Stick hand ivory, engraved, \$5. Ivory pen, \$1. Oriental perfume, phial, \$1.50. Postage free. American dollars, paper money, accepted. Pharos' Store, Fouad Stefan, Luxor, Egypt.

NEW Puzzle. Spelled numbers appear as total. Ten sample solutions for one dime. R. C. Hill, 602 W. Jefferson, Detroit, Mich.

STAMP COLLECTING

A COMPLETE Beginning Collector's Outfit for \$1.00. The Imperial Combination has proved one of the most successful offerings that we have ever made, for it provides the collector who is just beginning, or the non-collector who wishes to make a suitable gift to a beginner, and does not exactly understand what is wanted, a complete well-rounded outfit. Nothing is lacking for the collector who is just commencing to learn the fascination of the hobby. The Imperial Outfit is furnished in a strong, attractive envelope, and will be forwarded to any address, with your card enclosed if you so instruct us. The Imperial Combination contains the latest edition Imperial Postage Stamp Album, with spaces for 4,000 stamps, 1,000 Superior Stamp Mounts, Scott Seal Packet No. 15, containing 300 Different Foreign Stamps, Scott guaranteed. Philatelist Millimeter Scale, the Guide to Stamp Collecting. An attractively illustrated 48-page book which guides the beginner, clearly explaining step by step the things that collectors should do and know. \$1.00 Post Free. Scott Stamp & Coin Co., 1 W. 47th Street, New York.

500 DIFFERENT Stamps for 25c! Big Collection 500 Different Stamps from Bosnia-Herzegovina, Crete, Epirus, Hong Kong, Iceland, Kenya and Uganda, Liberia, Malta, Nyassa, Tanganyika, Wallis and Futuna, Zanzibar, and other "hard" countries. Catalogue value \$10.00. Price only 25c to Approval Applicants! Special Bargains: 1,000 different 7c; 15 triangle stamps 49c; 100 Africa 50c; 100 Asia 60c; 100 Balkan States 35c; 100 British Colonies 25c; 100 French Colonies, 30c; 100 Portuguese Colonies 50c; All 8 packets for \$3.00! Illustrated Lists Free. Loma Stamp Co., 2221 Madison Ave., San Diego, Calif.

MYSTIC'S "Queer Country" Packet! Contains scarce stamps from the following strange lands: San Marino, Antioquia, Congo, Cyprus, Fiji Islands, Gwallor, Hyderabad, Iceland, Jhind, Kenya, Uganda, Lebanon, Monaco, North Borneo, Nyassa, St. Thomas Prince, Port, Guinea, Sierra Leone, Tanganyika, Trinidad, Tobago, Ubangi, Upper Volta, Wallis Futuna, Zanzibar. Get this wonderful packet of "freak countries" and make your friends envious! Price only 10c to approval applicants! Write today. Mystic Stamp Company (Dept. 8), Camden, New York.

ANCHERS \$\$\$ Outfit—only 12c! Fine triangle stamp; set German stamps with (pre-war) value forty million dollars (interesting!); perforation gauge, mm. scale; small album; airmail set; scarce stamp from smallest republic on earth; newspaper set; packet good stamps from Travancore, Johore, Dutch Indies, etc. Entire outfit for 12c to approval applicants! (Nice pocket stock book, value 25c, with every order!) Ancher Stamp Co., 148½ Clerk St., Jersey City, N. J.

GET in on this. Collection 50,000 varieties broken up. Lists for approvals and want Liberal Discount. Reference Required. Tower Stamp Co., 42 Westville St., Dorchester, Mass.

\$1.00 FREE. Black U. S. Postage. Given Away with each order. Pioneer Stamp Album with 300 illustrations, 150 different stamps from 40 countries, Syria, Lebanon, Helaz, Liberia, New French Colonies, British, Portuguese Colonies, South Africa, Australia, 500 hinges, 56 page illustrated catalogue. All for 15c. Big Commission to Agents for the Best approval sheets of stamps ever offered. Write for sample outfit. Hossman Stamp Co., Dept. M, 620 Olive St., St. Louis, Mo.

VERY Special—500 Different 25c, 1,000 different 75c. Ask for price lists and approvals. Cleveland Stamp Co., Caxton Bldg., Cleveland, Ohio.

70 DIFFERENT Foreign Stamps—70 Different Foreign Countries— including Africa, Asia, Australia, Europe, West Indies for 16 cents. Free—With each order we give our pamphlet which tells you "How To Make a Stamp Collection Properly," also price list of albums—supplies and hundreds of Bargains in sets and packets. Queen City Stamp Company, Room 36, 604 Race St., Cincinnati, Ohio.

BEST one-cent approvals in America. F. P. Hand, 1117 S. 60th St., Philadelphia, Pa.

25 DIFFERENT Portugal Colonies 5c. 25 Different French Colonies 5c. Holtub, Approvals, Deland, Fla.

300 DIFFERENT 7c. 100 U. S. 25c. U. S. Stamps; Foreign Packets. Lists Free. Midwest Stamp Co., Kemper Bldg., Kansas City, Mo.

BIG Bargains. 4c up. Babcock, 407 E. Port, Detroit, Mich.

EUROPE Collection. 19th Century. Fine condition, over \$7,000.00 catalogue. Price \$400.00. Also Mint Collection, German Colonies complete. High values, sheets of twenty. Catalogue \$630.00, price \$500.00. Carl Hackert, 332 East 87th St. New York City, N. Y.

CANADIAN—25 different only 10c and asking to see our Excellent Approvals; receive Beautiful Confederation Jubilee stamp, 5 Newfoundland and Bargain Lists free. Victoria Stamp Co., London, Canada.

MOST Sensational values; over 140 diff. Algeria, Airplanes, Azerbaijan, Barbados, Cameroon, Gabon, Guyana, Irish set, large French Colony packet, largest stamp, 40 year old U. S. gauge, etc. for 10c to approval applicants. List free. 100 diff. U. S. 25c—1,000 hinges 3c—50 Bavaria 7c. Hawkeye Stamp Co., Cedar Rapids, Ia.

TO approval applicants enclosing 10c for our Marvel Packet of 55 different from Gabon, Togo, etc., we will send—absolutely free—a genuine scarce South African triangle stamp! Curhan Stamp Co., Gloucester, Mass.

105 CHINA, etc. 2c. Album (500 illustrations) 3c. Bullard, Sta. A. Boston.

STAMPS sent on approval at 70% discount. Reference required. Emory Renold, Hanover, Pa.

UNITED STATES—Send on approval. Send me your want list. Ref. Please. M. Hanna, New Kensington, Pa.

FOREIGN Revenues, Telegraphs, Locals, envelopes, rails, etc. pretty, different, cheap. Stamped Marine Policy free to applicants with references. Vanderhoof, 1114 Logan, Denver, Colo.

200 DIFFERENT stamps 10c; 1,000 Hinges 10c. R. H. Carlton, 380 W. So. Temple, Salt Lake, Utah.

COLLECT Newfoundland. Foundation packets: 80 Scotts varieties \$10.00; 63 for \$5.00; 38 for \$1.00; 23 for 25c; 127, 129 and 130 (3) for \$1.50; 131-144 for \$1.00. Illustrated Catalogue 10c. Rev. Butler, St. Georges, Newfoundland.

\$1.00 CATALOGUE value of stamps given free to applicants for our approvals. Stamps in Sets only. Real Premiums to First 50 Buyers. S. S. Kahn Co., Ardmore (4), Okla.

200 DIFFERENT stamps given to collectors desiring approvals. E. Lee, 539 South Salina, Syracuse, N. Y.

FRENCH Colonies Free—Jungles, Tigers, Native Chief, 2c postage. Empire Stamp Co., Toronto, Canada.

100 DIFFERENT Stamps Free to Approval Buyers. Postage 2c. Write now. Winchell Stamp Co., Woodbine, 26, Penna.

MINT packet free—53 different unused free to approval applicants. Postage 2 cents. Arthur Taylor, Box 830, Milwaukee, Wis.

FREE! Beautiful unused set 10 Jugoslavia 1920, cataloging \$1.81, to approval applicants. Pennsylvania Stamp Co., Greensburg, Pa.

TRIANGLES—6 different 15c, 15 different 40c, 25 different \$1. Elwood D. Weber, 1377 Park Avenue, Plainfield, N. J.

300 DIFFERENT Stamps and Premiums, 10c. Central News, Watertown, S. Dak.

THOUSAND Foreign Stamps, 50c; catalog free. Prof. McCreery, Chatham, Ontario.

200 DIFFERENT Stamps, Zanzibar; Album, 12c. Liberty, 3974 Arsenal, St. Louis, Mo.

35 BARBADOS 50c; 50 British Gulana 35c. Craven Stamp Co., Thompsonville, Conn.

APPROVAL books 50%, 25% on any country. Premiums with purchases. Noemus Stamp Co., 312 East 23rd St., New York.

1,000 DIFFERENT, \$0.80; 2,000, \$3.50. Fred Onken, 630 79th Street, Brooklyn.

OUR Surprise Packet at 25c includes—Rare Stamps, Coins, Shells, Arrow Points, Quills, Lists, etc. Ye Olde Hobbie Shoppe, Port Huron, Mich.

100 DIFFERENT Stamps, Cat. \$2.50, only 10c to applicants who send Reference. 2,000 Varieties only \$2.00. Ye Olde Hobbie Shoppe, Port Huron, Mich.

300—300—300—ALL different stamps (\$6.00 catalogue); 300 hinges, 5 approval sheets; duplicate stamp album; perforation gauge, millimeter scale and ruler to approval applicants for only 20c. Edgewood Stamp Co., Milford, Conn.

ANNIVERSARY Offer! Seven following sets: "Anniversary," "Jubilee," "Charity," "Airmail," "Eagles," "Prisoners," "Pictorials." Four following packets: (British, French, Dutch Colonies), (Precancels) (Bulgaria), (International) 15c to approval applicants. Deering, Fairmount, Marlborough, Mass.

PHILLIPS' Monthly Bulletin offers over 2,000 stamp items, bargains, sets, fine stamps. 32 pages. Free. Phillips, Box 1012, Hartford, Conn.

1000 UNITED STATES and Foreign Mixed Postage Stamps for Collectors. Including 300 different, 50c. C. W. Parker, 77 Kensington Heights, Meriden, Conn.

BORNEO Month at Wirth's. Six different, 20c; nine different, fine. 35c. Wirth, 139 Shepherd Avenue, Brooklyn.

FREE—50 to approval applicants. Postage. T. Hopes, 1602 Belle, Lakewood, Ohio.

DANDY packet free with approvals. Wm. Monjar, 1518 Waverly, Cincinnati, Ohio.

FIFTY stamps, album outfit 12c. Wonder Packet 10c. Clover, 608 Goldsmith Bldg., Milwaukee, Wis.

STAMPS sent on approval. Premiums Given. Philip Peyser, 2216 Wyoming Ave., Washington, D. C.

FREE! 4 Confederate States! Request Approvals, 2c and references. Southern, 1453 Graham, Atlanta, Ga.

150 GOOD mixed foreign stamps 3 cents. Stanton, Niantic, Conn.

110 NEW Europe All Different, a wonderful collection cataloging several dollars, free to collectors requesting our Net Approvals. Postage 2 cents. Badger Stamp Co., Milwaukee, Wis.

FREE Hungary Charity No. 505 to 567 and a surprise packet given to those requesting for my 1, 2, and 3c approvals, and also my 50% discount. Chas. W. Schmidt, P. O. Box 4832, Frankford Station, Philadelphia, Pa.

BORNEO, Malaya, Liberia, large U. S. revenue, commemoratives, with 105 other different U. S. and foreign stamps for only 9c. Fennell Stamp Co., Dept. M, St. Louis, Mo.

100 FOREIGN Postage Stamps for 4 cents postage, together with handsome stamp wallet offer and approvals. Lists free. Palmer Stamp Co., 8221 Linwood Ave., Detroit, Mich.

109 DIFFERENT, Arabia, Azerbaijan, Zanzibar, etc., 10c to approval applicants. Floyd Marsh, 524 Hamilton Ave., Indianapolis, Ind.

110 DIFFERENT Stamps, many unused, high values, free to collectors requesting our Net Approvals. Postage 2 cents. Christensen, Milwaukee, Wis.

ONE Dollar catalog value free with first purchase of \$1.00 net from my popular approvals. Better class of stamps for those willing to spend \$1.00 or more at a time. References please. A. Bauer, Palmyra, N. J.

500 DIFFERENT, 35c; 350 different, 25c; 200 different, 12c; 500 mixed, 18c. Evans, Box 360, Reading, Pa.

1,000 ALL different stamps \$1.00. New price list of all United States stamps free. Voorhees, 7 South Dearborn St., Chicago.

1,000 DIFFERENT Fine Stamps, 69 cents. Approvals. Kentworth Stamp Co., Ridgewood, N. J.

STAMPS, 100 varieties, Africa, Brazil, Peru, Cuba, Mexico, etc., 10c; 25 different U. S., 25c; 1,000 mixed, 40c; 1,000 hinges, 10c. List free. C. Stegman, 5941 Cota Brilliante, St. Louis Mo.

LIBERIA Snake Triangle and two other triangles in our packet of 53 genuine foreign stamps for five cents. Crowder Company, Waverly, Baltimore, Md.

24 VARIETIES Cuban stamps, 10 cents. List of 8,000 low-priced stamps free. Address Chambers Stamp Co., 1117, Nassau St., New York City, N. Y.

COVERTCO Packet, 250 varieties unused and used stamps 15 cents. Covert Stamp, 39 State, Rochester, N. Y.

STAMPS, 100 all different. Postage 2c. Lists free. P. M. Quaker Stamp Co., Toledo, Ohio.

FREE! Loose Leaf Postage Stamp Album at rate of 8 pages each month given with subscription to monthly Journal. Send 2c stamp for prospectus. United Stamp Co., Marquette Bldg., Chicago, Ill.

MAGNIFICARCIOS Packet foreign stamps, beauties from distant lands. (Many richly colored, unusual designs) free for 2c. Gray Stamp Company, Toronto, Canada.

TRIANGLES! 75% discount—Special approval sheets with each 5c packet containing set triangles. 2 sets war tax, set airplane, U. S. stamp before 1880, etc.; over 100 different stamps. Murray Stamp Co., 515A Tower Bldg., St. Louis.

PENNY Approvals that Satisfy. Nell Gronberg, Box 5441, Philadelphia, Pa.

100 STAMPS from 30 Countries, 5c. Lufbery, Port Orange, Fla.

OUR Latest 20-page U. S. and Canadian price list free. Stanley Gibbons, Inc., 37 Ann St., New York City.

FREE 40 Czecho Slovakia Stamps to approval applicants. 2c Stamp. Lightbown's, Osborn Rd., Nouthsea, England.

DIME approvals. Modern assortments. Sets—Packets—Singles. Free Premiums. Marney's, 400 Broadway, East St. Louis, Ill.

BEAUTIFUL Picture Stamps Sent Free. Paul Cornish, Schenectady, N. Y.

200 STAMPS, Bargain List. Magazine 15c. Harrey Teeple, Decatur, Ind.

509 DIFFERENT Foreign classy stamps cataloging \$10.00 for 19c; with pretty approvals, 1011 Ditt. Cat. \$25.00 for 69c. Rotnem Stamp Co., 809 N. W. Bldg., Minneapolis, Minn.

RARE COINS

OLD Money Wanted. Will pay \$100.00 for 1894 Dime, S. Mint. \$50.00 for 1913 Liberty Head Nickel (not Buffalo). Big premiums paid for all rare coins. Send 4c for Large Coin Folder. May mean much profit to you. Numismatic Co., Dept. H, Fort Worth, Tex.

OLD Coins Bought and Sold. Rare Coin Book 50c (Plus Postage). 700 Illustrations. Send 10c for Coin collecting booklet. Guttig Bros., 16 Exchange Place, New York.

50,000 COINS, medals, bills: Lists free. Collectors Exchange, 1536 Willington, Philadelphia.

GET Profit and Pleasure in collecting Old Coins. Send 10c for Large Illustrated Coin Catalogue. You'll be delighted with it. Send for it right now. B. Max Mehl, Numismatist, Mehl Bldg., Dept. P, Fort Worth, Texas. Largest Rare Coin Firm in the U. S.

UNITED STATES. Large Cent, two-cent bronze, three-cent nickel and Bargain List, 25c. Fifteen dates large cents, \$1.00. George Coffin, Greenwood Mountain, Me.

\$2 TO \$500 Each Paid for hundreds of old and odd coins. Keep all old money, it may be very valuable. Send 10 cents for illustrated coin value book, 42c. Get posted. Guaranteed prices. We buy and sell. Clarke Coin Office, LeRoy, N. Y.

25 DIFFERENT Coins 50c. Odderon, Box 681, Kansas City, Mo.

CONFEDERATE Note, White Metal Coin 10c. 2 coins, 3 notes, 10c; Russian Note, German Bond and catalog, 15c. Geo. Best, Cedar Rapids, Iowa.

OLD Coins. Large Spring Selling catalogue of coins for sale free. Catalogue quoting prices paid for coins, ten cents. William Hessler, 101A Tremont Street, Boston, Mass.

40 OLD coins, all different, \$1.00. 25 different coins 50c. 100 different coins \$3.00. 200 different coins \$5.00. 300 different Germany Bills \$1.00. Lexington Concord Half-Dollar, uncirculated, \$1.10. Claud Denney, Box 315, Dallas, Texas.

CALIFORNIA Gold—Quarter Size, 27c; 1/2 size, 53c; 3c Piece and Catalogue, 10c. Norman Schultz, Box 746, Salt Lake, Utah.

ROMAN coins 1000 years old, 25c. Durso, 25 Mulberry, New York City.

WANTED. Old Money. 8 Coins 25c; list free. Brooks, 2725 1/2 Live Oak, Dallas, Texas.

50,000 RARE coins, medals, bills: Lists free. Collectors Exchange, 1536 Willington, Philadelphia.

FOR BOYS

INTERESTED in Science? Form science club in your town. Conduct experiments, field trips, etc. Instruction booklet, club plans, membership blanks, sample magazine 25c coin. Scientific Clubs America, McComb, Miss.

DRAFTING. Learn Mechanical Drawing. Big demand for men. Pocket size. Start at beginning and learn by a series of simple lessons. Send no money. Just write postal for "Practical Course in Mechanical Drawing." Pay postman postage and \$1. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

BOYS, make "Wonder" gun, strong shooter, 36" long. Fun aplenty. Easy instructions 35c. Box 4185, Tampa, Florida.

TWENTYTH 1/2 p. electric motors. Fine for fans or experimenting. Runs off dry cells or radio battery. Finest workmanship. \$2.25 each, postage prepaid. Send cash or money order. A. Redmond Co. Flint, Mich.

SHALL I Become an Engineer? You can decide this all-important question better by reading a book called "Engineering as a Career," written by a group of eminent engineers. It costs only \$1.00. You will find the advice of these successful men to be of the greatest value. Pay postman price and postage when he hands you the package. Address Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

BOYS—Machined parts for electric motor free. Write for particulars. Hudson Valley Specialty Co., Box 643, Poughkeepsie, N. Y.

FILMS for Toy Machines. 200 feet \$1.50 Postpaid. Dixie Film Co., Box 2042, Memphis, Tenn.

FUN Making Things. Four large profusely illustrated books telling how to make almost everything from a sail boat to a toy automobile propelled by a motorcycle engine. Now \$2 per book or \$7 for the four if ordered at once. Send no money. Just write a postal saying, "Send the Boy Mechanic Library." Pay postman \$7 and postage. For single books, specify either Book 1, Book 2, Book 3, or Book 4. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

CAMERAS AND PHOTO SUPPLIES

PHOTOGRAPHIC equipment and accessories of every description are listed and illustrated in our 228-page catalog. It will pay you to secure a copy which is issued free, as our prices are low. We also deal in used goods which are sold under the same guarantee as new goods. Ask for our Bargain Book. Central Camera Co., Dept. E113, 112 S. Wabash Ave., Chicago, Ill.

MAKE money in Photography. Learn quickly at home. Spare or full time. New plan. Nothing like it. Experience unnecessary. American School of Photography, Dept. 3432, 3601 Michigan Ave., Chicago.

KODAK Film—Special Trial Offer—Your next roll developed 5c, prints 3c each. Beautiful 6x10 mounted Enlargement 40c. Same-day Service. Fleet Photo Service, 825 G St., N. W., Washington, D. C.

START a Home Travel Club. See interesting places in and out of United States without expense and discomfort of traveling. Ask particulars today. The Kenneth Sales Co., Dept. C, Box 823, Poughkeepsie, N. Y.

BIG Money Saved on Photographic Lenses and Apparatus—goods exchanged; repairing done. Ralph J. Golsen, 1123 Argyle St., Chicago. Dept. P.

FILMS Developed. Special Trial Offer. Any Size Kodak film developed 5c, prints 3c each. Trial 6x10 Enlargement in handsome folder 40c. Overnight Service. Roanoke Photo Finishing Co., 209 Bell Ave., Roanoke, Va.

HAVE You a Camera? Write for Free sample of our big magazine, showing how to make better pictures and earn money. American Photography, 115 Camera House, Boston, 17, Mass.

GERMAN Cameras, Bargains—2 1/2 x 3 1/4. \$4.5 lens, \$22.50. Bartro, 6436 Hotel St., Los Angeles, Calif.

AMATEUR Photographs Profitable. Booklet describing One Hundred Best Magazine Markets 10c. Snyder Publishing Co., Guilford, Conn.

FOR \$1.00 we develop your Film Free; make one dozen Postal Card prints from best negatives. Old Masters Studio, Station V, Cincinnati, Ohio.

PHOTOGRAPH from unpublished negative Abraham Lincoln \$1.00. Roessler, East Orange, N. J.

MOTION PICTURES

\$\$\$ 1250 FOR a Photoplay Story by an unknown writer and sold through our Sales Dept. We revise, copyright and market. Located in the heart of Motion Picture Industry, we know the demand. Estab. 1917. Send Mss. for free criticism. Booklet on request. Universal Scenario Company, 296 Western and Santa Monica Bldg., Hollywood, Calif.

FILMS: \$3.00 per reel up. Comedy, Western, Cartoon, Drama, Serial, Educational, Special Features. Best Movie Stars. Free List. Top Film 200 Feet Postpaid \$1.50. Dixie Film Co., Box 2042, Memphis, Tenn.

NEW and Rebuilt Projectors for Theaters, Schools, Churches, Traveling Shows. Supplies and Complete Theater Equipments. Bargain Prices. Free Catalog. Monarch Theatre Supply Co., Memphis, Tenn.

FOR Sale: Motion Picture Films, \$5.00 per reel and up. Short lengths for toy machines, 1/2c per foot in lots of \$2.00 worth or more. Progress Pictures, 3320 Lindell, St. Louis, Mo.

SEND \$2.00 for starting new Cinemeter. Gives exact exposure for all Movie Cameras or lenses. Fits pocket. Free Bargain List of Motion Cameras. Bass Camera Company, 109 North Dearborn Street, Chicago, Ill.

NEW 100-foot spring motor camera, \$100; 16 1/2-foot spring motor camera, \$37.50. Eastman negative film 3 cents foot. Motor drivers suitcase. Projector \$50. Movie printer, \$25. 50-foot developing outfit, \$200. Films, \$2 reel. 5 Mazda lamps, 25 volts, 3 amperes, \$5.00. Ray, 236, 5th Ave., New York.

CARTOON Movie Film. Fifty feet, one dollar. List. Alton Films, 205 Brush Creek, Kansas City, Mo.

FILMS and Machines, dirt cheap. Stamp for lists. Box No. 5836, Westport Station, Kansas City, Mo.

WESTERNS, features, \$2.00-\$3.00 per reel. Stewart Marshall, Rome, Ga.

1000 FEET of Comedy, \$2.00. No lists. Sunset Film Exchange, 298 Turk St., San Francisco, Calif.

SCENERY TO RENT

WORLD'S Most Beautiful Settings for operas, plays, minstrels. Amelia Grain, Philadelphia.

EDUCATIONAL AND INSTRUCTION

YOU can have a business profession of your own and earn big income in service fees. A new system of foot correction; readily learned by anyone at home in a few weeks. Easy terms for training; openings everywhere with all the trade you can attend to. No capital required or goods to buy, no agency or soliciting. Address Stephenson Laboratory, 1 Back Bay, Boston, Mass.

STORY Ideas Wanted for photoplays, magazines. Big demand. Accepted any form for revision, development and submission to markets. Estab. 1917. Send manuscripts for free criticism. Booklet mailed on request. Universal Scenario Company, 403 Western and Santa Monica Bldg., Hollywood, Calif.

WORLD-ROMIC System. Masterkey 5,000 languages. Primers, \$1.98; Arabic, Chinese, French, German, Italian, Japanese, Russian, Spanish. Languages, 15 W. 18th St., New York.

YOU Need a better grip on mathematics? Tell us to send you a copy of "Mathematics for the Practical Man," only \$1.50. By common sense methods it removes the mystery and difficulties so algebra and calculus are made simple. Assuming your knowledge is limited to arithmetic you quickly and easily gain a working knowledge of algebra, geometry, trigonometry and calculus. Simply pay postman when he hands you the package. Address Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

YOU can now secure a full correspondence school course and complete training in any business or technical subject for only \$10; complete course in business, traffic, law, banking, accounting, salesmanship, drafting, electrical work, railroad positions, mining, auto work, etc. Send for complete list of subjects and free, full information. American Vocational School, Lewisburg, W. Va.

FAMOUS Bailey Handbook—The book that prepares you to pass the examination for any grade of license for stationary, marine and Diesel engineers, firemen and boiler inspectors in any state of the union or any province of Canada. Flexible cover. Handy pocket size. Pay postman \$2.00 plus the postage when he hands you the package. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

\$1,000'S IN Prizes! Particulars of about 100 contests monthly. Articles and helpful hints by winners. Copies Contest News and our comic White Mule magazine (40c value) only 10c in coin. Fin-Ko Pub. Co., D-12, Toledo, Ohio.

LEARN Bookkeeping in Ten Lessons. Shelby course is brief, concise, complete. Makes bookkeeping easily understood. Price \$5. Write for particulars. Shelby Publishing Co., 605 Cotton Exchange Bldg., Memphis, Tenn.

MACHINE Shop Mathematics without attending School: Simple as A, B, C. How to figure Blue Prints, Feeds, Speeds, Piece Rates, Trigonometry, Etc., many daily Problems and Solutions. Complete \$1.00. Machine Shop Math. Sales Co., 2537 N. Armit Ave., Chicago, Ill.

DIESEL Engines—Marine, locomotive, stationary. Growing importance of the Diesel engine cannot be overestimated. This new book should be in the hands of every student of mechanical engineering. 500 pages, 280 illus. Pay postman \$5 and postage when he delivers book. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

FIREMEN. Brakemen. Baggage-men (white or colored), sleeping car, train porters (colored), \$150-\$250 monthly. Experience unnecessary. 810 Railway Bureau, East St. Louis, Ill.

8 KEYS. (Copyrighted) master double entry bookkeeping, easily, quickly, thoroughly. Guaranteed. International Bookkeeping Institute, Springfield, Mo.

LEARN Auctioneering at Home. 5 Lessons Free. American Auction College, Kansas City, Mo.

CARTOONING and Commercial Art. 25 lessons. 300 illustrations. 2 clothbound volumes and drawing outfit \$5 postpaid. Catalog Free. No-Way Art School, 220-B Graham Ave., Brooklyn, N. Y.

BE a Laboratory Expert. Earn from \$300 to \$500 Monthly. Study Microbiology Sanitation. Day, Evening classes, Diplomas, Degrees Granted. 71-piece outfit Free to students. Write for our Free Prospectus To-Day. International College of Microbiology, 2517 N. 76th Ave., Chicago, Ill.

USED educational matter. Lowest prices; terms. Catalog free. Mention Subject. Fred Goetz, 410-A Sansome, San Francisco.

USED educational matter sold on repurchase basis. Also rented and exchanged. Money-back guarantee. Catalog free. (Books, etc. bought.) Lee Mountain, Flagg, Ala.

CARTOONING—Complete course. Unusually low price. Particulars on request. Carlson Cartoon Service, Dept. M, 116 West 39th Street, New York.

AMATEUR Cartoonists: Make money in spare time with new cartoon selling plan. Write Smith's Service, PM1194, Wenatchee, Wash.

INSTRUCTION books, all kinds. Catalogue free. Winchell Book Co., Woodbine, 4, Penna.

EARN \$25 weekly, spare time, writing for newspapers, magazines. Experience unnecessary. Details Free. Press Syndicate, 881, St. Louis, Mo.

CARPENTERS Ideas for those who like to tinker with tools, and for professional carpenter. 40 articles on saw and sawing, 17 on benches and bench equipment, 22 on doors and door hanging, 18 on lumber, 13 on millwork, 74 on tools, 22 on shop equipment, and many others—304 in all, and 229 illustrations. Send No Money. Just write a postal. Pay postman postage and \$1.50. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

RADIO OUTFITS AND SUPPLIES

TRADE Radio receiving parts (must be new condition, latest models), you cannot use for new parts you can use. Parts only, no sets. Catalog and over two pounds circuits, etc., prepaid, 25c. Radio Exchange, Kent, Ohio. (Established 1921).

RADIO Cabinets: Limited stock of slightly defective phonograph cabinets; mahogany finish and quartered oak; formerly retailed at \$35.00; will close at \$5.00 each. May be changed readily to first-class Radio Cabinet accommodating panel about 8x15. Lower compartment 15x20. Lundstrom Mfg. Co., Little Falls, N. Y.

RADIO Receiver; All stations—American and overseas; all wave lengths—200 to 4,000 meters. This 6 tube Gnome Polyphase, the latest development in modern radio. Agents wanted. 100% profit—\$100—per week easy. Radio Exchange, 925 Broadway, New York.

RADIO Up-to-the-Minute. Telegraphy, radio reception, vacuum tubes, telephony, how to build receivers, broadcasting, all treated in new book. Send no money. Pay postman \$1.25 and postage. Just write postal for "Radio Up-to-the-Minute." Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

300-MILE "Pocket" Radio, \$2.00. No Tubes nor Batteries required. Useful and practical, loudspeaker volume. Order direct today. Spencer Laboratories, 116 Atlas, Akron, Ohio.

"B" ELIMINATOR chokes, 30H, 85M.A., \$2.75 postpaid. We estimate on kits and parts; send your material list. Radio Parts Sales Co., Orange, N. J.

GROUND Troubles Ended. Silver Streak Ground Rod, \$1.00 Postpaid. Cooper-Cheney Radio Shoppe, Lima, Mont.

BIG money building 5-tube Radios. Instructions 40c. Complete Kit \$13. B. C. Biggs, University Place, Nebra.

CATALOG listing Radio Supplies on request. Arthur Dombrowski, 4341 So. Campbell Av., Chicago, Ill.

BUILD your own trickle charger, costs less than \$2.00. Instructions and diagrams 25c. A. C. Fernekes, 117 Culver Parkway, Rochester, N. Y.

RADIOS, 5-tube assembled \$29.50; kits \$18.50. J. L. Daltovich, 4910 Grassell, East Chicago, Ind.

BEST Radio Book—New Third Edition, 1927. Revised—Radio Theory and Operating by M. T. Loomis of the Loomis Radio College is America's Standard Radio Text-Book. Used by the various gov't depts, and schools and leading radio schools. 385 pages, 700 illus., flexible krafty leather binding. Sent C. O. D. Pay postman \$3.50 and the postage when package is delivered. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

TRADE AND TECHNICAL SCHOOLS

LEARN Bricklaying and earn \$1 to \$1.75 an hour. Wm. M. Woods, who has trained 500 men will teach you bricklaying in our school run by 800 builders interested in giving jobs to Mr. Woods' students. Tuition \$60.00 per month. Time required 3 to 6 months. Board and room \$3.00 to \$10.00. Work is actual bricklaying; you become master in the craft, in line for highest wages and promotion. Ample space and material. Catalog free. Associated Building Employers, N-400, A. B. E. Bldg., Grand Rapids, Mich.

AUTO Industry wants National-trained men. Salaries \$50 to \$200 weekly. National has helped 16,000 inexperienced men to big pay. Earn while you learn in Los Angeles. Million dollar shops. Write for free book. National Automotive School, 4006, Dept. 30, Figueroa, Los Angeles.

HERE At Last—A real Home Study course in Decorating, Sign Painting, Show Card Writing, Gilding and Marbling—taught by Moving Pictures. We give you a Moving Picture Machine with the course. Write for full particulars: National Paint & Decorating Assn. School, 435 N. Clark St., Chicago, Ill.

GET a Foreman's job in any trade. You will earn more money. Become an expert Blue Print Reader. You can do it in spare time. My training will advance you quickly. Write now—tell me what trade you want—I will send my plan at once. Carroll Rumsey, 265 Drexel Building, Philadelphia, Penna.

TELEGRAPHY—Both Morse and Wireless—taught thoroughly and quickly. Tremendous demand. Big salaries. Wonderful opportunities. Expenses low; chance to earn part. School established fifty years. Catalog free. Dodge's Institute, Fern St., Valparaiso, Ind.

TRAIN for big pay electrical jobs on half million dollar equipment. Earn while you learn. Learn right. Low rates. Write for free book. National Electrical School, 4006, Dept. 40, Figueroa, Los Angeles.

LEARN barbering at home. Practice on the family. Complete barber college instructions, home study, for \$1 bill or money order. Foster, Expert Barber, 6128 Michigan Blvd., Chicago, Ill.

BUSINESS OPPORTUNITIES

NOTHING on earth offers bigger opportunity for building wonderful business this summer than manufacturing these popular profitable, big-selling specialties. Start small—watch business grow. Write today for valuable formula literature relative to making: Sealstite, guaranteed puncture proof liquid; Ducapol, automobile polish; Cellulac, Duco finishes in color, quick drying; Solvrit; powdered hand cleaner; Miracle, non-thermic ice cloths, mendit, fabric patching liquid; Liqui-Seal, radiator cement; Vanil-Ozone, "million-dollar" vanilla flavor; Fruitina; concentrated summer drinks; and a hundred other real honest-to-goodness, money-making propositions. 30 years headquarters for best formula service. Miller, Chemist, 1706-B Jetton, Tampa, Fla.

A GOLD mine of information for only \$1.00. Strongest man cannot lift you—secret 50c. To sober up instantly—great for those who over-drink, 50c. Guessing anyone's weight—circus stunt—never fails, 50c. Liquor remedy—stop drinking, 50c. Tearing telephone book in two—giant strength, 50c. Have a grip of steel—shake till it hurts, 50c. Five celebrated anti-tobacco formulas, 50c. Calfing heads or tails every time, 50c. All above secrets and 27 others for only \$1.00. American Sales Co., Postoffice Box 1278, San Francisco.

READ The Mail Order News—America's Pioneer Mail Trade Journal. Quarter Century Old. Approximately 600 pages yearly of valuable information for beginners and established mail-order houses. Analyzes mail-order business, its opportunities. Practicable mail-order ideas, legitimate money-making schemes, instructive articles. Tells how to start, what to sell. Published monthly. Subscription \$3.00 yearly. Send 25c for sample copy. None free. Mail Order News, 360 Bristol Bldg., New York.

ARTIFICIAL marble sanitary flooring instructions, covering wood or cement flooring 1/2 inch thick, fireproof, waterproof, all colors, low cost. Ornamental casting, concrete, plaster, papier-mache decorations, garden furniture, statuary, flexible molds. 17 years instructing the public; particulars and illustrations free. Chris. Mahler, Huntington, N. Y.

ENTER a new business. Earn \$3,000 to \$6,000 yearly in professional fees making and fitting a foot specialty, openings everywhere with all the trade you can attend to; easily learned by anyone at home in a few weeks, at small expense; no further capital required, no goods to buy, job hunting, soliciting or agency. Address Stephenson Laboratories, (1) Back Bay, Boston, Mass.

GOLD, Silver and colored sign letters for windows, sign boards, trucks, automobiles. Make them yourself with our instructions and letter patterns. Fast sellers, big profits all or part time. No experience required. Field unlimited. Collect two profits, making and selling. Stamp brings actual sample and complete description. Enterprize Systems, 616 North Michigan, Chicago.

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence O. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

GET into the mail order business. Unlimited opportunities for ambitious persons. Write today for our big "free" offer. Publisher, 6053-J Gravois, St. Louis, Mo.

PATENTS Procured; Trade Marks Registered—A Comprehensive, experienced, prompt service for the protection and development of your ideas. Preliminary advice gladly furnished without charge. Booklet of information and form for disclosing idea free on request. Richard B. Owen, 30-Owen Bldg., Washington, D. C., or 41-R Park Row, New York.

MECHANICS, painters, carpenters, start furniture refinishing, painting, handyman shop on nearly nothing; winning plan brings customers quickly. John Braceland, 1439 So. Ninth, Philadelphia, Pa.

\$750,000,000 MAIL order business in 1925. Many grow rich in this great trade. Sell merchandise, information, patented articles various preparations. Breniser's Famous Mail Order Handbooks tell how. Eleven brochures \$3. One book with complete catalog, 25c; none free. Breniser, (Established 1900), 1507 Sanson, Philadelphia.

15c PUTS your name on mailing list year. Receive offers, magazines, from wholesale supply houses everywhere. Kentucky Agency, Covington, Ky.

DON'T sell for others. Employ agents yourself. Make your own products. Follet Articles, Household Specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

SUCCEED Making Your Own Products. Use our Formulas, Processes. All kinds. All lines. Catalog, special circulars free. B. Thaxly Co., Washington, D. C.

BANG! A startling new mail-order manufacturing plan. Big circular gives all information. Write today. Chas. Bloom, 9322 132nd, Richmond Hill, N. Y.

BIG Useful Mails, year, 10c. Names, \$4.00 thousand. Rapid Service, Box 413, Mt. Vernon, Ohio.

TIRE of working for other people? Without experience, training or capital I'll show you how you can become financially independent. Easy, pleasant work. \$100 profit every week. Free automobile. Write today for particulars. Albert Mills, Mgr., 9352 Monmouth, Cincinnati, O.

START a Tire and Battery Shop. Buy equipment at wholesale. Send for catalog. Adams-Barr, Columbus, Ohio.

MIRRORS Resilvered at Home. Costs less 5 cents per square foot; you charge 75 cents. Immense profits plating like new; brassy, worn-off autographs, reflectors, tableware, stoves, etc. Outfits furnished. Details Free. Sprinkle, Plater, 127, Marion, Ind.

FREE mail-order information. Make big money, spare time, managing own business. J. P. Bailey, 3109 Manhattan Ave., Brooklyn, N. Y.

TOMBSTONE Cleaning; lonesome work, but dollars jingle. See under Classification (Formulas).

PAINT Manufactured for less than 50c per gallon. No machinery required. Free literature. Illinois Business Service, Chicago.

FLEXIBLE Glass Substitute—make it yourself. Big demand. Enormous profits. Sample with instructions for making and selling. \$1. Flexlite, 3935 Tracy, Kansas City, Mo.

FREE "Manufacturer's Bulletin" describes clever new products you can make and sell. Toys, Novelties, Fancy and Molded Goods, Accessories, Foods, Beverages, Preparations, etc. Commercial Methods. Manufacturer's Bureau, R37, 1129 East 31st, Kansas City, Mo.

THERE'S Money in Dirt! Read the ad on page 129.

WASH Dollars from Dirt! A new machine protected with patents (pending). Make \$15 a day in your city. Read page 129 and then write quick.

A BUSINESS in your own city. No competition and a contract to protect exclusive territory. Valuable franchise open. Read page 129.

YOU can have an independent business of your own, and I am here to show you the way. Write at once! Wm. E. Heinemann, 2415 Montrose Ave., Chicago, Ill.

MAKE your own gasoline saver. Materials cost 5 cents. Instructions 50 cents. Severance Service, 12310 Taft Ave., Cleveland, Ohio.

MAKE big money opening Safe and Setting Combinations. Wayne Strong, 3766½ Lan Franco St., Los Angeles.

ANYONE handy with paint brush can earn five thousand dollars or more yearly installing Wallex—a beautiful plastic paint of many shades and textures. Wallex is installed in homes or buildings where beautiful appearances are desirable. Sells on sight. Get full particulars. Everlastone Products Corp., Everlastone Square, Baltimore, Md.

LOOKING for mail order proposition. What have you? Whitmore, 730 Washington St., Denver, Colo.

RESPONSIBLE manufacturer wants competent men to manage office and salesmen. \$300 to \$1,500 necessary; will allow expenses to Baltimore if you qualify. Address Manager, 601 N. Eustaw St., Baltimore, Md.

BIG Mail. One Year, 25c. Listed, 4341 25th, San Francisco.

SIGNS and Showcards Easily painted with Letter Patterns. Large variety of Styles and Sizes. Samples for stamp. John Rahn, 22120 Nera Ave., Chicago.

TIRED of Working for Other People? Without experience, training or capital I'll show you how you can become financially independent. Easy, pleasant work. \$100 profit every week. Free automobile. Write today for particulars. Albert Mills, Mgr., 9352 Monmouth, Cincinnati, O.

WE Start You in Business, furnishing everything; men and women, \$30.00 to \$100.00 weekly operating our "New System Specialty Candy Factories" anywhere. Opportunity lifetime; booklet free. W. Hilber Ragsdale, Drawer 4, East Orange, N. J.

I MADE \$30 a Week Home. French Breadmaking, 15 years' experience; Free Booklet tells. Ashbrook 67, Marengo, Ohio.

UNPATENTED Ideas Can Be Sold. I tell you how and help you make the sale. Free particulars (Copyrighted). Write W. T. Greene, 810 Jenifer Building, Washington, D. C.

MAKE toys and novelties at home. Big profits. Instructions and Illustrations, 25c. Astroite Company, Sharpsburg, Pa.

"SCHEMER" Alliance, Ohio, 36 p. monthly, prints Schemes, Tips, Formulas. Subscriber reports \$25,000 from three; another \$10,000 from one. Try it! Year, \$1.00; 3 months, 30c.

MAKE Money at Home—making animal toys. We show you how. Send \$1 for complete working drawings and instructions. DeKalb Designing Co., Decatur, Ga.

START Mail Order Business of your own at home. We supply catalogues with your address on. Wincholt Sales Co., Box 4, Woodbine, Penna.

CHARTERS: Delaware; best, cheapest; free forms. Colonial Charter Co., Wilmington, Del.

OPERATE money-making mail-order business in spare time. Write for free particulars. Triangle Mail Order Service, 600 Blue Island Ave., R31, Chicago.

I AUTO Gas Saver Free. To introduce. All makes. Amazing mileage increase. Critchlow, C3-805, Wheaton, Ill.

MAIL Order Information, where to buy goods, Specialties, Imprint circulars, everything for mail order business 25c. Harvey Teeple, Decatur, Ind.

FREE Mail Order Information. Write today enclosing stamp. Mason, 3900 Broadway, Room 5, Chicago.

MAKE Toys, novelties, furniture; complete outfit, \$1.00. William Bagren, 2264 Herman Ave., New York.

ALL-METAL Screen frames made without Tacks, Nails, or Screws. Hinged or Sliding. 4 corners 50c. Strips 10c foot. A Profitable business anywhere. Diamond Hdw. Mfg. Co., Fourth Ave., Pittsburgh, Pa.

DELAWARE Incorporator. Charters; Fees Small; forms. Chas. G. Guyer, 901 Orange St., Wilmington, Del.

CHEMICAL Expert will furnish Formulas and Trade Secrets. All lines. Lists Free. W. L. Cummings, Ph. D., 228 Gordon Ave., Syracuse, N. Y.

LEARN the collection business. Good income, quick results. Interesting booklet, "Skillful Collecting" free. National Collectors Assn., Long St., Newark, Ohio.

EARN \$10 daily silvering mirrors, plating and refinishing metalware, autos, chandeliers, bedsteads, headlamps. Outfits furnished. E. Deeds Laboratories, 1133 Broadway, New York.

MAIL Order offers unlimited opportunities. Get free offer today. Messenger, Dept. 62, Stillwater, N. Y.

"INSIDE" mail order information and sources of supply 25c. Wholesale Company, Akron, Ohio.

TASTE flavor of real money selling Annie Blain Flavors, wholesale, retail; new system, samples; other unique methods. Geo. S. Parker, New Brunswick, N. J.

SELL by Mail! Books, novelties, bargains! Large profits! Particulars Free! B-Kifeo, 525 South Dearborn, Chicago.

NOW That you have read all these offers, send 50c for detailed information. (None free). "How" and "What" to sell by mail; through agents; or direct. We want 200,000 representatives! Opportunity is knocking—Answer! Surety Service, Dept. 270, 25 Exchange St., Rochester, N. Y.

TELEGRAPHY

TELEGRAPHY—Both Morse and Wireless—taught thoroughly and quickly. Tremendous demand. Big salaries. Wonderful opportunities. Expenses low; chance to earn part. School established fifty years. Catalog free. Dodge's Institute, H St., Valparaiso, Ind.

CHEMISTRY

CHEMICAL Analysis, Processes, Technical Information. Robert Henderson, Laboratory, Madison, Maine.

YOUR chemical problem solved and working formula or process furnished for \$5.00. Write me. W. Steadman Richard, Industrial Chemist, Box 2402, Boston, Mass.

ENJOY thrill of Chemist and Magician. Diploma awarded. Own a Chemical Laboratory. \$2.00, \$3.50, \$5.00. Write for circular. Safe Chem Set Company, New Haven, Conn.

EXPERIMENTERS—Bargain, 20 different chemicals for \$1.00. Service Laboratories, 900 Belmont, Chicago.

FORMULAS AND TRADE SECRETS

ANALYSIS, \$3.00. Practical Formulas, \$1.00. Manufacturing ideas made practical, \$5.00. With sample, \$6.00. Associated Chemists, Indianapolis, Ind.

1,000,000 FORMULAS, valuable information, 1016 pages, \$2.25. 500 Formulas Free if you order quick. Ideal Book Shop, Park Ridge, Ill.

TOMBSTONE Renewing: We will send amazing money getting process to 2 Men, Women or Boys to go partners working cemeteries; spare time or steady; lonesome work but dollars jingle. Sterling Specialty Co., 231 Federal, Denver, Colo.

TWELVE honest-to-goodness money making formulas \$1.00. Dorhan Co., P. O. 17, Woodhaven, N. Y.

FORMULA for printing photos on neckwear \$1.00. Gregg Novelty Co., 1540 East 65th Place, Chicago, Ill.

SUCCEED Making Your Own Products. Use our Formulas, Processes. All kinds. All lines. Catalog, special circulars free. B. Thaxly Co., Washington, D. C.

FORMULAS: Absolutely guaranteed. Best chemical science has devised. Don't risk your money till you've investigated these wonderful processes for all lines. Get my valuable "eye-opening" literature. Highest references. 30 years supplying the best. Miller, Chemist, 1706-P Jetton, Tampa, Fla.

10,000 FORMULAS. A real gold mine of money-making ideas. Tells how to make almost everything under the sun. You can make and sell cosmetics, mucilage, anti-freeze solutions, battery solutions, beverages, cheese, chewing gum, cleaning preparations, extracts, hair preparations, inks, blueing, leather polish, mirrors, perfumes, polishes, typewriter ribbons, carbon paper, washing powders, liquid soap, and hundreds of other profitable articles. Send no money. Just write a postal for "Henley's 20th Century Book of Formulas." Pay postman postage and \$1. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

15,000 FORMULAS in "Scientific American Encyclopedia of Formulas." Includes following and many others: Accidents and emergencies, agriculture, alloys and amalgams, artist's materials, beverages, cements, glues, pastes, mucilages, bleaching, renovating, coloring metals, dyeing, glass, heat treatment of metals, household formulas, tea cream, confectionery, chewing gum, lapidary work, exterminating vermin, lubricants, paints, varnishes, photography, condiments, canning formulas, rubber, soap, candles, soldering, toilet preparations, perfumes, waterproofing, fireproofing, writing materials. Send no money. Just write a postal. When postman hands you book pay \$5.50 and postal charges. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

500 FORMULAS including Luminous Paint—Renewing Dry Batteries—Resilvering Mirrors—Gas Tonic, Puncture Plugger, 25c. Catalog Free. Ideal Book Shop, Park Ridge, Ill.

200—ANY Formula, 20c. "Hawkins," 215 Lasanmas, Colorado Springs, Colo.

TWENTY Money Making Methods. Write Bruce Hudson, Clarks Green, Pa.

AGENTS WANTED

I WANT a partner-agent to take care of my business in your town. I furnish everything, including world's finest line of 175 household products and I split the selling price with you 50-50. Beautiful sample outfit makes selling easy; food products; household necessities; things people eat; highest quality—lowest price—quick sales—permanent repeat business; \$25,000.00 bond guarantees quality. I pay largest commissions—give Chrysler closed car besides. Get my amazing offer for your locality quick. Write or wire C. W. VanDeMark, Vice Pres. Health-O Products Co., 191F Health-O Bldg., 117 Duane St., Cincinnati, O.

SOFT Drinks in Powder—Orange, cherry, strawberry, etc. Makes best drink you ever tasted. Just add cold water and sugar. Reliable people wanted to place our drink powders in stores and appoint agents. Big profits to stores—you make \$8c to \$3.00 profit on each sale. Retail 10c package, makes 10 big glasses. Very attractive advertising matter—nearly everyone buys. Repeat sales sure. Also larger packages for those who sell by the glass. 85c clear profit on each dollar at 5c glass. Particulars free, or send 10c for 10 glass package; 50c for seven packages, all kinds (70 glasses), postpaid. Chas. E. Morrissey Company, 4417 Madison St., Chicago.

AGENTS—\$13.80 Daily in advance. Introducing New Insured Hosiery for men, women, children. Must wear or replaced free. 57 styles, 39 colors, including latest "Silk to the Top" Ladies' Hosiery. Nyland made \$595 in one month. Edwards, \$460.60. Mrs. Bone, \$425.45. Why not you? Even spare time should pay you \$3.00 an hour. No experience needed. We furnish samples. Silk hose for your own use free. New Plan. No matter what you are now doing, write quick. Maccohee Company, Road 2566, Cincinnati, Ohio.

EXPERIENCE Unnecessary. remarkable discovery removes dullness from polishing table silver, auto trimmings, all metalware, furniture. Abolishes sticky pastes, messy liquids and powders. Startling demonstrations make sales self-closing. Low price; quick cash gain. Up to 233% profit. Test samples free. E. B. Lightning Corporation, 1773 Greenleaf Ave., Chicago, Ill.

AGENTS, Salesmen, Crewmen—You'll have the Devil's-own-time finding a better seller than "Zippo." Splendid profit on snappy 50c "Go-Getter" repeat article that sells on a ten-second demonstration. Works while you watch it! Demonstrates value while others waste time making claims. New development! Greatest scientific triumph of the age! It's the berries! Write immediately for complete proposition. Karam-Smith Company, 606 Bozart Street, Fort Wayne, Ind.

AGENTS make \$40 to \$80 weekly selling typewriters re-manufactured like new by the "Young Process." Lowest prices and easiest terms ever offered. Big commission—no investment—real opportunity to start in business for yourself. Write today. Young Typewriter Co., Dept. 7190, 654 W. Randolph St., Chicago, Ill.

100% PROFIT. Every home buys "The Home Patrol" Burglar Alarm. Automatically sounds alarm and locks window. Agents earning money. Particulars free. Turk Mfg. Co., 32 No. Jefferson St., Chicago.

JUST Out—Patented Apron. No strings or straps; on or off instantly; \$20 a day easy; every demonstration a sale; over 100% profit; commissions daily; write today for free offer. Stuput Co., Dept. 206, St. Louis, Mo.

MEN—Women—Earn \$25 week during your spare time. Wonderful plan sells 9 out of 10. Experience unnecessary. W. C. Laboratories, 1223 Wabash, Chicago.

AGENTS, portraits, photo-pillow tops, frames, sheet pictures, medallions, photo-jewelry, guaranteed hose, laundry tablets, food products, toilet requisites, luminous crucifixes. Catalog 50 specialties free. 30 days' credit. Jas. C. Bailey, Dept. C-6, Chicago.

AGENTS—Can make \$250 weekly following our proven successful selling plan. An article you will never want to change from selling. Strictly first class every respect; just exactly right price to make big worthwhile money selling; over 75,000 sold in Philadelphia. Real \$250 weekly proposition appointing sub agents, agencies, individual sales. Fagley & Halpen, Desk 49, Philadelphia, Pa.

AGENTS—Best seller; Jena Rubber Repair for tires and tubes; supersedes vulcanization at a saving of over 800 per cent.; put it on cold, it vulcanizes itself in two minutes, and is guaranteed to last the life of the tire or tube; sells to every auto owner and accessory dealer. For particulars how to make big money and free sample, address Amazon Rubber Co., Philadelphia, Pa., Dept. 505.

SALESMEN—A live-selling Novelty—also suitable for advertising premium, priced under all competition. Guaranteed for life. \$1.00 brings samples on our refund plan. Crawford, 2346 N. Clark St., Chicago, Ill.

\$18 TO \$25 daily. Biggest selling line of 2-piece suits, \$9.95 and \$12.50; 3-piece wool suit, \$17.95 (regular \$28.00 value). All-wool overcoat, \$18.50. Splendid raincoats, slickers and boys' suits. Biggest commissions. Free outfit. "Jim" Foster, Inc., Dept. 90, 2250 S. Spaulding Ave., Chicago, Ill.

AGENTS Wanted for fast, easy seller—Marvel pipe cleaner; literature free. Costick Products, 400 West 23rd, New York.

AGENTS, Whirlie Gigs. Hot novelty for automobiles. Sample fifty cents. Service Oil Company, Sterling, Ill.

\$40.00 SUITS for \$23.50! All one price. Union made of finest quality Virgin Wool. You don't have to know anything about selling clothing. We guarantee your success if you are honest and willing to work. Write at once. William C. Bartlett, 859 Adams, Dept. 178, Chicago.

WOULD \$100.00 Per Week Interest you? Millions of photos all over the country just crying to be made into beautiful, artistic medallions. We have new plan. Lowest prices. Speedy service. Experienced agents making money every day they put off writing us. Art Medallion Co., Department 27, Corner Campbell and Jackson, Chicago, Ill.

THE Magic Bill Fold—A Wonderful Seller. Sample 25c. Elson's, 81 Heckman St., Phillipsburg, N. J.

AGENTS, \$17.50 daily. Bonus besides. Auto furnished. Introduce finest hosiery. Seven months' guarantee. New selling plan gets business fast. No experience needed. Write for Samples. Betterknit Textile Co., Silk 231, Greenfield, Ohio.

YOU Can Make Good Durable Paint and Varnish 40c per gallon. Write Dept. 2, Emswermann Bros. Mfg. Co., Indianapolis, Ind.

BUSINESS Guide with free legal service sells everywhere. Wells charged \$1.85 in 35 days. Write for free outfit. Nichols Co., Naperville, Ill., Box 6.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet articles, household specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

1 AUTO Gas Saver Free. To Introduce. All makes. Amazing mileage increase. Critchlaw, C5-805, Wheaton, Ill.

AGENTS—Sell car owners—Any make, new auto spring oiler. Increases riding comfort—tire mileage, prevents spring breakage. Attached instantly. Nothing like it. Large commissions. Protected territory. Write Dept. D, Liberty Auto Supply Co., Pomona, Calif.

DIFFERENT selling plan; low prices and quality gets the business. 100% profit. Over 100 fast selling brushes, dust mops and household necessities. State age and experience. Kautenberg Co., Box P, Preppert, Ill.

\$25 DAILY showing \$2.98 slickers. \$1.25 gift to customer makes sales easy. Outfit free. American, 724P, Roosevelt, Chicago.

BE Independent. Make. Sell Your own specialties. Immense profits. Catalog dependable Formulas, special selected agents' best sellers, free. M. Lustru, 822 East Pershing, Chicago.

100 MORE active men to introduce Chieftain Guaranteed Tailored Shirts, 3 for \$4.95. Latest novelties, colors. Dickman, Illinois, in 3 weeks made \$589; Hinton, Texas, in 12 days, \$219.60; Bend, Iowa, in 16 days, \$331.86. Why not you? No experience or capital needed. We deliver and collect. Full working outfit free. Cincinnati Shirt Company, Lane 1586, Cincinnati, Ohio.

AGENTS: Amazing new invention. Self-wringing mop. Simply push button and it's wrung. Hands never touch water. 80,000 sold one city alone. \$90 to \$135 week easy. Write today for quick selling plan. Sample furnished. National Products Company, Plan 831, Dayton, Ohio.

AGENTS—\$100 a week for full time; \$25 to \$50 spare time. Equipment and car free. Exclusive territory. Sound, permanent proposition. A rare opportunity, but you must act quickly. Write for particulars today sure. American Products Co., 9209 Monmouth, Cincinnati, O.

DISTRICT Managers—Agents: Capable men and women financially able to create and sustain branch office for new low-priced household necessity in big demand. Agents also wanted. For particulars write, Pittsburgh Sanatory Supply, Inc., Wilkensburg, Pa.

AGENTS, \$260 month. Bonus besides. Introduce finest line guaranteed hosiery you ever saw. 126 styles, colors. New sales plan a wonder. No experience needed. No license to pay. Auto furnished. Credit given. Spare time satisfactory. Samples furnished. Wilkitt Hosiery Co., Dept. 2431, Greenfield, Ohio.

AMAZING large cash commissions introducing beautiful \$3.95 and \$4.95 Fit-to-Measure Guaranteed Shoes. Actual samples furnished. Write for your territory. Style Arch Shoe Co., Dept. R-166, Cincinnati, Ohio.

YES you can make \$5.00 to \$15.00 daily selling our new adjustable waterproof aprons. B. & G. Rubber Co., Dept. 200, Pittsburgh, Pa.

TOMBSTONE Cleaning; lonesome work, but dollars jungle. See under classification (Formulas).

THANCO Vanilla—Bottle Yourself! Concentrated; add water! Free labels. Whirlwind seller! 500% profit! Crushes competition! Other Money-makers. Write Thomas Manufacturing Company, Indianapolis, Ind.

POSITIVELY the finest embossed show cards. Brilliant imported metallic letters. Greater variety of colors. Two sizes. Quick sales, big profits. Repeats. Embossed Show Card Co., 9474 Euclid Ave., Cleveland, O.

NOTHING Sells like Shoes. Every person a prospect. Take orders for Mason Shoes direct from factory. 85 stunning styles. Amazingly low prices. No experience needed. Free outfit. Mason Shoe Mfg. Co., Dept. 17-B, Chippewa Falls, Wis.

NEW Cigar and Cigarette Lighter sells for \$1.00. Does work of \$20.00 lighters. Your profit 100% in advance. Every lighter guaranteed 10 years. Amazing profit maker. Sale a minute. New Plan. Write for sample offer and details. Masterlite Company, Desk 600, 110 East 23 Street, New York City.

SPORT Sun Caps, Sun and Auto Goggles, Needle Packages, Snappy Comic Postcards, Bathing Girls, etc. Samples 10c each. Klees Co., 1710 Undercliff Ave., New York.

DISTRIBUTORS Wanted—"1927 Pruitt-Sheridan Directory" (where to buy half million articles wholesale). Pruitt System, Brookfield, Ill.

MONOGHAM Automobiles, \$1.35 Profit ten minutes' work; every owner wants them; millions without; particulars free. Motorists Accessories Co., Mansfield, Ohio.

NEW Dynamo Timer guaranteed life of car. 12,000,000 prospects. Earn \$100 weekly. Write today. Free sample. Dynamo Co., 426-1108 Eleventh St., Milwaukee, Wis.

MAKE \$100 weekly supplying demand for new invention. Makes autos run on 7% gasoline. Free sample. Write Whirlwind Co., 1941-357 Winnebago, Milwaukee, Wis.

SIMPLEX Vaporizer. 25 to 60% increased mileage guaranteed. Retail \$1. Thirty Days Free trial. Exclusive territory. American Fixture Co., 234 West Water, Milwaukee, Wis.

FLORAL Mirror, 25c. Send birth date. Jabe Studio, Kansas City, Mo.

AGENTS: Build a permanently profitable business on one easily sold item. Globe Re-Atomizers, a new, patented invention has an untouched, ten-million-dollar market awaiting it. Act now and obtain exclusive representation. Send \$1.00 for sample and complete information. References: Chamber of Commerce, R. G. Dun, National City Bank, Brotherhood Bank, Globe Sales & Distributing Co., 1018 Spokane St., Seattle, Wash.

HOSIERY Free and \$12 daily. Sell nationally known Pure Silk Hosiery. Amazing values. Experience unnecessary. Free sample outfit mailed immediately. Pure Silk Hosiery Co., 208 W. Monroe, Dept. P50, Chicago.

AGENTS: Men-Women, big money selling new wonderful silver polish—jewelry cleaner. Easily demonstrated. Repeats! Protected territory. 100% profit. Whole—spare time. Cynox, 1 West 34th, New York, Dept. C.

\$100 WEEKLY representing large Direct to Wearer Company. Complete Shirt, Necktie and work clothes line. Unbeatable combination means selling everyone. Advanced commission and bonus. Sales Compelling outfit free. Howard Shirts, 1213 Van Buren, Dept. M10, Chicago.

WOMEN—\$2 an hour spare time; 100% commission, new idea sanitary necessity; sells on sight; every woman buys; new feature never before used; designed by physician; revolutionizes old uncomfortable methods; pay every day; no deliveries, no collections, no experience or capital required. Particulars mailed in plain envelope. Write Mrs. Mary P. Coleman, Meriden, Conn.

EASY money wearing free shirts. Be my local distributor. Greatest values ever offered. Big Profits. Fashion Wear Shirt Co., Dept. G-942, 1220 Jackson St., Cincinnati, Ohio.

FREE Outfit—\$10-\$15 daily. Guaranteed all-wool tailored trousers less than store prices. Quick sales. Big money. Pay daily. Free trousers offer. Hutchins Pants Co., Dept. 160-FC, Cincinnati, Ohio.

AGENTS, Either Sex: Biggest 50-cent proposition on earth. Every firm and home a buyer. Sells itself. Send 50 cents for sample and full particulars. Earl Ramsey, Pirth, Idaho.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet articles, household specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

1 AUTO Gas Saver Free. To introduce. All makes. Amazing mileage increase. Critchlow, C4-805, Wheaton, Ill.

NO Dull Times Selling Food. People must eat. Federal distributors make big money; \$3,000 yearly and up. No capital or experience needed; guaranteed sales; unsold goods may be returned. We furnish you with sample case, license and Free Samples for customers—Sure repeat orders. Exclusive territory. Ask now! Federal Pure Food Co., A2307 Archer, Chicago.

\$60-\$200 A WEEK. Genuine Gold Letters for store windows. Easily applied. Free samples. Liberal offer to general agents. Metallic Letter Co., 438-B North Clark, Chicago.

GOLD Sign Letters. \$9.75 for Thousand. Non-Tarnishable. Free sample. Catalogue. Atlas Sign Works, 1032 E. 55th St., Chicago.

AUTO owner tire agent wanted each locality to use and take orders for hand-made Mellinger cord and balloon tires; guarantee bond 15,000 miles; shipped prepaid on approval; get your tires free; no capital or experience required; make \$100 to \$300 weekly. Write for wholesale prices and sample kit. Address Mellinger Tire Co., Dept. 400, Kansas City, Mo., or Dept. 400, Philadelphia, Pa., or Dept. 400, Oakland, Calif.

MEMBERS of Masonic Fraternity, Knights of Columbus Shrine lodges, Knights of Pythias, sell new hand-laced \$7.00 bill folds for \$3.50. Sent on approval, 10% discount allowed. The Fraternal Leather Goods Co., P. O. Box 1030, New Haven, Conn.

\$10 TO \$15 a day easily made. A whirlwind seller. Sample and particulars 10 cents (silver). Excello Sales Co., Shreveport, La.

AGENTS—Men, women, big profits selling Veripure Vegetable Soap. Wonderful new soap for toilet, bath, etc. Write today. Veripure Laboratories, Box 999-C, Chicago.

AGENTS: Salesmen—Sell New Thermostatic Automatic Carburetor Control Attachment for Fords. Big profit, full or part time. Increases mileage 50-100%. Attached in two minutes. No drilling. Cadillac now using Thermostatic Carburetor Control under Blawie license. Sales guaranteed. \$15.00 a day Guaranteed to Distributors. Write today, Blawie Auto Device Co., Dept. 805-H-X, 137 E. Erie St., Chicago.

SELL slickers. Plaid-lined \$2.65, value \$10.00. Pay daily. Bonus weekly. \$1.50 free premium. Silverstone, 2055AA, Charleston, Chicago.

WILL you wear a pair of genuine tailor-made shoes at my expense? Will you show them to your friends and take their orders? I will also send you Free our big selling Outfit showing 70 shoe styles and 60 actual leather samples. I pay my agents \$8.00 daily. Write quick. Tailor-Made Shoe System, 932 Wrightwood, Dept. 294, Chicago.

NEW Invention—100% profit. Liquid Quick mend for Hosiery and Fabrics. Stops Runs. Every woman buys. Hundred other fast sellers. J. E. Johnson Co., Dept. 454, 6145 Wentworth Ave., Chicago.

WE Pay \$50 A Week And Expenses and give Ford Auto to men to introduce poultry and stock compounds. Imperial Co., D23, Parsons, Kan.

EVERY Autoist buys Auto Mitten Dusters. Costs 25c, sells for 75c. Sample given. National Fibre Broom Co., St. Louis, Mo.

AGENTS: Make \$500.00 monthly. Pay daily. No investment. Rhinestone initial buckles and novelties. Sell easy everywhere. Exclusive territory. Chaston Novelty Co., 606 Blue Island, Chicago.

AGENTS, make \$3.00 an hour taking orders for our 40 fascinating Kitchen Specialties. No competition. Write quick. General Products Co., Dept. T-E, Newark, N. J.

\$10.00 SLICKERS only \$2.98. Biggest commissions. Represent manufacturer. 10 colors. Free outfit. Roselle Manufacturers, 713 Roosevelt Road, Dept. H-3, Chicago.

AMAZING 30-day Offer! To prove our Mexican Blu-Flash Gem really matches finest genuine Diamond Side-by-side, we'll mail perfect \$5.00 picked sample, alive with rainbow fire, for only \$1. with catalog, proof of our claims, and Free \$5 Jewel case proposition. Sells at sight; enormous profit! Write quick. Mexican Gem Co., Box P-56, Monterey, Calif.

MIRRORS Realized at Home. Costs less 5 cents per square foot; you charge 75 cents. Immense profits plating auto-parts, reflectors, tableware, stoves, refinishing metalware, etc. Outfits furnished. Details Free. Write Sprinkle, Plater, 128, Marion, Ind.

PORTRAIT Men, largest frame Portrait House on coast. Foreign shipments our specialty—twenty-hour service. Victor Portrait Co., 2223 Brush, Oakland, Calif.

EARN \$80.00 weekly with Paris Fashion Frocks for women. Factory prices. Advance commissions. No experience necessary. New plant! Fashion Frocks, Dept. D-100, Cincinnati, Ohio.

WHY not sell us your spare time? \$2.00 an hour, \$19.70 Daily Easy Full Time. Introduce 12 months Guaranteed Hosiery—57 styles, 40 colors for Men, Women, Children, including latest "Silk to the Top" Ladies' Hose. No capital or experience needed. We furnish samples. Silk hose for your own use Free. New Plan. M. H. Mathews, Road 5866, Cincinnati, Ohio.

FOODS always sell. 100% profit. Big repeaters, new sales plan. Write for territory. Mother Hubbard, 353 Congress, Chicago.

ALTA Snubbing Shock Absorbers. Agents wanted. Six dollars cash. Retailing sixteen. Big money maker. Results satisfactory. ALTA Shock Absorber, 900 O'Farrell, San Francisco, Calif.

THANCO Vanila-Bottle Yourself. Concentrated; add water! Free labels. Whirlwind seller! 500% profit! Crushes competition! Other Money-makers. Write Thomas Manufacturing Company, Indianapolis, Ind.

GET exclusive territorial sales right for Becklin Quick Adjustable Close Quarter Pipe Wrench. Make substantial percentage on sales; build permanent business for yourself. Becklin Wrench Company, Seattle, Wash.

AGENTS or Live-Wire Salesmen, sell invention rights to people, home manufacturing, a new novelty. Tools Furnished. Write, Max H. Feist, Toledo, Wash.

NEW, Fast Seller; 150% profit; "Best-ever Powdered Hand Soap"; removes grease, paint, ink, dirt; great repeater. Sample Free. Bestever Prod. Co., 4319-P, Irving Park, Chicago.

GET 50 cents from every auto owner you meet. Amazing new product. Sed-Ex poured in radiator cleans cooling system of three to five pounds rust and sediment. Ends overheating, adds power. Guaranteed harmless. Every motorist buys, also garages. Good for \$10 to \$20 daily. Walker & Walker, 81 E. Madison, Chicago.

SUCCEED Making Your Own Products. Use our Formulas, Processes. All kinds. All lines. Catalog, special circulars free. B. Thaxly Co., Washington, D. C.

PORTRAIT Agents—Write for new Catalogue—Enlargements, Frames, Medallions, Sheet Pictures, Luminous Crucifixes. Adam J. Kroll & Co., 2539 So. State St., Chicago, Ill.

NEW Wonderful Seller, \$1.40 profit on every \$1.50 sale, monogramming autos. Free samples. Monogram Co., Desk 11, Worcester, Mass.

FIBRE Brooms—detachable handles, fine finish. Good profits, repeat sales. The Fibre Broom People, 147-C New Jersey Ave., Brooklyn, N. Y.

AGENTS—Make a dollar an hour. Sell new kind of sharpeners. Sharpens all knives and tools quickly. Demonstrating sample free. Premier Mfg. Company, Dept. 68, Detroit, Mich.

\$50,000. PICTURE Man Friedman made canvassing. Beginners can make \$100.00 weekly with my sales talk. Experienced men make more. Free book. "Profits in Portraits" explains. Samples Free. Picture Man Friedman, Dept. 8-H, 541 W. Lake, Chicago.

A PAYING Position Open to representative of character. Take orders—shoes, hosiery direct to wearer. Good income. Permanent. Write now. Tanners Shoe Mfg. Co., 5-50 C St., Boston, Mass.

\$61.50 WEEKLY. Introducing and selling a new gas-light burner for kerosene lamps. Beautiful light. No chimney. No mantle. Samples free. Luther Manufacturing Company, Dept. 396, Cincinnati, Ohio.

AGENTS clean up. Sell automobile flags for decoration day. Write Unger, 371 Harrison, Chicago.

AGENTS Make 200% Profit Direct Sales; 100% selling retailers, 50% selling jobbers. Regular and Pleasant medicated gums. Fast sellers; permanent repeats. Exclusive territory to producers. Pleasant Products, 134-P ME. Pleasant, Newark, N. J.

MAKE Fifteen Dollars per day. New Grass Shear—sells on sight—season just starting. Amazing profits for you. Alliance Toy & Specialty Co., Alliance, Ohio.

DOUBLE Your Income. Read Opportunity, the Magazine that offers thousands of openings to double your income. Sent Free. Just send name and address. Opportunity Magazine, 750 N. Michigan, Dept. C-2, Chicago.

AGENTS. \$240 month. Complete line auto specialties. 100% profit on every article. Territory given. Write quick for particulars. American Accessories Co., Plan 231, Cincinnati, Ohio.

72 SALES in Four Hours. Profit \$64.80 (Sworn Proof). That's the record of "Doc" Barber. Every woman buys on 10-second demonstration. Profit up to 150%. We want 500 ambitious men and women. Exclusive protected territory. New self-wringing mop that really wrings dry, without wetting hands. No gears, bolts, or screws. Weighs only 2 pounds. Simple, Practical, Perfect. Lasts a lifetime. Territory going fast! Write quick! Delphos Mop Co., A101 Tenth St., Delphos, Ohio.

AGENTS—Make \$100 weekly selling Gray Seal—automatically, instantly, and permanently seals all tire punctures. Demonstration closes a sale every time. Exclusive territory assigned. Brass pressure-gun given Free with sample can for \$1 (enough for any tire). Money-back guarantee. Gray Seal Products Corp., 200 Rutger St., St. Louis, Mo.

75c PROFIT on \$1.00 sale. Auto, furniture and glass cleaner. Your name on label. Exclusive rights; free sample. Mfg. E. 213 Griswold, Detroit, Mich.

STARTLING New Invention for the Lawn. Medicine bottle for the lawn and garden. Turns water to medicine for the lawn, yet uses only water. Attach it to a hose, turn on the water, and watch the crowds gather to see what's going on; makes water roll up like a smoke bank. Gets 'em all. Takes the place of sprinkler; everybody buys. Sells for only \$2.00. Agents make half and more. Selling by the thousands. Nothing like it. To save delay, send one dollar for agents' sample. Write for our proposition. Lawn Invention Company, La Crosse, Wis.

CASH Paid for Butterflies, Insects. See Sinclair Display Advertisement on page 32.

WANT Producing Agents and salesmen? See advertisement under Advertising Agencies, page 49. Frank W. Lenhoff Advertising Agency, Chicago.

IT'S the cat's meow. Brand new novelty. Biggest seller on earth. Write today for particulars. Novelties, Box 10, Mt. Washington, Ohio.

JUST Landed. New, imported double-edged safety-razor blades. Retail 50 cents dozen. Big seller and money maker. Write. Suburban, Mt. Washington, Ohio.

BIG Money easily made without peddling or outlays. Free particulars. Elite, 38 Elizabeth St., New York.

BIG Money Monogramming Automobiles. \$1.40 Profit on \$1.50 Sale. Particulars and samples free. Evans Products Company, Midland Avenue, Windsor, Conn.

\$100.00 WEEKLY selling Tooth Whitener Display Cards to stores. Fast repeats. Exclusive territory. Wonder plan assures permanent income. Write quick. Terrell Products Company, Martins Ferry, Ohio.

AGENTS: It's a winner. Combined cigarette and match case. Black grain finish leatherette. Holds package cigarettes and box matches. Sells on sight. Big profits. Write for details. All-In-One, Dept. A-6, 2810 Portland Ave., Minneapolis, Minn.

"MAKE and Sell Your Own Goods"—Guaranteed formulas. All kinds. Catalog free. Clover Laboratories, Park Ridge, Ill.

SALESMEN—Are You Making Enough Money? Let us show you how to make Big Profits with Jiffy Washing Tablets. No experience required. Write for Free Sample and Plans. Jiffy Soap Products Co., Dept. A, Dayton, Ohio.

300% PROFIT: Whirlwind selling household, store, office necessity. Fast repeater. Free sample. Magic Products, Room 200, 332 East 31st, Kansas City, Mo.

NEWEST European Novelty Just Out. One article has four uses. Sells less than dollar. Over 100% Profit. Write T. Kobayashi Co., 208 N. Wabash, Chicago.

SELL Surety, the Original. Genuine. Powdered Hand Soap, and make \$5,000 yearly. We furnish sales plans, advertising and free samples. Write quick. Surety Mfg. Co., Dept. 56, 26 W. Washington St., Chicago.

SELLING Like Blazes! Eleven piece toilet goods assortment at \$2.25 with two piece carving set free to your customers. 100% profit. Davis Products Co., Dept. 56, 1321 Carroll, Chicago.

OUR Agents average better than \$75 a week; Rich's pure fruit soft drink powders. Every home, store, drink dealer buys. Sample Free. Sol P. Rich Co., 632 S. Sangamon, Chicago.

WHY work for small pay? Make \$10 to \$20 day selling Re Nu Edge Knives—new magic knife that does away with Dull Knives. Barnett Mfg. Co., B3 418 San Pedro, Los Angeles, Calif.

AGENTS: We have a whirlwind seller. Get details. Webster, 608 Wrightwood, Chicago, Ill.

FREE "Manufacturer's Bulletin" tells about salable new products you can make and sell. Gives reliable commercial information. Manufacturer's Bureau, B38 1125 East 31st, Kansas City, Mo.

\$35 PROFIT on \$1.50 outfit. Gold transfer monogram; free sample. National Station D, Brooklyn, N. Y.

SELL Electric Fixtures to every home owner, complete line, easy sales, no investment, beautiful catalog, big commissions. National Illuminating Company, 1123 Broadway, New York City.

MAN with auto; one day weekly: \$35. Bens, Woodside, N. Y.

MAKE \$10 a day without selling. New plan. We send customers to you for greatest gas saver. Cuts gas bills 25%, guaranteed. Gives motor more pep and power. Removes carbon. Positively no cold turkey work. We have perfected a plan that sends you buyers as fast as you can handle them. Big money, easy. Write today for complete plan. Mac Auto Products Company, Dept. 506, 6355 Broadway, Chicago.

SELL America's Quality all brass Spark Plug; sample outfit Free; openings for state and county distributors; excellent profits; product guaranteed; write "ASKO," Canton, Ill.

ARE You Old at Forty? See our advertisement on page 74 of this issue. The Electro Thermal Company, 2169 Main St., Steubenville, Ohio.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet articles, household specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

HUNDREDS of manufacturers, formerly agents selling other goods now owe their success to Miller's Guaranteed Formulas for making biggest-selling, advertised specialties in all lines. Investment small. No machinery needed. Profits great. Make your own goods—get the profit you're entitled to. Write today for my "eye-opening" literature. It's free and tells all. Miller, Chemist, 1706-W Jetton, Tampa, Fla.

AGENTS—To Sell the New Featherweight All Purpose Waterproof Coat. Weight only 26 ounces, latest styles and colors. Men's \$1.98, Women's \$3.98. Liberal commissions. Write today for sales plan. Featherweight Coat Company, 5719 Euclid Ave., Cleveland, Ohio.

AGENTS—Radio product; unlimited possibilities! Write. Kinley Electric Co., 2663 Main St., Buffalo, N. Y.

\$16 A DAY Easy—I start you in auto accessory business; no investment; no experience necessary. Landin, 3433 Montrose Ave., Chicago.

GENUINE Gold Leaf Letters anyone can put on Store windows. Guaranteed to never tarnish. Large Profits. Enormous Demand. Free Samples. Write today. Metallic Letter Co., 428-D North Clark, Chicago.

GOLD-LEAF Sign Letters; make and sell; 1,000% profit. Johnston Co., Quincy, Ill.

AT Last! Diamond Rival Discovered! Amazing blue white Rajah Gem astounds jewelry world and deceives experts. Beautiful sample case free! \$100 weekly. Quick! Rajah Diamond Co., Dept. F20, Salisbury, N. C.

\$31.00 PROFIT—with \$1.50 Outfit—Big Money—Easy Work. Selling Gold Monograms for Automobiles, Luggage, Windows, Wagons. No Experience. No License. "Samples Free." NuLife Monograms, Hartford, Conn.

OUR New Household Device washes and dries windows, sweeps, cleans walls, scrubs, mops. Complete outfit costs less than broom. Over half profit. Harper Brush Works, 132 2nd St., Fairfield, Iowa.

REAL Whirlwind Seller—Nopolout Custom Shirt. Every man buys them. Patented—no competition. Liberal commission. Free selling kit. Make \$15 up daily taking orders direct from consumer at manufacturer's prices. District or local agents. Write Nopolout Shirt Co., Dept. Y, Hazelton, Pa.

SELL absolute necessities. Cost 2c, sells 25c. Prices lowest. Seven different samples 30c. Catalog Free. Mills Sales Co., 13 East 16th St., New York.

SELL men's neckwear; wonderful proposition. Astor, 318-M Broadway, New York.

DO you want good live agents—fellows who can get the business? Ask me how others are doing it. I'll gladly render the necessary assistance without cost to you. Address, M. L. Rund, Mgr. Classified Advertising, Popular Mechanics Magazine, Chicago.

NOVELTY bedspreads. Silk and cotton fabrics. Guaranteed. Reasonably priced. Every housewife wants one. Liberal territory and commission. Write Rainbow Novelty Mills, Grover, N. C.

WE Start You Without a Dollar. Soaps, Extracts, Perfumes, Toilet Goods. Experience unnecessary. Carnation Co., Dept. 2480, St. Louis.

\$75 WEEKLY. Man or Woman Wanted with ambition and industry to distribute Rawleigh's Household Products to steady users. Fine openings near you. We train and help you so you can make up to \$100 a week or more. No experience necessary. Pleasant, profitable, dignified work. Write today. W. T. Rawleigh Co., Dept. IL8253, Freeport, Ill.

WANT Distributing Agent for Handslick, powdered hand soap; removes anything from hands; everybody a customer; sample free. Solar Products Co., J-2142 S. Troy, Chicago.

ALL-YEAR-ROUND profitable business selling wonderful new water softener and cleaner. Removes grease, oil, ink and dirt quickly. Every home and business place a live prospect. 100% profit. Big repeat orders. Exclusive territory. Write for free sample. Seacoast Laboratories, Sea Bright, N. J.

GOLD Leaf window letters and script signs. No experience; 500% profit. Samples free. Consolidated, 69-17 West VanBuren, Chicago.

AGENTS: both sexes, we manufacture and control new household article. Fast seller. Big profits. Exclusive territory. Write now. Connolly, 123 Liberty St., New York.

SEND name, address on postcard. Free introductory copy Salesology Magazine; contains 1,000 money-making opportunities. Offered by big reliable firms; no obligations. Salesology Magazine, Desk B-38, 500 No. Dearborn, Chicago.

32 SECONDS complete tire change by Detmer, Ohio, with Morey Quick Action Rim Tool. Sold, singly, 49 three days, cleared \$100. Anderson, Mont., sold 1400 in 14 weeks. Get details for good territory. Harvest time now. M. Morey Rim Tool, Buffalo, N. Y.

SOMETHING New. Every motorist a buyer of our electro-magnetic-emergency Wonderlamp; takes only one minute to demonstrate and make a sale; no experience necessary; \$5.00 an hour easily made, full time or evenings. Write for sample. Wonderlamp Co., 926 Flisk Bldg., Dept. 10-A, New York.

SELL—Farm necessity for repairing sagging fences. Write Hawbaker Co., Elmore, Minn.

AGENTS and District Managers: 250% profit selling exclusive, new process Artistic Signs. Hundreds of titles for every business. No competition. Write for details. Artistic Signs, 199R Broadway, New York.

WILLIAMS' Powdered Hand Soap has taken auto owners by storm. Cleans dirtiest hands instantly. Easy demonstration sells on sight. Free sample and particulars. W. R. Williams, Inc., Dept. 266, Montclair, N. J.

I AUTO Gas Saver Free. To introduce. All makes. Amazing mileage increase. Critchlow, C6-805, Wheaton, Ill.

AGENTS—Mosco Corn and Callous Remover will build you a steady repeat business. Send today for pocket size trial outfit. The Moss Co., 357 Searle Bldg., Rochester, N. Y.

EVERYBODY uses toilet preparations. Sell dainty, exquisite, delicately scented, Duo compacts, perfumes, powders, creams and lotions, Flavoring extracts and Specialties. Duo Co., TP-1, Attica, N. Y.

RADA-DIAMOND rivals the genuine diamond. Rich or poor buy them. Low price, fast sales, big profits. \$10,000 yearly for hustlers. Pocket case free. National Co., Box 1174-PM, Omaha, Neb.

AGENTS. Get our prices on Coffee, Tea, Desserts, Soaps, Perfumes, etc. Endless variety, superb quality, quick service. Sample display free. Address Blair Laboratories, Lynchburg, Va.

AGENTS: 500% profit. "Happy Home Make Shampoo" builds your own big business. Martin of Indiana made \$75.00 in one day. Missouri man made \$750.00 one month. Exclusive territory. Geo. A. Schmidt & Co., Dept. P, 236 W. North Ave., Chicago.

PHOTO Medallion Men and Women, the largest line of Photo Novelties in the world. Lowest prices, quickest service. Send for catalogue showing over 200 money makers. Photo medallions, photo medallion clocks, photo mirrors, photo fountain pens, photo powder compacts, photo jewelry and photo buttons. Gibson Photo Jewelry Co., 608-614 Gravesend Ave., Brooklyn, N. Y.

SELL "Fixit" Rubber Repair. Big pay. Doubles mileage of tires and tubes. Self-vulcanization without heat or tools. Big season now. Marquette, Z 2325 Wolfram, Chicago.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet Articles, Household Specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

THE best tooth-paste for Pyorrhea is Zl-O-Dine. Every tube guaranteed. Taste and cleansing qualities wonderful. Fifty cent tubes. Agents wanted. Iodine Products Co., Laurel, Miss.

AGENTS: Our gold-eyed Needle Cases are wonderful sellers; immense profits; \$50 to \$300 weekly; proof and particulars free; sample outfit 10c; factory prices. Paty Needle Co., 231 Davis Square, Somerville, Mass.

CALIFORNIA performed heads selling like hot cakes. Agents earning money. Big profits. Catalog free. Mission Factory P., 3328 W. Pico, Los Angeles, Calif.

OUR Luminous Crucifix Shines in the Dark. Every one amazed at the wonderful effect. Easily demonstrated. Easily sold. W. G. Hannan Co., Dept. B, 2539 So. State St., Chicago.

DIRECT Factory representatives for changeable letter window display signs. Good income assured. Experience unnecessary. Maze Manufacturing Co., Norwood Station, Chicago.

A BUSINESS of Your Own—Making Sparkling Glass Name and Number Plates, Checkboards, Signs, Big Book and Sample Free. E. Palmer, 512 Wooster, Ohio.

AGENTS—New Plan, makes it easy to earn \$50.00 to \$100.00 weekly, selling shirts direct to wearer. No capital or experience needed. Represent a real manufacturer. Write now for Free Samples, Madison Company, 566 Broadway, New York.

GET Our Free Sample Case—Toilet articles, perfumes and specialties. Wonderfully profitable. La Derma Co., Dept. A, St. Louis, Mo.

BIG Money and Fast Sales. Every owner buys Gold Initials for his auto. You charge \$1.50; make \$1.35. Ten orders a day easy. Write for particulars and free samples. American Monogram Co., Dept. 40, East Orange, N. J.

POLMET—The Wonderful Polishing Cloth that cleans all metals without liquid, paste or powder. Approved by "Good Housekeeping" and "Modern Priscilla"—sells fast at 25c. Sample free. Gale & Co., Inc., 15 Edinboro St., Boston.

MAN in each town to plate auto parts, reflectors, bathroom fixtures, refinish beds, mirrors, chandeliers; by new method. No capital or experience required. Simple plan of manufacturing at home starts you in big money-making business. Outfit furnished. Free particulars and proofs. Gun Metal Co., Ave. H, Decatur, Ill.

REPLATE brass worn-off Automobile parts. Reflectors, Bath Room Fixtures, Worn Spoons, Forks, etc., with pure silver. Looks like new. Use U-Kan-Plate Polish. Positively no mercury. \$1.00 half pints. Post Paid. Satisfaction Guaranteed. Agents wanted. Dept. A, U-Kan-Plate Co., Philadelphia.

AGENTS—Stamping names on Pocket Key Protectors; sample Check with your name and address, 25c. Stamping Outfits. Emblem Checks, Check Fobs, Name Plates. Hart Mfg. Co., Desk 2, 303 Degraw St., Brooklyn, N. Y.

ONE of the biggest malls on earth. Sent to any address for 10c. Louisiana Distributing Service, Dept. PM, Harrison, La.

AGENTS—Build permanent business with our gold sign letters. Easy work. Big profits. Samples free. Acme Sign Letter Co., 312 Dunn St., Sta. B, Cincinnati.

NO difference what you're selling, you can increase your sales 500% by giving our \$1000 policies as free premiums. Costs you nothing. Write National, 715-M Baltimore Bldg., Chicago.

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

NEW Camera. Regular black and white photos finished quickly inside camera. Make money selling cameras, taking photos or doing both. Crown Company, Dept. 461, Norwalk, Conn.

"LIQUID-LEATHER" Fills Holes in Shoes, Rubbers, Tires. Dries Instantly. Pillable, Waterproof. Just Imported from France. Tube Retail 75c—Cost 35c. Sells Housewives, Sub-Agents. Nulife Leather, Hartford, Conn.

REMNANT Store, Bethel, Ohio. Greatest Dry Goods Bargains on Earth. Agents and Dealers.

AGENTS—Clever Invention! Inkspoon makes every pen a fountain pen. Fast office seller; big profit, demand increasing everywhere. Exclusive territory offered. Sample free. H. Marui Company, Tribune Bldg., New York, N. Y.

EARN \$10 daily silvering mirrors, plating and refinishing metalware, autos, chandeliers, bedsteads, headlights. Outfits furnished. E. Decie Laboratories, 1133 Broadway, New York.

AGENTS—Make a dollar an hour. Sell Mendets, a patent patch for instantly mending leaks in all utensils. Sample package free. Collette Mfg. Co., Dept. 404, Amsterdam, N. Y.

AGENTS—Send for Free Sample "Fret-not" Washday Wonder. Big Profit. You don't have to talk; if she doesn't buy at sight, leave sample. Exclusive territory. Credit given. Empire Specialties Co., 1549 N. Wells, Dept. 101, Chicago.

AGENTS make \$100 week placing advertising Cigar Lighters with glass front. Every dealer wants one. Write for free plan. Drake Mfg. Co., Dept. M, Milwaukee, Wis.

BIG Profits. Sell "No-Splash" 4-Strainer Water Filters. Fast sales, lowest prices; send for 6 dozen, \$1.80 postpaid. Jones Mfg. Co., 243E2 Franklin St., Boston, Mass.

FREE Sample. "Rain Shield Wiper," Retail \$1.00—Cost (25 cents). Sold Clear and Rainy Days. No Cloth—No Paste—No Attachment. (1) Rub keeps windshield clear 48 hours. Experience Unnecessary. Nulife Corporation, Hartford, Conn.

\$50.00 WEEKLY easy. Applying Gold Initials on Automobiles. No experience needed. \$1.45 profit every \$1.50 job. Free Samples. "Balco Monograms," 1943 Washington, Boston, Mass.

OVER 100% Profit. Self Lighting Gas and Cigar Lighters. Everybody interested, repeat business. Sell individuals, dealers, subagents. Particulars Free. P. Bernhardt, 127 West 30th St., New York.

AGENTS—N-R-G Laundry Tablets, the old reliable moneymaker for live agents. Millions sold—200% profit—sales waiting for you. Clothes washed spotlessly clean in 10 minutes without rubbing. Free samples. N-R-G Company, 230 W. Superior, Chicago.

HAIR Tonic—Concentrated. Add water and bottle. Labels free. Outfit for 36 dollar bottles, postpaid \$1.00. Casey, 1043 Washington, Boston, Mass.

AGENTS—Mac's Ointment (liquid mustard plaster) for coughs, rheumatism; Mac's Black Lotion for pyorrhea, wounds, sore gums, piles. Mac Chemical Corp., 74-A West St., New York.

EVERY Woman Wants a Sewing Set. Home Sewing Sets contain 142 useful sewing articles. \$4 an hour easily made with this 50c set. Prentice-Lee, 145 East 23rd St., New York.

BIG Profits. Steady Income our line food products, toilet articles, soaps. No cash or experience needed. Sample case free. Write Linro Co., Dept. 242, St. Louis, Mo.

HIGH-GRADE SALESMEN WANTED

WANTED—Tailoring Salesmen, make \$60 to \$125 per week. We are the largest made-to-measure tailoring house in the country, furnishing elaborate sample equipment. Over 150 all wool fabrics sell at \$23.50, \$29.50, \$34.50 and \$48.50 which includes commissions of \$3.50 to \$8.50 and bonus. Guaranteed absolute satisfaction, perfect fit, best workmanship, or no sale. We maintain an absolute 6-day delivery schedule. Write for our line and all accessories to be sent free. Tell us all about yourself. Edward E. Strangs & Co., Inc., Dept. 101, 402 So. Market St., Chicago.

TRAVELING Salesmen Calling on Retail Stores wanted by large manufacturer of fast-selling specialties entirely different from the average. Year-round sales, main or sideline. Big commission paid immediately on original and repeat business. Opportunity for well paid and permanent connection with old-established firm. If not making \$150 weekly, write today. Union Specialty Works, Dept. 222, Boonville, N. Y.

\$10,000 YEARLY Easy. No Experience Necessary. Selling Fast Seller Royal Special Policy which Pays \$5,000 Accidental Death, \$1250 Death from Any Cause; \$25 Sick Weekly Benefits, \$50 Weekly Accidental Disability—\$24 yearly—Other Amounts Proportionate. No Medical Examination. Greatest Bargain. \$5,000 Accident Policies given free to first 500 answering this ad. Mr. Minnee, American Peoples Life, 1107-159 North State St., Chicago.

WANT Producing salesmen and agents? See advertisement under Advertising Agencies, page 48. Frank W. Lenhoff Advertising Agency, Chicago.

PAVED Road Maps—Handy, inexpensive for advertising and premiums. Sell on sight. Full or sideline. Proposition, samples on request. George P. Cram Company, Indianapolis.

GOLD Leaf window letters and script signs. No experience; 500% profit. Samples free. Consolidated, 69-V West Van Buren, Chicago.

SPECIALTY Salesman qualified for position making \$1,000 monthly. New electric sign. Extends 4 feet over sidewalk. Illuminated letters and border. Selling on sight at \$35. Big commission. Flashtrix, 2126 Hudson, Dept. P-2, Chicago.

BIG Season Just Ahead. Advertising pencils more popular every day—every business prospect. Our line repeats. Big commissions. Established 1902. North American Pencil Works, 126 So. Clinton, Dept. 129AB, Chicago.

SALESMEN—Get free outfit and make \$90 a week taking orders for famous Taylor rain-proof, made-to-measure caps and knickers for men. Also eight other big profit-makers. Commission in advance. We deliver. Taylor Cap Manufacturers, Desk U-2, Cincinnati, Ohio.

\$75.00 WEEKLY to introduce "Chief-tain" 3 for \$4.95 Guaranteed Tailored Shirts. Full working outfit free. Your own Shirts Free. Cincinnati Shirt Company, Lane 2946, Cincinnati, Ohio.

IF you want to get into a real money-making business, and help others at the same time, sell Radiumized Health Products. A world-wide unlimited field now open to producers. Exclusive territory. Write Radiumized Applicator Co., 1303-P Fillmore, Buffalo, N. Y.

SELL Paint. Easy to sell Paint, Varnishes, Roofing, Motor Oils, on 60 days' credit. We pay freight. Big commission. Money advanced. We deliver and collect. Write today for Free Sample Outfit. Loverin & Browne, F1647 So. State, Chicago.

IF You Think In Terms Of \$6,000 This Year, write us now. Strong line for retail stores. Nationally advertised. Established concern. Best season now starting. Liberal weekly advance to producer. Continental Co., 2010 Euclid, Dept. 1300, Cleveland, Ohio.

EARN \$30 a Day. Established income for life selling for \$1 a year \$1,500 accident policy. Write W. C. Stone, A-11 So. LaSalle, Chicago.

SELL Printing—Business and Personal stationery. 40% commission. Large line; big repeater. Samples free. Roberts Printing Co., 515-I Broadway, Albany, N. Y.

MEN—Sell dependable shrubbery, fruit trees, etc. Steady demand. Complete co-operation. Commissions paid weekly. We deliver and collect. Write Perry Nurseries, Dept. R-6, Rochester, N. Y.

\$60-\$200 A WEEK. Genuine Gold Letters for store windows. Easily applied. Free samples. Liberal offer to general agents. Metallic Letter Co., 438-A North Clark, Chicago.

FOUR \$7.50 sales to merchants net you \$20.00 daily. Sayers Systems, 2803 Sheffield Ave., Chicago, Ill.

ANY Salesmen Can Sell Them! Merchants everywhere use punchboards. Someone sells them, why not you? Collect big commissions daily. Newest, largest, elaborate catalog sent upon request. Lincoln Sales Co., 9 So. Clinton, Chicago, Dept. D.

BECOME Your Home Town's Leading Business Man. Big commission. Selling Groceries, Coffee, Canned Goods, Paints, Motor Oils, Roofing, Tires, to consumers. Free Sample Case. Money advanced. Liberal Credit. No experience necessary. Loverin & Browne, F1615 So. State, Chicago.

SALESMEN—Become Independent. Own Your business, experience unnecessary selling our \$7,500.00 Accidental Death; \$50 Accident; \$25 Sick Weekly Benefits—\$12.50 Yearly. Other Amounts proportionate. Guaranteed steady income from renewals. \$250,000 Deposited Insurance Department. Universal Policy. Dept. A, 30 Clinton St., Newark, N. J.

MILLIONS of business men waiting for Brand New indispensable \$10.00 office utility saving hundreds of dollars annually. One man sold sixteen in three hours. Splendid profits. Write quick for trial offer and exclusive Virgin territory. Lightning Calculator Co., Dept. FT, Grand Rapids, Mich.

COLLECTS Money from the Dead-Beats. Retail \$5.00—Cost \$1.00—Profit \$4.00. "New Method." Every Storekeeper, Doctor buys quickly. Wonderful Money Getter. Federal Association, Hartford, Conn.

75c **PROFIT** on \$1.00 sale. Auto, furniture and glass cleaner. Your name on label. Exclusive rights; free sample. Mfg. E., 213 Griswold, Detroit, Mich.

SALESMEN earn One Hundred Dollars a week selling lowest priced, high-grade electric signs on easy terms. Commission to start; salary, expenses in thirty days. The McSweeney Company, Springfield, Ohio.

TOOL Salesman for complete line of automotive tools sold direct to mechanics and repair shops; exclusive territory; 30% commission. Automotive Tool Mfg. Co., Milwaukee, Wis.

DOUBLE Your Income. Read Opportunity, the Magazine that offers thousands of openings to double your income. Sent Free. Just send name and address. Opportunity Magazine, 750 N. Michigan, Dept. C-3, Chicago.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet Articles, Household Specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

\$20 DAILY easily. New Patented Metal Specialty. Merchants buy on demonstration. You collect and retain your commission. We make deliveries and collections. Exclusive territory. Manager, 1059 Bell Telephone Bldg., St. Louis, Mo.

MR. BRUSH Salesmen—Old Established New York brush manufacturers require services of men in all territories to sell their extensive line of Sanitary Twisted in Wire Brushes. We pay larger commission than any other brush house in the country. Write immediately for our proposition. Wire Grip Sanitary Brush Corporation, 15 Mercer St., New York.

CAPABLE salesman organizer. Good references. Ask about district manager proposition. Permanent, interesting work. Same territory. Your own business. Big annual income. Fairview Nurseries, Dept. MC, Geneva, N. Y.

SEND name, address on postcard. Free introductory copy Salesology Magazine; contains 1,000 money making opportunities. Offered by big reliable firms; no obligations. Salesology Magazine, Desk B-39, 500 No. Dearborn, Chicago.

SPECIALTY Salesman wanted. Big commissions being earned selling Ever-Ready pens. Write for particulars. Ever-Ready Can Company, Greenfield, Ohio.

TAKE orders for coffee, flour, dried fruits, canned goods, staple groceries, toilet articles, paints, radio sets, auto and tractor oils. No capital or bond required. We deliver and collect. Permanent business. Big pay. Write at once. Hitchcock-Hill Co., Dept. 50, Chicago.

MOTION—Color—Light plus changeable letter system make ours the last word in window salesmen. Actually boosts sales 200% to 400%. Every show window means an interested prospect. Get the facts and start pocketing \$100 weekly. Display Products Company, A409 East 31st, Kansas City, Mo.

TOOL Salesmen—Mechanics—Distribute guaranteed line auto repair tools. Exclusive business of your own. Show 71 samples in case. Big commissions. Quality Tools Corporation, New Wilmington, Pa.

HELP WANTED

WANTED—Men—Boys. Learn Auto Repairing. \$35.00 week. Sample lessons free. Franklin Institute, Dept. K-400, Rochester, N. Y.

WOULD you risk a 1c postal against the chance to make \$5 to \$15 daily during the next four months with an absolutely new line of Insured Hosiery, guaranteed 12 months? Your pay daily. Monthly bonus extra. Magnificent sample outfit furnished. If so, send name and address now to Macoshee Textile Company, Road 2606, Cincinnati, Ohio.

YOU Are Wanted. Men-Women 18 up. Get U. S. Government Life Jobs. \$95.00 to \$250.00 Month. Steady work. Paid summer vacation. Pull or experience unnecessary. Common education sufficient. We coach you without leaving home. 32 page book with full particulars free. Write immediately. Franklin Institute, Dept. K3, Rochester, N. Y.

DOUBLE Your Income. Read Opportunity, the Magazine that offers thousands of openings to double your income. Sent Free. Just send your name and address. Opportunity Magazine, 750 N. Michigan, Dept. C-1, Chicago.

MEN to train for locomotive firemen on railroads nearest their homes—everywhere; beginners \$150-\$250 monthly; promoted, locomotive engineer, \$3,000-\$4,000 yearly. Best paying positions on railroads. Railway Association, Desk M1, Brooklyn, N. Y.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet Articles, Household Specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1970W Broad, Richmond, Va.

GOVERNMENT Jobs. Mail Carriers—Clerks, Railway Postal Clerks. \$1700-\$3000 year. Men 18 up. Steady. Sample coaching free. Write today sure. Franklin Institute, Dept. K16, Rochester, N. Y.

IMMENSE Profits Silvering Mirrors at Home. Plating autoproducts, headlights, tailware, stoves, etc. Outfits furnished. Details free. Write Sprinkle, Plater, 287, Marion, Ind.

IF you can devote spare time to profitable work that pays \$2.00 to \$4.00 an hour, write us at once. No experience necessary. Nawco Company, Dept. 6-E, Covington, Ky.

MEN wanting to prepare for forest ranger job; \$125-\$200 monthly; nice cabin. Hunt, trap and patrol. Nat'l Forest list free. Write, Rayson, Dept. B-46, Denver, Colo.

IF you are a man worthy of the name and not afraid to work, I'll bet you \$50.00 you can't work for us thirty days and earn less than \$20.00. Think I'm bluffing? Then answer this ad and show me up. Openings for managers. Wonder Box sells on sight. The best selling proposition in America today. Write Tom Walker, Dept. 126, Pittsburgh, Pa.

POSTAL Clerks—Carriers. \$1700-\$3000 year. Men 18—up. 25 coached free. Write immediately. Franklin Institute, Dept. K16, Rochester, N. Y.

ARE You Old at Forty? See our advertisement on page 74 of this issue. The Electro Thermal Company, 2169 Main St., Steubenville, Ohio.

CASH paid for butterflies, insects. See Sinclair Display Advertisement on page 32.

MEN, Qualify for forest ranger job; \$125-\$200 month and home furnished; permanent; hunt, fish, trap. For details write Norton, 226 McClann Bldg., Denver, Colo.

U. S. GOVERNMENT wants men. \$1,700-\$1,900 and up at start. Railway Mail clerk examination coming. Let our expert (former Government examiner) prepare you for this and also Rural Carrier, Post Office, Customs, Internal Revenue, and other branches. Write today for free booklet. Dept. 8, Patterson School, Rochester, N. Y.

GOVERNMENT positions pay \$35 to \$75 weekly. We help you get them. Big List Free. Write, Mr. Ozment, 101, St. Louis, Mo.

EARN \$10 daily silvering mirrors, plating and refinishing metalware, auto, chandeliers, bedsteads, headlights. Outfits furnished. E. Decle Laboratories, 1133 Broadway, New York.

BECOME a Landscape Architect. Uncrowded profession of wonderful opportunity for money-making. Easily mastered by mail. Earn while you learn. Write for book. American Landscape School, 58-E, Newark, N. Y.

SILVERING Mirrors, French Plate. Easily learned; immense profits. Plans free. Wear Mirror Works, Excelsior Springs, Mo.

SEND name, address on postcard. Free introductory copy Salesology Magazine; contains 1,000 money-making opportunities. Offered by big reliable firms; no obligations. Salesology Magazine, Desk B-40, 500 No. Dearborn, Chicago.

GOOD Profits. Send 25c cartoon lesson \$1.00. GPO, Box 471, New York.

INFORMATION

3 INTERESTING Magazines, 30c. "Judge Lindsey Debate." "Life Enigma." "Hell Fallacy." Exponent, Orlando, Fla.

SPEECHES. No matter where you must speak, here is help. 366 pages of instruction and anecdotes, toasts and complete speeches for the amateur or professional. Send no money. Simply write a postal for "Speeches, Their Preparation and Delivery." Pay postman postal charges and \$1.25. Popular Mechanics Press, Room 900, 200 E. Ontario St., Chicago, Ill.

THIS is the season for making repairs about the home. Easily done with instructions in our new book. Tells exactly how to use tools, sharpen tools and cutlery, repair furniture and cabinets, upholster, work metal, solder, work glass, paint, stain, varnish, hang paper, repair plumbing, furnace, electrical equipment, shoes, harness, gloves and concrete work. Send no money. Just write and ask for "The Practical Book of Home Repairs." When postman hands you the book, pay him \$2.50 and the postal charges. Popular Mechanics Press, Room 900, 200 E. Ontario St., Chicago, Ill.

MAILING LISTS

1,000 NAMES. \$1.00. Mention Classification. Wincholt Sales Co., Woodbine, Penna.

LETTER SPECIALISTS

LETTER Specialists, national reputation! Powerful Messages \$5.00! Practical! Resultful! Investigate! Finkel, 15 Fairview, Jersey City, N. J.

BUSINESS SERVICE

COLLECTION stimulators that collect accounts \$3. Fred Beach & Co., Vincennes, Ind.

BROADWAY 200—Best address in New York. Two blocks from Wall Street. Beautifully furnished office. Woodwork snow white, green carpets, oak furniture. "Desk" or "Mail Privilege" exceedingly reasonable. We forward your mail daily. Room 404.

ACCOUNTS. Notes, claims collected everywhere. No charges unless collected. May's Collection Agency, Somerset, Ky.

PERSONAL Representation in Washington, D. C. Anything. Anytime. Service, Victor Bldg.

TYPEWRITERS AND SUPPLIES

UNDERWOOD Typewriters—only \$3.00 down. Easy monthly payments. Low prices at less than manufacturers. 10 days' free trial. Rebuilt, all worn parts replaced. Just like a new machine. 5-year guarantee. Write for a big free catalog. A-151, Shipman-Ward Mfg. Co., 1515 Shipman Bldg., Chicago, Ill.

100 TYPEWRITERS Free. Overstocked. Rent Rebuilt Underwood or Remington \$3.00 month. If you pay its value in rental, we give machine free. Particulars free. Pittsburgh Typewriter Exchange, 945 Hersch Bldg., Pittsburgh, Pa.

TYPEWRITERS, all standard makes. \$10 up. Fully guaranteed. Free trial. Write for complete illustrated lists. Northwestern Typewriter Exchange, 121 N. Francisco Ave., Chicago.

100 CARBONS \$2.00; Typewriter Ribbons, guaranteed, 75c; two \$1.25. PJH, 1927 N. Hoyne, Chicago.

TYPEWRITERS, all standard makes, thoroughly re-manufactured by the famous "Young Process" and shipped direct from factory to you on 10 days' trial. Guaranteed 5 years. Easy monthly payments. Write today for free catalog. Young Typewriter Company, Dept. 6746, 654 W. Randolph St., Chicago.

TYPEWRITERS, \$5-\$35.00; Motorcycles, \$15.00-\$75; Radios, \$9.00-\$65.00. Knight's, 1512 Locust, St. Louis, Mo.

PRINTING, ENGRAVING AND MULTIGRAPHING

NEARGAYTRE Process Printed Stationery—Exquisite Samples—See the Difference. Solidays, Knox, Ind.

RESULTS-BRINGING printing—writing—artwork—complete advertising and printing service. Moderate cost. Tricraft House, Box 290, Harrisonburg, Va.

MULTIGRAPHING business correspondence, two dollars thousand. Hammermill letterheads, four dollars. Miscellaneous printing. Mayera Corporation, Monmouth, Ill.

GENUINE Engraved Stationery—125 sheets and 100 envelopes engraved three lines for \$5. Request samples. Artcraft Engraving Co., 117 N. Wells, Chicago.

MIMEOGRAPHED Letters by Specialists; Low prices; Samples. Letter Service, 620 Woodland, Kansas City, Mo.

200 Sheets and 100 Envelopes printed, \$1.00. Write for samples. J. Brooks, Printer, Glasgow, Ky.

PERSONAL Stationery. Excellent quality paper. Name address neatly printed. Samples free. Wesley Dyer, 40 Pleasant St., Auburn, Me.

BOND letterheads, envelopes, billheads, statements, 250, \$1.50. Andrews, Box 1051, Fargo, N. D.

PRINTING: Catalogs, folders, letters, etc. Lowest prices. Samples free. Pitts, Amara, Iowa.

250 **HAMMERMILL** Bond Letterheads. Envelopes, \$3.00. Midland Press, 543 West Hickory, Kankakee, Ill.

100 **EACH** letterheads, envelopes; business, social; \$1.00 postpaid. Sherman, Printer, Anderson, Mo.

\$3.00 **DELIVERED**, 500 watermarked bond letterheads 8 1/2 x 11 and 250 envelopes. Cash. Catalog free. Printing bargains. National Printing, Goshen, Ind.

COMMERCIAL Printing. Prices Right. Samples Free. The Fox Press, Frankfort, N. Y.

DISTINCTIVE—Artistic Business Stationery that Creates Confidence. 1,000 Letterheads or Envelopes \$3.00. Samples. Moulton Printing Company, 1410-P East 8th, Kansas City, Mo.

We print Stationery, Booklets, Catalogs, Circulars. Samples. Commercial Press, Batavia, Ohio.

QUALITY Printing! Reasonable Prices! Send for Free Standardized samples and prices. Folders, Circulars. Catalogs our specialty. Ernest Fantus, 525 South Dearborn, Chicago.

100 **CALLING** cards and genuine leather case \$2.00; over one line 10c line extra. 200 standard business cards \$1.00; over 5 lines 10c line extra. Sample for stamps. Business Card Specialty Co., Q552, Jackson, Mich.

250 **LETTERHEADS**, 250 Envelopes—Bond, \$3.00. Arrow Press, Kankakee, Ill.

250 **BOND** Letterheads, Envelopes, Billheads, Cards, \$1.35 each. Economic Press, Leonia, N. J.

STATIONERY Printing Deluxe. Samples free. Industrial Press, Jefferson City, Mo.

PRINTING, OUTFITS AND SUPPLIES

PRINT Your Own Stationery, cards, bookplate, Christmas cards, circulars, book, pamphlets, etc.; complete outfits, \$8.85; larger, \$11, \$29; rotary \$140. Print for others. Easy and interesting; rules sent. Write for catalogue presses, type, paper, etc. Kelsey Company, K-11, Meriden, Conn.

PRINTING Presses, type, supplies. List 2c stamp. Bargains. Geo. Foster, 4342 North Robey, Chicago.

PRINTING Outfits—Presses, type supplies, type novelties. Send stamp for catalogue. Model Press, York, Penna.

DUPLICATORS AND DEVICES

YOU can make 50 to 100 copies of a letter, notice, etc., at a cost of three cents on a Meyer Quality Duplicator. Write for free trial offer. The Meyer Duplicator Co., 14 S. Wells St., Chicago, Ill.

RUBBER STAMPS

AGENTS Wanted. Many Rubber Stamps for the price of one. Sells at slight 20 or more different impressions from 6-line Multiplex. Send your Name, Business, Street, City, State and \$1.50 (Special Price). Will mail you prepaid 4-line Multiplex. Multiplex Rubber Stamp Co., 1777 Gower St., Los Angeles, Calif.

RUBBER Stamp! Name, Address, two lines 25c. Three lines 35c. Brush & Co., Auburn, Neb.

ADDING MACHINES

NEW \$3.50 Automatic Adding Machine. Adds, subtracts, multiplies absolutely accurate. Capacity \$999,999.99. Fully guaranteed. 75,000 pleased users. Makes adding easy, positive, quick. Eliminates mistakes. Saves time. Postpaid \$3.50. Bassett Co., 1458 F Hollywood Ave., Chicago.

FREE trial. Marvelous Calculator. Adds, Subtracts, Multiplies, Divides automatically. Work equals \$300.00 machines. Five year guarantee. Price only \$15.00. Write today for free trial offer. Special: \$3.00 Pocket Calculator. only \$2.00 cash. Lightning Calculator Co., Dept. E, Grand Rapids, Mich.

FOR SMOKERS

SEND 10c. Silver or Stamps, for sample package 20 finest quality cigarettes. Large tin Special smoking tobacco sent for 10c. Direct-to-Smoker. French Tobacco Company, Dept. 19, Statesville, N. C.

TOBACCO Postpaid, guaranteed. Best Mellow, July red leaf chewing, 5 lbs. \$1.40; 10, \$2.50. Best smoking 20c lb. Mark Hamlin, Sharon, Tenn.

CIGARS, hand-made wonderful flavor, 10c retail quality. 19 in can, postpaid only \$1. (or C. O. D.). Order today. Hoffbauer Bros., 589 52nd St., Brooklyn, N. Y.

FOR THE HOME

GRANDFATHER'S Clock Works, \$5.00. Build your own case; Instructions free; make good profits selling your friends. Clock works with chimas for old or new cases. Write for full particulars. Clock Co., Ruffner St., Philadelphia.

CEDAR chests only \$11.65—"Red-I-Kut" complete with rich copper trim—you assemble and save half—send for pictures. Kuempel Furniture Company, Guttenberg, Iowa.

FORGED decorative articles. Andirons, fireplaces, scroll and grille work, lamps, candle sticks, coat hangers, knockers and other hand-forged decorative articles can be made with instructions in new printing of "Hand Forging," by Thomas F. Googerty. Profusely illustrated. Send no money. Write a postal asking for Hand Forging. Pay postman postage and \$2.00. Popular Mechanics Press, Room 906, 200 East Ontario St., Chicago, Illinois.

THAT Concrete Job. Don't be afraid to tackle it. With the instructions found in Popular Mechanics Concrete Handbook you can make 173 articles of utility and beauty ranging from ordinary steps to garden furniture. This book with our Home Mechanics Handbook that contains 329 helps about jobs that come up about the home will be sent for only 98c plus postage C. O. D. Send your order today to Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

THE Home Patrol Burglar Alarm sounds alarm and locks window \$2.00 each. Guaranteed. Agents write J. B. Pitts, 32 No. Jefferson St., Chicago.

HOME Redecoration Time is here. Get newest ideas and methods from books just published for sale by Popular Mechanics Press. Interior Wall Decoration, Plain and Decorative Finishes, Practical Working Methods. 450 pages. Price \$4. Mixing of Colors and Paints, 292 pages \$2. Wood Finishing, Plain and Decorative, 360 pages, \$2. House Painting Methods, Brush and Spray Gun, 386 pages, \$2. Books will be sent C. O. D. Pay postman price plus postage when he hands you the package. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

HOW to Make and How to Mend, 1000 articles telling how to repair almost everything in use or needed about a home or farm. Many illustrations; formulas and trade secrets. Send no money. Just ask for "How to Make and How to Mend." Pay postman postal charges and \$1.00. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

RAZORS AND BLADES

GENUINE Gillette Razor With Blade 25c prepaid. Address Croddy, Box 1089, Sacramento, Calif.

BOATS AND LAUNCHES

CLIPPER Ship, 20" overall, spars, sails, deadeyes, blocks, steering wheel, anchor \$5.00. Deadeyes all sizes 60c dozen. List of fittings. Dime. Roy Hancock, 323 Douglas Ave., Portsmouth, Va.

NEW Boat Book telling how to make 21 kinds of boats. Also many other helpful ideas on boating. Profusely illustrated. With this we include the big book, "Outdoor Sports the Year Round." Directions for making all sorts of devices for outdoor recreation. Send no money. Simply pay the postman \$1.98, plus postage when books are delivered. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

BUILD your own boat for this season's use using Brooks Knock-Down parts or patterns. 55 Models, 9' to 40'; send 25c for complete catalog. Brooks Boat Co., Inc., Rust Ave., Saginaw West Side, Mich.

LATEST Ship Model Book—How to make a model of an American clipper ship, "Sovereign of the Seas," by Capt. McCann. Simplified construction. Complete details. Order a copy and pay postman \$2.50 and the postage when he hands you the package. Address Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

BOAT Building Plans for amateurs. Rowing, sailing, speed, cruising. Free catalog. Rudder Publishing Company, 9 Murray Street, New York.

HUBBELL Marine Coolers convert Ford engines into marine motors. Booklet free. Ford speedboat, easily built, blueprint and directions, sixty cents. C. C. Hubbell, 14B Cottage St., East Norwalk, Conn.

PROPELLERS, stuffing boxes, bearings, etc. Used reverse gears bought, sold. Wm. H. Baker, Pond St., Quincy, Mass.

AIRPLANE Tachometers, Register Engine revolutions, cost government \$50.00, sacrificed \$10.00. Equipment, Carle Place, N. Y.

SHIP Models—Worth while. Easy to make. Decorative Ships Picturesque Barbary Pirate Felucca and Beautiful Spanish Treasure Galleon (both 17th century). Instructions so simplified that any handy person can make these models with a few household tools almost without expense. No personal knowledge of ships or naval architecture required. New book only one of its kind. Pay postman \$2.50 plus postage when book is delivered. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

DIAMONDS, WATCHES AND JEWELRY

TRADE your old broken watch for new Elgin or Waltham. Small difference. Ralph Pile, Somerset, Penna.

WATCH REPAIRING

ALL makes of Watches repaired by experts. Write International Watch Service, Box 5P, Fordham Station, New York.

ANTIQUES, WAR RELICS AND INDIAN GOODS

WANTED, odd, rare or curious articles for resale. Something out of ordinary. Ralph Pile, Somerset, Penna.

100 **GENUINE** Indian arrowheads from Arkansas \$4.00 postpaid. H. Daniel, Lamar, Ark.

SEND 5c for One new list Indian relics, antique firearms. F. E. Ellis, Webster Groves, Mo.

PHONOGRAPHS AND RECORDS

BUILD your own phonograph. We furnish everything. Catalog sent free. American Phonograph Co., 4116 West 24th Place, Chicago.

MUSIC AND MUSICAL INSTRUMENTS

TREMENDOUS Stock, cornets, saxophones, trumpets, slide trombones, sousaphones, clarinets and other instruments. New, rebuilt. All makes. Ukuleles, violins. Catalog, bargain list free. Walbersdorf's, Rebuilders, Creston, Iowa.

VIOLINS—Fine hand-made. Low Prices. Lehto, 535 14th, San Pedro, Calif.

PIANO JAZZ! Fifteen Hot Beginner's Lessons. Particulars! Write Will Mulveney, Toronto, 3, Canada.

REAL Jazz piano lessons at home. Five breaks, endings; African harmony, brilliant runs; professional jazz guaranteed; booklet. Sample Lesson Free. United Schools, P. O. Box 1959, Boston, Mass.

SONG poems wanted. A different proposition. Richard Broughton, Sioux Falls, S. Dak.

SONG Poem Writers—Address Ray Hibeler, D1, 2104 N. Keystone Ave., Chicago.

VIOLINS. Deep, Mellow, Soulful—on credit. Easy terms for wonderful instrument. Get details today. Gustav F. Henning, 2424 Gaylord St., Denver, Colo.

"MUSIC Composed" to words. Bauer Bros., (formerly of Sousa's Band), Oshkosh, Wis.

SONG Poem Writers Address Monarch, 1472 Broadway, Dept. 104, New York.

WRITE Songs. Big money and reputation. Write for information. J. Gordon Pub. Co., 201 N. Hove Ave., Chicago.

I WANT Song Poems. Casper Nathan, 3544 N. Racine, Chicago.

SONG Poem Writers—Stamp brings "Song Writers' Guide." Wm. Van Beaver, B1-1239 Elm St., Green Bay, Wis.

SONGWRITERS—Music Publishers. Expert professional service. Particulars free. Diamond Music Company, Department EHS, 790 Seventh Avenue, New York.

CORNETISTS—Trombonists—Saxophonists—Clarinetists. Get "Free Pointers." Name instrument. Virtuosi School, Buffalo, N. Y.

PATENT ATTORNEYS

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

PATENTS Procured: Trade Marks Registered—A comprehensive, experienced, prompt service for the protection and development of your ideas. Preliminary advice gladly furnished without charge. Booklet of information and form for disclosing idea free on request. Richard B. Owen, 30-Owen Bldg., Washington, D. C., or 41-R Park Row, New York.

MILLIONS spent annually for ideas! Hundreds now wanted! Patent yours and profit! Write today for free book—tells how to protect yourself, how to invent, ideas wanted, how we help you sell, etc. American Industries, Inc., 509-Victor Bldg., Washington, D. C.

INVENTORS—Write for our Guide Book, "How to Get Your Patent" and Evidence of Invention Blank. Send model or sketch of your invention for our prompt examination and instructions free. Randolph & Co., Dept. 430, Washington, D. C.

PATENTS, Trade-marks, Copyrights. Reliable services by an experienced practitioner devoting personal attention to each case. Inquiries invited. References furnished. R. P. Fishburne, Patent Lawyer, 525-A McGill Bldg., Washington, D. C.

INVENTORS having ideas to patent: Write for Booklet explaining Co-operative Plan for handling your applications. Tells how to sell and safeguard your inventions at lowest cost. Ralph Hurch, Patent Lawyer, Jenifer Bldg., Washington, D. C.

ESTABLISHED 1864. Milo D. Stevens Company. Free Booklet, Patents, Trade-Marks, Copyrights. Offices, Monastnock Block, Chicago; Barrister Building, Washington, D. C.

PATENTS, Trade-Marks, Designs. This firm has 27 years' experience and gives expert personal service at reasonable rates. We properly protect your invention. Write for free information and exact cost of procuring patent before proceeding. John B. Thomas & Co., 902 F St., N. W., Washington, D. C.

UNPATENTED Ideas Can Be Sold. I tell you how and help you make the sale. Free particulars (Copyrighted). Write W. T. Greene, 807 Jenifer Building, Washington, D. C.

RICHARD E. BABCOCK, Patent Lawyer, Washington Loan & Trust Bldg., Washington, D. C. Booklet.

"INVENTOR'S ADVISOR," Patentbook, with 139 mechanical movements, illustrations, sent free. Labriere, Patent Attorney, Three Parkrow, New York.

"INVENTORS' Guide" sent free on request: this book contains illustrations of patented inventions and gives valuable information and advice for all who have original ideas or improvements. Frank Ledermann, Registered Attorney and Engineer, Woolworth Bldg., 1712, New York.

INVENTORS: Send sketch or model for advice and exact cost of patent. Ask for our Free book: "How to Obtain a Patent." Tells what every inventor should know. Established twenty-eight years. Highest references. Prompt service. Reasonable charges. Chandler & Chandler, 474 Seventh, Washington, D. C.

PATENTS. Booklet free. Highest references. Best results. Promptness assured. Send model or drawing for preliminary examination. Watson E. Coleman, Patent Lawyer, 724 Ninth St., Washington, D. C.

PERCY S. WEBSTER, 203 Saving and Loan Building, Stockton, California. Long established organization. Patent booklet free.

UNITED STATES and Foreign Patents and Trade Marks: Low rates; easy terms. H. Sanders, Registered Patent Attorney, 7 Rand McNally Building, Chicago.

PATENTS—Write for our Guide Books and "Record of Invention Blank" before disclosing inventions. Send model or sketch of your invention for Free Inspection and Instructions. Terms reasonable. See advertisements on pages 142 and 143. Victor J. Evans & Co., 934 Ninth, Washington, D. C.

EDWARD C. SASNETT, Formerly a Principal Examiner U. S. Patent Office, Attorney at Law. Strictly personal service. Correspondence invited. McGill Building, Washington, D. C.

MONROE E. MILLER, Ouray Bldg., Washington, D. C. Patent Lawyer; Mechanical, Electrical Expert. Booklet and Priority Record blank gratis.

PATENTS obtained under Co-operative Payment Plan. Write for particulars. W. E. Beck, Registered Patent Lawyer, 951 Jenifer Bldg., Washington, D. C.

PATENTS—Write for Instructions. Carl Miller, Registered Patent Attorney (former member Examining Corps United States Patent Office), McGill Building, Washington, D. C.

PATENTS Procured. Prompt service. Personal, careful and efficient service. Highest references. Moderate fees. Send sketch or model for actual search and advice. George P. Kimmell, Master of Patent Law, 51-H Legal Bldg., Washington, D. C.

LACEY'S Patent Sense. Valuable book free. See ad page 116.

FOR INVENTORS

PATENTS. If you have an invention which you wish to patent you can write fully and freely to Munn & Co., for advice in regard to the best way of obtaining protection. Please send sketches, or a model of your invention and a description of the device, explaining its operation. All communications are strictly confidential. Our Hand-Book on Patents is sent free on request. This explains our methods, terms, etc., in regard to Patents, Trade Marks, Foreign Patents, etc. "Scientific American" contains Patent Office Notes, Decisions of interest to inventors and particulars of recently patented inventions. Munn & Company, Solicitors of Patents, 1533 Scientific American Building, 24 W. 40th St., New York City; 523 Scientific American Bldg., Washington, D. C.; 1313 Tower Bldg., Chicago, Ill.; 666 Hobart Bldg., San Francisco, Calif.; 521 Van Nuys Bldg., Los Angeles, Calif.

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

WANTED: Specialists of electrical or mechanical nature, patented or not, that can be marketed through automotive accessory, hardware, electrical trades. If specialty meets Delta quality standard, will buy outright or manufacture on royalty basis and market it through our established channels under nationally known Delta trademark. Send full information and drawings. Delta Electric Company, Marion, Ind.

PATENTS Procured: Trade Marks Registered—A comprehensive, experienced, prompt service for the protection and development of your ideas. Preliminary advice gladly furnished without charge. Booklet of information and form for disclosing idea free on request. Richard B. Owen, 30-Owen Bldg., Washington, D. C., or 41-R Park Row, New York.

INVENTORS Universal Educator—containing 900 mechanical movements; 50 perpetual motions. Tells how to obtain and sell patents. Suggests new ideas. Explains how to select your attorney and avoid patent sharks. Price (revised edition) \$1.00 postpaid. Albert E. Dietrich, 621-Ouray Bldg., Washington, D. C.

GET your own patents. Legal blanks, complete instructions \$1. Cutting Sons, Cambell, Calif.

INVENTORS—Write for our Guide Books and "Record of Invention Blank" before disclosing inventions. Send model or sketch of your inventions for our free inspection and instructions. Terms reasonable. See advertisements on pages 142 and 143. Victor J. Evans & Co., 151 Ninth, Washington, D. C.

PARTNER wanted to patent my inventions. Fred Petterson, Dothan, Ala.

I SELL Patents. Established in 1900. Experience, Reputation, Efficiency, Equipment. The nonsense left out. The service you will eventually employ if you have a valuable patent to sell. Send Patent copy for consideration. Charles A. Scott, 774-M Garson Avenue, Rochester, N. Y.

MARKET your own inventions. Free counsel. See advertisement under Advertising Agencies, page 19. Frank W. Lenhoff Advertising Agency, Chicago.

PATENTS Wanted by manufacturers; send description. Box 126, Dowagiac, Mich.

PATENTS obtained under Co-operative Payment Plan. Write for particulars. W. E. Beck, Registered Patent Lawyer, 950 Jenifer Bldg., Washington, D. C.

INVENTORS: Manufacturers' names in the line of your invention \$1.00. W. D. Schwenk, Box 123, Ferndale, Mich.

INVENTIONS Developed—Your crude ideas developed into practical form for your patent application. Model not necessary. Send rough sketch and description for estimate of cost and advice. 27 years' experience. Albert E. Dietrich, Engineer and Registered Patent Attorney, 621½ Ouray Building, Washington, D. C.

WANTED—Substantial articles for mail-order business. What have you to offer? Write Liberty Novelty Company, 3537 W. 22nd St., Chicago, Ill.

GOOD Pending Patents readily marketed. Booklet free. American Institute of Patents, Barrister Building, Washington, D. C.

INVENTORS—Sell Your Patent Yourself; get my copyrighted sales plan and list of buyers. Leroy Brown, 1311 Broadway, Baltimore, Md.

UNPATENTED Ideas Can Be Sold. I tell you how and help you make the sale. Free particulars (Copyrighted). Write W. T. Greene, 806 Jenifer Building, Washington, D. C.

I AM in touch with hundreds of moneyed men and manufacturers who wish to buy good inventions. Write Hartley, 38 Court St., Bangor, Me.

WE pay cash for patented ideas we can use in the manufacture of amusement devices. Send us your ideas. Spillman Engineering Corp., North Tonawanda, N. Y.

LACEY'S Patent Sense. Valuable book free. See ad page 116.

PATENTS—Write to B. P. Fishburne (a South Carolinian). Registered Patent Lawyer, 525-E McGill Bldg., Washington, D. C.

PATENTS FOR SALE

THE Hub coffee percolator. A real money-making proposition, will produce a perfectly clear coffee for particular people. Can be cheaply manufactured with a liberal margin of profit. Market unlimited. This invention is for sale outright or the article may be manufactured on a royalty basis. This receptacle can be used in any style coffee pot, old or new, for home use, restaurant use and for medicinal purposes such as brewing herbs, etc. For particulars and terms address, Lawrence Ronell, 204½ E. 22nd St., Chicago, Ill.

TWO-ARM Turnstile, half usual width, for theater, park, railroad, omnibus. New principle. Francis J. McLoughlin, 141 Broadway, New York.

FOR Sale. Controlling interest on patent. John Naef, Ironton, Mo.

FOR Sale Outright—Animal trap patent. Catches mice and other animals automatically. Extremely simple. Enormous field for sale of this trap. Can be made for 18 cents, sells for \$1.00. Dies ready to begin operations. Pat'd in 1925. Novelty Mfg. Co., 323 N. Market St., Lancaster, Pa.

OUTRIGHT, belt guide; keeps belt from running off tractors, etc., when working with side wind. Otto Buchman, Tyndall, S. Dak.

OUTRIGHT: Slip Joint Pliers—Takes the place of pipe wrench, ordinary wrench, socket wrench, band vice. Patent No. 1,541,248. Elmer R. Carlson, 517 S. E. 4th St., Galva, Ill.

NEW Glass Shield. Easily installed on any make cars. Placed and replaced on passing a car. Gives perfect satisfaction regardless how bright approaching lights are. H. E. Stampley, Shirley, La.

OUTRIGHT or royalty. Patent No. 1,575,332. Paring Knife. Just the article for aluminum manufacturer. F. E. Hall, Morris, Minn.

NEW Device Saves $\frac{1}{4}$ to $\frac{1}{2}$ fuel of gas engines—eliminating carbon and engine troubles—increasing mileage and power. For automobile and stationary gas engines. Quickly installed. Sell outright or Royalty. Mrs. J. C. Mowrey, 527 Spokane Ave., Portland, Ore.

OUTRIGHT or Royalty: Signal to fasten on rear of car. Directs Right, Left, ahead, back, park. Controlled by thumb of left hand on steering wheel. Is compact, accurate, inexpensive; has one bulb. Write Harry Sorensen, Box 29, Elk Horn, Iowa.

PATENT For Sale, on Directional Signal for Vehicles; a valuable device in roadway. Sell outright or royalty. For particulars address J. M. Almedia, Arcade Station, Box 512, Los Angeles, Calif.

OUTRIGHT or Royalty basis. Newly patented and useful automobile radiator spout attachment. Paul Schnormeler, Hubbard, Iowa.

PATENTED Stamped Metal Duck Decoy excels all others. Hurd, B-591, Klamath Falls, Ore.

ROYALTY on wheeled toy. Nothing like it. H. L. Holloway, 112 W. Lane Ave., Columbus, Ohio.

NOCOST Water Heating Gas Burner, water heated by gas used for other purposes. J. A. Frisk, 3339 Roscoe St., Chicago, Ill.

THE lack of proper finance is holding me back on a number of practical useful inventions. I have three wrenches, a drawing tool, coal saver, and a dozen others still in the rough. If interested write me at once. All letters confidential. C. B. Stevens, 702 Umatilla Ave., Portland, Ore.

OUTRIGHT, reasonable, pipe joint for bath tubs, basins, toilets, sinks. Robert Dawson, Fairview Cottage, Skillman, N. J.

PAT. 1,509,690, self-cleaning Berry-picker. Cash or royalty. Write to Wester Wainio, Box 81, Wainio, Mich.

FOR Sale—Patent on bread slicing machine. Cuts whole or parts of loaves without changing. Good for hospitals, hotels and restaurants. John Jarosz, 110 Lakeside Ave., Lowell, Mass.

FOR Sale, Outright—Patent Mop Holder, very strong; will fit any Mop Head. R. B. Flake, care Cleggs Hotel, Greensboro, N. C.

FOR Sale—United States and Canadian Patents—Electric Washing Machine Mounted within a wash tub. Clara Schultz, 717 88th Street, Brooklyn, N. Y.

OUTRIGHT, Royalty—Adjustable Table, for beds—chairs. No. 175, Griggsville, Ill.

THE cheapest continual power ever invented—takes the place of expensive gas engines, wind mills, steam engines in many ways. Patent Pending. Joseph Weber, Lone Rock, Wis., Inventor.

FOR Sale—Patent, Improved Flour Sifter, outright or Royalty Basis. Harry Nakagawa, Tanana, Alaska.

WHY let your patents lie idle? Tell our two million five hundred thousand readers about it! The majority of our readers are especially interested in new ideas and inventions. Ask me to tell you how other inventors successfully sold their patents. M. L. Rund, Mgr., Classified Advertising, Popular Mechanics Magazine, Chicago.

ELECTRICAL

ELECTROLYTIC Process of re-sharpening files and hacksaw blades; absolutely cut like new. Inexpensive. Your opportunity to start that business you have always wanted. Process and plans \$1.00 bill, check \$1.10. Instolyte Co., 3124 37th Ave. S., Minneapolis, Minn.

MAKE Things Electrical. Complete instructions for making medical coil, buzzer, rheostat, sign flasher, electric toaster, heater, electric grill, soldering copper, crystal receiver, transformer, Tungar rectifier, Duram receiver, motor and other things in fine illustrated book costing \$1.25. Pay postman price and postage when he hands you the package. Address Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago.

TWENTIETH h. p. electric motors. Fine for fans or experimenting. Runs off dry cells or radio battery. Finest workmanship. \$2.25 each, postage prepaid. Send cash or money order. A. Redmond Co., Flint, Mich.

FOR MECHANICS

ATTENTION—Home Mechanics: We sell unusual cabinet hardware, chest trimmings, tea wagon wheels and casters, big line small hinges, locks, etc. Upholstering supplies, electrical hardware, knocked down cedar chests, etc. Send ten cents stamps for catalog. Thurston Manual Training Supply Company, Jobbers and Manufacturers, Anoka, Minn.

"BLUEPRINT Reading" is a compact book telling how to read machine blueprints. Send no money. Just pay postman postal charges and \$1. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

KINKS on Metal Work. 419 discoveries for anyone who works with metal. For machinist, machinist or the man who tinkers at home. 287 illustrations. Send no money. Just write a postal asking for "Machinist's Kinks." When postman hands you book pay postage and price of book, \$1.50. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

SURVEYING INSTRUMENTS

LARGEST stock of new and used surveying instruments in the country direct from factory. Satisfaction guaranteed or money refunded. Wissler, 619 N. Broadway, St. Louis, Mo.

MODELS AND MODEL SUPPLIES

PATENTS. Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instruction or write for free book "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. See pages 140 and 141.

THE Modelmaker, a magazine for all interested in making working models, boats, etc. Sample 10c. Modelmaker, 123 Liberty St., New York.

WOOD'S for Models, Scroll Work and Inlaying. George Wild, 510 East 11th St., New York.

SPECIAL machine builders, tool and die makers, inventor's models, production work of all kinds. Dept. L, Quality Hardware & Machine Co., Ravenswood and Thorndale Avenues, Chicago, Ill.

WE make working models for inventors and do experimental work and carry a complete stock of brass gears and model supplies. Send for catalogue. The Pierce Model Works, Tinley Park, Ill.

MODELS, Experimental Work, Light Manufacturing, and Stamping. Frostholt Bros., Syracuse, N. Y.

SPANISH Galleon Ship Blueprints, including instructions for building, painting, rigging, beautiful 2 foot model. \$1.00 complete. Leonard Allen, 332 E. W. Hellman Bldg., Los Angeles.

SHIP Model Hulls. Flying Cloud, $\frac{1}{8}$ " Scale \$9.00. Constitution, $\frac{1}{16}$ " Scale \$10.00. Spanish Galleon \$10.00. Also complete Construction Sets. Roy Hancock, 523 Douglas Ave., Portsmouth, Va.

WORKING models built. Drawings prepared free. Let our designing and engineering departments and 27 years' experience assist you with your invention. Lowest prices. Hohmeier Mfg. Co., 1385 E. 17th St., Cleveland, Ohio.

LET our experience be your guide. Models that are models: tools and equipment for economic manufacture. Patterns of all types; manufacturing in all branches. Satisfaction guaranteed. United Machinery Company, Cincinnati, U. S. A.

DECORATIVE Work. Directions for decorating with pressed leaves, antique painting, preserving plants, bouquets of colored grass, tree cone decoration, fungi decoration, decalcomania, crystallized grasses, Grecian painting copper impressions of leaves, skeleton leaves, leather work, modeling in clay, moss work, paper flowers, pearl work, ornamenting with shells, etching shells, transparencies. All this and much more in "Youman's Household Guide." Send no money. Just order on postal. Pay postman \$2 and postal charges. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

MODEL and Experimental Work at lowest cost. Wagar Model & Machine Works, 115 So. Clinton Street, Chicago.

WELDING AND SOLDERING

WELDING, Lead burning and soldering outfits. Manufactured by the Welders Supply Co., 120 Opera Place, Cincinnati, Ohio. Write for literature.

MANUFACTURING

MODELS, Dies, Manufacturing Ideas developed, screw machine products, metal stampings, and contract manufacturing of metal parts. Schroer Manufacturing Co., 2104 Campbell St., Kansas City, Mo.

WANTED to manufacture on royalty basis, some Mechanical Appliance or Automobile Accessory. Cincinnati Automatic Machine Co., Cincinnati, Ohio.

WE manufacture your invention, help perfect it, make models, dies. Free information. Strand Mfg. Co., 644 W. Randolph St., Chicago.

PATTERNS, wood and metal. Models, tools and dies. Brass, bronze, aluminum and iron castings. Screw machine work, production work of all kinds. Write Modern Machine & Pattern Co., Terre Haute, Ind.

WE help you design, make your models, dies, manufacture your products. Standard Die & Specialty Co., 1932 Austin Ave., Chicago.

SPECIAL Machinery or parts, dies, tools, metal specialties, models, special gears, stock gears and model supplies. Send for Catalogue. The Pierce Model Works, Tinley Park, Ill.

MANUFACTURING Models, Dies, Stampings, Brass Work, one or thousands. Baum's Metal Specialties, Kansas City, Mo.

WIRE goods made to order. Cooley Mfg. Co., 530 N. Western Ave., Chicago.

FURNITURE—Make furniture at home. Popular Mechanics books tell how to make all pieces. "Mission Furniture and How to Make It," Book 1, Book 2, Book 3. Send no money. Just write a postal. Pay postman postage and \$3. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

INVENTORS, Complete Organization at your service in developing patents, ideas, builders, designers of special machinery, experimental work, models for demonstration, drawings, tracings, wood metal patterns. Weydell-Nobach Co., 12 So. Clinton St., Chicago.

STAMPING and light manufacturing. Acme Tool Co., Mason City, Ia.

REFRIGERATING Machine, homemade. Operates successfully. Gives better service than ice. This and 328 other practical articles in our book "Home Mechanics." Just ask for this and "Handbook for Women," containing 394 valuable household helps and pay postman 98 cents and postage for the two books. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

MACHINERY, TOOLS AND SUPPLIES

FOR Sale—Owens No. 6 Milling Machine with cutters; almost new. Price \$275.00. Stainforth, Winthrop, Mass.

SMALL Milling Machine for sale. B. L. Nordved, Ethan, S. Dak.

\$25 KENNEDY Utility Saw will rip, cross cut, sand, and grind. With extra attachments you can plane, groove, tongue, plough, miter, bevel, bore, rabbit, mortise, joint, make mouldings, etc. Ball Bearing Table top. Ralph Kennedy, 111 N. 7th St., Philadelphia, Pa.

CONCRETE Building Block Machine and Molds. Catalogue free. Concrete Machine Co., 5 N. Main St., St. Louis, Mo.

OTHERS have successfully sold their machinery through our columns—so can you. Ask me for proof. M. L. Rund, Manager, Classified Advertising, Popular Mechanics Magazine, Chicago.

NEW Westinghouse $\frac{1}{2}$ H. P., 110 Volt, 60 cycle, A. C. Motors, complete, latest type, all enclosed. Price, \$15.00 each. Rotzink Brothers, Inc., 67 Water St., New Haven, Conn.

CARPENTERS—Ideas for those who like to tinker with tools, and for professional carpenters. 40 articles on saws and sawing, 17 on benches and bench equipment, 22 on doors and door hanging, 18 on lumber, 13 on mitering, 74 on tools, 22 on shop equipment and many others—366 in all, and 229 illustrations. Send no money. Just write a postal. Pay postman postage and \$1.50. Popular Mechanics Press, Room 906, 200 E. Ontario St., Chicago, Ill.

PATENTED Steel Frame, pulley and governor, for using Ford motor for belt work. Satisfaction guaranteed. Write for bulletin. Dunlap Fordpower Co., Wichita, Kans.

PIPE second hand, guaranteed suitable for all practical purposes with new threads and couplings, sixteen feet and over; cut to your requirements, also Boiler Tubes, New Fittings. Pfaff & Kendall, 102 Weydell St., Newark, N. J.

START Business of your own, small investment required, doing nickel, copper and silver plating. This work is in big demand. Full information free. Electro Platers Supply Co., 547 Considine Ave., Cincinnati, Ohio.

SPEED Lathe \$10.50 complete. 7 inch swing, 3 speed cone. Jefferson Mfg. Co., Fairfield, Iowa.

NEW foot-power Motor-driven Mortiser \$150.00. Cash or terms. Woodworkers Tool Wks., 222 So. Jefferson, Chicago.

FOLEY-Saw-File, hand drive, complete with Saw Set. Will sacrifice for half factory cost. Detailed information by letter, H. Appenzeller, Puerto Cortes, Rep. of Honduras, C. A.

16" x 8" PRENTICE engine lathe, \$175.00. 20" x 10" Davis engine lathe—quick change, \$550.00. No. 60 Heald Cylinder Grinder, \$750.00. 10x32" Landis Universal Piston and General Grinder, \$375.00. 20" Drill Press, \$75.00. 14" Drill Press \$40.00. Complete line of machinery and small tools. Write for catalog, Cincinnati Machinery & Supply Co., 218 East Pearl St., Cincinnati, Ohio.

KINKS on Metal Work. 419 discoveries for anyone who works with metal. For mechanic, machinist, or the man who tinkers at home. 287 illustrations. Send No Money. Just write a postal asking for "Machinist's Kinks." When postman hands you book, pay postage and price of book, \$1.50. Popular Mechanics Press, Room 906, 208 E. Ontario St., Chicago, Ill.

ENGINES, MOTORS AND DYNAMOS

BARGAINS—Motors, Machinery. 1/4 H.P. \$6.00. 1/2 H.P. \$18.75. 1 H.P. \$25.00. Electric Drills \$14.95. 100 other bargains. Send for "Bargain Sheet No. 630." Acme Tool Co., 637 Washington St., Chicago.

STEAM Engines. 1 H.P. \$18.00; 1/2—\$12.00. James Chambliss, Bessemer, Ala.

ALTERNATING and direct current motor bargains. All sizes, all kinds, new and rebuilt. Wholesale price list free. Guaranteed makes only. Motors bought, repaired, exchanged. Special fan prices. Hyre Electric Co., 615 N. Dearborn St., Chicago.

ANOTHER lot new 110 v. alternating current washing machine motors, \$5.50 each; three, \$5.25 each; six, \$5.00 each; 1-12 horse 110 v. universal, \$2.75 each. Single motor cash with order, quantity \$5.00 cash, balance on delivery. Also other bargains. Queen City Electric Co., 1736 Grand Ave., Chicago, Ill.

GOVERNORS for all auto engines where used for power plants. Send for circulars. A. C. S. Governor Co., Springfield, N. Y., or 215 W. Manchester, Los Angeles.

WRITE for bargain catalogs on electric motors, generators, electric drills, etc. Do not buy, consult us first. General Distributing Co., Security Bldg., Duluth, Minn.

MOTORS—New OE 110 or 220 volt 60 cycle Single Phase 1/4 HP, \$11.00; 1/2 HP, \$22.50; 1 HP, \$38.50. Mail \$3 check or money order. We will ship COD anywhere. Motor Specialties Co., Crafton, Penna.

GUARANTEED A. C. 1/4 H. P. 110 V. 60 Cycle Washing Machine motors with cord \$5.00. 25% required, balance C. O. D. Ellis & Co., 1018 W. Lake, Chicago.

BLACKSMITHS

BE a Master Mechanic Blacksmith and Expert Tool Maker and Dresser with colored tempering charts. Price \$1.00. Valuable samples free. W. M. Toy, Sidney, Ohio.

BENDING MACHINES

THE Famous Rossfeld "Wrenchless" Universal Iron Bender is the last word in bending machines; bends both Pipe and Bars to most any conceivable shape. Bends Eyes, "U"s, Angles, Rings, Coils, etc. Accurately bends anything from a small nail up to a 1 1/2-in. pipe cold. Instantly adjusted without a wrench. Thousands in use. Write for descriptive circular and prices. Rossfeld Mfg. Co., Box 344, Winona, Minn.

FOR SALE—MISCELLANEOUS

HAIR Grows when your Vacuum Cap is used a few minutes daily. 60 days' free trial. No drugs or electricity. 20 years success. Stops falling hair and dandruff. Booklet free. Modern Vacuum Cap Co., 555 Quincy, Denver, Colo.

ADDRESOGRAPHES. Letter Folders, Multiplicators, Envelope Sealers, Duplicators, less than half price. Guaranteed. Profit Co., 117 No. Market, Chicago.

FOR Sale or Exchange—One Internal bathing system. One Violin Course. Dale Snavely, Haxtun, Colo.

WANTED—MISCELLANEOUS

MAIL us your discarded Jewelry, Gold, Crowns and Bridges, Watches, Diamonds, Silver, Platinum and old False Teeth. Money promptly mailed. Goods returned if offer refused. United States Smelting Works (The Old Reliable), Dept. 71, Chicago.

REAL ESTATE, FARM AND ORCHARD LANDS

\$10 IS all I ask down on 20 acres in Mich. Potato Belt. Very easy terms. Near markets, lakes and streams. Write for particulars now. G. W. Swigart, P1276 First Nat'l Bank Bldg., Chicago.

STATE Rd, Riverside Farm, 50 Acres, Private Pond, Furniture, Poultry, geese, implements; bus at door, excellent 7-room house, new hen house, ample barn, etc.; RR. town nearby, only \$2500, part cash. Details pg. 48 Spring Catalog. Free. Strout Agency, 255-P, 4th Ave., New York City.

EASTERN New Mexico farms and ranches, also oil and gas leases, royalties. Western Land Company, Portales, New Mex.

LAND Free if planted to bananas. Bananas bear a full crop the second year. \$5.00 monthly will plant five acres, which should pay \$1,500 profit annually. Reliable companies will cultivate and market your bananas for one-third. Bananas ripen every day and you get your check every 90 days. For particulars address Jantha Plantation Co., Empire Bldg., Block 726, Pittsburgh, Pa.

OZARKS—10 acres near White River and proposed power dam, \$100, \$5 monthly. Alvin Zimmerman, 1802 N. 5th, Kansas City, Kans.

SELL your property quickly for cash, no matter where located. Don't pay big commission. Particulars free. Real Estate Salesmen Co., Desk B, Lincoln, Neb.

PECAN-Orange-Fig Groves "On the Gulf" Monthly payments, Guaranteed care. Big, quick returns. Suburban Orchards, Dept. M, Biloxi, Miss.

LAND Sale. \$5 down, \$5 monthly, buys 40 acres Southern Mo. Price \$200. Send for list. Box 22, Kirkwood, Mo.

SEEDS, PLANTS, ETC.

WRITE Today for Prices on 1936 Ginseng Seed Booklet on Golden Seal Growing. 10c. W. N. Long, Florence, Ky.

TOMATO—Sweet Potato—Pepper; all kinds Garden and field Plants. Write for list and prices. Wm. Guenther, Owensboro, Ky.

POULTRY

NO. 2 Half-Price Chicks. We have cut our prices almost in two. All kinds. Quick shipment. Three-color catalog free. Missouri State Hatchery, Box 711, Butler, Mo.

RABBITS

MAKE big profits with Chinchilla Rabbits. Real Money-makers. Write for facts, 852 Conrad's Ranch, Denver, Colo.

ROOTS AND HERBS

HERB Doctor and Medicine Man Book, 10c. (Worth dollars.) Contains over 250 valuable herb medicine recipes for home use. Shawnee, 145 West 113th Street, Chicago.

HERB Doctor Book—10 cents. 250 recipes for making herb medicine. Hazard Company, Box 1, Vanderveer Park, Brooklyn, N. Y.

DOGS AND PETS

POLICE Dogs and Puppies, Sired by Champion. Catalog free. Caninus Winkelmann, Wausau, Wis.

BEAUTIFUL Fox Terriers, Collies, Shepherds. Barnes Farm, Clay Center, Neb.

RUSSIAN Wolfhounds, registered. Kanyon Kennels, W. S. Friedrich, Arbon, Idaho.

GERMAN Police pups. Registered stock. Best bloodlines obtainable. N. S. Mumpower, Bristol, Tenn.

PERSONAL

SPARETIME Employment at home. Details stamp. Gluco, 507 Aetna Bldg., Rochester, N. Y.

FREE: Valuable book telling the uses of roots and herbs. Box 29, Station L, New York.

TOBACCO or Snuff Habit Cured or no pay. \$1.50 if cured. Remedy sent on trial. Superba Co., N3, Baltimore, Md.

SEND 25c coin and your date of birth for forecast of your vibrations for 1937. Aryel Synclaire, Numerologist, Rt. 1, Box 26, Redlands, Calif.

MOST Fascinating Discovery of Modern Science—Key to success and failure. Teaches how to arouse the marvelous four-fifths of you now buried beneath the surface. Shows how to awaken the "Real You" and become the amazing, successful person you should and can be. Write for Free (fascinating) book. Desert Publishing Company, Box M-2, Dept. G, Hollywood, California.

WONDERFUL health book for only 10c (publisher's price \$1.00). Appreciated by every reader, sick or well. Teaches health the natural way, also suggest reliable self treatment of disease. Address, Author, Box 437, Seattle, Wash.

TAKE up Visualism and Cultivate your Memory. 6 simple courses give extraordinary results. 12 courses make you a Genius. 1st Course \$1. 6 Courses \$5. 12 Courses \$9 only. Newhall, Church Institute, Stormo-way, Scotland.

INROWING Nails or any foot ailment corrected. Write, Eaton's Foot Specialties, P20, Bandon, Oregon.

HIGH Blood Pressure inexpensively overcome, without drugs. Send address. Dr. Franklin Stokes, Mohawk, Fla.

FALSE Teeth Repaired. Missing teeth \$2.00 up. Gold teeth \$5.00 each. Broken plates \$2.00. Herlan, 70 West Broad St., Bethlehem, Pa.

DON'T guess. Have your character analyzed. Prof. Albert Peterson, Sentinel Butte, No. Dak.

MISCELLANEOUS

MIRRORS Resilvered at Home. Costs less 5 cents per square foot; you charge 75 cents. Immense profits plating auto-parts, reflectors, tableware, stores, refinishing metalware, etc. Outfits furnished. Details free. Write Sprinkle, Plater, 286, Marion, Ind.

LOCKSMITHS—Something new. Write. Also buy, sell and exchange codes. Free list. Locksmith, 1650 Lawrence, Denver, Colo.

CASH in on your Artistic Ability. Your home, your office, your spare time, your gold mine. Not a correspondence course. Sample and particulars 10c. Straco, 1013 Mulberry, Springfield, Ohio.

A PENCIL portrait of your photo. Send clear photo and \$1.10. A. Seemann, 2104 Liberty Ave., Terre Haute, Ind.

MEXICAN-MADE pistol holsters, cartridge belts, lariats; hand-carved belts and holsters; horse-hair belts, hat bands, fobs; rattlesnake belts, fobs. Tex-Mex Leather Co., 309 Esperson Bldg., Houston, Tex.

WEEDS—Cut them with cutter bar on Shaw Garden Tractor. Also plows, cultivators and runs belt machinery. Low prices. Immediate delivery. Shaw Manufacturing Company, Department C, Galesburg, Kans.

CUTS anybody can make. Simple, cheap process. \$1. Specimens, particulars. 2c stamp. M. Day, Windfall, Ind.

HOMEOPATHIC and Biochemic preparations sent postpaid to all parts of the world. Manual and booklets free. Halsey Bros. Co., 645 St. Clair St., Chicago, Ill. Established 1855.

ARTIFICIAL Eyes. Booklet free. Denver Optic, 559 Quincy, Denver, Colo.

TATTOOING Supplies Direct from Manufacturer. "Waters," 965 Putnam, Detroit.

GENUINE Scout Knife \$1.50. 2 1/2-inch blade, can opener, bottle opener, punch, screw driver. Best knife for mechanics, hunters, fishermen, farmers. Buskett, Joplin, Mo.

AMATEUR Cartoonists: Make money in spare time with new cartoon selling plan. Write Smith's Service, PM1194, Wenatchee, Wash.

NATIONAL Fun Review one year and 12 postcard views, 25c. Sample, 5c. Sadny, 299 Willis Ave., New York.

TATTOOING—Learn how with my outfit. Descriptive circulars sent anywhere. Sergt. Bonzey, 367 South Main, Providence, R. I.

CASH paid for butterflies, insects. See Sinclair Display Advertisement on page 32.

TELL an army of 3,000,000 live readers all about your offer! If you have anything to sell, buy or exchange, or if you have any reasonable proposition, tell our readers all about it—they'll respond quickly. Our booklet "How to Create More Business" contains some very interesting, helpful facts. Write today for your copy—it's free. M. L. Rund, Manager Classified Advertising, Popular Mechanics Magazine, 200 E. Ontario St., Chicago, Ill.

Slingerland MAYBELL BANJOS

**\$10⁰⁰
Given**



*I'm sitting on top of the world
with my De Luxe May Bell.
Dorothy Kelly*

THEY have that pleasing penetrating tone that musicians have been asking for. Quality Banjos at the right price.

**We will give
a ten dollar
trade coupon**

To apply as part payment on any Tenor Banjo to anyone finding a town or city that does not have a dealer selling Slingerland Maybell Banjos.


Write for free illustrated catalogue

Slingerland Banjo Mfg. Co.

World's Largest Makers of Banjos and Banjo Ukuleles

1815 Orchard St. Dept. 12 Chicago, Ill.

*See and try one
at your dealer's
and you will
have no other*



\$280 worth of outdoor equipment will be given for the 31x
Largest Brook Trout caught in 1927 and entered in the

Big Fish Contest

Conducted by America's leading magazine for the Outdoorsman. Complete details in the current issue. Get copy from newsstand or send \$1 for 5 months' trial subscription to Desk C, 41 W. 45th St., New York, N. Y.

FIELD & STREAM

*send \$1
for
5 months
trial*

For 16 years, these contests have been to the angler what the National Field Trials are to the dog lover. Record fish listed in World Almanac. With 82 prizes covering 15 classes of game fish, many prizes will be won this year by fish of no great size. Free and open to all. Winners select their own prizes.

Field & Stream has over 50,000 feet of the finest motion pictures of hunting and fishing ever made, obtainable on terms amounting to FREE LOAN. The best entertainment for banquets, smokers or other meetings of clubs and associations of every kind, or private entertainments. Write for full particulars.



Learn SIGN AND SHOW-CARD Lettering

Fascinating work. Pays \$50 to \$200 weekly. Vassar gets \$25 for a sign-card. Some posters bring \$300. Many earn while learning. Study in spare time. Learn quickly. For facts and guarantee write: DETROIT SCHOOL OF LETTERING, 173 Holmes, Detroit, Michigan.

HERE AT LAST—

A Home Study Course in Sign Painting—Decorating—Show Card Writing—Graining and Machining—taught by MOVING PICTURES. We give you a Moving Picture Machine for using your own Home with our course. Write for full particulars.

LEARN the Movie Way



National Painters and Decorators Ass'n School
Dept. 3 435 N. Clark St., Chicago, Illinois

How to Straighten Bow and Knock-kneed Legs!

Improve your personal appearance by using the new patent "Lim-Straitner," Model 18. Corrects bow Bow and Knock-kneed legs safely, quickly and permanently at home. No costly operation or discomfort. Is worn at night. Easy to adjust. Its result will save you soon from further humiliation and will improve your personal appearance 100 per cent. Write today for copyrighted Physiological and Anatomical book and experience of others without obligation. Enclose a dime for postage.

M. TRILETY, Specialist

Dept. 1524L
BINGHAMTON, N. Y.

Michigan State Automobile School

Operating Under Jones-Schweitzer Plan



The biggest auto school catalog—19" high—get your copy—send the coupon

The dollars spent for autorepairs are mounting by millions every year—Car owners have to pay out all the time,—it's \$15 here, \$100 there, 22 million cars running now,—and every one of them has to be repaired regularly. You can get in now on this big and bigger growing business. Make big money. A few weeks' Detroit training at this world's famous auto school will start you to success. This great school, endorsed by auto factories, has put thousands of men on easy street. Send the coupon above for particulars.—big illustrated 16th Anniversary Catalog.

Highest Grade
Auto
Work

Auto Repair MEN Are Sitting on Top of the World To-day

Mail Me!

Michigan State Automobile School
306 Auto Building, Detroit, Mich.
Send me free and without obligation full information about Detroit training to make the most money. Also send me FREE your big new illustrated Catalog and Automobile Training Book.

Name.....
Street Number or R. F. D.....
City..... State.....
I am interested in
12 weeks' Auto Course
20 weeks' Master Course
Home Study Course

Get this BOOK Free

We have more calls for trained men than we can fill. We can train you quick to make big money. Learn a trade that is good the year round. Become a trained auto repairman, welder or machinist. Auto repairing has jumped to a tremendous world-wide business. Be trained to get part of this fortune. Wonderful opportunities for jobs or to open a shop of your own.



YOU CAN GET THERE QUICK

It pays to get your hands dirty. Auto repairmen have steady work. Garage owners want men who know how to do jobs right. They're willing to pay well to get them. Car owners are getting more particular all the time,—won't trust their cars to any but trained men. Here in Detroit the auto center you learn right, at the old reliable "Michigan State." Here you have new cars to study on,—actual equipment supplied to us by auto makers. Expert instructors teach you every detail. You learn with tools. You get head training too. The knowledge we put in your head guides the skill we put in your hands.

Aviation—Another Coming World Business

As a money-making business, aviation will soon rival the auto industry. Skilled men are needed in this new industry even now. Look to the future, lay your plans now to be one of the leaders,—the time is ripe.

Business Course Included

So you can run your own shop, we teach you thoroughly business methods, stock-keeping, systems, banking. A leading business man of Detroit teaches this course. No extra cost. This is just another one of the big advantages of learning at "Michigan State."

Home Study Course

If you cannot come to Detroit now, start by learning at home. Our home study course is taught by the same instructors who teach our resident course. This will enable you to get a job or will be the foundation for your practical course if you can come here later.

Send for the Big Book

The big auto school catalog,—19" x 12". The day you get it will be your luckiest day.

MICHIGAN STATE AUTOMOBILE SCHOOL

A. G. ZELLER, President and General Manager

The Old Reliable School—Established 17 years

306 Auto Bldg., DETROIT, MICH.

IMPROVE YOURSELF!

Authentic Texts, Self-Teaching, Self-Explanatory—Educative, Instructive, Cultural—Little Blue Books, Pocket Size, 15,000 words per Volume—Your choice 5¢ each.

5¢

ORDER BY NUMBER

EACH

- | | |
|--|-----------------------------------|
| 1251 Question and Answer Games | 740 Camping Manual |
| 112 Secret of Self-Development | 750 Hints for Hikers |
| 7 A Liberal Education | 1096 How to Dress on Small Salary |
| 897 How to Enjoy Reading | 1092 Beauty Hints |
| 868 Self-Improvement | 1005 Enjoying the Orchestra |
| 821 How to Improve Your Vocabulary | 984 Harmony Self-Taught |
| 697 Words often Mispronounced | 414 Art of Happiness |
| 696 How to Pronounce Proper Names | 651 Psycho Analyzing Yourself |
| 1003 How to Think | 217 Puzzle of Personality |
| 367 How to Improve Your Conversation | 1052 Instincts & Emotions |
| 435 100 Best Books | 417 Nature of Dreams |
| 1097 Memory Improvement | 1069 Conquest of Fear |
| 1049 How to Sing | 761 Food and Diet |
| 995 How to Play the Piano | 1126 Eating for Health |
| 859 How to Enjoy Music | 98 How to Love |
| 556 Hints on Etiquette | 997 Home Cooking |
| 82 Common Faults in Writing English | 877 French Cooking |
| 855 How to Write Letters | 1180 Cooking Fish & Meats |
| 734 Useful Phrases | 685 Interior Decoration |
| 639 Most Essential Words | 1032 Home Gardening |
| 364 How to Argue | 1070 Fighting Nervous Troubles |
| 681 Spelling Self-Taught | 1009 Typewriting Manual |
| 682 Grammar Self-Taught | 688 Mouth Hygiene |
| 683 Punctuation Guide | 811 Genetics (Heredity) |
| 822 Rhetoric Self-Taught | 139 Eugenics Explained |
| 823 Composition Manual | 709 Sociology Facts |
| 902 Foreign Words | 405 Economics Outlined |
| 856-857 Arithmetic Self-Taught (2 vols.) | 467 Evolution Explained |
| 1004 How to Save Money | 419 Nature of Life |
| 1074 Commercial Law | 815 Familiar Quotations |
| 998 How to Make Money in Wall Street | 1065 Lives of Presidents |
| 1189 How to Make Money at Home | 847 Card Games |
| 629 Local Forms | 1103 Puzzle Book |
| 835 Useful Tables | 78 Public Speaking |
| 986 How to Talk & Debate | 192 Book of Synonyms |
| 75 Choice of Books | 1185 All About Weather |
| 679 All About Chemistry | 1231 Best 1926 Jokes |
| 994 All About Physics | 1089 Sex Common Sense |
| 895 Astronomy Manual | 773 Good Habits |
| 725 All About Zoology | 86 How to Read |
| 703 All About Physiology | 1109 Spanish Self-Taught |
| 491 Beginners' Psychology | 1208 Success Easier Than Failure |
| 710 All About Botany | 830 Crossword Puzzles |
| 1139 Photography Manual | 499 Classical Dictionary |
| 1064 Radio Manual | 905 Biblical Allusions |
| 1230 Radio Stations | 1174 Business Letters |
| 1023 Popular Recitations | 893 500 Riddles |
| 1031 Owning Your Home | 74 Sex Life |
| 853 Guide to Songbirds | 167 Health Rules |
| | 342 News Reporting |
| | 708 Romance of Words |
| | 58 American Slang |
| | 1186 Rules of Golf |
| | 466 Sculpture Guide |
| | 468 Architecture Guide |

GREAT BARGAIN! Your choice, any book in above list, 5¢ per copy, plus 1¢ per book for carriage charges (otherwise your order will be shipped express collect). Canadian and foreign price 7¢ per book.

Haldeman-Julius Publications Dept. 5-61
GIRARD, KAN.

TELEGRAPH-RADIO

\$18 to \$35 a week while training for Radio and Telegraph Operator jobs at \$150 to \$300 per month. Write for particulars.

CHICAGO TELEGRAPH INSTITUTE
Dept. 1-6-7 1338 S. Michigan Avenue, CHICAGO

\$75 to \$350 Weekly
in Aviation jobs. Learn under actual flying conditions in 30 lessons. Send for **FREE BOOKLET** about Aviation and the opportunities in it for you.

CHICAGO AERONAUTICAL SERVICE, INC.
Dept. B 608 S. Dearborn St. Chicago, Ill.



DO YOU LIKE TO DRAW?

It's Easy To Learn When Shown In The Right Way

Some of the cleverest cartoonists and comic artists in America today learned how to draw quickly—by following **CARTOONIST EVANS' SIMPLE AND EASY METHOD**. This school is recommended by foremost cartoonists because they know the students are handled right. If you like to draw, send 6¢ in stamps for **portfolio of cartoons and full details**. The course is **NOT EXPENSIVE**.

The W. L. Evans School of Cartooning 521 Leader Building
CLEVELAND, OHIO



\$1900 to \$2700 a year



Long vacations with pay. Work easy. Travel on fast trains with all expenses paid, including hotel. No worries about the future.

MY FREE BOOK TELLS HOW

Get my big free book about the Civil Service which tells all about the Railway Postal Service, and other positions, and how I can help you. Write today.

PATTERSON SCHOOL

Arthur R. Patterson, Civil Service Expert
86 Wiser Bldg. Rochester, N. Y.

Be a REAL ESTATE Specialist

Learn my amazingly successful system—right at home—in your spare time. Let me train you for real success. Let me put you in touch with big business. Let me do for you what I have done for other wide-awake men and women. D. H. Garrett says: "Made \$630 in one week before I was half through your training." Mrs. A. Moore says: "Have a new car, a dandy office and money in the bank, all through my own efforts and without any capital to start with." M. I. Stokes says: "Made \$900 in three months in my spare time." Send your name and address at once for my new, free book, "How to Become a Real Estate Specialist," giving full facts about my remarkable Home-Study Course, my Free Business Service and positive proof of big success. Address, **DIRECTOR**, Dept. 44 F. F., American Business Builders, Inc., 18 East 18 Street, New York, N. Y.

SKIN-TROUBLES

ANDRE'S ACNE CREAM is Excellent for all Skin Troubles

no matter how severe or chronic. Pimples, Blackheads, Eruptions on face or body. Eczema, Barbers' Itch, Scabies, Crusts, Pustules, Enlarged Pores, Oily, Shiny or Itching Skin. Lightens Freckles, softens and whitens the skin. Immediate Results. Write for full particulars.

Andre & Co., 4029 Cottage Grove Av. Suite 451, Chicago, Ill.

Save Your Feet

When all else fails, end your suffering with the

Heefner Arch Support

No Metal




Fully patented. It re-adjusts the entire foot. Write for free book and statements from doctors and users.

Heefner Arch Support Co. 652 N. E. Taylor Bldg. Louisville, Ky.

Learn To Hypnotize!

Complete course of Hypnotism, Mind-Reading and Magnetic Healing, 25 fascinating lessons. How to become an expert, hypnotize at a glance, make others obey your wishes, overcome bad habits and enemies, gain in power, wealth, love. Simple, easy system. Equals \$20 course; now only \$1. Send stamps, cash or M. O. No more to pay. **EDUCATOR PRESS, 19 Park Row, New York, Dept. 71**



Air Commerce Needs Men!

Don't envy the Highly Paid Air Man—Be One! Air Men are in demand. Beat the other fellow to the High Salaried Jobs in Aviation. **Western** training will qualify you to enter Aviation. Learn how through our catalog, sent on request.

Write for Free Catalog
"Airplanes and Flying"

Aeronautical Training Division

WESTERN AIRPLANE CORPORATION

Dept. M-6 Monadnock Block Chicago, Ill.

ENCYCLOPEDIA BRITANNICA

in the New Form—at a saving of 40%

Write for full details. Address Dept. PM5

THE ENCYCLOPEDIA BRITANNICA, INC.

342 Madison Ave., New York City

DRAW CARTOONS

Turn Your Talent Into Money

Cartoonists earn from \$70 to \$300 per week—some even more. Remarkable new Circle System of Drawing teaches you in half the usual time. Send for **booklet** and sample **lesson plate** explaining full details of the Course.

THE NATIONAL SCHOOL OF CARTOONING
 623 Penton Building Cleveland, Ohio



FOUND A New Fountain of YOUTH!

Now a way has been found to rejuvenate every cell in the body! One of America's leading doctors and surgeons—one of the pioneers in discovering the fact that the 12 endocrine glands control vitality, vigor, youth—recently discovered a means of *feeding the glands* that is producing amazing results with both men and women. If you feel run down, tired, worn-out—lack the energy and vigor that compels accomplishment—the vital impulse that makes the womanly woman and the manly man—you will be astonished with the results even a few days' use of this new gland food produces.

FREE TRIAL OFFER

This new discovery revitalizes the glands, rebuilds blood, brain, nerves—all tissues of the body. Ailments caused by an impaired function are quickly corrected. The rapidity with which it works is incredible to one who has not tried it. This discovery is being adopted by medical practitioners generally—because it does what no drug known to medical science will do—and does it quickly. If you would be fully *alive*—if you want to enjoy life to the fullmost—write today for complete evidence and full particulars of the **FREE TRIAL** offer we are making for a limited time. Mail the coupon below—**NOW!**

Please print name plainly

FREE TRIAL COUPON


HORMOCINE LABORATORIES, Dept. 2
 180 North Michigan Ave., CHICAGO, ILL.

Send me by return mail, in plain envelope, full particulars of your Endocrine Discovery and Free Trial Offer.

Name.....

Street No.....

City..... State.....



Thousands Enjoy Popularity!!

Popularity can be yours. We start you by presenting this handsome, full size professional tenor banjo. We want to present one of these wonderful, delightful instruments to each of 1,000 readers of this magazine. We want every music-lover to attain success and this offer is made to pave the way. No previous musical knowledge is necessary. Under personal supervision you will be given, by mail, the benefit of Prof. Harry Six's 22 years as Director of Glee and Instrumental Clubs of N. Y. University. Our method is different because so easy and simple.

Learn in 30 Minutes With My Picture Method

We furnish pictures and, as an additional guide, phonograph records of the professor playing the pieces you are learning along with our thorough, printed and illustrated, easy-to-learn course. It is easy. If you could sit at our desk and see letters from students, you would be convinced that we have perfected this simple course to insure your mastering tenor banjo.



Don't Send a Single Cent

Investigate today. Don't put off until tomorrow, because you might forget. It might be the turning point in your career. Don't send a single cent. Just drop a line—use coupon, or postal card will do—telling you are interested in receiving full particulars about course, and to reserve one regular eighteen dollar, full size professional tenor banjo for you, which is given you when you enroll. **Act Now!**

EARN BIG MONEY

HUNDREDS
HAVE STARTED
ORCHESTRAS
AND ARE
MAKING
BIG
MONEY

FREE BOOKLET COUPON

New York Academy of Music
 Studio 106, 100 Fifth Avenue, New York

Please rush all free information relative to your Tenor Banjo Course, sample lesson, and reserve a gift tenor banjo for me. This obligates me in no way whatever.

Name.....

Address.....

City..... State.....



My Rupture Fear Vanished in 2 Seconds



In a flash I knew that at last science had given to rupture victims real, quick, positive relief. I knew that through the discovery of a well-known American Scientist my rupture suffering was over.

Tiny Magic Dot a Rupture Wonder

A N extraordinary little device, weighing less than 1-25 of an ounce, now makes heavy, cumbersome, old-fashioned devices, cruel springs, heavy straps and pads unnecessary. This new invention is called "Magic Dot," and by its use it is now possible to walk, run, jump, exercise, bend, etc., with perfect security—without cruel pressure or barbarously tight strapping. At last, here is a way to prevent coming down of rupture, and tiny Magic Dot is only a part of the wonderful New Science System.

Breathes Air

A wonderful new pad, light in weight, soft and pliable actually breathes air. Smaller, much smaller, than you ever thought possible. It fits the contour of the body as no old-fashioned pad could do. It is washable, sanitary.

FREE Sample

The pad is made of an amazing new material called Airtex and a sample will be mailed absolutely free to those who ask for it.

These two items are only a part of this new system for supporting and healing rupture that is said by doctors and rupture victims alike to be a thousand years ahead of all other methods.

"See It First"

We could never tell you all of the remarkable features of this modern, scientific rupture relief, but without risk on your part you can see it in your own home. Send no money. You can easily get full particulars and free illustrated material. Merely clip coupon, write your name and address plainly and mail it to

NEW SCIENCE INSTITUTE

2137 Clay Street Steubenville, Ohio, U. S. A.

NEW SCIENCE INSTITUTE

2137 Clay St., Steubenville, Ohio

Please send me at once full details of the New Science System and your "See It First" offer. I am not obligated.

Name.....

Address.....

City.....State.....

No Joke to be Bald



Grow
New
Hair
Quick

Let Me PROVE It To You FREE

What I accomplished on my own head, pictured above, I believe I can do for you, provided you are under 45 years of age and loss of hair was not caused by burns or scars. Anyhow, I must succeed or you pay nothing. No apparatus—my home treatment is simple, quick and inexpensive.

Send No Money Just your name and address and I will mail you full information with PHOTOGRAPHS, NAMES and addresses of men and women who have successfully used my treatment for dandruff, falling hair and particularly for baldness. Write Now. A postal will do.

VREELAND'S, A-135 Euclid-Windsor Bldg., CLEVELAND, OHIO



Deafness

Perfect hearing is now being restored in all cases of deafness caused by Catarrhal troubles, Relaxed or Sunken Drums, Thickened Drums, Roaring or Hissing Sounds, Perforated, Wholly or Partially Destroyed Drums, Discharge from the Ears, etc.

Wilson Common-Sense Ear Drums

require no medicine but effectively replace what is lacking or defective in the natural ear drums. They are simple devices, which the wearer easily fits into the ears where they are invisible.

Free Book on Deafness

Soft, safe and comfortable. Write today for 168-page book on deafness giving full particulars and many testimonials. The hearing of thousands of grateful users has been restored by these "little wireless phones for the ears."

WILSON EAR DRUM CO., Incorporated
619 Todd Building LOUISVILLE, KY.



Beautify your NOSE

to shapely
proportions—
while you sleep!



Gold Medal
Won 1928

ANITA NOSE ADJUSTER

is SAFE, painless, comfortable. Speedy, permanent results guaranteed. Doctors praise it. No metal to harm you. Small cost.

Write for FREE BOOKLET

ANITA CO., Dept. F-12 ANITA Bldg., NEWARK, N. J.



BEFORE-AFTER

STOP USING A TRUSS



Reduced
Fac-Simile
Gold Medal

STUART'S PLAPAO-PADS are different from the truss, being mechanico-chemico applicators made self-adhesive purposely to hold the distended muscles securely in place. No straps, buckles or spring attached—cannot slip, so cannot chafe or press against the pubic bone. Thousands have successfully treated themselves at home without hindrance from work—most obstinate cases conquered. Soft as velvet—easy to apply—

inexpensive. Awarded Gold Medal and Grand Prix. Process of recovery is natural, so afterwards no further use for trusses. We prove it by sending Trial of Plapao absolutely

Write name on Coupon and send TODAY. **FREE**

PLAPAO CO., 733 Stuart Bldg., St. Louis, Mo.

Name.....

Address.....

Return mail will bring Free Trial Plapao.



Tobacco Is Hurting You

Look at the facts square in the face, Mr. Tobacco User. You may think tobacco is not hurting you.

That is because you haven't as yet, perhaps, felt the effects of the nicotine poison in YOUR system. For you know that nicotine, as absorbed into the system through smoking and chewing tobacco, is a slow working poison. Slow, yes—but sure.

Tobacco is lowering your efficiency. It slows a man down. Makes it harder for you to concentrate your mind on your work. You haven't near the amount of "pep" and energy you would have if you stopped using it. There's many a man twice as old as you in years who's twice as young in energy, simply because he lets tobacco alone.

Some day you will realize to what an alarming extent tobacco has undermined your system.

When your hands begin to tremble—
and your appetite begins to fail—
and your heart seems to "skip a beat" now and then—
and slight exertion makes you short of breath—
then you have a right to suspect that
TOBACCO is getting the upper hand.

Any well-informed doctor will tell you that these are only a few of many symptoms of tobacco poisoning.

And YOU know that the use of tobacco in any form is an expensive, utterly useless habit. You know you ought to quit.

Tobacco Habit Banished Let Us Help You

It doesn't make a particle of difference whether you've been a user of tobacco for a single month or 50 years, or how much you use, or in what form you use it—whether you smoke cigars, cigarettes, pipe, chew plug or fine cut or use snuff—**Tobacco Redeemer** will positively remove all craving for tobacco in any form in a very few days. Not the slightest shock to the nervous system. Your tobacco craving will usually begin to decrease after the very first dose—there's no long waiting for results.

Tobacco Redeemer contains no habit-forming drugs of any kind and is marvelously quick, scientific and thoroughly reliable.

It is in no sense a substitute for tobacco. After finishing the treatment you have absolutely no desire to use tobacco again or to continue the use of the remedy. It helps to quiet the nerves and make you feel better in every way.

Results Guaranteed A single trial will convince you. Our legal-binding, money-back guarantee goes with each full treatment. We will refund every cent you pay for the treatment if after taking it according to the easy-to-follow directions, it should fail to banish the tobacco habit completely.

SEND Coupon for Free Proof Let us send you our free booklet on the deadly effects of tobacco, together with testimonial letters from men all over the country telling how they have been absolutely freed from the tobacco habit by this simple home treatment. You could not ask for stronger proof that **Tobacco Redeemer** will free you from the habit than the evidence we will gladly send on request. Just mail the coupon—or a postal will do.

NEWELL PHARMACAL CO.

Dept. 300 Clayton Station St. Louis, Mo.



Free Book Coupon

NEWELL PHARMACAL CO.

Dept. 300 Clayton Station St. Louis, Mo.


Please send, without obligating me in any way, your free booklet regarding the tobacco habit and proof that **Tobacco Redeemer** will positively free me from the tobacco habit or my money will be refunded.

Name

Street and No.

Town State

Learn Electricity IN LOS ANGELES



FREE Employment Service!


There are more calls for "National-Trained-Electrical-Men" than we can supply. Jobs are open now paying \$50 to \$200 a week—but you must first get the right training. Get it at National—a world-famous institution with a quarter century record of success in training big pay men.

All These Advantages:

1. Unlimited Training Until Competent.
2. Free Employment and Welfare Service.
3. Million Dollar Training Shops.
4. Personal, individual training guaranteed.
5. You actually perform work that employers pay big money for.
6. Official Diploma and certified record of work performed.

FREE

Read how National insures your success. Send for this free Electrical catalog—illustrated by actual photos of students training under instructors on a half million dollars' worth of new electrical equipment. Mail coupon now.



National Electrical School

Dept. 507, 4006 Figueroa St.,
Los Angeles, California.

Send me your big free illustrated catalog of Electrical Opportunities.

Name

Address

City State

For Vacation Time Reading

Let us send you a list of books that
are 100% entertaining

Beau Geste—Old Ironsides—The Nervous Wreck—
One Minute to Play—Stories by Zane Grey, James
Curwood, Peter Kyne, Sabatini, Burroughs, Edna
Ferber, Gene Stratton Porter, Mary Roberts Rinehart
and many others.

We have inaugurated a convenient book ordering service for our readers. Simply drop us a line requesting that we send you a list of the latest and best books. You will receive by return mail and from time to time thereafter, attractive lists and announcements of the newest and most worth while books, the majority of which will be in the popular 75 cent editions.

You will be placed under no obligation whatsoever. The service is to enable you to select from the works of your favorite authors and to keep you informed about the really big things that come out practically as soon as the publisher's announcements are made.

Books ordered will be delivered to your door at no advance over the publishers' prices except that you will be asked to pay the postage.

Send us your name and address today—now—to receive the benefit of this new service. Address:

POPULAR MECHANICS PRESS
200 East Ontario Street, CHICAGO

What Do You Do When You Cannot Find the Book You Want?

Don't give up in despair. Send for a copy of the unique catalog published by Popular Mechanics Press. It contains 5000 books listed alphabetically under 2000 main subjects and sub-headings—literally from A to Z—Abrasives Manufacture to Zoologist and everything in between.

FREE UPON REQUEST

Send for your copy today

POPULAR MECHANICS PRESS
200 E. Ontario Street, CHICAGO

Practical Plans for Tourists

133 practical plans for making automobile touring easier, less expensive and more enjoyable. These include:

Camp Equipment; Stoves and Campfires; Complete Homes on Wheels; Beds for Car and Camp; Luggage Carriers; Tables for Car and Camp; Pantry Boxes; Making Tents; Improving Tents; Portable Radio Receivers; Repairing Tires; Handling Tire Chains and Getting Out of Mud; Carrying Food; Making Camp Without Tents; Camp Cooking; Making Chairs and Stools; Car Repairs; Roads and Landmarks; Miscellaneous.

With the Auto Tourists' Handbook we supply a Touring Atlas of the U. S., showing Road maps of every state, road distances, logs of national trails and other authentic touring information.

Just write us to send you these books and when postman hands you the package pay him 68 cents plus the postage. If outside U. S. remit with order and include 15 cents extra for postage.

POPULAR MECHANICS PRESS
Room 606 200 E. Ontario St. CHICAGO

Time, Labor and Money Saving Ideas for Auto Repairmen



334 Valuable Discoveries made by Hundreds of Auto Mechanics are contained in our Automobile Repairman's Handbook. 337 Illustrations.....Price 50c

301 Ways to use drills, drill presses, taps and dies with more effectiveness are given in our Drilling and Thread Cutting Handbook. 298 Illustrations.....Price 50c

259 Kinks furnished by 106 of the most successful Lathe Operators are found in our Lathe Handbook. 212 Illustrations.....Price 50c

These three books (regular \$1.50 value) are offered for a limited time only for 98 cents plus the postage. Pay postman when he delivers the package. If outside U. S. send remittance and include 15 cents extra for postage.



POPULAR MECHANICS PRESS
Room 604
200 E. Ontario St. CHICAGO

Wait Just a Moment, Mr.!

Before You Light That Cigarette, Cigar or Pipe—Or Take a Chew of Tobacco—

REMEMBER THIS:

That no man can escape the bad effects of tobacco. Its active principal—nicotine—is a *deadly* poison which, in time, is simply bound to injure your health—perhaps seriously.

Most tobacco users realize this. But when they try to quit unaided they find it next to impossible because of the almost unbreakable hold the habit has on them.

Thousands of inveterate tobacco users have found it easy to quit with the aid of the



Keeley Home Treatment For the Tobacco Habit

A sane, scientific Treatment based on the prescription of Dr. Keeley, who founded the famous Keeley Institute for liquor, drug and tobacco addicts more than 50 years ago. Quickly and completely banishes all craving for tobacco in any form. Contains no habit-forming drugs. No bad after-effects. Not a tobacco substitute. A wonderful tonic. Improves appetite and digestion.

Money-Back Guarantee It, after taking this Treatment according to directions you can honestly say you have not been benefited, we will refund your money.

MAIL COUPON for FREE BOOK which gives plain facts about the injurious effects of tobacco and tells how easy it is to quit with the aid of this remarkable treatment.

THE KEELEY INSTITUTE

Dept. P. M.-6 DWIGHT, ILL.

The Keeley Institute, Dept. P.M.-6, Dwight, Ill.

Send without obligation your free booklet telling how to rid myself of the tobacco habit.

Name

Address



DRAFTING ENGINEERING, ELECTRICITY and ARCHITECTURE

CHICAGO TECHNICAL COLLEGE

One of "America's oldest and largest schools of specialized engineering" offers you a maximum of practical training in a minimum of time, here at Chicago, the country's building and engineering center. Technical training of college standard for men who have neither the time, money nor preliminary education to attend a university. Each year more than 1000 men and women enroll in day and evening classes.

Short, Intensive Training

practical in every respect, puts you quickly into a high salaried position. Many of our students are assisted to responsible positions before graduation . . . they earn while they learn.

In Spare Time At Home

If you can't come to Chicago, learn Drafting at home. Your spare time is enough. Some practical course. Quick, easy—yet thorough.

Trial Lesson FREE

Test yourself and see how easy you can learn Drafting by the Chicago Tech. method. Trial lesson sent free if interested in home study. Address Dept. G-200.

COURSES are arranged to suit your needs—2 year diploma; 3 year B. S. degree; special 3 and 4 months' short courses adapted to the individual. Expert instructors actively at work in the very professions they teach.

Tuition low, terms easy. Enter any time. Day and Evening Classes.

Write for FREE 84 Page Blue Book

It tells about all the courses . . . fully describes them; about the great demand for Chicago Technical College trained men; about college athletics and other interesting facts you'll want to know. Gives you a vivid picture of what you may expect at this leading technical college. There is no obligation. Send for this free Blue Book today . . . now!

Address Registrar G-75

Chicago TECHNICAL College
Dept. G-75 118 East 26th St., Chicago

Will You accept this \$7 Pen as a Gift?

For a limited time and to get QUICK ACTION we offer this genuine \$7 over-size GREEN JADE fountain pen without cost. Because we want you to BORROW these pay-raising Auto books NOW—not "tomorrow"—because we want you to know how they help men climb to better jobs—quick!

Auto Engineering LIBRARY LOANED FREE!

Even the one chapter on IGNITION may double your pay. And in the FIVE volumes, 2450 pages, over 3000 wiring diagrams, charts and illustrations there are ALL the facts about every branch of auto work you'll ever need—right at your finger tips. Of priceless benefit to mechanics, garage men, foremen, auto owners. Get in on this great opportunity NOW. Send no money, just mail the coupon.

American Technical Society
Dept. A-119, Chicago, Ill.

Send No Money No C. O. D. American Technical Society, Dept. A-119, Chicago

I want to borrow FREE for 15 days use, a brand-new set of "AUTO ENGINEERING," the latest 5 volume edition. I will pay the few cents express charges when books are delivered, but not one penny for the use of the library itself. To return for this, I agree to look them over very carefully and determine for myself if I wish to keep them. If I do, I will pay you \$2.00 after 15 days and you will then send me the \$7 Fountain Pen absolutely without extra cost. The balance of your special advertising price \$24.80 I will pay at the rate of \$3.00 per month. If not wanted, I will return express collect, and owe you nothing.



3 Free Features

1. Home-Study guidance FREE.
2. Membership in Society and a year's consultation FREE.
3. FREE Employment Service.

Name

Address

Attach letter stating references and employer's name and address, or write same plainly in margin.

Get Strong QUICKLY and Stay So!

DEVELOP your muscles this quick way. Get big broad shoulders. Fill out your chest. Become the strongest man in your town by using the famous GIBLARTAR EXERCISER—the strongest tensioned apparatus made! Many famous athletes and strong men use it.

Can be adjusted to from 10 lbs. to 200 lbs. resistance. Every man, woman and child should have one. Made of finest quality, genuine para rubber elastic cables. (Guaranteed 50 rubber strands)

to each cable. Do not compare this apparatus with cheap imitations.

We have made arrangements with a prominent author and publisher, who is an authority on physical culture, to present you with 16 complete booklets on every subject pertaining to your muscles and organs.

It is only by special arrangement and additional expense to us that we are able to offer you this wonderful premium ABSOLUTELY FREE OF CHARGE with each exerciser.

ONLY \$3 For 5 Cables
10 Cables, Double Strength ONLY \$5

SEND NO MONEY

All 16 booklets will be shipped free to your home with the exerciser, and you simply pay the postman the price of the exerciser, plus a few cents postage. When ordering, mention that you want a five cabled or ten cabled exerciser. If you live outside the U. S. send cash with order.



FREE INSTRUCTION

Remember!

The name Gibraltar on an Exerciser means as much as Sterling on silver.

GIBLARTAR EXERCISER COMPANY
Dept. 306, 225 W. 34th St., New York City
Please send me your [10 cable] EXERCISER.
[5 cable]

It is understood that I am to get the 16 booklets on the body absolutely free with this order.

NAME
ADDRESS
CITY STATE

Tires Won't Puncture

No Wonder Agents Make Such Big Money

Now—no matter how many nails you drive into a tire, it won't puncture—can't leak a bit of air! Magic new discovery seals all punctures while driving—slow leaks and valve leaks, too! Simply astonishing!

Every motorist is vitally interested on sight. Agents are simply coining money showing AIR-STOP to friends and motorists! A. Otis made \$167 in 2 days. J. H. Rosen made \$22.95 in 1½ hours. Right now we offer to send you no-cost SAMPLES at our risk and generous proposition. Test them FREE. Drop a postal for details. Do it now!

AIR-STOP MFG. CO.
6-526 Hewitt Bldg. Des Moines, Iowa

GET OUT OF YOUR RUT

Make your dreams come true!

Increase your income. Better your position. Restore the joy of living and doing. Tear yourself free from the fetters of the past.

Strike for a new and brighter future! Membership with us shows you how. Full information on request. No obligation. It's free. Just write your name and address on a postal and send to us. NOW!

Self Improvement League of America
Suite 701, 75 Westland Avenue, Boston, Mass.



Be a drummer!

Trap Drumming made easy in a short time. Our free instruction course furnished with genuine Ludwig Trap-Drum Outfit. Develop your natural sense of rhythm. Go to your nearest dealer or write for full details.

LUDWIG & LUDWIG, 1611 North Lincoln Street, Chicago

Earn \$75 Weekly Building Radio Sets

Join the Association! We train you to build and repair radio sets—start you in business—enable you to earn \$3 an hour upwards. Free 5-Tube Radio Set to Members. Write for special limited-time plan whereby your membership need not cost you a cent. Write today!

RADIO ASSOCIATION OF AMERICA

Dept. PM-6 4513 Ravenswood Ave., Chicago, Ill.

BOYS

You can earn money and win prizes in your spare time.

Write Me Today

Jim Thayer, Dept. 26, Crowell Publishing Co. Springfield, Ohio

Tell AGE and FORTUNE of YOUR FRIENDS!



No one can deceive COMET MAGIC CARDS. Tell anybody's exact age, date of birth, lucky days, also of bank account. Answers many questions. Roaring fun for everybody. Very useful. Get yours at once. FREE—If You Send Now 32 page "Planetary Calculator." Analyzes person's character by year, month, and day born. Tells how to be popular, successful in love and business. Accurate. Send dollar bill for COMET MAGIC CARDS, and get "Planetary Calculator" FREE. Money back if not satisfied. Agents Wanted. International Printers, 2110 S. Halsted St., Chicago

FORD**40 Miles on a Gallon**

"We have tried them out. Ford got 40 miles on a gallon."—F. S. Carroll.

STUDEBAKER**Saves 50%**

F. A. Cole writes he put one on a Studebaker Special Six. Reports a saving of 50% in gasoline.

BUICK**36 Miles On 1 1/4 Gallons**

"Yesterday I made a trip of 36 miles and used only 1 1/4 gallons."—L. L. Robinson.

CHEVROLET**43 Miles On a Gallon**

"We have tried them out. Chevrolet got 43 miles."—F. S. Carroll. Rex Dean, another Chevrolet owner, reports he got 25 miles a gallon. Took the device off and mileage dropped to 19. Put it back and mileage moved up to 25.

OLDSMOBILE**Almost Double**

J. R. Wood writes he increased mileage on his Oldsmobile from 17 miles a gallon to 30 miles a gallon by actual count on 3,000 miles.

INTERNATIONAL TRUCK**Saves 41%**

"I find it better than you recommend it. On the International Truck we use, we are saving by positive test 41% in gas and our engine uses less oil."—George Bell.

Sworn Affidavit

I, L. G. Stransky, Vice President J. A. Stransky Mfg. Company, being first duly sworn depose and say that the J. A. Stransky Mfg. Company have in their files thousands of unsolicited testimonials from satisfied users all over the world.

Signed, L. G. Stransky,
Vice President.

Subscribed and sworn to before me this 29th day of November, 1928.

(Signed) Ernest Henegar,
Notary Public.



With This Amazing Device I Drove 1300 Miles Without Buying Gasoline

No wonder over two million car owners have installed the Stransky Vaporizer. Here's a remarkable instance of gas-saving (one of many) reported by J. R. Wood of St. Louis. Before installing it, he got only 17 miles on a gallon. On a 3,000 mile test after installing it, he got 30 miles on a gallon. Thus he saved 77 gallons of gas which, at 17 miles a gallon gave him 1300 miles without buying gasoline! Read the inventor's daring no-risk offer to you.

\$75 to \$200 In a Week

SELDOM if ever has such a money-making opportunity been offered distributors—experienced or otherwise—full time or spare time. Think how fast the money rolls in when Foster could make \$137.50 in a week—Fuller, \$104.50 in five days—Cronk \$51 in an hour!

If your present job doesn't pay you \$75 to \$200 in a week, think fast! Full page newspaper ads are being used all over America. Over a million car owners have installed it already—on all makes of cars, trucks and tractors—even on an aeroplane. Thousands of car owners have ordered direct from the factory because they couldn't find a distributor. Jump in quick and get your share of the cream!

How It Works

The Stransky Vaporizer was invented by J. A. Stransky, former candidate for Governor of South Dakota. It is based on a newly-discovered scientific engineering principle that has stood

thousands of tests by car owners, dealers, garage mechanics and other authorities. It has no delicate parts to get out of order. There is nothing complicated about it. You can attach it to your engine in about three minutes and it needs no further attention.

Official tests show that most car owners waste 20 to 30% of their gas by improper combustion. Thousands of car owners say that this amazing device has saved them as much as 50%: that it picks up power more quickly, ENDS spark plug and carbon troubles, and works in all weathers or roads. And so convinced is the inventor that it will prove its story that he makes the following no-risk offer.

Mail Coupon Below

Over one million car owners have installed the Stransky Vaporizer at the inventor's risk. This coupon will bring you full details of our plan to let you test this device on your car in the same way. You will also learn a definite plan that has helped others earn \$75 to \$200 in a week, full or spare time. Your request will not obligate you. Rush the coupon today.



J. A. STRANSKY

Former candidate Governor of South Dakota is the inventor of this amazing device now installed by over a million car owners.

The STRANSKY VAPORIZER

Saves Gasoline

J. A. STRANSKY MFG. CO.
Dept. G-10 Pukwana, S. D.
Resources \$500,000.00

Free Gasoline Offer

J. A. Stransky Mfg. Co.,
Dept. G-10, Pukwana, S. D.

Yes, send me without obligation full details of your no-risk test offer. Also tell me about your distributor's money-making plan.

Name.....

Address.....

City.....State.....

Quickly Learn to Play Hawaiian Guitar Play Like This Native

Bring the romantic, enchanting, entrancing and melodious strains of the great instrument of the Hawaiian Islands into your soul. Become popular and successful. This **short cut method** of home instruction enables you to quickly master Hawaiian Guitar so you will **play as well as Native Hawaiians**.

Our staff of Hawaiian instructors have perfected a method of teaching, so simple, that without musical knowledge, you quickly learn to play real music from notes. **Simple as learning your A, B, C's** and it will not be long before you will play latest Broadway hits.

Only four simple motions to learn. You will then play any music, whether it be popular, dance or classical. Almost from first lesson, you play love songs like Aloha Oe.

To help you get started, we furnish with-out extra charge when you enroll as a student, a beautiful, full tone, genuine, \$18.00 Hawaiian Guitar. Only 1,000 free instruments given away; if you want to get in on this offer, write for particulars at once—you must act quickly.



New Invention—

Kno-All-Chart QUICKLY TEACHES YOU HOW TO PLAY

The newest invention of our Hawaiian instructor, which is exclusively used by us and which we call the "Kno-All-Chart," quickly

teaches you how to play and read notes. So simple is this device that any one can understand it and begin to play immediately.

Picture Method Easy

GIVEN
\$18 Hawaiian
Guitar when
you enroll!

We do not depend upon our printed instructions alone for your success as a student, but we also supply you with many pictures of our professors' playing. This enables you to imitate the pictures. Isn't this easy?

Phonograph Records Given

As an additional guide, we also furnish you with phonograph records of our Hawaiian instructor's own playing of the pieces you are learning. This practically brings our professors from our studio to your own home and enables you to listen to their playing just as if they were actually in front of you.

Genuine \$18 Hawaiian Guitar Given

Enroll as a student, and secure a beautiful, full tone, genuine \$18.00 Hawaiian Guitar. We also furnish every bit of equipment so it is never necessary for you to spend an extra penny. When you graduate, you get a beautifully engraved diploma and after graduation, we also give you six months' free service and consultation. Send for free particulars now.

JAZZ

**Your Way to
Popularity and
Success**

No forming class to wait for. Start at once and join band wagon of success and popularity. Do it through Hawaiian Guitar. Send for free First Lesson and Book. Be positive are we you will become one of our students, that if you write at once, we will send you free, our first lesson which will enable you to see just what you can expect when you enroll. You will also receive our big book of full particulars. Write for your copy and free lesson today.

Write at Hawaiian Studio No. 5206
once
of New York Academy of Music
100 Fifth Ave., New York, N. Y.

**HAWAIIAN STUDIO No. 5206
of New York Academy of Music
100 Fifth Avenue, New York, N. Y.**

Please rush your book, "How to Learn Hawaiian Guitar" and my first free lesson. Also reserve a Hawaiian Guitar for me without extra charge. This obligates me in no way whatever.

Name.....

Address.....

City.....

State.....



BOW LEGS and KNOCK- KNEES UNSIGHTLY

Those afflicted with BOW LEGS should wear the "PERFECT LEG FORMS" and overcome this deformity. Trousers hang perfectly straight. Made of the highest grade Aluminum. Sanitary, Light and Durable. Easy to put on or off. Send for booklet showing photos of men with and without the "PERFECT LEG FORMS."

PERFECT SALES CO.
140 N. Mayfield Ave. Dept. 9 Chicago, Ill.

America's Standard Radio Text Book

Radio Theory and Operating

By M. T. LOOMIS

President, Loomis Radio College, Washington, D. C.

By far the best Radio Text and Reference Book ever produced

Third Edition—Revised—1927

585 Pages. 700 Illustrations. 5 1/2 x 8 Inches
Flexibly bound in red craft leather

Used by

The Department of Commerce
U. S. Naval Radio Schools
U. S. Coast Guard Academy
U. S. Signal Corps

Leading Radio Schools of U. S. and Canada

Price \$3.50 Postpaid

POPULAR MECHANICS PRESS
Room 606, 200 E. Ontario St., CHICAGO

Outdoor Opportunities

How to raise rabbits, guinea pigs, milch goats, silver foxes, ferrets, white rats, white mice, dogs, cats, pigeons, pheasants, bantams, canaries, bees, frogs, mushrooms, ginseng and golden seal for profit. Practical 250-page book with 120 illustrations. Will be sent C. O. D. When postman hands you the package, pay him \$2 plus the postage.

POPULAR MECHANICS PRESS
Room 506 200 E. Ontario St. CHICAGO

WANTED—Volume I, Number 1, January 11th, 1902 issue of Popular Mechanics Magazine. Must be intact and in at least fair condition. Will pay 50c to \$1 for same. Communicate with Manager, Book Department Popular Mechanics, 200 E. Ontario St., Chicago, Ill.

SCIENCE FINDS NEW DRUGLESS GLAND STIMULANT

Science has discovered a new method of applying a positive-nature force. The method is wholly different—a tremendous step forward in regaining prostate gland health. Amazing effects produced in thousands of men, many beyond sixty.

"A hundred years ahead of modern medicine," writes a New York physician. Doctors and osteopaths are using and prescribing it. No drugs, medicine, massage or violet rays. Absolutely safe.

Does what Gland Tablets can never do. Directly stimulates prostate gland and often restores it to normal size and functioning in six days! Also tones up entire system, usually routs constipation and piles. Bladder weakness and frequent painful urination relieved in most cases. These results are unconditionally guaranteed.


Scientist's FREE Book, "Why Many Men Are Old at Forty," explains these amazing facts. This book is now FREE. No obligation at all. Simply ask for FREE book.

THE ELECTRO-THERMAL CO., 2170 Main St., STEUBENVILLE, O.
Western Address: Suite 21-N, 303 Van Nuys Building, Los Angeles, Calif.

Auto Owners Mystified By New Device MAKES CARS RUN ON 7% GAS

Washington:—Patent has been applied for by an automotive engineer on a device that is stated will revolutionize the automobile industry. The theory of his invention is that of adding 93% air to 7% gasoline in such a way as to create perfect combustion. The device, by actual tests on various makes of cars, including Fords, Chevrolets, etc., has cut gasoline consumption unbelievably. The Whirlwind Company, 1041-361 Winnebago St., Milwaukee, Wisc., is acting as sole distributor for the inventor. They are appointing men in each locality to take care of the enormous demand that is being created. This offers an opportunity

to make \$5000 or more a year. Write them today for full particulars and free sample offer.—Adv.



WANT WORK AT HOME?

Earn \$18 to \$30 a week RETOUCHING photos. Men or women. No selling or canvassing. We teach you and furnish WORKING OUTFIT given with each enrollment. Limited offer. Write today. **Artists' Studios, Inc.** 50, 3500 Sheridan Rd., Chicago

BUCHSTEIN'S FIBRE LIMB



Send for Catalog Today

Is soothing to your stump—strong, cool, neat, light. Easy payments. Braces for all deformities. **D. BUCHSTEIN CO.** 610 3rd Ave., So. MINNEAPOLIS, MINN.

FREE TRIAL Grows Hair



AMAZING NEW
ELECTRICAL
DISCOVERY

A noted surgeon has discovered an amazing way to grow hair, called Dermo-Ray. In 30 days no more dandruff. Scalp tissues are given new life. Then within a few weeks, luxuriant new hair! The startling discovery of the almost magic effect of Infra-Red Rays on the hair-growing tissues was made by a leading surgeon. Two years ago he was himself bald. Today his hair is full and thick.

FAMOUS SURGEON'S DISCOVERY
Here is his own personal, home treatment, called Dermo-Ray. At last a home method endorsed by science. Guaranteed to bring you these same results in 30 days—or you pay nothing. You can use Dermo-Ray in any home with electricity. The warm, soothing Infra-Red Rays vitalize the scalp while you rest—a few minutes each day is all the time required.

SEND NO MONEY Complete facts about this astounding new scientific discovery, opinions of authorities, incontrovertible evidence, and details of special trial offer sent free, if you mail the coupon below. To end your scalp and hair troubles, act at once. Print your name and address plainly—and mail the coupon NOW!

-----FREE TRIAL OFFER-----

The Larson Institute

Michigan Ave. at Lake St., Dept. 39, Chicago, Ill.

Send me at once, without obligation, full particulars—in plain envelope—of your 30-day Free Trial of DERMO-RAY.

Name

Address

City State

LOANED

FREE to ambitious men!

Just Out!


Business Management and Commercial Law!

Here's the quick way to PRO-MOTION for men eager to win success in business. The "just word" in Accounting, Finance, Production, Sales, Advertising, Commercial Law. 9 great volumes by Bell, McKinsey, Simmons, Gauss, Chamberlain and others. A reference work for executives, a complete reading course for the student. \$2 after 15 days free loan, then \$3 a month until \$29.50 is paid.



A-B-C!

A for Architectural, B for Building, C for Carpentry and Contracting. Here's the easy, quick road to success in the great building industry. 3 volumes, thousands of illustrations, plans, etc. \$2 after 15 days free loan, then \$3 a month until \$24.80 is paid.



Auto Engineering

"Master the one chapter on Ignition and double your pay." The most complete work on every branch of automotive engineering we have put out. Prepares you for a fine position in the ten billion dollar auto maintenance field. 3 volumes. For Garages, Mechanics and auto owners. \$2 after 15 days' loan, then \$3 a month until \$24.80 is paid.

- 3 Free Features**
1. Home-Study Guidance Free.
 2. Membership in Amer. Technical Society with a year's free consulting service.
 3. Free employment service.

American Technical Society

Dept. X-A19 Chicago, Ill.

- ☐ Architecture, Building & Carpentry, 3 vol. \$24.80.
☐ Civil Engineering, 9 volumes, \$24.80.
☐ Electrical Engineering, 8 volumes, \$34.80.
☐ Auto Engineering, 3 volumes, \$24.80.
☐ Business Management, 9 volumes, \$29.80.
☐ Modern Shop Practice, 6 volumes, \$24.80.
☐ Law, 13 volumes, \$49.80.
☐ Drafting, 4 volumes, \$14.80.
☐ Steam and Gas Engineering, 7 volumes, \$24.80.

Name

Address

(Attach letter stating references and employer's names and addresses, or write same in margin plainly.)

Pay-raising TOOLS—not just Books!

A better JOB—bigger PAY—real opportunities now within your reach through these great home study libraries. Built by America's greatest Engineers especially for men with limited schooling. Borrow a set free, and see how easily you can master a better-paid line of work!

PICK THE JOB YOU WANT

we'll help you land it!

Get Into Electricity — Building Construction — Engineering — Auto Work, where they pay man-size salaries and where the sky's the limit for advancement! Where salaries range from \$60 to \$125 a week and more. Where you'll be "sitting pretty" regardless of business conditions.



Electrical Engineering

Thousands of men with only common schooling have prepared themselves for good electrical jobs with this famous reference library and reading course. New revised 8 volume edition, complete and simplified. Borrow a set free, \$2 after 15 days' loan, then \$3 a month until \$34.80 has been paid.

Other BIG-PAY Lines

Any set loaned FREE so you can prove its value for yourself. Return only \$2 after loan period, then \$3 a month.

Civil Engineering—Written so you can understand it. Includes Steel Structures, Surveying, Railroads, Public Works. New 9 volume edition, \$34.80.

Modern Shop Practice—Machine Shop, Foundry and Factory Practice and Management. Production, Drafting, etc. 6 volumes, 2500 pages, 2500 illustrations, \$24.80.

American Law Library—With reading course of 24 texts, 13 volumes, intended for the business man as well as for the prospective lawyer, \$49.50.

Drafting—Mechanical and Architectural. 4 volumes, 1578 pages, 1000 pictures, blueprints, etc., \$14.80.

Steam and Gas Engineering—7 volumes, 3500 pages, 2500 illustrations, only \$24.80.

Fire Prevention and Insurance—1 volume, 1300 pages, 600 illustrations, \$14.80.

Sanitation, Heating & Ventilating—4 volumes, 1434 pages, 1450 pictures, \$14.80.

Employment Management & Safety Engineering—7 volumes, 1800 pages, 540 charts and pictures, \$24.80.

No C.O.D.—Send No Money

AMERICAN TECHNICAL SOCIETY,


Dept. X-A19, Chicago, Ill.

Please loan me FREE set marked X below. In return for this favor, I agree to pay the few cents express on same and to look them over carefully. If I decide to keep them I will pay \$2 after 15 days and then \$3 a month until special price is paid. But I may return them at your expense if I wish and owe you nothing.

- ☐ Fire Prevention & Insurance, 4 volumes, \$14.80.
☐ Sanitation, Heating & Ventilating, 4 volumes, \$14.80.
☐ Employment Management, etc., 7 volumes, \$24.80.

Big Pay Now

Since he learned AUTOS at National



Plenty of Jobs
\$50 to \$200 a week

Over 16,000 men are now making more money because they learned all about automobile repairing in a few months of practical shop training at National.

Hal Edwards was only earning \$100 a month when he entered the National shops. Today he is the highest-paid man in the big garage illustrated above. His earnings have increased 300% as a result of National training!

Skip 6 Years of Hard Work— Jump Right Into a Big-Pay Job

It will take you years to learn the Auto business as an underpaid apprentice. In National's million-dollar training shops you actually perform work that employers pay big money for. You get unlimited personal training under expert instructors until you are competent to take over a big job after a few months' training.

FREE EMPLOYMENT SERVICE

There are more calls for "National-trained Auto Repairmen" than we can supply. Employers are eager to get expert men. Special "Earn While You Learn" plan pays expenses while training.

Big Free Auto Book Starts You on Road to Bigger Pay

Read how National training insures your success. Learn how National has helped thousands of men like you. Mail coupon for free Auto Book explaining how to get into the Auto business.



National

Automotive & Electrical School

Dept. 669, 4006 Figueroa St.,
Los Angeles, Calif.

Send me Free Auto Book describing
National training methods and opportunities
in Auto Industry.

Name.....

Address.....

City.....State.....



PLUMBING-HEATING

Install Your Own—Save Half




Lowest wholesale prices on highest quality Grade A goods. Any Handy Man can install his own Plumbing and Heating BY OUR NEW EASY METHOD. Get the best and pay only a little each month.

Send for FREE Book

New bargain catalog just issued. With our cut-to-fit systems you save waste material and high labor cost. 60 years of economical service to home owners, farmers, builders and mechanics. Million Dollar Plants back up our Bonded Guarantee. FREE book gives you the whole story. Write for your copy today.

OVER 50 YRS. HARDIN-LAVIN Co. EST. 1876
107-17 West Pershing Road, Chicago, Ill.

LEARN to PITCH



Lessons by "MATTY," ED. WALSH, "DOC" WHITE, WALTER JOHNSON, "NAP" RUCKER, "SMOKY JOE" WOOD, PITCH THE FADE-A-WAY, SPITTER, KNUCKLER, SMOKE BALL, etc. Clearly Described and Illustrated on 56 Pictures. Entire COURSE OF LESSONS SENT POSTPAID for 60 cents.

BENEDEK, 2300 N. Mason Avenue, CHICAGO, ILLINOIS

Tire Repair Business is good now!

\$500 a month

Nation-wide chain of Tire Surgery Shops now being extended to every town and city. Men handy with tools and willing to work are needed. We train you, furnish everything and establish you in a shop of your own. Small investment required. Write for interesting book.

HAYWOOD TIRE EQUIPMENT CO.,
1308 S. Oakley Ave., Chicago


Free Book GIVES DETAILS



Be Your Own Boss

HAYWOOD TIRE & CO.

Raise Chicks Without Loss



Prof. Quisenberry's new 1927 FREE Book Now Ready. Shows how to raise more chicks—less losses. Money making poultry secrets FREE. Quisenberry's NEW WAY made many countrymen rich. Send name, address and kind of poultry you like.

American Pty. School, Dept. 70, K. C., Mo.

EXPOSED!

69 Tricks of Mediums Fully Explained

Every detail given for performing the seemingly impossible feats of famous mediums. Startling revelations that show how easy it is to fool the credulous. Many of these tricks have made the greatest magicians wonder.

You Can Do These Tricks

What makes a trick good is its simplicity. No complicated or expensive apparatus needed for these, the best of spiritualistic tricks. You can do such wonders as:

1. Produce spirit message on blank paper.
2. Read messages while blindfolded.
3. Produce spirit rappings.
4. Produce spirit voices.
5. Produce writing on blank slates.
6. Read sealed letters in total darkness.
7. Reproduce a burned message.
8. Read messages retained by the writers—and 61 other marvels used in spiritualistic seances.

Make Money Giving Entertainments

Clubs, Lodges, Sunday Schools, Churches, and organizations of all sorts are eager for entertainers who can mystify audiences with such inexplicable manifestations as these. You can make from \$10 a night up to \$50 or more, depending upon the size of the community in which you work. Anyone can do this. You need no special gifts.

Price \$1.50 Sent C. O. D. anywhere in U. S. Pay postman price and postage. If outside U. S. remit when ordering and include 10 cents extra for postage.

POPULAR MECHANICS PRESS
Room 703, 200 East Ontario Street CHICAGO, ILL.

BIG PAY IN THIS NEW PROFESSION Get This Free Book?



It shows how easily you can have an independent future and salary as an Ornamental Iron and Bronze Draftsman. Beginners can earn \$65 a week—\$500 a month frequently paid to trained men. Wonderful opportunities to become an executive. Not enough trained men for positions open. Easy for you to qualify. No books, higher mathematics, or experience necessary. Learn while on your present job. Don't wait—write for the Free Book right now.

American Institute of Ornamental Iron & Bronze
3039 Hennepin Ave., Minneapolis, Minn.

STATEMENT OF THE OWNERSHIP, MANAGEMENT, CIRCULATION, ETC., REQUIRED BY THE ACT OF CONGRESS OF AUGUST 24, 1912, OF Popular Mechanics Magazine, published monthly at Chicago, Ill., for April, 1927.
State of Illinois, County of Cook, ss.
Before me, a notary public in and for the state and county aforesaid, personally appeared H. H. Windsor, Jr., who, having been duly sworn according to law, depose and say that he is the editor and business manager of the Popular Mechanics Magazine and that the following is, to the best of his knowledge and belief, a true statement of the ownership, management, etc., of the aforesaid publication for the date shown in the above caption, required by the Act of August 24, 1912, embodied in section 411, Postal Laws and Regulations, printed on the reverse of this form, to-wit: First, That the names and addresses of the publisher, editor, managing editor, and business manager are: Publisher, Popular Mechanics Co., 200 East Ontario St., Chicago, Ill.; Editor, H. H. Windsor, Jr., 200 East Ontario St., Chicago, Ill.; Managing Editor, L. R. Webster, 200 East Ontario St., Chicago, Ill.; Business Manager, H. H. Windsor, Jr., 200 East Ontario St., Chicago, Ill.; Second, That the owner is (if owned by a corporation, its name and address must be stated and also immediately thereunder the names and addresses of stockholders owning or holding one per cent or more of total amount of stock. If not owned by a corporation, the names and addresses of the individual owners must be given. If owned by a firm, partnership, or other unincorporated concern, its name and address, as well as those of each individual member, must be given.) J. H. Windsor, 200 East Ontario St., Chicago, Ill.; H. H. Windsor, Jr., 200 East Ontario St., Chicago, Ill.; L. R. Webster and Henry H. Windsor, Jr., Executors of the Estate of Henry H. Windsor, deceased, Chicago, Ill.; Third, That the known bondholders, mortgages, and other security holders owning or holding one per cent or more of total amount of bonds, mortgages, or other securities are: (If there are none, so state.) None; Fourth, That the two paragraphs next shown, giving the names of the owners, stockholders, and security holders, if any, contain not only the list of stockholders and security holders as they appear upon the books of the company but also, in cases where the stockholder or security holder appears upon the books of the company as trustee or in any other fiduciary relation, the name of the person or corporation for whom such trustee is acting, is given; also that the said two paragraphs contain statements embracing within their full knowledge and belief as to the circumstances and conditions under which stockholders and security holders who do not appear upon the books of the company as trustees, hold stock and securities in a capacity other than that of a bona fide owner; and this affiant has no reason to believe that any other person, association, or corporation has any interest direct or indirect in the said stock, bonds, or other securities than as so stated by him; H. H. WINDSOR, Jr., Editor and Business Manager. Sworn to and subscribed before me this 28th day of March, 1927. J. GRAHAM, Notary Public. (My commission expires June 17, 1928.)

Tri-State College of Engineering

Makes you a civil, mechanical, electrical or chemical engineer in 96 weeks. No entrance examinations. High school diploma not required. Compact courses of essentials only. Expenses low. Degree granted. Enter Sept., Jan., March, June. For catalog address, Box M-67, Angola, Ind.



Learn Tenor Banjo

BANJOISTS! Earn big money through Charles McNeil's famous Home Study Banjo Course. Simple as A B C—yet has all technical requirements. Includes photograph record demonstrating jazz strokes, "breaks" and chords, played by Charles McNeil, 5 years with Igham Jones-Brunswick Records. Easy pay, month. Send for Free Book.

CHICAGO BANJO INSTITUTE
Dept. A-135 3345 N. Lincoln Street CHICAGO, ILL.

Fibre-Lite Limbs

BRACES AND TRUSSES
DO NATURE'S WORK. GREAT INVENTION. EASY TERMS. AGENTS WANTED
WRITE FOR FREE FIBRE SAMPLE. **WORMAN CO.** 252-P HENNEPIN AVE. MINNEAPOLIS, MINN.

NO JOKE TO BE DEAF

—EVERY DEAF PERSON KNOWS THAT

I make myself hear, after being deaf for 25 years, with these Artificial Ear Drums. I wear them day and night. They stop head noises and ringing ears. They are perfectly comfortable. No one sees them. Write me and I will tell you a true story, how I got deaf and how I make you hear. Address

GEO. P. WAY, Artificial Ear Drum Co. (Inc.)
80 Hoffman Bldg., 2530 Woodward, Detroit, Mich.



"We couldn't save a cent"

"I HADN'T received a raise in years and my small salary scarcely lasted from week to week. Margaret scrimped and saved and did all her own washing and housework, but the bills kept piling up and I could see she was always afraid I would lose my position. But still I kept drifting along in the same old rut.

"Then one day I met Tom Wilson, who used to work right beside me. He told me he was making \$5000 a year and had a nice home in the suburbs, a new car and everything. I asked him how he happened to get ahead so fast. 'Oh, I got tired working for a small salary,' he said, 'so I started studying at home through the International Correspondence Schools.'

"That woke me up. I told Margaret that if the I. C. S. could help a man like Tom Wilson it could help me. So I cut out that I. C. S. coupon and mailed it to Scranton.

"It certainly was a lucky day for me. In four months I received a raise in salary and before the end of the year I was next in line for manager of my department. We've got a car of our own now and a bank account that's growing every day."

How do you stand when your employer checks up his men for promotion? Does he think of you? Is there any reason why you should be selected? Ask yourself these questions. You must face them squarely if you expect advancement and more money.

At least find out what the I. C. S. can do for you. It doesn't cost you a penny or obligate you in any way to ask for full particulars, but that one step may change your entire life.

Mail Coupon for Free Booklet

INTERNATIONAL CORRESPONDENCE SCHOOLS
Box 5655-E, Scranton, Penna.

Without cost or obligation, please send me a copy of your booklet, "Who Wins and Why," and full particulars about the course before which I have marked X in the list below:

BUSINESS TRAINING COURSES

- | | |
|--|---|
| <input type="checkbox"/> Business Management | <input type="checkbox"/> Salesmanship |
| <input type="checkbox"/> Industrial Management | <input type="checkbox"/> Advertising |
| <input type="checkbox"/> Personnel Organization | <input type="checkbox"/> Better Letters |
| <input type="checkbox"/> Traffic Management | <input type="checkbox"/> Show Card Lettering |
| <input type="checkbox"/> Business Law | <input type="checkbox"/> Stenography and Typing |
| <input type="checkbox"/> Banking and Banking Law | <input type="checkbox"/> English |
| <input type="checkbox"/> Accountancy (including C.P.A.) | <input type="checkbox"/> Civil Service |
| <input type="checkbox"/> Nicholson Cost Accounting | <input type="checkbox"/> Railway Mail Clerk |
| <input type="checkbox"/> Bookkeeping | <input type="checkbox"/> Common School Subjects |
| <input type="checkbox"/> Private Secretary | <input type="checkbox"/> High School Subjects |
| <input type="checkbox"/> Spanish <input type="checkbox"/> French | <input type="checkbox"/> Illustrating <input type="checkbox"/> Cartooning |

TECHNICAL AND INDUSTRIAL COURSES

- | | |
|---|--|
| <input type="checkbox"/> Electrical Engineering | <input type="checkbox"/> Architect |
| <input type="checkbox"/> Electric Lighting | <input type="checkbox"/> Architects' Blueprints |
| <input type="checkbox"/> Mechanical Engineer | <input type="checkbox"/> Contractor and Builder |
| <input type="checkbox"/> Mechanical Draftsman | <input type="checkbox"/> Architectural Draftsman |
| <input type="checkbox"/> Machine Shop Practice | <input type="checkbox"/> Concrete Builder |
| <input type="checkbox"/> Railroad Positions | <input type="checkbox"/> Structural Engineer |
| <input type="checkbox"/> Gas Engine Operating | <input type="checkbox"/> Chemistry <input type="checkbox"/> Pharmacy |
| <input type="checkbox"/> Civil Engineer | <input type="checkbox"/> Automobile Work |
| <input type="checkbox"/> Surveying and Mapping | <input type="checkbox"/> Airplane Engines |
| <input type="checkbox"/> Metallurgy <input type="checkbox"/> Mining | <input type="checkbox"/> Agriculture <input type="checkbox"/> Navigation |
| <input type="checkbox"/> Steam Engineering | <input type="checkbox"/> Mathematics <input type="checkbox"/> Radio |

Name.....

Street Address.....

City.....State.....

Occupation.....

Persons residing in Canada should send this coupon to the International Correspondence Schools Canadian, Limited, Montreal, Canada.

A Great Book Free with this pay-raising library

For a short time only we will give every subscriber to the New Library of Machine Shop Practice a copy of French's Engineering Drawing—the greatest book on mechanical drawing ever written. This book makes drawing as plain as day—tells you all about instruments, plans and methods—and prepares you to handle any drawing job you will ever have to do. It comes to you absolutely free with


Machine Shop Practice

9 volumes — 3065 pages — 3608 illustrations
(A combined home study course and reference library)

The New Machine Shop Library is written for practical men. It gives you the best methods for every kind of machine shop work. It explains machine tools and their operation, drawing and design, tool work, gears and grinding, fits and fixtures, automatic screw machines and their tools and all of the mathematics you will ever have to use. It is plainly written, completely illustrated—the very best kind of help to the machine-shop man who wants to advance himself.

Sent

**F
R
E
E**



No money down—
only 7c
a day

FREE EXAMINATION COUPON

McGraw-Hill Book Co., Inc., 370 Seventh Ave., New York

Send me for 10 days' free examination the New Library of Machine Shop Practice. If satisfactory, I will send you \$1.50 in 10 days and \$2.00 monthly until the special price of \$19.50 is paid. If not wanted, I will return the books at your expense.

On receipt of my first payment of \$1.50, it is understood that I am to receive, free of charge, a copy of French's Engineering Drawing.

Signed.....

Address.....

City and State.....

Position.....

Employer..... P.M. 5-1-27

Be a Civil Engineer!

Learn
at
Home!



Cyclopedia of Civil Engineering

9 great volumes.
4000 pages.
3000 illustrations.
New edition just
off the press, by
twelve of America's
greatest engineers.
Includes: Surveying,
bridges, railroads,
steel structures, mu-
nicipal engineering,
water supply, road
building, etc.

Earn
\$5000

a Year—and Up!

"CIVIL ENGINEERING"—in plain English written so you can understand it, even if you have only a limited education. Prepares you for a well-paid railroad structural or public works position. Covers every branch of Civil Engineering practice. At once a reading course for the ambitious student and an authoritative reference work for the experienced engineer. Borrow a set—free. Look over the test questions which help you master each subject quickly. Mail the coupon without obligation today!

American Technical Society
Dept. C-A19 Chicago

American Technical Society,
Dept. C-A19, Chicago.

I want to BORROW the CIVIL ENGINEERING Cyclopedia for 15 days FREE. I will gladly pay the few cents express, but I am to pay nothing for the loan of the 9 big volumes if I return them within 15 days. If I wish to keep them I will send you \$2 after the 15 days, then \$3 a month until special advertising price, \$34.99, is paid.

Name.....

Address.....

(Attach letter showing age, occupation, employer's and references' names and addresses.)

Loaned Free!

to prove you can learn Civil Engineering at home in your spare time. And because no description here could do it justice, to let you see for yourself the scope and simplicity, the authority and quality of this great home reading course. Cost and terms are within your reach. Send no money—just mail the coupon.



BOYS It's Fun to Make Things



Let the other boys wonder how you can make so many interesting things. Make your own automobile. Make your own radio. Make your own kites and gliders. You can learn how to make almost anything that any boy could want by following the pictures and the simple directions in

The Boy Mechanic Library

And just think of it, there are nearly 4,000 separate articles in the four beautiful volumes! Some of the most fascinating subjects are listed below:

How to Make Things

Boats	China painting
Winter sports	Decorative metal work
Camping	Furniture making
Ice boats	Farming
Water sports	Fondry
Toboggans	Models
Tents	Laboratory helps
Skis	Household helps
Indian snowshoes	Wood working
Skiing	Electrical devices
Gymnasium	Photography
Wind wagons	Music
Motor sleds	Outdoor games
Radio	Stoves
Magic	Furnaces
Trapping	Wireless
Pets	Tricks
Leather work	Fences
Carpentry	Bicycles
Painting	Flowers
Toys	Hunting
Flaxing	Kites
Fruit growing	Metal working tools
Entertainments	Secret locks
Automobile	Swings
House decorations	Sleds
Drafting	Power devices

Buy the complete library, including Book 1, Book 2, Book 3 and Book 4 for \$7, thus saving \$1 as single volumes are \$2. If you want individual books at \$2 each order by number 1, 2, 3 or 4.

When the postman delivers the books to your door, pay him the price of the books and the postage. That is all. If outside U. S. remit when ordering and include 28 cents per volume extra for postage.

POPULAR MECHANICS PRESS
200 E. Ontario St.
Room 606 CHICAGO, ILL.

Learn To Fly From Men Who Know

We have taught hundreds of students. Many are now doing commercial work at large salaries. New air rates, mail and passenger, creating big demand for men.

Learn to Fly by Sweeney System

**An Actual Photo of One of Our Training Planes—
A SWALLOW**



**GROUND SCHOOL
FOR AVIATION
MECHANICS**

**BIG
MONEY
in Flying**

Aviation Mechanics—
\$50-125 Week
Riggers—\$50-175 Week
Flyers—\$125-225 Week
Fuel Work—\$100-300
Aerial Photo Pilot—\$200-
\$250 Week
Aerial Messenger Service—
\$125-200 Week
Aerial Advertising—\$225-
\$500 Week
Crop Dusting—\$125-200
Crop Survey—\$125-225
Week

Here's the great business of the future. The National Air Transport alone has invested \$700,000 on the Kansas City air route. They are spending \$1000 a day to operate an over-night service to New York City. Ambitious men are wanted as pilots and ground mechanics. You can go into postal, government, or commercial work. Flyers are in demand, earning big money at fairs, taking up passengers, etc., \$5 for a 10-minute flight is pretty fine pay!

If You Want to Be a Pilot

The student, if he wishes, goes into the air and qualifies as a pilot under safe and experienced pilots, with double controls for actual flying.

You take all the actual flying necessary to make you a competent pilot. Now when you understand that two to seven hours is all the average man needs to learn expert flying you will appreciate what this ample experience in the air under skilled men will do for you. Aviation is no longer a mystery—no longer a hazard; no, it is a business growing greater and more important. This has been wonderfully demonstrated in the successful flights over the North Pole.

**150 Acre Flying Field
Hangar and Club House
Instructors
Thorough Construction Course**

LEARN TO FLY BY FLYING
Sweeney
SCHOOL of AVIATION
3806 SWEENEY BLDG, KANSAS CITY, MO.

Sweeney Students Are

trained by DOING. Thorough ground school work, under skilled instructors in the construction and repair of planes, recovering wings, tuning motor, etc., learning everything about the mechanical work by actual practice. This fits you as an aviation mechanic. You can build your own plane and do anything required in aviation mechanics and construction and repairing when you have finished this work. You are thoroughly taught motors, etc., and work with thousands of dollars' worth of new material, including all types of engines. Aviation is now playing in commercial activities. Progress is rapid. More men are needed every day. You can qualify as a mechanic, or an engineer, or repair man, or builder; five men on the ground are needed for one man in the air.

SEND NAME TODAY for full details of this aviation mechanical course and photographs of planes and equipment actually used; also full information as to the commercial end of flying and opportunities for young men. No colored students accepted.

— — — — — "SEND THIS NOW" — — — — —

EMORY J. SWEENEY, President
3806 Sweeney Bldg., KANSAS CITY, MO.
Please send me full information about your Aviation Course.
Name.....Age.....
Address.....
Town.....State.....

1952



Torpedo Boats of the Air Attacking a Dreadnaught of the Sea; an Unusual Drawing from a Scene during the Recent War Games of the British Grand Fleet; the First Successful Torpedo Planes Were Built by the U. S. Navy during the War

airplane Bomb

2/12/27

Popular Mechanics Magazine


REGISTERED IN U. S. PATENT OFFICE

WRITTEN SO YOU CAN UNDERSTAND IT

Vol. 47

JUNE, 1927

No. 6



Burros and Flivvers Compete Rushing Prospectors to the Maddest Wide-Open Mining Camp Seen in a Generation

TWO nineteen-year-old Nevada boys started out one morning a few months ago to look for gold, found it at noon and flivvered home across the desert in the cool of the evening with samples that assayed \$78,000 to the ton.

That started the wildest gold stampede in a generation, founded a tidy little city overnight, and even brought about a bitter fight in the state legislature over a proposal to revoke the anti-gambling laws and establish Weepah, the new gold town, as a roaring mining camp that would equal anything seen in a "Days of Forty-Nine" show.

The two boys who made the discovery, Frank Horton, Jr., and Leonard Traynor, were working an old claim owned by the father of Horton, and made their strike within a few yards of an abandoned prospect shaft, where the father had dug in

vain for gold. They had stopped work for lunch, but, while one prepared it, the other picked over the ground, following a badger hole. Suddenly he gave a shout that brought his partner on the run, and both boys scooped up handfuls of rich quartz, shot through with streaks of gold.

Back at Tonopah, twenty-seven miles away, they showed their finds to old and seasoned prospectors, who declared the supposed gold was only iron sulphide, the "fool's gold" of the prospector, and was worthless. Crestfallen, the boys passed out many of their samples to friends, one of whom was interested enough to have the rock assayed, with the result that it was found to run nearly \$80,000 to the ton. By the time he reached the boys with the good news, the latter figured they had given away more than \$4,000.

Fortunately they had not disclosed the

Cont. John Anson Ford,
205 Union League Bldg.
Los Angeles, Calif.

location of their claim, and they kept the information a secret until the elder Horton returned home to protect their interests. Later the two leased their ground to a syndicate which took \$30,000,000 in dividends out of the Goldfield mines twenty years ago.

When the rush to Weepah started, a typical tented mining town sprang up overnight. Its streets, to which the sage brush still clung, were thronged with bearded desert prospectors, many of whom had not met since the last rush a generation ago, and with tourists and gold seekers from nearly every state in the union. Patient burros, loaded with the meager equipment of the seasoned desert "rat," brushed against flivvers that ferried their owners back and forth each day from the hotels of Tonopah, and costly touring cars that came, loaded with all the patent equipment an inspired sporting-goods salesman could sell.

The center of attraction was a trench, ten feet long and four feet deep, on the discovery claim. Beside it, for days, always under guard, rested thirteen sacks of ore, declared to contain between \$50,000 and \$100,000 in gold.

Tonopah, coming out of the sleepy days that followed its decline, shared the glory of Weepah as a roaring mining camp again. Because of lack of accommodations and supplies at the discovery claim, most of the prospectors and visitors lived in the older city. Gambling houses flourished again, while the legislature debated lifting the ban against them, and dozens

of mining companies were born overnight in hotel rooms and even in the streets, where miners met.

At Weepah, out on the barren desert, everything, even down to water, had to be imported for sale in the canvas-and-board-shack stores. One thriving emporium posted a sign advertising water at \$2 a barrel, gasoline fifty cents a gallon, ham and eggs for eighty cents and "white mule, fifty cents a drink, chaser free."

Gold strikes seem to run in bunches, for hardly had the news of the Horton-Traynor find been flashed to the world than discoveries were broadcast from Dripping Springs, Ariz.; Angels, Calaveras county, Calif., in the district made famous by Mark Twain and Bret Harte, and from the Silver Peak mountains of Nevada. The last find was made by Frank Horton's older brother Fred and a Chicago youth, while they were touring across country in a battered small car.

Across the Continental Divide from Weepah, at Del Norte, Colo., another gold discovery is waiting for spring to remove the deep snow so that work can be resumed. There, a pair of Denver men, who leased the old Little Annie mine, first opened back in 1871, made a strike that turned out as much as \$16,032 from a 259-pound sack of ore.

Another old mine is being worked again after being abandoned for years with the reopening of the Loraine shaft, 22 miles west of Blythe, Calif. The new vein has yielded ore which has assayed as high as \$1,400 to the ton.




Burros, Known in the West, Because of Their Braying Sing Song, as "Rocky Mountain Canaries," Are Still the Mainstay of the Veteran Desert Travelers and Prospectors

WHERE THE OLD AND NEW MET AT GOLD STRIKE



Frank Horton, Sr., Next to His Son,
and Frank Traynor, His Companion
in the Discovery



Desert Miner Panning
Out the Gold and
Carefully Saving the
Precious Water to Be
Used Again; a Rock-
ing Motion Carries the
Lighter Stones and
Earth Away and
Leaves the Nuggets
Behind in the Pan

Boom-Day Prices
Are Charged for
Everything in the
New Camp. For
All Supplies
Have to Be
Freighted in from
Tonopah; the
Sign Indicates
That Weepah Is
Being Run as a
Wide-Open Camp

Water - \$2.00 Bowl
Gasoline - .50¢ Gallon
Ham & Eggs - .80¢ —
White Mule .50¢
Chaser free




Too Late to Stake a Claim,
the Shoe Repairer Opens
Shop in His Flivver



The First Building in Wee-
pah, a Thriving General
Store, Is Offered for Sale

207 884

GIANT NET PROTECTS THE PENSTOCKS OF DAM



Rigging the Steel Net to Catch Logs Before They Can Strike and Damage Penstocks of Dam near Tacoma, Wash.; Meshes Are Six Inches Square

In order to protect the penstocks at the Lake Cushman dam, recently completed near Tacoma, Wash., from waterlogged timbers, carried along beneath the surface of the water, an enormous steel net has been stretched across a short distance from the upstream face of the dam. It is woven of wire and steel cable, the meshes being six inches square. A strong cable, securely anchored on either side of the canyon, supports it.

WEIGHT OF HAIR TELLS RACE
EXPERIMENTS SHOW

Scientists now can determine your race by weighing your hair, tests at the University of Chicago have shown. Using ten strands, each of the same length, the investigators found that the hair of Mongolians is heaviest, that of the Caucasians next and the Negroes' is lightest, partly because of the large number of air bubbles it contains. Research also disclosed that a white woman's hair attains an average length of twenty-five to thirty inches and

that four years are required to achieve this growth, as against twelve to sixteen inches for a white man's hair. This difference is not found among other races. Women's hair, however, is lighter than the males'.

1503
EASILY DRIED SHAVING BRUSH
HAS REMOVABLE BRISTLES

Packing a damp shaving brush into the traveling kit is said to be no longer necessary with a brush that has removable bristles. They can be spread widely apart for quick drying, or a new filler may be inserted. This last feature adapts the brush to barbers' usage and to greater cleanliness, and comfort. The handle is of metal and the bristles are attached to a ferrule which may



quickly be taken out for spreading the brush or changing the filler.

Ans. H. R. Kyle,
6347 Forest St.
Electrobrush, Inc.

Mr. Barnette, working under Mr. Hay. Conifer Creek.

Ant. Ontario, Toronto, Shave Co. Jan.

STATIC FADES AS TRAIN SPEEDS RAILROAD RADIO SHOWS

2207

Static decreases and radio-station strength increases with and in proportion to acceleration in the train's speed, experiments with a receiver on board a car of the Northwestern railroad have shown. When traveling toward a station, the signals are stronger than when going in the other direction. Bluffs or other obstructions tend to deflect or aid the signals of stations near by, according to their relative location, but do not appear to influence the reception from distant transmitters. A steel bridge with no superstructure, helped to increase the volume of the reception while one with a superstructure decreased it.

METAL CLARINET WON'T CRACK AND HAS GOOD TONE

2014

Especially adapted for localities subject to sharp changes in temperature and for traveling orchestras that encounter a wide range of weather conditions, a metal clarinet has been introduced in America from France. It is said to have the same tone quality, correct intonation, evenness and carrying power of the wood instrument and the added advantage of being immune to cracking and checking. It is made with two tubes, the soldering and tone-hole drawing operations being on the outside casing. When very cold, it may be quickly warmed up to the proper playing pitch.



All-Metal Clarinet as Substitute for Wood; It Does Not Vary So Much under Changes of Weather

H. J. Schmitt, cl. no.
C. K. Nash, ind.



Grip Strap on Top of Umbrella Can Be Slipped over Wrist, to Make Carrying Easy

VANISHING STRAP ON UMBRELLA MAKES IT EASY TO CARRY

Umbrellas are carried from the top instead of the grip handle by means of a disappearing strap an English inventor has patented. This prevents the ribs from opening up part way when not secured by the catch at the bottom. The umbrella is but twenty-two inches long when closed, and, when open, the strap is hidden.


INSECTS IN THE CLOUDS

2208

Hunting bugs with an airplane, half a mile above the ground and more, is one of the latest methods of scientists who are intent on keeping plant-destroying pests under control. Sticky-paper traps are attached to the planes or to kites, in order to catch any insects that might be flying, and a "patrol" is made over an area where the bugs are believed to be traveling. Flies of two species and an adult corn maggot have been caught at altitudes of 1,000 to 3,000 feet. Some of the insects were believed never to travel at heights of more than a few feet.

State Entomologist of Tallulah, La.
Mr. E. P. Field, New York
Mr. B. R. Coad, G. S.

20th RAISING ORNAMENTAL FISH AT UNIQUE COLLEGE



Tank at the Fisheries School with Model Equipment; Close View of the Incubating Vats, and, at the Left, Studying the Fish Elevator

Crossing a moonfish with a swordtail and getting an ornamental species whose like never swam before is only one incident in the work at one of the world's most unusual schools, the college of fisheries at the university of Washington, at Seattle. It teaches not only how to fish and how to make fish ready for market, but also how to raise them; how to make

them thrive better, and how to combat diseases. Batteries of hatching jars and glass tanks, chains of miniature hatching pools, rooms full of laboratory equipment, and complicated arrangements of model traps, seines, fishwheels and canning apparatus make up the equipment for instruction. During the winter the students are engaged in classroom and laboratory work, while the spring and summer months send them afield, each working in some branch of the fishing industry. Some go north


Wash. Director John Nathan Cobb.

to Alaska for the salmon run, where they work in the canneries, at the traps, and on the water. Others cruise on the halibut banks or work the oyster beds and lobster pots on Puget sound, and even go north to the Columbia river for the annual early spring run of smelt. Commercial fish farming, which has reached a point where 400,000 of trout was marketed to hotels and restaurants from fish farms in the state of Washington alone last year, is being stimulated by the distribution of bulletins telling how to prepare and conduct farms. Similarly, the newer industry of raising ornamental fish, which is now beginning to thrive, is being guided with expert advice; and here the college gathers and breeds rare specimens from all parts of the world. The fish frequently are distributed to private breeders as a part of the work of encouraging the development of new and beautiful bizarre forms. Besides conducting research among native species of commercial marine forms, the college is busy transplanting new forms. A huge Japanese oyster, which weighs a pound or more and is almost as large as a beefsteak, has been introduced and is now beginning to thrive, according to reports.

2043

RADIO RECEIVER FOR THE BLIND HAS PINHEADS FOR NUMBERS

To enable blind persons to tune in different stations on the radio receiver, the dial numbers are converted into raised characters by placing pinheads in the proper arrangement to form the Braille equivalents for the usual symbols. This plan was devised by two blind men who found some difficulty in using the ordinary receiving set with standard equipment.



Close View of the Raised Numbers on Radio Tuning Dial, and Blind Man Demonstrating Their Use

William Lynch and Everett Astel,
Maine Institute for Blind
Portland, Maine



Not a Toy, but a Serviceable Car: the Midget Electric Auto

TINY ELECTRIC ROADSTER RUNS THIRTY MILES ON CHARGE

Weighing but 344 pounds, complete with storage batteries, a midget electric roadster for two persons has been designed for sport and utility as well. It saves using the large car on many occasions, is serviceable in large industrial plants and can be taken on outing trips where the ordinary automobile would not be practical, as at the beach. A speed of ten to twelve miles an hour is obtained from two standard six-volt storage batteries. This rate may be increased several miles by using a special sixteen-volt battery. Under favorable conditions, a single charging

of the six-volt batteries will give thirty miles. The car is equipped with a lock brake, is easy to operate and the battery box may be employed as a seat for a third person when desired.

During 1926, more than 22,000,000 motor vehicles were registered in the United States.

62 in. wheelbase - adults and older children \$200.00
42 in. wheelbase - children \$125.00
32 in. wheelbase - children \$100.00

Regular Junior

in a slight pressure on the driving-brake pedal stops the car instantly. There is also an emergency locking device for parking.

electric motor

The Rec. at

2177 Antyphone Standards
2061 Broadway
New York


Aut.

17th Floor. Military

Park Plaza. New York

60 Park Plaza. New York

Flirting with Death



By HAMILTON WRIGHT, JR.


HURTLING down a straightaway at nearly three and a half miles a minute, a thirty-year-old English war veteran recently covered the famous speed course at Daytona beach, on the Florida east coast, faster by far than man has ever moved on land.

Riding in the biggest racer ever built—a car almost thirty feet long, six feet wide, and so packed with machinery, including two huge 500-horsepower engines, that there was only room for one small seat—Maj. H. O. D. Segrave set a mark of slightly better than 207 miles an hour with the wind and more than 200 miles an hour against it, for an average speed of 203.79.

In a time so brief that it was measured in split seconds, he went so fast that a spectator who blinked his eyes didn't see him go past, for his speed was about 300 feet a second. In four-tenths of a second—the time it takes for the hand to act on a message from the brain—he traveled nearly 150 feet. At that speed, had the front wheels of his car been twisted ten degrees from their straight path, the rider probably would have been dead before the hand could act, for the wind resistance was so great that even that slight swerve would have sent the car somersaulting over the sands.

Born in Baltimore, Md., of English par-

for a World's Record



new york

ents, thirty years ago. Maj. Segrave for fifteen years has worked, trained, slept, eaten and talked with one thing in mind—speed. When the dream came true at Daytona beach, he was at the wheel of a car that cost \$100,000 to build, besides another fortune to bring it to America for its trials, and that, in the words of its driver, "has no practical use." It is a speed creation, pure and simple.

His record was made on the same stamping ground where famous speed kings demonstrated new possibilities for swift transmission many years ago. Alec Winton, in 1902, roared over this very same course for a mile in fifty-one seconds flat. Then came W. K. Vanderbilt, who negotiated it in thirty-nine seconds. Later

Louis Roth of Boston made the mile in twenty-eight and three-fifths seconds in a Stanley steamer. Victor Demogoet, of Paris, made two miles in fifty-eight and four-fifths seconds in a Darracq. Bruce Brown, in 1911, made ten miles in a little over five minutes. All these records were capped by the three-mile-a-minute pace set by Sig Hangdahl, Norwegian speed king, April 6, 1922.

Maj. Segrave is a daring aviator with a splendid war record. Realizing the desperate nature of his long-planned test, he brought with him seven of the finest mechanics in all England and four experts from leading automobile concerns. Each man had been trained to his capacity and knew just what to do to get the maximum

2132




W. K. Vanderbilt at the Wheel of the Mercedes, in Which He Made a Mile in Thirty-Nine Seconds on Daytona Beach in 1902, When Auto Racing Was Confined to Wealthy Sportsmen

speed from the "Mystery-S," as his car was called. Each knew that a man's life was at stake in this attempt. To withstand the peril of such speed, every nut and bolt, valve and spoke had to be super-perfect. Nothing could be taken for granted. There were ninety-six valves, twenty-four pistons, super-crankshafts, vacuum brakes, wire wheels, every spoke of which must be perfect, and a thousand other important parts to look after, some of which had never before been seen in this country. These men were the advance explorers into the new continent of speed which lay in a plane above that already explored.


There are perhaps no more than a hundred people, close students of rac-

ing, who really know what Maj. Segrave was forced to overcome in accomplishing this great feat. When the wheels revolve at a speed of 2,000 revolutions per minute, one of the greatest difficulties to secure is perfect balance. Any inequality in the tire is tremendously magnified. A wheel appearing to have perfect balance at fifty miles an hour may be thrown out of balance after passing 100 miles an hour, setting up vibrations in the car which make its maximum speed impossible even though wind resistance is reduced to a minimum. At a 200-mile-per-hour speed, the rubber must hold as true as a steel wheel and not fluctuate even a fraction of an

inch. The centrifugal force is so great that tires, rims and wheels have a tendency to come off or fly to pieces. No longer is the weight they bear a factor. It is the strain of another force. To keep the tires on at such a high speed, Segrave was obliged to have nearly 100 pounds' pressure



Maj. Segrave at the Wheel of "Mystery-S" and Giant Car Itself as It Appeared on the Florida Beach



The Fastest Thing That Ever Ran on Land, Maj. Segrave's Giant 1,000-Horsepower Car; First Automobile Racer to Be Equipped with Two Engines and Perfect Streamlining

in the tires. They had to be very thin to overcome heat resistance. It sometimes takes weeks to balance a wheel perfectly. When traveling over 160 miles per hour in an ordinary racing car, the resistance of the air overcomes the traction of the rear wheels and they do not take good hold on the ground. This was, to a large extent, overcome in the "Mystery-S," by the great weight of the car and the partial inclosure of the wheels by the chassis. Moreover, the vacuum created in the rear of the rushing car tends to lift the back wheels, while it is conceivable that the downward pressure exerted by the wind on the nose might cause the car to somersault. The front and rear-end design of the "Mystery-S," while not radically different from that of other racing cars, is more pronounced to meet these problems.

Maj. Segrave has always been speed-crazy. Nothing moves too fast for him. He talks fast, eats fast, thinks like lightning and can't sit still a minute. And yet he knows his car better than its creator, Louis H. Coatalen. If a valve, one in ninety-six, wasn't working right, as he coasted to the beach pits, he'd tell the mechanic just which one it was.

"Suppose your car caught fire when you were traveling about three miles a minute," he was asked, "would you have driven it into the ocean as so many others have done?"

"I don't know," he laughed. "It takes me two miles to stop and if I ever hit the water, even by accident, the impact would

crumple us up as if I had struck a stone wall going sixty. It took about three miles before she was wide open, two to set the record and two to stop. During that two-mile stretch, when I was going around 200, the wind was so terrific as it roared by my ears, that I feared I would have been knocked unconscious, had I leaned beyond the protection of the built-in cowl. This pressure of the air when proceeding at a velocity of 200 miles per hour is equal to a weight of 112 pounds hanging from one's nose. It took fully 500 horsepower, one-half the entire power of my car, to cut down wind resistance at that speed.

"At 200 miles an hour the car has a great inclination to get up and fly. Had any strong gust of wind struck the car when I was going my fastest, I would have been turned over. It's like an airplane hitting a hill. During the tests we made a few days previously, gusts of wind would strike the car at 150 miles an hour and it felt as though I had hit a bale of hay. Even a cross wind of only eighteen miles made it extremely difficult to keep the car from sliding inside."

The beach at Daytona is some twenty-seven miles long and about 500 feet wide at low tide. It is the smoothest natural stretch of land in the world suitable for auto racing and is much sought as a winter and summer resort. The sand is hard-packed. An ordinary touring car leaves only a hair-line mark when slowly moving over it. It is hard because of the fact that its great width has permitted the tide to continually

roll and grind the sand, reducing the grains in size and packing them tightly.

The dangers encountered by Maj. Segrave were confirmed by Sig Haugdahl, who on the same beach thrilled the world a few years ago. At a speed of 180 miles per hour, Sig said, the closest you can drive your car to a straight line is 100 feet. "The slightest move may throw you into the ocean on one hand or into the sand dunes on the other," he said. "The front wheels, turning at 180 miles per hour, act like gyroscopes and won't turn quite enough with the steering gear to keep the car in a straight line. That is one of the dangers of driving fast. When you are going at this speed, the resistance of the air overcomes the traction of the rear wheels and they do not take hold on the ground. The currents of air on the beach move the car. You keep your foot on the throttle and pray to God."

Maj. Segrave came to Florida with a car well prepared to overcome these difficulties. "We built an exact model of the car in miniature and tested it out in a wind tunnel at Vickers', in Weybridge, England, to see how it would act at 200-miles-per-hour wind resistance," he said. "At 210 the wind resistance is figured at 1,020 pounds and at two hundred, 920 pounds. The model we built looked pretty good

and I figured that, when the two engines were in, she'd hold the ground. But the wind resistance was so intense that over half the power of my car, 500 horsepower, was used to cut it down.

"This machine was built to test theories," continued Maj. Segrave. "The auto of the future will travel ninety or a hundred miles an hour. In America and in England, superhighways will be built to allow a very high speed. In England we have several great thoroughfares where you can step on the throttle and hold it down for almost an hour at a time. They have been especially built for speed. Among the new devices and accessories that were placed upon the 'Mystery-S' for the test was a new type of tire which, because of its thinness to resist heat, eliminates a great amount of wear that comes from friction. The tires become so hot at high speeds that thin rubber at present is the only relief known. Centrifugal force stretches the tire fully an inch and a half at 200 miles an hour. The rubber is only one-sixty-fourth inch in thickness.

"We have new alloys in the engine to be tested. An alloy that will stand up under vibrations at such a speed will last on an ordinary car for nearly twenty years or until it is obsolete. The spokes in the wheels embody a new design that we hope will prove much more satisfactory than present-day wire wheels. They are what is called a quadruple-spoke design on the rear wheels and a triple-spoke design on the front wheels. Flexibility is one of their biggest features.

"The steering mechanism is another arrangement that will no doubt prove interesting to American manufacturers as soon as details of it are made known. One can



From a Standing Start, This Small American Racer Beat an Airplane over a Mile Course at Daytona; the Jump from the Start Gave the Automobile the Advantage



Barney Oldfield Getting the Checkered Flag at the End of a Mile in His Famous "Blitzen Benz" at Daytona; Maj. Segrave Followed the Same Course in Making His World's Record

steer the car at 100 miles per hour with almost a thought, and, no matter what contour the road might take, the front wheels tend to hug the ridge or top."

The car cost well into \$100,000. It is practically useless for anything but experimenting and breaking records. The two engines eat up one and one-quarter gallons of special fuel every mile. It can

run on one or two engines. In actual practice, the rear engine is first started up by means of compressed air. The front engine has one, while the rear motor requires two radiators. There are four valves per cylinder and two spark plugs; also four magnetos for each engine, and all valves are operated by means of overhead cam shafts.

2171

ALARM-CLOCK MEMO PAD AIDS IN KEEPING APPOINTMENTS

Besides reminding the business man or other worker of his appointments, a desk memorandum device, introduced in France, keeps an accurate record of tasks performed at any hour of the twenty-four, so that the report may be filed away for reference. It has several features not found in other units of its kind.

For instance, there are keys at the side of the memo blank which may be set for any hour of the day and, when the time is reached, the clockwork mechanism rings a bell. The record sheet is divided into spaces for appointments at intervals down to five minutes apart, and there is another division for general notations. The reminder is especially adapted



to process work, as in a factory where experimental tasks are under way. The record sheets would give timely notice when certain things were to be done in a test, for instance, and they could be kept for later consultation.

2206

SANDWICH MAKING AN INDUSTRY THROUGHOUT UNITED STATES

Sandwiches are now considered one of the leading industries in the United States, the total revenue from this popular form of food approaching that from motor cars and movies. From careful estimates, it is believed that at least 1,000,000 sandwiches are eaten every working day in the Broadway restaurant district in New York alone. Figuring each one at a cost of twenty cents, a moderate amount, the daily revenue in this section of the city alone would be \$200,000 or more than \$70,000,000 a year. These figures are believed to be typical of many other parts of the country.

Mr. C. Marnet & Co.
59 Rue de Richelieu
Paris, France.

from Washington Technology



How Carl Hallstammar Reveals Life in Wood; the Artist and Examples of His Work; the Groups Are Carved from Single Blocks, Not Fabricated; Color Is Applied to Emphasize Features

With three or four chisels, a saw, mallet and a few pieces of basswood or pine, you can be a wood sculptor if you have the talent. This last and most important item is likely to be overlooked on a first visit to the studio of Carl A. Hallstahammar, Swedish craftsman, for his entire equipment is no more elaborate than that mentioned above, and the ease with which he works makes the task appear extremely simple. He uses few drawings or outlines, developing the work directly from the wood block. His studies are not built up from smaller units but are made entirely from a single piece. Color is used to give expressions and costumes more realistic appearance. Through the medium of

wood, the sculptor depicts his subjects in many moods with the skill of the cartoonist. The pieces have been accorded wide recognition in this country. He began carving when he was twelve years old.

DIAMOND ONCE AN IDOL'S EYE BROUGHT TO AMERICA

One of the world's most famous precious gems, the Nassak diamond, has been purchased by a New York jeweler. In 1911, it was valued at \$148 000 but just recently it was appraised at \$400,000 in view of the increased price of the stones and its unusual history. Originally, the diamond is believed to have come from a temple about

M. Franz Boissier
300 Park Ave.
New York


 $3/23/24$

Mr. James

100 miles from the present city of Bombay, where it had been set in an image of the god Siva as a glittering eye. The stone was taken from an Indian prince and came into the possession of Warren Hastings, who sold it to the East India company. A London jeweler purchased it and subsequently it was recut into smaller dimensions but better shape by the then Marquis of Westminster, who bought it in 1831. It had been in the family continuously since the purchase by the marquis until it was bought by the New York dealer. It is said to be the only large blue-white diamond that is owned by a jeweler.

—2089—
**YOKE LINCOLN CUT
PRIZED RELIC AT
UNIVERSITY**

That Abraham Lincoln's woodworking activities were not confined entirely to splitting rails is seen in the sturdy ox yoke he carved from black walnut and hickory and which is now one of the highly valued relics on display at the university of Illinois. It was fashioned about 1830, while Lincoln was living at New Salem, Ill. His brother-in-law, Clark M. Smith, bought it at an auction sale and later placed it on exhibition in his business office in Springfield when Lincoln was elected to the presidency. He finally decided to give it to the university. The yoke is kept in a case of oak boards from the floor of the Lincoln home in Springfield.



Carved by Lincoln and "Rescued" at an Auction Sale, the Ox Yoke Now at the University of Illinois



Wide World
Rounding One of the Seventeen Curves on the Garage Race Track; a Thrilling Moment on the Outer Ramp

**AUTO RACE ON GARAGE RAMPS
TESTS SMALL CARS**

Racing from the second basement to the seventh story of a Paris garage, on the outer ramps used to transport cars from one level to another, gave French drivers a chance to test their skill and the flexibility of their autos recently. The course also had curves which were rounded at high speed, showing the efficiency of the small car, as compared with larger ones.

*Director of Publicity
University of Illinois*

896
2027
17, Boulevard des Capucines, Paris, France

POPULAR MECHANICS



Found under Wall Paper at French Inn, Fresco of Joan of Arc by the Late Paul Gauguin

RARE MASTERPIECE IS FOUND HIDDEN ON BRICK WALL

How a torn piece of wall paper led an American artist to discover a lost painting by the late Paul Gauguin, is a romantic incident of recent happening. The artist had entered the little inn of Marie Henri in Brittany, not knowing that this was one of the favorite retreats where the great Gauguin often amused himself and companions by painting on the walls and ceiling when unfavorable weather prevented work outdoors. A tear in the wall covering revealed a bit of color on the brick beneath. The artist removed all the paper, exposing what proved to be a fresco of Joan of Arc, by Gauguin, and another painting by DeHan, a contemporary. They had been covered by layers of wall paper

and lost for years. The nature of the find was explained to the amazed woman owner of the inn; she was paid for the paintings, and then came the work of their removal. Parts of the wall on which the frescoes were made, were braced, carefully cut out and lowered to the floor. The backs were next reinforced with cement and steel and the paintings taken to Paris. The removal was considered remarkable, because no mortar was broken from the pictures during the process. They are to be exhibited in America soon.

NON-SINKABLE SURFBOARD

1779 MADE OF METAL

Weighing but thirty pounds and constructed so that it cannot sink or capsize, a surfboard of novel form has been introduced in California. Its fish-pattern design affords a saddle and a chin rest for the rider and propulsion is obtained by a hand-over-hand crawl stroke and foot movements. For those who desire it, a set of paddles can be attached, although these have not been found practical in rough water. Frame and breast board are of duraluminum.

And. H. H. Newby San Quentin, Calif.

ELECTRIC DRIVE FOR PUMPING

2167 EASILY INSTALLED

Especially adapted for a home water-works system, an electric drive can be quickly attached

to the pump, operates indoors or out and, in emergencies, may be run with a gasoline engine or by hand. The stroke is adjustable to fit wells of different depths and size of cylinders. Patented features are said to afford economy of electric current and ease of operation. No foundation is required for the rig, which loops around the pump or well casing. Gears, sprockets and chain run in an oil-tight dust-proof box, making lubrication easy.



4 ft. 3 in. high
by 2 ft. wide

Cullman Wheel Co.
1346 Altgeld
Chicago

Between 1887 and 1889



Demonstrating the Circulation in the Holland Tunnel with Smoke Bombs; Note How the Smudge Is Being Drawn to the Ceiling; It Failed to Spread More than Fifty Feet in Any Direction

SMOKE BOMBS IN AUTO TUNNEL TEST VENTILATION

The efficiency of the ventilating system in the Holland vehicle tunnel under the Hudson river was graphically illustrated recently when smoke bombs that gave off fumes, equivalent to those from hundreds of automobiles or a good-sized fire, were lighted in the passage. The smudge failed to spread more than fifty feet in any direction and within two minutes after the bombs were exhausted, the tunnel was practically clear of the last trace of smoke. Circulation is effected by batteries of fans, eighty-four in all, half of which blow pure air into the tunnel while the rest draw out the gases and used air. The fans are operated by

twenty-five-horsepower motors and are run according to traffic conditions.

SAIL LIZARD ROAMED AMERICA MILLIONS OF YEARS AGO

Discovery of fossils and skeletons is constantly helping scientists to reconstruct a picture of the world as it probably was long ages ago. Recently, a party from the University of Chicago found the



Reconstructed from Fossil Remains Found in Texas; the Sail Lizard As It Probably Appeared

skeleton of a sail lizard in rocks while specimen-hunting in Texas. The discovery enabled scholars to correct a minor point, for the skeleton showed that the lizard had a long tail instead of a short one as had been supposed. It is thought to have lived on this continent some 20,000,000 years ago.

*U.S. Museum at
Washington.*

SPIRIT OF ANCIENT CHINA STILL CLINGS TO



Chinese Fortune Tellers Have Been Working Overtime during the Recent Warfare, for They Are Highly Honored Citizens, and Always Believed; Above Is One of Them, Reading the Fate of an Ancient Patriarchal Fakir, While the Neighbors Look On




Chinese Students in a Christian Missionary Workshop Weaving a Rug; Carpet Making Is One of the Chief Industries, and Fine Examples Command Big Prices



Chinese Soldiers and Their Equipment; the Umbrellas, at Right, Resemble the Huge Shields Worn by Knights of the Middle Ages




SOLDIERS WHO CARRY UMBRELLAS TO WAR



The "White Train of the Whites" Which Carries Foreigners from Tientsin to Peking under the Protection of the Festooned Flags of the Allies; Despite the Warning White Paint It Is Often Fired Upon



The Chinese God of Destiny, Above, Seems a Fitting Leader for the Warring Factions; Below Is a Red-Cross Dressing Station of the Army Which Recently Lost Shanghai to the Cantonese Reds



FISHES' SECRET SOUGHT TO ADD SPEED TO BOATS



Above, German "Fish Boat," Showing the "Gills" through Which It Sucks Water; at Top, Left, the Boat Being Launched in a Wheeled Cradle, and, Below, as It Appears When under Way



Hunting for an explanation why some fast-swimming fish had more gills than their slower brothers, a German inventor, A. Boerner, of Dresden, has evolved a new type of boat that breathes water and even has scales along its sides. First tests showed that his boat, the "Forelle," which is German for trout, developed extraordinary speed in proportion to its size and power. It is about thirty feet in length, and driven by a six-horsepower engine. Boerner decided that the accepted idea that a fish propelled itself by means of its tail fin, was not entirely correct, after investigating fast sharks that had as many as five gills, whereas slower-moving fish got along with two. His theory is that the fish take in water through the mouth, then compress the gill bags, to get pressure, and eject the water backward through the gills, with the result that it covers the body with a thin sheath of water and eliminates

the "skin friction" which holds boats back. The fish's scales, he says, act to break up whirls in the water, since any current trying to move forward raises the scales, just as the hand does when brushed from the fish's tail toward its head, and so the current is converted into a propulsive force. To supplement the film of water, the fish also exudes an oily scum which covers the body. To test his theories, Boerner built the "Forelle." Beneath the water line, at the bow, the boat has two large open tubes, one on either side of the stem, and in each tube is a turbine wheel, geared to the engine. The water sucked in through the turbine is expelled through rows of small nozzles along the sides and bottom of the hull, while scalelike embossings on the hull surface break up whirls and convert their action into forward power. The nozzles are so placed as to envelop the hull in a film of water, cutting down the resist-


ance of the water. Steering is taken care of by reducing the flow of water from the nozzles on the side toward which it is desired to turn.

STAMPS PRINTED BY THE MILE

In Franklin's day, letters were sent and charged for by the sheet and the distance they were carried. Ten cents was the rate for one sheet, twenty for two, and so on. For every fifty miles, an additional charge was made. There were no envelopes, the sheets just being folded and mailed. To-day, there are so many letters that stamps are literally printed by the mile. Some 1,500,000 letters are mailed each hour of the twenty-four in a day. To carry the year's letters, 15,000,000,000 postage stamps and 60,000,000 special-delivery stamps are sold. More than 1,500,000,000 postal cards are used yearly. The government has 30,000 railway postal clerks who cover 220,000 miles daily in handling the mails.

RUBBER KNEADED LIKE DOUGH MOLDED INTO DOLLS

Kneadable rubber that can be fashioned into many objects, such as dolls, decorations, masks and other things, has been developed by German chemists. It is colored so that figures can be imitated in a realistic manner and the substance clings together firmly so that almost any posture can be reproduced, depending upon the skill of the modeler.



Boxing Dolls Modeled from Rubber "Dough"; the Substance Clings Together Firmly

STREET LAMPS TESTED TO SHOW IF LIGHT IS WASTED



Testing Street Globes to Determine Their Efficiency; Amount of Light They Pass Is Accurately Gauged

Certain kinds of colored-glass globes on street lamps restrict more than half of the light, while other types are almost as inefficient, according to interesting tests made under the direction of Prof. L. T. Clark, at the University of Southern California. To find out how a lamp is "behaving," a study is first made to determine if the rays are being projected in a direction that will not serve the public, or if the light is properly shed to give the street the best possible illumination. Then, light, globe, and all, are placed inside a hollow sphere which is painted white on the interior, a measuring apparatus is inserted in a hole in the side of the sphere and the amount of light actually passing through the globe is accurately gauged. It was discovered that plain, round, shades of the ordinary kind, allow about eighty per cent of the light to pass through. Those less efficient were mostly of art-lantern type.

By recent count, the earth has 430 active volcanoes.

Mittelland-Summwerke A. S.
Hannover-Linden, Germany

Chicago Tribune

3/9/27

Mr. John Harris
of the Harragut
Washington, D.C.

1924 Well to ready 1928


Chicago Division St. Chicago
500 W.



Capt. Harris and One of the "Mercy Bullets" Intended to Render Animals Unconscious from Anæsthetic

"MERCY BULLETS" TO SUBDUDE JUNGLE BEASTS FOR ZOO

Bullets tipped with a half-inch barbed needle which will inject an anæsthetic into an animal, so that it can be captured alive and without undue suffering, are to be used by Capt. Barnett W. Harris in hunting specimens for the proposed Chicago zoological gardens. Beasts unsuited for the collection will be allowed to escape after they have revived from the effects of the drug, while those that are wanted will be bound and made ready for shipment



Roping Gear Adjusted on Horse, and Drawing to Show How It Is Attached to the Saddle

while unconscious. Capt. Harris plans to go to Borneo, Sumatra, Australia, India and Africa in his quest for animals.

2105

CARING FOR THE LINER

When an ocean liner has been docked, the officers and crew often begin their hardest work, for between the docking and departure, the great ship must be thoroughly overhauled and cleaned. One of the first tasks is the repainting of the hull. Next, the funnels must be scraped and brightened with a fresh coat. The mere cleaning of a first-cabin dining room is a huge task in itself. Such a room may seat from 500 to 600 persons. The carpeting must be vacuum-cleaned, tables polished and all the interior decorations minutely inspected and restored. It is necessary to count, sort and check some 35,000 pieces of linen. Glassware on a liner seldom numbers less than 25,000 to 30,000 pieces.


COWBOY ROPING GEAR REDUCES STRAIN ON HORSE

Pulling up short on a plunging steer at the end of a lariat involves considerable strain on horse, saddle and other equipment; so, to ease the cow pony's work and insure greater safety, an Idaho man has devised an improved roping gear. It is a variation of the breast collar. Its two sides, instead of fastening together at the top of the horse's neck, are buckled to straps attached to the saddle just under the two front strings. The sides of the rig lie along the animal's shoulders and do not interfere with its movements. The tie-down snaps into a small ring set in the center of the breast piece. This arrangement is said to eliminate wear on the horse's neck, holds the saddle in place in heavy roping, preventing complete turn-overs even if the seat is loosely cinched, and since the pull is distributed to the horse's breast, it gives the pony more power.

Chicago Zoological Expedition 5 Dr. Chuain

Dr. C. E. Shipley Bancroft, Idaho

FROM RAW MATERIAL TO PLANES IN TWO WEEKS



Naval Planes Are Being Turned Out Complete at the Philadelphia Factory in Two Weeks and Are Then Ready to Be Placed aboard the Aircraft Carriers; the Top Picture Shows the Fuselage-Assembly Department with Rows of Frames for Fast Scouts; Below, the Engines and Side Panels Have Been Added, and in the Background Wings Are Being Attached; at Left Is a Barge Load Bound for the Ship




1931
904

Henry Miller News Picture Service
519 15th St N.W.
POPULAR MECHANICS
Washington, D.C.
HOME IS BUILT WITH WRENCH IN EIGHT HOURS

*House: McAlister Homes, 12 E. 44th St. New York
645 N. Michigan Ave. Chicago*



The Army Times, Dec. 12 & 19th St. Norfolk



(Portable house that can be built with wrench - Her notable construction Co. Whitewater, W.)

Completed House and Stages in Construction; the Units Are Joined by a Special Rod Arrangement with a Monkey Wrench, So That No Hammer Is Necessary; the House Contains Three Rooms and Bath

To demonstrate a means of solving the housing problem in the army, a home with three rooms and a bath was put up by three men in eight hours. A monkey wrench was the only tool used in the actual construction, as the sections were joined by a patented arch-rod system. The principal material was a kind of synthetic lumber and, while the house was said to be portable in that the parts could readily be taken apart for reconstruction elsewhere, the finished structure was permanent and regarded as strong enough to resist severe storms and earth tremors.

No foundation was necessary. Stucco was used for the outside finish. The total cost was said to be twenty-five per cent less than with ordinary methods.

TASK OF WEIGHING THE EARTH
2096 TAKES SEVEN YEARS

Begun by the bureau of standards seven years ago, the job of weighing the earth is not quite finished, but Dr. Paul R. Heyl, government scientist and official weigher, expects final calculations to show that the figure already reached is not more than a

Bureau of Standard

few million million million tons in error. Under present estimates, the world weighs five sextillion, nine hundred and ninety-seven quintillion tons. Calculations show that it is five and one-half times as dense as water, or, in other words, it would take five and one-half globes of water the size of the earth to balance the weight of the sphere. The atmosphere around it weighs five million million tons, the entire population less than one 400-billionth part of the whole, and the earth is believed to be solid from surface to center and of about the same rigidity as steel. A miniature system of planets are used for the weighing. They are in a room thirty-five feet below the street, in the bureau of standards building at Washington. Two little platinum balls are suspended in a vacuum and permitted to swing in response to the gravitational attraction of two cylinders, each weighing 104 pounds. The distance of the swing is measured as accurately as possible to obtain a constant upon which to base comparisons indicating the weight of the earth. These measurements must be repeated thousands of times to eliminate error.

FLOWERS AND FACES OF SHELLS LATEST ART NOVELTY

Painting seashells to represent flowers, faces, birds and other objects and then mounting them, is the novel occupation of a California woman who has found a ready sale for her work. The pieces are arranged with a suitable back and foreground and can hardly be distinguished as shells when properly mounted.



Fashioning Flower and Other Designs from Shells; They Are Mounted and Framed for Decorations



Flare Signal Which Helps Guard Traffic Policeman in London Fog and Aids in Giving Directions

LIGHTS FOR FOG ARE CARRIED BY TRAFFIC POLICE

When a "pea-soup" fog settles over London, the traffic police have to get out their kerosene flares, not only to escape being run down, but to let the traffic know when to start and stop. Usual methods do not give enough light to pierce the kind of fogs London is occasionally obscured by, so it became necessary to resort to the huge column of flame from the oil flare to do the work.

The Popular Mechanics Bureau of Information offers its free service to all readers of this magazine. Names and addresses of manufacturers and dealers in articles described, and any other details in our possession, will be promptly furnished by the bureau.

*Bertha Montaine Tolley
29 Alhambra St. Angeles
Los Angeles*

*Mrs. Montaine
Tolley
Los Angeles
Calif*

Keystone View Co

For information - wrote Col. John A. Paeglow, Commanding
Affair. Scott Field, Belleville, Ill.

Flying Uncle Sam's



Flying in V-Formation, a Pair of Army Blimps. Photographed from the Control Car of the "RS-1," with a Smoke Screen Laid Down by a Martin Bombing Plane in the Background

A FAT little silver-gray gas bag, supporting a pair of roaring motors and an open passenger car shaped like a high-speed, flat-bottomed motorboat, comes sidling across the wind into a flying field, points its nose for the ground and drops down until a pair of drag ropes can be dropped to a waiting crew.

The ship is hauled down for a few moments, while a quartet of passengers in heavy fur-lined suits and boots climb stiffly out and others take their places. The engineer opens the gas tank, sticks a measuring wand in, cranks up the twin motors, the ground crew leaps clear and the little craft points its nose up and runs off on another two-hour training flight.

The place is Scott Field on the flat Illinois prairies, some thirty miles east of St. Louis. The airship bears about as much resemblance to the long lean, graceful cigar-shaped bodies of the "Los Angeles" and other mammoth Zeppelins as a flyver does to a parlor-car-type motor bus.

Its squat little gas bag, 150 feet or so in length, is shaped like an enormous teardrop, big and blunt at the nose and tapering away to a point at the rear. Where the Zeppelin has an elaborate framework of keel and girders, the army blimps on which the soldiers of the air are trained are just gas bags. Deflate them and they collapse like a toy balloon, and collapsed the whole works, gas bag, rudders, elevators, passenger car and engines, can be stowed on one railroad car.

Only the pressure of the gas and air in the bag makes it keep its shape in flight. Even the big fixed tail surfaces, with their hinged flippers, sticking out at right angles on top, bottom and both sides to act as rudders and elevators, are supported entirely by the pressure within.

With such simple contraptions, however, the British patrolled their coast line during the latter years of the war and escorted ship convoys for 150 miles at sea, and it is their boast that they never lost a

Rubber Gas Bags

ship that was protected by a blimp. For the little airships, flying 2,000 to 3,000 feet above the sea, and with a speed of fifty miles an hour, could circle around and spot the shadow of a lurking submarine long before it came to the surface or exposed its periscope.

In the big hangar at Scott Field as many as nine or ten ships are kept inflated at one time. The hangar is as high as that of the "Los Angeles" at Lakehurst, 172 feet to the top of the roof, and is even longer, being 810 feet from door to door. Out of it, the year around, in all kinds of weather, they come to train the army's lighter-than-air pilots, who are taking the hardest course

of training offered by any service school in the country. The student who graduates from Scott has learned more widely diversified things in one year than other army branches require in a lifetime. When he gets through, he is not only a qualified pilot of dirigible airships of any size, but likewise an expert operator of free and observation balloons, a skilled navigator, a proficient machine gunner, a fine radio operator, an all-round motor mechanic, a good photographer, and half a dozen other things.

The course in free-balloon flying is necessary, for, when the engines go wrong for any reason, an airship becomes simply a balloon, and the pilot must know how to navigate it and bring it to earth. It was free-balloon training that saved the men who sailed away on the nose of the wrecked "Shenandoah." Five day-



Control Car of the "RS-1," with the Elevatorman at the Left and the Helmsman Watching the Compass in the Background

time flights, of at least an hour each, are made with an instructor, and one two-hour flight at night, and then the student is sent up alone to handle the gas bag without assistance or advice. The rule is to sail away before the wind for the required time, then pick out the nearest paved road, bring the balloon down beside it and telephone for a truck from the flying field.

Next comes fifty hours in captive-balloon training to be an observer. In the classroom, a reproduction of a portion of the battle front in France, twenty feet square and with cleverly concealed electric lights to indicate battery flashes, has been used to instruct the students. They sit on high benches, with field glasses at their eyes, getting the same effect as being in a balloon a thousand feet in the air, while the instructor flashes lights all



Engineer's Cockpit of a Blimp, with Pilots in the Background; the Projecting Wings Support the Two Engines

over the map and calls for their exact positions from the class.

Not until the observer's course is completed, is the student ready to go out with a blimp, first only as a student member of the crew, with experienced instructors to explain the dozens of gauges and controls and the secrets of rising, flying and landing.

The training ships are all small blimps, though the field boasts one large semirigid for final polishing off. The passenger cars are open, with a waist-high side wall, and a few deep leather chairs. No safety belts, such as airplane pilots wear, are used. In a cross wind the light cars roll through an enormous arc, until they are lying almost on their sides. Despite the rolling, the crews learn to move about at will without much difficulty.

All the blimps are filled with helium gas, which will not burn but is too precious to waste, so they must be handled, if possible, without letting out gas. The

lower part of the bag contains two ballonets for air, and as the gas contracts in landing, air is forced in to maintain the pressure and keep the bag filled out to its correct shape. A pair of scoops hang below the bags of the little training ships, looking much like the pipes the locomotive crews lower from wayside water tanks to fill their tenders; only, instead of water flowing down, when the scoops are lowered behind the propellers, in the rush of air driven from them, the air flows up, lifts a valve and fills the ballonets. Besides keeping the bag taut when the gas contracts, or letting off air to give the helium room to expand at higher altitudes, the ballonets also are useful in landing and taking off. When the bow ballonet is filled with air, weighting down

the nose, it points toward the ground and the motors can drive the ship down despite the fact that it is lighter than air and wants to rise. And when it is time to take off, the bow ballonet is emptied and the stern one filled, the bow rises and the motors drive the ship upward and forward, instead of having it rise vertically as a free balloon normally would.

From the blimps, the new pilots graduate to the army's largest lighter-than-air craft, the semirigid "RS-1," 282 feet long, with a gas capacity of three quarters of a million cubic feet, making it about the size of the "Norge," which flew over the north pole. Unlike the smaller blimps, the "RS-1" has a framework inside its gas bag, but it consists of only a keel and a nose cap, so that when the bag is deflated, instead of retaining its shape, like a Zeppelin, the fabric bag collapses and rests on the keel.

The keel itself is just a triangular passageway, walled by balloon fabric and


1677



A Small Blimp Ready to Cast Off, at Scott Field, Above, and, Below, the Radio Operator of the "RS-1," with the Bomb Dropper at His Feet, Sitting over the Sighting Apparatus in the Floor



The Navigating Officer of the "RS-1" at His Chart Table, Equipped with Recording Instruments, and, Below, One of the Engineers at His Post in the Gondola, Each of Which Carries a Pair of Motors



containing gasoline tanks and a catwalk by which the crew can reach the pair of engine gondolas, or climb up to a trap-door in the nose when the craft is moored at a mast. When in flight, an engineer sits in a chair in each engine nacelle, watching an instrument board that tells how the two big engines which drive each of the propellers are working. An indicator, like those used on ships, brings him the pilot's orders from the control car, which he can see half a hundred feet ahead of him.

Between the two motor cars is a narrow metal walk connecting them, and from it a ladder leads to a hatch in the bottom of the keel, so that relief crews can come and go.

The control car itself is a two-room compartment, mostly glass in front, where a pair of helmsmen stand, one at the rudder, with an ordinary ship's compass before him, to keep the ship on its course, and the other at a second steering wheel, which controls the elevators and points the big gas bag up or down.

Beside them, the watch officer keeps one eye on their activities, and the other on the controls of all the gas and air valves, the blower that takes the place of

the air scoops on the smaller ships, the ballast releases and the drag ropes. The other occupant of the forward cabin is the navigator, seated at a table with the map spread before him, and, in addition to the usual instruments of a navigator at sea, a set of recording indicators that give air speed, altitude, compass course and other information.

The second cabin contains the radio operator, the bomber, who sits in a hatchway that opens up in the floor, and four canvas bunks for men off duty.

To fly a ship of that size, with the lives of a large crew at stake, requires exceptional training. Some idea of how rigorous it is, may be gained from the fact that, of twenty candidates who had been picked recently for the service, only four got by the rigid physical examination at Scott Field, and only one of the four passed the mental examinations for entrance. And by no means all of those who actually get in and take the year's course are passed as pilots or observers.

Col. John A. Paegelow, who rose from a private in the army in Spanish-American war days to be commander of all the observation balloons of the First Army in France, and is now commander of the

training school, says airship piloting takes an entirely different type of man from that needed for an officer on the ground. "He has to have more self-reliance, more ability to work and to act in emergencies. Infantry on the ground could be described almost as a mob fighting. In aircraft a man is his own commanding general and he must be able to act on his own initiative—and instinctively.

"The sluggish man is no good, for his brain doesn't work fast enough. The pilot of a big airship has to have mind and muscle so perfectly coordinated that he does everything instinctively at the right moment. He



The Giant Army Airship Hangar, with a Blimp and a Balloon Inside, and Another Blimp beside the Small Balloon Hangar



How Aerial Observers Are Trained: the Class, with Binoculars, Spots Battery Fire as the Instructor Switches on Concealed Lights beneath the Replica of Part of the Front Line in France

has to feel a deviation from course or a rise or fall of a few feet and instinctively correct it. Just learning to steer a straight course is a task in itself. It is hard enough to hold a ship on its course in such a comparatively stable medium as water, and tremendously harder to do it in air, when you are at the mercy of every current, and have no foaming wake or landmarks to set you right."

Despite all its difficulties, however, Col. Paegelow believes there is a good future in lighter-than-air ships for a young man of good physique and a good education, particularly in mathematics. The future lies not only in the service, but in the commercial airship lines which, he believes, are sure to come within a few years, particularly for long routes across the ocean.

There is the same future for the enlisted men who qualify as mechanics, for they are proving so popular with commercial flying companies that many are being bought out of the service to earn good salaries with private concerns.

The piloting school is open to anyone who can pass the tests, including enlisted men from eighteen to twenty-seven. Quite a few privates have made the grade, getting the title of cadet—and three times a private's pay while in the school—and later are entitled to qualify for lieutenants' commissions.

Before they have finished the year's course, however, they have sat up many nights wrestling with textbooks that cover such subjects as army administration, field regulations, guard duty, military courtesy and customs, hygiene and first aid, military law, rules of land warfare, aerodynamics, service supply, armament, army organization, artillery liaison, free and captive balloons, communications, gas, meteorology, military sketching and map reading, aeronautical motors, motor transportation, balloon winches, parachutes, aerial photography, physics, mathematics, panoramic drawing, practical observation, tactics of balloons and airships, and an almost endless array of navigating and control instruments.

Besides the classroom work and theory, the students tear down and rebuild aircraft engines until they can do it in the dark; build and take down machine guns blindfolded; help build new ships and repair old ones, learn to rig balloons and patch gas bags, and a thousand and one other things.

When the time comes, though, to take aloft one of the smaller blimps on a solo flight, with no instructor along to give advice and only an engineer and possibly a radio operator as companions, there comes a thrill that is unlike any thrill in heavier-than-air navigation.

THE AMERICAN SOLDIER AND HIS LATEST WEAPONS

The Doughboy and His Arms, Which Include All the Infantry Weapons, from Pistols to Battle Tanks



Modern warfare, as represented by a group picture recently made by the war department, shows the infantry uses such varied arms that the foot soldier must be a skilled mechanic before he can fill all departments. The picture displays eight different weapons, ranging from a hand grenade to a battle tank. On the left is an infantryman about to throw a hand grenade; next a companion is loading a Stokes mortar, built to be set up in a


trench to throw large bombs into the enemy lines. The third figure carries the standard army rifle with fixed bayonet, while behind him kneels a soldier with a rifle grenade fitted in the barrel ready to be fired. Next, prone on the ground, is an automatic-rifle operator with his portable machine gun, and beside him a machine gunner with a large water-cooled weapon, while a thirty-seven-millimeter field gun and a battle tank are in the rear.

TIME LOCK TELLS WHEN STORE IS OPENED AND CLOSED

Accurate record of the time the store is opened, when it is closed, and by whom, is afforded the proprietor in a special lock equipped with a clockwork mechanism and registering tape. It insures punctuality and keeping the doors open the required time to prevent loss of trade. There are six keys to each lock for as many employees. Each key has a different initial at the end. When it is inserted into the lock, it presses against

a tape, registering the initial and the time when the door was opened or closed. By removing the tape at the end of any desired interval, an accurate check is obtained as to how long the store was open,

Side View of the Store-Door Time Lock; as the Key Is Pressed, Hour Is Registered on Tape



who released or secured the lock each time, and when, so that any departure from schedule is plainly indicated for that period. The device is said to be especially suitable for chain stores, filling stations and similar concerns, but is equally adapted to individual shops, stock rooms and manufacturing plants.

The Recording Devices Co.,
Columbus, Ohio.

39 W. Adams, Chicago.
Mar. 30 10

Westinghouse Lamp Co. 13 Lombard, N.Y.

423 Race St. Denver, Colo.

AUTOMATIC RADIO-TUBE TESTER MAKES FEW MISTAKES

As evidence of the large-scale production that is necessary in many radio-manufacturing plants today, an automatic tube tester has been installed at an eastern plant with a capacity of 30,000 tubes a day. This is about fifteen times the number that a skilled person can test by hand in ten hours. During operation for several months, the outfit maintained an accuracy record of 99.9 per cent, the small fraction of error being charged to the accidental introduction of defective tubes into the good stock, according to the engineers. The tester consists of a revolving disk, about three feet in diameter, with sockets for tubes on one of its faces. As the disk turns, the tubes are connected successively with instruments which test them for various characteristics. Those that are defective are pushed out of the sockets by a plunger. Bad tubes are put in a scrap heap; those that can be reclaimed are laid on moving belts to be conveyed to operators for further treatment, and the good ones are sent to be wrapped.



Benches Just for Two Persons Have Appeared in the Denver Parks; Occupants Face Each Other

PARK BENCHES BUILT FOR TWO TO SIT TETE-A-TETE

Fifty benches so arranged that the occupants sit opposite each other were placed in the Denver parks early this season, supplanting an equal number of the older, long kind. They are intended to make conversation easier and prevent interruption of a visit between two persons.

MOTOR BUS LIKE STREET CAR HAS TWO ENGINES

Marked resemblance to a street car is seen in a forty-two-passenger motor bus, recently built for surface lines in Chicago as a "feeder" to the main system. It has two four-cylinder engines and these are placed under the center of the car. Front and rear entrances are provided. The bus weighs 13,000 pounds and costs considerably less than the average street car.

PLAN JAIL BREAK WITH GLIDER

Authorities at San Quentin prison in California recently thwarted what was believed to have been a jail break planned on modern lines, an attempt to escape by means of a glider. The machine, in course of construction, was found on the roof of the furniture factory. Parts had been obtained from various prison departments and the covering for the wings and fuselage was a bolt of material taken from the flag room. The builders might easily have sailed over the prison wall from the roof.



Double-Motored Bus Resembling Street Car for "Feeder" Service in Chicago

Blocks of salt were once used by the people of China for paying taxes.

Used by Chicago Surface Lines have proved satisfactory

216! Anatin 3/2/27

Walter C. Becker - 12139 W. 1st St. Supt. Bus Service
Twin Coach Corporation, Dist. Mgr. Earl W. Bradley, + Bank Bldg

WOMEN IN BANK ARE TRAINED IN USE OF REVOLVER



Women Revolver Experts and a Silhouette Target as It Appeared after Practice at Forty-Five Feet

Women employes of banks in South Bend, Ind., are given revolver practice so that they will be able to cope with bandits in case of an emergency. One woman made a perfect score from a distance of forty-five feet and others showed creditable marksmanship after only a few lessons. The result of one group's shooting is indicated on the target in the illustration.

MERRY-GO-ROUND HOUSE TURNS WITH THE SUN

Sunlight in any room and at almost any time of the day as well as a changing view are possible in a "merry-go-round" house devised by French architects. It is constructed on a turntable like that used in railroad yards. A touch of a button starts it moving, and it may be stopped in the same manner. The buttons are placed in various parts of the house for convenience. The speed is dependent upon the size of the motors, but an automatic arrangement permits starting the house moving in the morning so that it will follow the sun all day without the need


of pressing a button. A novel arrangement of rooms permits new schemes of interior decoration.

METEOR NEARLY STRIKES MAN ON NIGHT BICYCLE RIDE

Many meteors fall to the earth during a year, but there is apparently no record of one killing a person. One of the nearest approaches to such an accident was reported recently from England by a cyclist who declared that a meteor fell within seven yards of him while he was riding at night. He first heard a peculiar whistling noise, then saw a bluish-green light. The noise increased while what appeared to be a ball of fire, about the size of a coconut, fell in front of him. He dismounted and found that the road was covered with a peculiar ash at the spot. It stuck to his shoes and to the tires of the bicycle. Observers, on hearing the cyclist's story, expressed their belief that it could hardly be doubted, and several persons reported they also had heard the noise of the meteor.

COMBINE PLANE AND DIRIGIBLE FOR GREATER UTILITY

Trips across the Atlantic in sixty hours are visioned by a Los Angeles inventor who has devised a model dirigible of novel form, to suggest the means by which he hopes to realize his dream. The ship is essentially different from others in that it is flat instead of cigar-shaped and there are twelve propellers, five on each side and two in front. There is a running gear for land travel, and it is expected that the



Model of the Combination Plane and Dirigible Intended to Make Rapid Flights across the Ocean

Letter ret'd.

ship could skim over or upon the water and sail entirely in the air. The envelope is to be filled with gas.

MORE MUSICIANS FOUND IN U. S. THAN LAWYERS

Full-time musicians, those dependent entirely upon music for a livelihood, greatly outnumber the clergymen or lawyers, in this country, a music house reports. Three times as many persons are earning their living with music as there are dentists or actors, and there are five times as many musicians as journalists. These figures do not include the many thousands who supplement their regular occupations by some form of musical endeavor. One of the signs of the developing interest in music is the increasing number of school bands and orchestras. Teaching formerly was confined largely to assembly singing, but now many schools have various musical organizations, and the value of musical education is recognized.

AUTO MATCH AND ASH HOLDER WON'T RUST OR RATTLE

Easily attached to any part of the automobile, a holder for matches and ashes can be manipulated with only one hand and does not tarnish, as it is finished in dark lacquer over solid brass. The ash chamber is deep so that the contents cannot blow out, and it is easily emptied.



Price - \$1.50

Ruby Mfg Co.
Springfield Ohio.



Illustrating How the Radio Rescue Set Could Be Used in the Alps; Sending Outfit in Foreground

RADIO REPLACING ST. BERNARDS FOR RESCUE WORK IN ALPS

Travelers lost in one of the passes over the Swiss Alps can now signal distress by radio from sending units placed at several dangerous places on the mountain side. Guides, equipped with portable receiving sets, go to the rescue on short notice.

CHURCH SPIRE AS LIGHTHOUSE GUARDS ATLANTIC COAST

For many years, a light in the steeple of the First Baptist church in Beverly, Mass., has been a guide to mariners, and now, upon request of several sea captains, the government has taken over the spire and it is under the jurisdiction of the lighthouse service. Although it is several miles inland, the light is visible far out at sea.

Chicago agent Harry Alpa does not handle



Table Golf
 Indoor Golf with Billiard Cues: Table Top as Eighteen-Hole Course with Numerous Hazards

GOLF GAME PLAYED ON TABLE WITH BILLIARD CUES

Indoor golf on a table, the top of which is spaced off to represent eighteen holes, is played with a heavy disk, about the size of a dollar, for a ball and ordinary billiard cues for clubs. Various obstructions are provided as hazards, and those who have played the game declare that it affords much of the thrill and enjoyment of the regular outdoor pastime.


EDISON JOINS HUNT FOR RUBBER THAT CAN BE RAISED HERE

One of the most important studies the government ever has made, is the four years' search for a kind of rubber tree that can be grown in this country to give us our own supply and make us independent of foreign monopolies. To help in this hunt, there was enlisted recently the aid of America's greatest inventor, Thomas A. Edison, who is seeking a solution of the riddle, not by plant culture but by trying to devise a machine that will cheaply and efficiently extract the juices from rubber-producing plants

labor, -to compete with the grower in Africa, for instance, who pays thirty cents a day or less. He is working on the problem near Fort Myers, Fla., and is using the Madagascar rubber vine as raw material. This plant is known to grow well in Florida, but, so far, no practical way has been found for extracting its juice. Edison declared recently that he was "willing to work twenty-four hours a day," if necessary, to see the accomplishment of the great aim for American-grown rubber. In 1923, congress appropriated \$500,000 for study of the problem.

DISCOVERY OF CYANITE PROMISES BETTER SPARK PLUGS

Quantities of better spark plugs are expected as a result of the discovery of a huge deposit of cyanite, a silicate of aluminum, that can withstand repeated exposures to high temperature, in North Carolina. Investigators estimate that there are 100,000,000 tons of the material in a single mountain, and the specimens so far taken are, of remarkable purity, some of them assaying ninety-five per cent.




Where Valuable Cyanite Deposits Have Been Found, Sample of Mineral Discovered in North Carolina

W. J. Jones 3/20/27

J. A. Ballard

Wilho My. G. 15498 20th St. Los Angeles, Calif. 928



By LIEUT. COL. J. H. PATTERSON, D. S. O., 201 E 24th St
Place, Tulsa, Okla.

WHILE life is counted cheap in the wilds with its savage beasts and strange peoples, yet Africa holds a lure of its own and is probably safer than our large cities because there the danger is realized and can be guarded against.


And, despite the hidden perils, how happy are the days on the sunny African uplands far from the crowds and noise, grind and gloom of modern civilization!

One day on the wide Athi plains, when I happened to be out all alone exploring that region, I saw a black object in the distance, and believing it to be an ostrich, stalked carefully toward it. On getting near, however, I found it to be a rhinoceros lying down, so I determined to try and take a photograph, but he jumped up and circled around until the wind gave him a clue of my whereabouts when, to my dismay, with the agility of a cat, he suddenly whipped around, snorted loudly and came for me straight as a dart. I only had a small-bore rifle and soft lead bullets with me and, of course, it was quite useless with this toy weapon to attempt to stop

him. What was I to do? To run away would be of no avail for there was no shelter. To my frightened eyes the great beast looked like a mountain as he raced for me, and there was not a moment to be lost. I tore off my big sun hat and flung it from me, hoping he would see and rend it instead of me. I then dropped to my knees. Lower and lower I crouched until I lay full length in a little bit of grass, and with a quaking heart awaited my fate. Onward thundered the brute, and to my intense relief he charged between me and my hat without seeing either.

As soon as he had passed, I felt so happy that I could not resist the temptation of sending a couple of bullets after him to speed him on his way, but the soft bullets simply splintered against his thick hide, sending clouds of dust off his back. The bullets, however, tickled him up and apparently infuriated him, for he stopped short in his tracks, turned around, moved his great head right and left, tore up the ground with foot and horns and then—to my horror—repeated his tactics of trot-

2056
Noted for Its Fierce Charge and Unexpected Agility,
the Rhinoceros Is a Formidable Adversary



ting around in a circle until he again got my wind, when he once more, with snort of rage and tail erect, bore down upon me.

This time I feared there would be no escape and the dire predicament in which I now found myself was entirely due to my own folly. I felt the ground tremble as the great brute rushed toward me, and every moment I expected to be trampled to death or tossed on his formidable horns—but luck was with me again, and as I lay pressed flat into the grass, hardly daring to breathe, I was overjoyed to catch


a glimpse of the enraged monster crashing by, and practically over me, not more than a couple of feet away. My relief may be imagined, and when I had summoned up enough courage to take a peep, the most charming sight I ever looked on in my life was the rhinoceros disappearing over a hillock.

After this adventure I left the plains and took to the Kikuyu hills, where I suddenly found myself surrounded by a horde of naked savages armed with spears and shields. Their bodies were smeared all over with white clay, and many artistic designs had been produced by removing the clay with a stick and leaving the skin to

form a background. A little diplomacy and a present of "Amerikani" (cotton goods) got me out of their clutches and I went on my way rejoicing.

The Athi plains again called me, and here I had yet another narrow escape from death, this time from the king of beasts. I went lion hunting one morning on this vast expanse, accompanied by a friend who had shot tigers in India, but who had never yet encountered the African lion. On this occasion I rode Aladdin, a spirited Arab charger, and my friend, Spooner,

LIEUT. Col. Patterson, known as one of the greatest authorities on lion hunting, was sent to British East Africa in 1898 to help build a railroad through the jungle. He arrived as a civil engineer and departed world-famous as the killer of two man-eating lions that had devoured 135 of his workmen before they were slain. In all, he has killed twenty-eight lions. Col. Patterson served in the Boer war and was awarded the Queen's medal and made a Companion of the Distinguished Service Order. During the World war he was in command of the Zion mule corps in the Gallipoli campaign. He has traveled in many parts of the world.





Natives of the Kikuyu Hills with Spears and Shields and Bodies Smeared with Clay, to Form Designs; the Dark Marks Are Skin Areas from Which the Clay Has Been Removed


rode in a tonga, a two-wheeled cart drawn by a couple of ponies. We scoured the broad plains for hours without much success. When we were about to give up our quest and return to camp, I suddenly felt my horse tremble violently and then up out of the grass close by jumped a spotted hyæna. I looked after the ugly beast for a moment, but as Aladdin continued restive, I glanced over my left shoulder and saw two huge lions a few hundred yards off, sitting dog-fashion gazing intently at us. I shouted to Spooner, who was following me in the tonga, "Here's what we're after." I jumped off Aladdin and we advanced on the lions. "Now, Spooner," said I; "you take the one to the right and I'll take the one on the left. Fire when you're ready and take no notice of me."

The moment Spooner fired, I pressed my trigger and had the satisfaction of seeing my quarry rise up and claw the air as he was hit. Both lions, instead of rushing at us, as I had expected, instantly turned and disappeared over the bank on which they had been sitting. I ran to Aladdin, leaped into the saddle and gave chase. After about a quarter of a mile of hard going, I began to overtake the fleeing beasts,

and then, when they found I was catching up with them, they lay down and waited for me. When I had approached a little nearer, one of the lions made a vicious charge. I immediately turned around and made Aladdin show his best paces. The lion's charge only covered some sixty yards. He then lay down and waited. Presently Spooner arrived with the rifles and I said to him, "You shoot that lion"; so he knelt down, took careful aim and knocked the lion over stone-dead. The second lion watched us all the time, but never moved. He now growled viciously and swished his tail so vigorously that he raised quite a dust over his body. We advanced cautiously toward him. I was on the left a little in front, and on Spooner's right was his gunbearer, who carried a spare heavy rifle. The moment Spooner fired, the brute came for me. I fired, but apparently missed, and he was almost within one bound of me when he suddenly flashed past, and then I saw Bhoota, the gunbearer, running away. The next instant, the lion had seized the unfortunate man by the leg and had rolled him over as a greyhound would a hare. All this happened in an instant. I began to run up



Bunks in Trees Where Railroad Workers Slept to Avoid Lions, and "Fort" of Ties Built on Girder at Station during War on the Man-Eaters



to the lion and as I did so thrust a cartridge into the breech of my rifle. I had to face the lion's head and saw him chewing Bhoota's left arm. Spooner was actually trying to shove the lion off the unfortunate man so that he might get at the heavy rifle, which the poor fellow still clutched. The enraged brute never saw me until I put the muzzle of the rifle to his brain. Then I pressed the trigger and, horror of horrors, the rifle missed fire. The lion saw me and I felt that my last moment had come. He opened his jaws, and slowly threw himself on his haunches as if to spring. I remember saying to myself, "He'll never give me time to reload." I looked into his eyes steadily as I carefully and slowly moved one pace back. I moved two paces back, and then it suddenly struck me that in the hurry and excitement of the moment, I had forgotten to cock my rifle. To do so, and put a bullet into the lion's brain, was the work of an instant, and, as he was about to launch

himself upon me, he fell dead on top of Bhoota. We rolled him off and hurried the unfortunate Shikari back to camp. We had to amputate his leg and, although he lived for about six weeks, the shock was too much and he died.

My life-and-death struggle with the man-eating lions of Tsavo was the last round in the long fight which has gone on all down the ages between man and beasts. I am convinced it is the last fight, because, owing to the advance of civilization, such happenings as I am about to set forth

can never again occur.

Tsavo is situated some 130 miles from Mombasa on the East African coast. It is in the depths of a vast impenetrable jungle of thorn scrub, stunted trees and dense undergrowth. In this tangle, the man-eaters laughed at all our efforts to destroy them. We could not penetrate it save by slashing and hacking a path every yard of the way, while to the lions the jungle was as an open book.

I was engaged in this wilderness building a railway bridge over the Tsavo river when there appeared upon the scene the notorious man-eaters, whose record for sheer ferocity and absolute contempt of man surpasses anything hitherto known in lion history. They feared nothing—neither the roar of the rifle nor the blaze of the campfire. Traps, spring guns and firebrands they alike laughed at. They waged an intermittent warfare against our



Bhoota, Center, Sitting Up in Bed under the Shadow of the Skin of the Lion That Wounded Him; Spooner Is at Left and the Author at Right of the Picture

laborers and in the end succeeded in bringing the work to a complete standstill. In spite of all our precautions, man after man was taken from the midst of his sleeping comrades and devoured in the surrounding thickets.

My own first encounter took place near a vacated camp site which I felt sure the lions would visit. I had a wagon placed near the opening of the inclosure, and there, in the company of my friend, Dr. Brock, we sat in the open doorway and waited. When I now think of the foolhardiness of this procedure, it makes me shudder, but at that time we did not think of the danger we ran. We sat in the wagon for a couple of hours in perfect silence enveloped in darkness and then I heard a dry stick snap.

"The man-eater," I whispered to Brock.

A few minutes afterward there was a dull thud, as if some heavy body had jumped over the inclosure. Then we heard some cattle running about inside, and after that all became still. I proposed to my companion that I should climb out and lie on the ground so as to get a better shot at the brute if he should come in our direction with his prey, but Brock fortunately persuaded me to remain where I was, for at that very moment the man-eater was actually stalking us.

After a few minutes of intense peering into the darkness, I thought I saw something glide to a bush near our front. I

asked Brock under my breath, "Did you see anything move?" but he made no reply, so I held my rifle in readiness and waited.

Those two or three moments I shall never forget. I felt instinctively that some uncanny deadly creature was stealing toward us, and I even thought I could discern a form of some kind, but I feared to fire lest it were only my imagination running away with me, and in that case I should merely frighten the man-eater away.

The darkness and silence could almost be felt, and for those few seconds the strain on my nerves was almost unbearable. Then—suddenly—a huge body sprang at us. "The lion!" I shouted, and both our shots rang out simultaneously. The noise and flash of our rifles so terrified the man-eater that, instead of leaping right into the wagon, he turned in his spring, but he got so close to us that I felt the swipe of his paw across my face.

We fired a few more shots in the darkness in order to prevent a second attack and then lit a lantern, and while I closed the door Brock stood ready to shoot. We had the luckiest escape that night that it is possible to experience. Only our keen vigilance and some good guardian angel saved one or both of us. Next morning we found Brock's bullet imbedded in the sand close to a footprint. It could not have missed the lion by more than an inch.

or two. Mine had hit the lion in the mouth and smashed away two of his tusks.

A little later on, the man-eaters got bolder and, instead of attacking singly, as was usual, both lions entered the camp together and each seized a victim. I sat up night after night near likely places, but always in vain. Either the man-eater saw me and went elsewhere, or else I was unlucky, for as I sat watching over one camp, both brutes would attack another a quarter of a mile away, and I would have the mortification of hearing the agonized cries of the unfortunate men as they were being carried off.

This constant night watching was most dreary and fatiguing, but I felt that it was a duty that had to be undertaken, for the workers naturally looked to me for protection. I wish I could convey some idea of what it felt like to be perched in a tree all alone in that desolate wilderness on a dark night and to hear the deep roars of these dreadful monsters reverberating through the jungle and drawing gradually nearer and nearer. In the whole of my life, I have never experienced anything more nerve-shaking than to listen to these lions give forth their death challenge and to know that some one or other of us was doomed to an awful death before morning.

Once the lions reached the vicinity of

the camps the roars completely ceased and we then knew that they were stalking for their prey. Shouts would pass from camp to camp "Khabar dar, bhaieon, Shaitan ata" (Beware, brothers, the devil is coming), but the warning cries would prove of no avail, and sooner or later, agonizing shrieks would break the silence, and another man would be missing from roll call next morning.

About this time I invited Mr. Whitehead, the district governor, who lived some thirty miles away, to come and assist me in my campaign against the man-eaters. He accepted and told me to expect him about dinner time. His train was due at six o'clock in the evening, so I sent my Indian servant up to the station to meet him. In a short time he came rushing back, trembling, in terror, and informed me that there was no sign of a train or of any of the railway staff, but that a big lion was walking up and down the platform. As Whitehead did not turn up, I went on with dinner, and heard a couple of shots fired, but as shooting was a common occurrence, I paid no attention.

Shortly after dusk I took my position in a crib made of sleepers perched on the end of a girder, and soon heard the man-eaters growling and purring, and crunching up bones about seventy yards away.

(Continued in the next issue)




All Foodstuffs and Barter Goods Had to Be Carried for Hundreds of Miles on the Heads of Natives; Some Parts of Africa Have Not Yet Been Explored by White Men

WELL FORECASTS STORMS AND WEATHER CHANGES BY WHISTLING

In eastern Oregon is an interesting well that not only gives supplies of good water but acts as a sort of barometer to tell the approach of storms or changes in the weather. From twelve to twenty-four hours before a storm, it "exhales" a current of air. The draft increases as the storm approaches, sometimes reaching the intensity of a whistling, roaring jet and shooting up a mist of water with it. After the disturbance has passed, the well draws in air until an apparent equilibrium is established within and it is quiet until the next weather change. One theory explaining the phenomenon is that the shaft connects several pockets or chambers containing air of a temperature and pressure approximately constant. Air flows out or into the well, according to changes in the pressure at the surface. The long periods of activity are explained by the smallness of the opening through which the air must pass. The well is drilled to a depth of 458 feet through basalt and other older formations.

CUTLERY FROM OLD WIRE ROPE HAS KEEN EDGES

Discarded wire rope has been utilized by an Oregon blacksmith in fashioning various kinds of cutlery from hunting to carving knives. Plow-steel hoisting cable was used for the knife in the accompanying illustration. A short piece was flattened, welded, shaped and tempered for eight inches of its length. The remaining twelve inches were curved forward and welded to the hilt to form a handle. When ground and sharpened, the knife had an edge that rivaled that of a razor and held its keenness longer than the average kitchen carver.



Carving Set from Old Wire Cable; the Blade Keeps Sharp Edge as It Is Made of Plow Steel

John Bowen,
North Bend, Oregon



Heater Lowered and Raised to Serve as Shelf; It Saves Space and Is Easily Installed

ELECTRIC HEATER FITS ON WALL AND SERVES AS SHELF

Double service is obtained from an electric heater intended especially for installation in the bathroom, doctor's office, nursery or similar place. It is made of porcelain-enameled steel and either is hung against the wall or may be swung up at right angles, as a convenient rack for heating flannels and clothing, keeping medicines warm, or for drying towels and other articles when the current is on. A switch gives three stages of heat.

BELLS HUNG ON RATS' NECKS TO DRIVE PESTS AWAY

Officials in charge of a postal substation in Dallas, Tex., adopted a scheme of bell-ing rats to drive the rodents out. Four of the animals were caught with traps, and small bells were placed on their necks. They were then released and apparently spread dismay among the others, for the station basement and rooms were quickly rid of the pests.

Wittborny 5/33 Spruce St
Cmt. Thos H. W
George Young
Supr. of Mails
Dallas, Tex



Where Cactus Grows to Tremendous Heights; Ladders Are Needed in Examining California Specimen

GIANT CACTUS AFFORDS HOME FOR SCREECH OWLS

Examination of species of giant cactus, in Lower California, required the aid of a ladder, as some of them grew to such a great height that the tops could not be reached without climbing. Screech-owl homes were found in some of the holes that woodpeckers had made in the cactus.

BIG ELEVATOR UP MONT BLANC TO CARRY FIFTY PERSONS

The top of Mont Blanc, Europe's highest mountain, will soon be reached in two hours without climbing or guides by the completion of a cableway from Chamonix to the summit of Aiguille du Midi. The installation is like a big hotel elevator and carries from fifty to seventy passengers. Construction was begun seventeen years ago but was delayed by the war. The trip

to Aiguille du Midi takes one hour and the remaining two-thirds of a mile to the top of Mont Blanc is easily covered in another hour by a new comfortable road.

FIFTY-THOUSAND-YEAR-OLD LOG FOUND IN DIGGING WELL

Pieces of a tree believed to have been buried at least 50,000 years ago were brought up from a depth of 754 feet while digging a well in Tacoma, Wash., recently. The wood was well preserved and the bark readily distinguishable from the rest of the trunk. While the species was not determined, it apparently was some kind of conifer. The discovery indicates that the area was timbered before the glacial age, as the strata in which the tree was found are believed to have been deposited before the last ice period in that part of the country. The glaciers and river deposits had covered the trunk, and as it was almost completely immersed in water, it had not suffered any decay.

Tacoma Ledger 3/16/27

SEAT FOR INFANT FITS ON CHAIR IN AUTO OR SWING

Fitted with a tray, a secure back and sides, a seat for infants is hooked to an ordinary chair or may be used in the auto or suspended by cords as a swing. The bottom can be thrown back and the seat used as the toilet. The hook is rubber-covered to afford a firm grip and prevent damage to the furniture.




Infant's Seat and a Few of the Typical Uses to Which It May Be Adjusted

The Frank L. Taylor Co., Norwood, Massachusetts

Illustrierte Zeitung
P. 245 - 2/24/20

1750 City. 8000 Miles
623 E. Birch Ave.
Denver, Colo.



Sectional Diagram of the Moffat Tunnel and Its Companion Water Bore; the Saddle above It Is Rollins Pass, through Which the Railroad Has Made Its Way for Many Years

How Rail Builder's Dream Came True

Moffat's Tunnel Cuts Coast-to-Coast Lines Seventy Miles and Opens Vast New Empire for Cities and Farms in West

TWENTY-FIVE years ago, a sixty-five-year-old pioneer of Denver dreamed a dream in which the Colorado metropolis became a stopping place of a through continental railroad; in which the vast and potentially valuable western section of Colorado was opened to settlers with an assurance of direct transportation to the markets for their produce, and in which the backbone of the Rockies was to be pierced by the greatest railroad tunnel in America, to make the dream come true.

He labored for nine years, sunk his own great fortune and the fortunes of many of his friends, and when David H. Moffat finally died, the tunnel had not even been started and only 214 miles—about one-third—of his proposed railroad to Salt Lake City was completed.

It took another sixteen years to see the Continental Divide blasted through with a six and nine-tenths mile tunnel, but finally it has been opened and the Moffat tunnel is in operation as a permanent me-

morial to the visionary who conceived it. As a result, a new combination of railroads is in prospect to create a transcontinental system that will be seventy miles shorter than any existing route, and, when a connecting link is built, Salt Lake City will be brought nearer by 173 miles to Denver.

When the traveler rides at ease through the long bore, he will pass 2,400 feet below Rollins pass, through which the railroad, after a tortuous climb, has wound its way all these years since Moffat saw the first rails laid. For a time, the bore will hold the title of the longest railroad tunnel in America, though the Cascade tunnel, now being built by the Great Northern, is soon, with its seven and a half miles of length, to take that honor away.


In one way, however, it will remain unique—the only railroad tunnel ever built by a city, for it was the money of Denver, aided by surrounding counties, which made the tunnel possible. Eventually the city and counties will get it all back, with

interest, through the railroad rentals, but in the meantime the people who furnished the funds will secure two advantages—one the opening to their market of western Colorado, and the other the use of the pioneer bore, a smaller tunnel seventy-five feet to one side of the big one, as a water conduit. Years ago, anticipating future water needs, the city of Denver filed on 100,000 acre-feet along the headwaters of the Fraser and other streams, on the west side of the Continental Divide. When it came time to build the railroad tunnel, a smaller bore was rushed through parallel to it, with short connecting tunnels at intervals, so that work on the railroad tube could be carried on from a number of points. Now these connecting passages will be closed and the water from the Pacific side of the Rockies will be carried through the mountain to be consumed on the eastern slope.


With unparalleled engineering difficulties to face, the pioneer bore enabled the builders to complete the work in the allotted span of forty-six months. The cost, estimated at \$6,720,000, has been nearly doubled because of the difficulties encountered, and to solve them, the engineers have had to create their own machinery. One trouble arose when Crater lake, a pretty little mountain pool lying in a valley nearly a thousand feet above the bore, began to drop its entire contents into the shaft. Huge pumps worked for months to carry away the flood and keep it down to the point where men could work. To facilitate drainage, the tunnel has been

built with a peak in the center, sloping away to the east and the west.

Another problem arose when the miners found that the rock inside the west portal, where geologists had predicted hard granite, was really soft and crumbly and dissolved into muck when exposed to the air. It made easy digging, it is true, but it was so soft that the walls and ceiling would slide into the hole as fast as the tunnel was dug, so soft that it oozed between all but the most perfectly fitted timbers. Huge twelve-by-twelve-inch beams were crushed under the immense weight into a mass of match sticks. It was only possible to dig when the roof was supported, and to support it the engineers devised an entirely new machine in tunnel work—the traveling cantilever needle bar. The needle bar was really two immense steel girders, three and a half feet thick and sixty-five feet long, tied together by rigid struts and braces and supported on enormous foot-square stringers of Oregon fir. Resting on the "bench" at the tunnel heading, and with a third of their length projecting to the rear, the girders carried the supporting timbers that held up the roof while the muck was carried away and permanent timbering put in place. All big tunnels are dug with a bench at the heading where the men work, because their size makes it impossible to work from floor to ceiling without scaffolding. To get around the difficulty, the miners blast out the top half first, and leave the lower half, or the bench, which is removed, always a day behind, the heading being twenty to



Map Showing How the Moffat Tunnel Pierces the Divide and Cuts Off Many Miles of Tortuous Curves and Steep Grades on the Railroad Route from Denver to the West Coast



West Portal, with the Final Wooden-Segment Arches in Place and the Space Above Packed with Dry Cordwood, Used to Hold Back the Enormous Weight of the Crumbling Rock

thirty feet ahead of it, depending on the nature of the rock.

The needle bars also carried between them an endless-belt conveyor to remove the muck from the face to the waiting cars, while specially designed electric shovels, built to work in close quarters, scooped up the muck of the bench as it was blasted free and eliminated the usual gangs of "muckers."

The new territory in northern Colorado which is now being opened to intensive development includes 15,000 square miles of coal lands, 11,000,000 acres of forests, vast beds of oil shales, and an extensive deep oil pool which has been opened within the last two years near Craig, the present terminus of the Moffat road. Building stone, marble quarries, cement, valuable clays, metals of various kinds

and radium-bearing earth, as well as fertile valleys are also among the resources.

STEAM BUS RUNS SMOOTHLY

1570 AND BURNS OIL
Elimination of unpleasant fumes as well as the noise and vibration attending the operation of a gasoline motor, is one of the desirable features attributed to a steam bus with a rotary engine. It burns fuel oil or kerosene, one gallon of which is said to give as much mileage as a gallon of gasoline in a motor bus of like capacity.



Chassis of the Oil-Burning Steam Bus with Rotary Engine

The Steam Appliance Co.
Q.R. of America
1052 Union

General Syndicate, Inc.
17 E. 42nd St.
New York City

Chicago agent
Rotabaker
Chapman
Ohio

*Chas. H. Tourneur
Thundersley,
Essex Eng.*



Miss Dorothy Thompson
Another Use for Ostrich Plumes; Fashioned into Decorative Floor-Lamp Shade

OSTRICH-FEATHER LAMP SHADE LATEST NOVELTY

Uncurled ostrich feathers of an orange hue have been found effective in making floor-lamp shades, to harmonize with certain schemes of interior decorating. They shield the eyes from the direct rays, diffuse a pleasant glow and can be made in much less time than is required for those of silk or other fabric.

PAPER MONEY TO BE SMALLER FOR LONGER WEAR

Easier to count and handle, the smaller sizes of paper money proposed for circulation in the near future will save the government about \$4,000,000 a year, and as the bills will not have to be folded so many times, it is expected they will last longer. They will be "greenbacks," much harder to counterfeit than the yellow notes, as they will be printed in dull green and brown colors that defy accurate reproduction under a camera. At present, there are five kinds of \$10 bills. In the new series, there will be but one of this denomination and of all others, a distinc-

tive design being chosen for each. It is planned to drop the \$2, \$500, \$1,000, \$5,000 and \$10,000 issues. The new ones will be six inches long and two and one-half inches wide, the dimensions of Philippine currency, which has been in circulation there for twenty-five years.

2170 DRESSING IN GRASS

Nettles are usually associated with unpleasant sensations, but a species of the plant is widely cultivated in China for the manufacture of a soft silklike fabric for textile purposes. In strength, beauty and texture it is said to compare favorably with the finest grades of silk and is less costly. The "grass cloth" of China has been used for more than 4,000 years. Pineapple fiber is also employed in the manufacture of fabric for handkerchiefs and other articles.

1689 EXTENSION DRAFTING TABLE FOR BIG SIGNS

Show cards but a few feet square as well as large signs may be painted on an adjustable table which rises or lowers, tips to different angles and is light enough for easy carrying. It may be made as small as two by four feet, as high as seven feet and of almost indefinite length, depending upon the number of units employed. The parts are held together by bolts and screws which are quickly inserted or taken out.




Table as It Appears When Closed; for Larger Signs It May Be "Stretched" Out to Great Length

Cap/pers 3/26/27.

*George A. Cole
1973 Beaumont Ga.
note to Smith*

AIR LINER BUILDING FOR TRIPS ACROSS CONTINENT



Framework of the Dirigible under Construction; Duralumin Is the Main Material and the Ship Is to Employ a "Vacuum" Principle of Propulsion Instead of the Usual Propellers

Round trips between the Pacific and Atlantic coasts can be made in three days with a new type of dirigible, its inventor believes. In construction, it is much like other ships of its kind, the chief difference lying in the method of propulsion. Instead of boring through the air, it is equipped with a blower which is said to take most of the air from the nose of the dirigible, creating a partial vacuum. The air is then discharged at right angles to the surface of the ship at high velocity, thus on account of the shape of the envelope providing a propulsive force. The craft is to be 400 feet long and somewhat lighter than existing dirigibles of its size. Steam tur-

bines will be used for motive power and it is believed the load-carrying capacity will make long trips practical.

AUTO WINDSHIELD KEPT CLEAR WITH CHEMICAL WIPER 1903

Easily attached to any windshield wiper, automatic or hand-operated, a special blade spreads a chemical which is said to clear the glass of moisture and keep it so

for several hours without the necessity of constant repetition. The blade can be put on with a screwdriver and has two layers, one of rubber to scrape off the dirt and a felt section which serves to distribute the chemical.



Chemical Blade for the Windshield Wiper, and Drawing Illustrating Its Efficiency

Thomas B. State
Glendale Calif

J. H. Christens Mfg Co.
319 Orleans St. N.

retail - Marshall Field



Rum-Chaser Airplane Equipped with Lewis Machine Gun; the Craft Can Travel through the Air or on Water

SIX RUM-CHASING AIRPLANES HAVE MACHINE GUNS

Airplanes equipped with Lewis machine guns have been added to the regular rum-chasing fleet to prevent smuggling. They can travel in air or on water.

NAVY TO BURY ITS EXPLOSIVES TO AVOID DANGER

Artificial caves, built into the sides of hills, will be used in the future by the navy department for the storage of ammunition as one means of preventing another disaster like that which wiped out the Lake Denmark depot last year. The caves will embody all the lessons learned in past explosions, and when the system is installed, ordnance experts believe that it will be impossible for a fire starting in one building to communicate the explosion to others. The first ammunition depot of the new type is to be installed at Yorktown, Va.

Each building will be constructed in a recess dug in a hillside, with the earth banked against three side walls, leaving only the front open, and it will be covered by an earth barricade a few feet in front of it. All steel used in construction will be joined together to prevent sparks jumping from one piece to another if struck by lightning.

QUICK REPLANTING SAVES UPROOTED SHADE TREES

Many beautiful shade trees, uprooted each year by storms, are cut up and carted away when they might be replanted and

saved if given fairly prompt attention. After the hurricane in Cuba last fall, trees were "salvaged" in this manner and, within a month, had sprouted new leaves and were prospering. It is thought that all traces of the wind's damage will have disappeared within a few years. The tree is trimmed back and braced with props, in many instances, to support it while the new roots are forming, and it is often necessary to supply fresh earth. Crews with derricks and other hoisting apparatus can handle large trees with comparative ease.



Large Tree, Partly Uprooted by Hurricane in Cuba, Was Saved by Quick Replanting and Trimming

Cont. Norman Stepien
1121 Ash St.
Winnona, Minn.

Cont. Ernest Longherty
514 W. Crawford Bldg
Washington D.C.

ELECTRIC QUESTIONNAIRE SPEEDS PUPILS' STUDY



Pupils Taking Test by the "Electric Questionnaire": a Buzzer Is Sounded to Announce When the Time Allowed for Answering Each Question Is Up

Alertness and quickness in answering questions are said to be developed in pupils through the use of an electric buzzer and special sets of test questions and answers, covering a variety of subjects. After a question is announced, a reasonable time is allowed for writing the answer, then the teacher plugs in the buzzer, which signals that the time limit is up. Papers are exchanged and the pupils correct each other's, according to the answers.

at St. Petersburg 2036
**USE ICE TO LOWER CONCRETE
FOR BANDSTAND FLOOR**

Sunshine and ice were utilized by engineers in Florida in lowering a sixteen-ton concrete slab which forms the floor of a bandstand at a municipal pier. Screw jacks could not be used, as it would have been impossible to remove them after the concrete was in place, and the difficulty was further increased by the fact that the work had to be done in an exceedingly narrow space. The floor was to be lowered eighteen inches. It was first elevated two feet, then thirty-two fifty-pound cakes of ice were fitted under it as supports. The jacks were then removed and while sun-

shine melted the ice, engineers removed the two-foot props and substituted six-inch blocks. Men with long-handled mops took care of the water that formed, and the job was completed in sixteen hours.

TRAPDOOR ASH TRAY IS CLEAN AND HAS LARGE CAPACITY

Ashes are kept from blowing about and unpleasant odors are eliminated in a large



where they are securely held for later removal. The bowl or main ash receptacle is large enough to make daily emptying unnecessary. The tray also is provided with a bracket for a match box and supports for cigars.

Chicago Evening Post.
3/2/27

Matchless Utilities
Co., 690 Eighth Ave.
New York

Chicago. 6259 St. Lawrence Ave.

1535

Cmnh H. S. Williams Esq
4. Crowhurst Road, London
Epsom, S.W.9, England

1st J. Williams Esq.
Colombier, Barnesburg Road,
New York City, N.Y.

What is the TRUTH



leads to seeing things that aren't there.

Ghosts have always had one drawback from the standpoint of careful investigation—they are usually seen by people who don't want to see them, and almost never by persons who go looking for them. There is a simple explanation for that, and for the ghosts that are heard as well as those that are seen. The visible ghosts, scientific investigators declare, exist only in the eye of the beholder, and the audible ones in his ear.

Everybody, even those who have never claimed to have seen a ghost, has lain awake at night and heard queer sounds, abnormally loud, even though they would have been inaudible to anyone else, because they existed only in the hearer's own ear. The sounds were made by blood pulsing

GHOST stories are being bought and sold in the London real-estate market as a result of the discovery that old castles with spooky reputations are preferred by buyers, particularly wealthy Americans. Not that the purchasers believe in ghosts, but there is something about owning a home with a tradition of being haunted that makes it worth thousands more, in the estimation of many purchasers.

England is well supplied with good ghost stories, and the list is constantly being added to, largely, it is believed, because candles are still extensively used for illumination and the dim light of a candle is very favorable, according to scientists, for producing the condition that

through the veins of the ear. Picked up by the eardrum, which amplifies them just as a radio receiver amplifies an incoming signal, the ear sounds, heard in moments of apprehension or nervousness, can easily be imagined to be the stealthy steps of a burglar or the movements of a more ghostly visitor, particularly if one is sleeping in a centuries-old castle well supplied with ghostly legends.

As for the ghosts that are seen, they are classified medically as Purkinje images or Sanson specters, both named after their discoverers, and it is in seeing them that the weak light from a candle plays such an important part. Purkinje discovered that under certain conditions the blood vessels


about GHOSTS?

in the retina, that film at the back of the eye which is directly connected with the nerve leading to the brain and which really sees the image focused on it by the eye lens, could produce images of its own. To do that, though, a dim light is necessary, as a bright illumination furnishes so much light that the blood vessels do not cast their shadowy reflections. It is as when one meets an approaching automobile at night. If the car has bright lights on, that flood of light blinds the eye, whereas if the dimmers are turned on, the retina is able to distinguish all the details of the roadway clearly.

Like the Purkinje image, the Sanson specter is produced within the eye, either on the front surface of the cornea, which is at the front of the eyeball, or on either the front or back surfaces of the crystalline lens, a convex lens like that in a camera, which focuses the image on the retina. When you look through a street-car window under certain light conditions, you not only see the passing buildings outside, but likewise images of the people behind you, or buildings on the opposite side of the street, the images being formed on the window glass. The Sanson specters are something of the same sort, tiny images, usually badly blurred, of things which are at one side, out of the direct line of vision. But the optical nerves, accustomed to placing things they see by their size and relation to other objects, transmit a message to the brain saying that these blurred specters are ahead, and, like the images on the street-car window, you can look right through them and see solid objects behind.

Given a dim candle flame and a condition of nervousness, grief, or even indignation, it isn't hard to imagine that you are seeing images of ghostly figures, particularly as they appear to be almost transparent, and move and shift position as you move.

"We know now," says Dr. Frederick Graves, an English scientist, "that ghosts



The Front Surface of the Cornea. Marked A, the Front and Rear Surfaces of the Crystalline Lens, B, and the Blood Vessels of the Retina, C, Are Three Places Where the Eye May Create Ghost Images

are mostly figments of the subconscious mind that gives us dreams. Certain abnormal states, as when toxic matters linger in the system, produce visions readily; even from errors of diet, a person may have startling revelations.

"That unconscious element that slumbers not and, when unfettered by the will of the conscious mind, can act by itself, as in hypnotism, somnambulism, automatic walking and writing, accounts for many queer things. Those myriad cells on the verge of the gray matter of the cerebrum are always storing impressions, and now and then throw the surplus out, often jumbled together and wildly distorted, as in a nightmare. There are two sides to the brain, and there have been many Jekylls and Hydes in real life."

But despite the scientific laying of the whole ghost story, specters remain pop-


ular, may be because, as science has discovered, even a "creepy" feeling can be highly agreeable. To satisfy that desire, the Martin part of the Tower of London was recently opened to the public, largely because it has a satisfactory ghost story connected with a one-time keeper of the crown jewels, who made his home there. On a Sunday night in October, the keeper of the jewels and his wife were seated at supper when a pale figure, like a glass tube filled with a dense white and blue fluid, emerged from the wall, floated across the room and started to seize the frightened woman, when her husband heaved his chair at it, and the ghost promptly disappeared. A short time later a sentry at the tower door saw a gray, shapeless thing approaching, challenged, and then lunged with his bayonet, following which he fainted and was found unconscious by the officer of the guard. He escaped court-martial for sleeping at his post when an officer in a near-by room reported hearing the challenge.

So the government opened the tower to visiting Americans looking for ghosts. The old Tower of London, where kings and queens and lesser folk were imprisoned, has more than its share of ghost stories. There are rooms where, on dark nights, weeping is heard. There are stories of the rustling of ghostly silks, as royal ladies flit over the cold stone floors. There

is a tale of an officer of the guard who climbed a ladder to peer through the window of an empty Norman chapel to investigate a ghostly light and saw a sight so terrible he never told what it was. That last is a not uncommon added touch to a number of ghost stories.

While the ordinary ghost stories—victims of bold bad barons and the dangerous dukes of the Middle Ages—are being quoted in the real-estate market at thousands each, there is one specter in England that probably would be worth a million if his home should be placed on sale. He is the royal ghost of Buckingham palace, the town castle of the king and queen in London. According to legend, the spirit of the mad king, George III, haunts the corridors of Buckingham of nights. Up and down the red-plush-draped corridor at one end of the royal home, in and out among the gilded chairs, the ghostly king is said to pace, pausing before the long windows to look out at the dancing shadows of the trees, a spectacle that always fascinated him in his lifetime.

Ghosts of men and women who appear and disappear silently or pause to rattle ghostly chains and exhale tremendous groans are more or less commonplace in the legends, but Windsor castle has a real novelty in the story of a pack of ghostly deer hounds that, according to people who claim to have heard them, bay with as musical a note



Eridge Castle. Home of Lord Henry Neville. Which Boasts the Ghost of a Young Girl Who Pined Away after Being Imprisoned in the Main Turret by a Bold Bad Baron of the Middle Ages



Hurstmonceaux Castle, Deserted, Boarded Up and Headed for Ruin, But with Its Legends of Ghostly Inhabitants in the Long Echoing Corridors Still Keeping Vandals Away

as they ever uttered in real life. To make the thing complete, the spectral hounds, instead of chasing the live deer in the great Windsor forest park, have ghostly prey, too, and are guided by a ghostly hunter. The legends say that a royal huntsman named Herne, dismissed from his post, hanged himself in an oak that was afterward known as Herne's oak. Then by mistake, the mad king, George III, he whose restless spirit is said to walk Buckingham palace halls at night, ordered the oak cut down in 1793, whereupon Herne the Hunter came back to haunt the palace and brought his hounds along.

As recently as last October, the specter pack was reported chasing the ghostly deer across the park. The wife of a farmer, living at the edge of the royal preserves, heard the old clock at Windsor strike midnight—the favorite moment for all ghost stories—and then heard the bay-ing of the distant hounds hot on the ghostly scent of their non-existent quarry. And, relates the farmer's wife, "exactly two weeks later, again at midnight, I heard the same thing. My daughter knocked at the door and asked, 'do you hear them?' Not having spoken to her of my first experience I said, 'hear what?' 'They must have been Herne the Hunter's hounds,' she replied."

Waldorf Astor, one-time American but now English, recently acquired the ghost legend of no less a person than Anne Boleyn, wife of Henry VIII, when he bought romantic Hever castle, in Kent. Under the frowning walls of the old stone pile flows the river Eden, spanned by a bridge across which, at each Christmastide, glides the alleged ghost of the lady who lost her head in the Tower of London. Hampton court, built by Cardinal Wolsey, is reported to be haunted by two queens and a prince of the church in the ghostly persons of Queen Jane Seymour and Queen Catherine Howard, two more of the eighth Henry's wives, and the cardinal himself, who died after being stripped of his power by his king.

For several years, according to the Hampton court legends, a spinning wheel was heard at night though no wheel could be found. The noise seemed to come from behind a dead wall; so, recently it was broken through, and there was the wheel, covered with the dust of several centuries. An old plan of the castle showed this had once been the private apartment of unfortunate Queen Jane.

Two women, both royal pensioners living in the castle, claimed they met Queen Catherine one night standing by the great staircase wringing her hands and sobbing



Ruins of an Ancient Scottish Keep on Wild Loch Aber, Still Said to Be Frequented by the Spirit of a Pictish Warrior Who Was Killed There in Battle Nearly 2,000 Years Ago

piteously, and her screams, they say, are often heard. Search of history discloses that the queen was sitting near the stairway some 400 years ago when she heard

the king had decreed her death. She attempted to rush to his presence, but was dragged back, screaming, by the men of the royal guard.

ALMOST TOTALLY DEAF HEAR WITH SOUND AMPLIFIER

Persons with but twelve per cent of the normal capacity for hearing are said to distinguish sounds through an amplifying apparatus recently demonstrated in New

York city. It is intended for permanent installation, not as a portable outfit, and picks up noises in any part of a room with such great amplification that an almost totally deaf person can hear them. The equipment is provided with vacuum tubes, ear phones, microphone and other radio devices. It is designed especially for use in the home or office.



Aid for the Extremely Hard of Hearing; the Amplifying Cabinet and Attachments

HUMAN HAIR OPERATES FOG GUN IN LIGHTHOUSE TOWER

How a slender ribbon of human hair has been adjusted to fire a fog gun whenever the mists endanger shipping, is one of the romances of engineering. This installation is found in the Antioch lighthouse tower on the southeast coast of France. Hair absorbs moisture and, under tension, will lengthen slightly when the atmosphere has a high degree of humidity. This is the principle which has been harnessed for saving of human lives. When fogs arise, the hair ribbon, about eight inches long and composed of 100 individual hairs, stretches sufficiently to close an electric circuit which, in turn, fires the gun at the rate of two flashes a minute. The explosions are made by igniting a mixture of acetylene gas and air. Sufficient "ammunition" is provided for 300 hours of continuous firing. Building the tower

Harper Cloutier Co. Boston, Mass.
1826
1036 Old South Building

Chas. William Harper

near Claron Island

was an engineering accomplishment in itself. Its foundation reaches six and one-fourth feet below the low-water line and the work could be carried on only a few hours each day; in all, forty or fifty times during the months from July to October when shallow boats could reach the site. The fog gun fired by the "hair trigger" was installed last fall and has worked satisfactorily since.

GROWING FROGS FOR FOOD

Bullfrogs at \$48 a pair and tadpoles forty-eight cents each—such prices are reported common in Japan where frog raising recently has become a popular industry since the legs have been in demand for food. Frogs have been purchased in large quantities from the United States and, since 1922, the imperial university of Tokyo has been working in co-operation with bodies here to promote frog culture. The common bullfrog is the one popularized as food. It grows to about eight inches in size, has the power to change color and spends two winters as a tadpole, reaching its full growth at seven years.

AUTO-TRUCK TANK FOR TROUT SAVES HANDLING CANS

Transporting live trout from the hatchery to the streams has been simplified by an Idaho man by means of a special tank on a one-ton motor truck. It will carry as many fish as could be contained in sixty cans, saves bothering with the separate containers and is emptied directly into the stream simply by pouring the contents through an extension at the rear. The tank has an aerator for emergency use, two ice hoppers, each containing 100 pounds, and holds 250 gallons of water. Fish have been delivered in it as far as 300 miles in a single day's drive and were in as good condition when they entered the stream as when taken from the hatchery.



Discharging the Live Trout Directly from Auto-Truck Tank; No Cans Need Be Handled

ROTOR IS HARNESSSED TO PUMP AS WINDMILL SUBSTITUTE



Rotor Windmill Rigged to Pump, near Berlin, as Substitute for the Ordinary Wheel

Successful adaptation of Flettner's rotor, the novel method of ship propulsion, to pumping is reported from Berlin. The rotor, mounted on a tower in place of a windmill, was rigged to operate a pump.

TREATING CREAM WITH LIME TO IMPROVE BUTTER

The use of lime to reduce acidity in cream for making butter was discussed recently by Prof. O. R. Overman, of the University of Illinois. The treatment, he says, prevents excessive loss of fat which would result from churning cream that had been pasteurized while very sour; eliminates undesirable flavors, and produces butter that keeps longer. The use of lime as a neutralizer of the acid also gives a small additional food value.

W. S. Meader, Meader
Trout Farms, Portneuf Valley

near Jungfernheide

all station in Berlin

1366

2063

New York Times 3/13/27

1681


From Illustrations Getting 12/2/26

All National Lime Association, D.C. 927-1518 & 744

PHONOGRAPH CHANGES DISKS AND PLAYS FOR HOUR

An hour of music without bothering to change the records by hand can be enjoyed from an automatic phonograph, which is fitted with a magazine that holds twelve disk records, and shifts each when it has been played and puts on the next one. With this convenience, whole sym-

Automatic Orthophonic



Automatic Phonograph, Showing Receiving Drawer for Played Records; at Left, Pressing the Reject Button, and, Below, Steps in Changing Records




phonies may be reproduced and special programs of dance or instrumental music. The apparatus is electrically operated. Removal of records is accomplished by a mechanical "hand" which tilts the completed disk off the turntable into a velvet-lined receiving drawer, takes off the next one from the magazine and deposits it in playing position. The tonearm swings to permit both movements. When the last rec-

ord has been completed, the motor is shut off automatically. By pressing a "reject" button, any record may be ejected from the turntable at any desired point in the music, and the instrument may be stopped at any time or operated without the automatic feature when single records are to be played. The magazine is adapted to ten-inch or twelve-inch disks, but the two cannot be mixed.

RUBBER LUMBER FOR AIRCRAFT SUBSTITUTE FOR WOOD

Numerous points of superiority are claimed for a rubber lumber which is intended to replace wood, metal and other materials in many uses. Its strength and lightness commend it for aircraft construction, but it is suited for various other purposes as well.



Cross Section of a Rubber "Board"; Outer Layer of Fabric May Be Replaced by One of Metal if Desired

Outwardly it resembles ordinary hard rubber, but in reality it is quite different. The central portion consists of hard sponge rubber with minute air spaces. On each side of the core is a layer of denser rubber compound, and the external surface consists of strong fabric cured as a unit with the section on which it rests. If desired, the fabric may be replaced by metal, such as duralumin, and may be

B. F. Isodrich Co., Akron, Ohio.

105 W. Monroe - Chicago


1925 S. Michigan - Chicago

1899

applied on one or both sides of the rubber board. Tests have shown that the material is stronger than wood, can be worked up into different shapes, does not split, can be softened under high temperatures and loses none of its strength when cooled. Its natural flexibility enables it to withstand great strain, such as encountered in an airplane. It does not absorb moisture, resists corrosive action, and, when used in water, barnacles are said not to settle upon it as readily as upon wood. At the present time, the cost of the rubber lumber is considerably higher than corresponding sizes of wood, but this drawback is expected to be eliminated when production reaches a large volume.

PORTABLE FURNACE-TEST SET REDUCES FUEL LOSS/887

For rapid and accurate analysis of combustion conditions in furnace fires and the location of boiler troubles, a portable testing outfit is intended to aid the service man and engineer. It includes instruments for telling what kind and proportions of gases are going up the flues, temperatures of the gases, and a draft gauge that shows if the fire is receiving the proper amount of air. Accurate regulation of dampers, reduction of stack losses and location of leaky settings, broken baffles, and other troubles, are possible with the testing outfit. The case can easily be slipped into an automobile or underneath a train seat, weighs less than twenty



Testing Set Attached to Furnace for Measuring Gases, to Show How Fuel Is Being Consumed

pounds with all instruments, and there is room for extra tools and overalls.

*The Jas. W. Hays Corp,
Michigan City, Ind.*

1620



Another Triumph for Concrete Construction, Huge Mine-Hoist House in Holland

CONCRETE MINE-HOIST HOUSE INSURES RIGIDITY

In order to have a more rigid structure, reinforced concrete was chosen for the material in a hoisting house at the pithead of a mine in Holland. It is 179 feet high, and more than 340 tons of steel rods, plates and iron were used in the building.

PLANTS GROW IN NIGHT/939

With the aid of special measuring apparatus, Prof. F. M. Andrews of Indiana university has found that the stalks of some plants grow more in the night than they do in the day. The leaves showed as much development in the light as they did when the sun was down.

☛ Nearly a third of the homes in the United States are without bathtubs, according to a survey.

*at the National University
at the University of Holland.*

431 D. Harborn Chicago



Personal-Appearance Mirror for Bus Employees; Attention Is Called to Details Often Overlooked

MIRROR FOR BUS CONDUCTORS CHECKS DRESS POINTERS


Recognizing the importance of neatness in the personal appearance of its employees, a motor-coach company has adapted a lettered, full-length mirror for the special use of its men. Attention is called to such details as clean collars, polished shoes and leggings, pressed uniform and a shave, so that conductors and others, by checking their reflection with the "gauge," can tell at a glance if they measure up to standard. The plan saves time and enables each man to act as his own "inspector."

LIVE IN A CAVE FOR TWO YEARS TO STUDY THE SUN


1913 Housed in quarters arranged in a natural cave on the rim of a mountain in southwest Africa, two observers for the Smithsonian institution have started a two-years' vigil to delve deeper into the secrets of the sun. A principal object of the investigation is to gain further data as to the relationship between the sun's variation and the weather. The observatory is the third established in connection with the Smithsonian's study of solar radiation, and the location was selected because of the high altitude and consequent decrease of error due to atmospheric losses, freedom from clouds and the wide distance from other stations, far separation being necessary in order to obtain entirely independent observations. The other stations are located at Table Mountain, Calif., and Montezuma, Chile. For their diversion, the observers have taken along a large supply of phonograph records and will also do some hunting.

CORK PULLER STOPS BREAKING AND REMOVES CAPS

1439 Corks are lifted out of bottles with ease, and safety, and without damaging the stopper, by the aid of an all-metal puller which has three long spikes. These are driven into the cork, the top is given a gentle twist and the cork comes out complete and undamaged. The bottle is not jerked or pulled, so that there is little danger of spilling the contents. Broad heads on the spikes keep them from falling out of the puller, which also has a curved notch for prying off caps. To remove milk-bottle caps, one of the spikes can be used.



35 cents
The Unique Necessities Co.
Baltimore - Eden St.



Charging a Peppermint Still on an American Farm with a Load of Mint Hay; a Canvas over the Wagon Bed Catches Every Leaf Broken off the Stems in Transit, So There Is No Waste

Bringing a Japanese Industry to America

Healing Mint Is Successfully Raised for Menthol in Latest Farming Venture in California

By H. SIBLEY,

1240 S. Figueroa
Los Angeles, Calif.

FOR many years Japan has produced the bulk of the world's supply of menthol, which is made from the oil of the native peppermint.

Although America is one of the largest consumers of menthol for use in healing salves, cough drops and similar preparations, it is only within the past year that Japanese oil has been produced on anything like a commercial scale here.

Preliminary experiments in California were so successful that considerable acreage has been planted to the imported mint, and a number of large stills have been put in operation. It has also been grown in Indiana, Michigan and North Carolina, as well as in Oregon. The Japanese mint must not be confused with the American black-stem mint, raised so extensively in Indiana and Michigan. The Japanese va-

riety has a high menthol content—sometimes as much as seventy per cent.

In spite of the vastly superior and efficient American methods of cultivation and distillation, and the greater yield per acre, Japan is still a serious competitor because the low labor cost is in her favor. In Japan, over three-fourths of all the mint is grown on the northern island of Hokkaido, where only one crop is possible a year. Here three crops have been raised and each has yielded more crude oil than the corresponding acreage in Japan.

Japanese methods present a strange contrast to the American way. When it is in blossom, the harvesters—usually girls—cut the plant with a curve-bladed knife, similar to the old-fashioned mid-west corn-stalk cutter. The plants are cut three or four inches from the ground, and then



Japanese Peppermint at Harvest Time; the California Variety Is Much More Heavily Leaved, Yielding More Oil

hung, upside down, on a rack. This is much like a fence with a narrow thatched roof. Here the mint is cured, a process which in that humid climate requires about four weeks. In California it is cut with a horse-drawn mower and cured in windrows in about thirty-six hours. It is then picked up in the morning while the dew is still on it, preventing the leaves from shattering off.

The Japanese still is more primitive than a moonshiner's outfit. It consists of a wooden tub over a shallow iron pan, and has a removable lid which is held as nearly steam-tight as possible by cords. A copper pipe carries off the oil-laden steam through a coil condenser submerged in a tall wooden tank. The water in the tank is replenished by hand, with a bamboo bucket. Dried bean vines, straw, leaves and twigs constitute the only fuel, and it is necessary to fire all day and night to distill a single charge of about eighty pounds of mint hay. The average American still will run through one charge or half a ton in less than two hours.

Crude oil from the condenser drips into a bucket along with the distilled water, and as the oil quickly rises to the top, it is readily skimmed off. The farmers all through Hokkaido do most of their distilling in the idle winter months, producing from a few pounds up to two or three hundred, according to the size of their crop. This is then taken up by brokers,

who in most cases have contracted for it at the time of planting, and have advanced the farmers money for living expenses.

Some interesting experiments have been made with the exhausted charges of mint hay after it has been distilled. For a time its disposal was a problem, for it could not conveniently be plowed under for fertilizer because of the long, tough stems. However, by accident it was discovered that live stock eat it readily—sheep in particular. Cows like it, but it has not proved a good diet for milk production. Horses eat it greedily, and at least one team, which subsisted upon it almost entirely, grew fat in a few weeks.

With a bright future, the Japanese-mint industry is the very latest thing in American farming ventures.

LOCK STRIP IN CONCRETE FLOOR TO PREVENT CRACKING

1821 In place of unsightly scored joints, a patented metal anchor strip for concrete floors allows compensation against cracking and improves the appearance of the finished surface. It is especially adapted for use with two or more colors and for flooring consisting of an aggregate of crushed marble and cement, as it prevents scoring and chipping between sections.



Metal Strip Being Applied to Composition Flooring; the Locking Units Are Seen at the Side

*The Brantel Marble Co.
Webster Ave - East River
Long Island City, N.Y.*

French Clock
near Croydon Aerodrome, England.



Where Each Plant Has Its Separate Greenhouse; Globe-Covered Garden in England for Producing Early Vegetables; the "Bells" Are Easily Removed for Tending the Growth

GARDEN UNDER GLASS BELLS YIELDS EARLY PRODUCE

Bell-shaped glass covers, one for each plant, are used in a vegetable garden in England. They are considered more successful in some respects than the usual hotbeds, as separate plants can be given special care, the "bells" are easily carried about and lifted off, and no permanent structure is needed.

TWO-BLADE WINDSHIELD WIPER CLEARS ENTIRE GLASS

Driven by motor suction and controlled by a switch on the dash, directly in front of the driver, a double-bladed windshield wiper cleans the entire glass, and, when not in use, occupies a position that will not interfere with his vision. The blades are fixed in a vertical plane and move from side to side, the lateral action permitting moisture to run downward to aid in ridding the shield of snow or rain. Each blade cleans half of



Two-Bladed Wiper Installed, Showing How It Keeps Entire Surface of the Glass Free from Snow or Rain

the glass. The motor is in the shape of a long tube which is fastened under the visor just the width of the shield.

ELECTRIC EYE TO COUNT AUTOS DOES WORK OF POLICEMAN

One of the latest adaptations of the photoelectric cell is for the purpose of counting the number of automobiles that pass a given point in a day. Installed on a lamp-post on one side of the street and exposed to a source of light from the other, it serves as an accurate traffic register, saving the work of a special policeman, or other attendant, for the task. The counting is done as the passing automobiles interrupt the beam of light to the cell. Their shadow causes sufficient reaction to operate an automatic counter, and a faithful record is thus kept for each day. Other uses for the cell include color matching, sorting cigars and certain vegetables, transmitting photographs and motion pictures by radio, and recording time signals.

Washington, D.C.

Emt. S. D. Winters, District National Bank Bldg.

*Re. 16322 Abs. 13, 1926.
N.Y. 6, 1926 pend.*

*Trico Product Corp.
624 Elliott St. Buffalo, N.Y.*

*Ed. A. Howard.
Chief, U. S. Bureau of
Entomology*

tures which otherwise would go unnoticed in the darkness.

BUGS SAVE RANGES IN AUSTRALIA

Insects from Texas and South America are being used with great success in Australia to devour the prickly pear that infests the live-stock ranges. A cochineal bug, a red spider, a moth larva and a sucking bug have been enlisted in the warfare against the plant with such good results that the spiny growths have been reduced to a state of utter collapse, according to reports. An additional encouraging feature is that the insects are not likely to attack crops or other desirable vegetation. A possible source of trouble is seen in a kind of beetle that feeds on grass-eating

Chicago daily news. 10/12/27




Glowing Terraces of the Night; Illuminated Upper Stories of the New Paramount Theater Building in New York City

LIGHTS ON THEATER TOWER RIVAL THOSE OF STREET

Like the buildings, the brightest spots of the modern city are reaching toward the sky. This is shown in the illumination on the crest of the Paramount theater building in New York. Its pyramid tower is floodlighted at night under the brilliance of powerful rays that emphasize the evenly back-set outlines of the upper stories and seem to dim the glow of the signs and displays on Times Square below. Entirely aside from the viewpoint of picturesqueness and beauty, the installation of such a lighting system is considered sound and practical advertising, since it calls the attention of night crowds to the building's fea-

mealy bugs, but it is believed that, by the time these insects are exhausted, the prickly pear will have been conquered, so no great harm will be done if the beetle attacks the helpful bugs which have been introduced to eat the plant pest. A similar experiment, attempted in Hawaii, was not wholly successful, because the insects also attacked a valuable plant.

AUTO TRUCK SERVES AS TRAIN ON BRANCH RAILROAD



"Flyver" Fast Mail on Missouri Railroad; an Auto with Flanged Wheels Makes Prompt Deliveries

Fitted with railway-car wheels, an automobile truck is run upon a small branch railroad in Missouri to carry the mails. The cost is only a fraction of that required for a steam train, and the schedule is said to be almost as fast.

*Cont. Charles Phelps
Cushing 138 W. 65th St. N.Y.C.*

HUNGER BEATS MOTHER LOVE OF UNIVERSITY'S RATS

Hunger is a more compelling motive than either mother love or the desire for companionship, Dr. F. A. Moss, of George Washington university, discovered when he made a series of tests with rats. The reactions of the rodents, he believes, fixes rules that also will apply to other animals and, possibly, to man. Dr. Moss used a cage built in three parts, with the center section so wired that a rat passing through it received a slight electric shock. Ten rats were placed in one end and food in the other. Within seventy-two hours eight of the ten risked the shock to reach the food. In the next experiment mother rats were installed in one section and their young in the other, but only three of the ten mothers would pass the charged wires.

BRANDING TORCH MARKS TIRES - BATTERIES AND CUSHIONS

To identify tires with initials or mileage records and to stamp batteries, cushions and other accessories, a hand torch holding a pint of fuel is also equipped with a disk having ten numbers and separate letters. They become heated in a few minutes and the torch may be used steadily for any combination of numbers desired, as all are hot.



Stamping a purchaser's initials on a tire has been found an effective way to increase trade, and the torch is well suited to such a purpose.

STREET-CAR WINDOW HEATER KEEPS GLASS CLEAR

Electric heaters on the sills of windows in street-car vestibules have been found effective in keeping the glass free of snow and frost, so that the motorman has a clearer view. The heater occupies but small space and requires little current.



Looking into the Portable Plumbing Shop Which Has Space for More than 2,000 Different Articles

PLUMBERS' "PIE WAGON" CARRIES MANY TOOLS AND SUPPLIES

Men from a Chicago plumbing concern are not likely to arrive on a job without the necessary tools and equipment, for they travel in autos modeled after a pie wagon with bins and shelves for more than 2,000 different articles. The firm has seven of these cars.

QUICK-ACTION CIGAR LIGHTER HAS WEIGHTED BASE

Occupying but small space on the counter, an electric lighter for smokers has a weight in the base to prevent tipping over and the element heats up almost instantly when the button on the side is pressed. It is designed to consume less current than the usual type.



1343 d. wearborn, Chicago

Consolidated Car
Heating Co.

Verhot Mfg. Co. 619 d. 10 St. Maywood, Ill.

1490

C. J. Euckman Co. 584 7 d. Halsted

Millhamer & Gray
8 d. Halsted (Chicago)
645 W. Washington

General Appliance Corp.
120-8 St.

Cont. d. ra. W. esulamy
1527 N. Mariposa Ave
946 Hollywood, Calif.
1561

POPULAR MECHANICS

Chicago Daily News
3/15/27



To Catch the Eye of the Home Buyer; Real-Estate Sign in Los Angeles Which Emphasizes Direct-Purchase Plan

IMITATION TREE STUMP USED AS REAL-ESTATE SIGN

Prospective house and real-estate buyers in Los Angeles are attracted by an imitation stump on which is mounted a model of a cottage and an appropriate sign, erected by a dealer. The device emphasizes the idea of direct transaction from tree to finished dwelling, and is further decorated with imitation woodsmen's tools and a realistic cut as though the stump were being felled.

IRIDIUM IS HARDEST METAL THALLIUM THE SOFTEST

Iridium, a metal belonging to the platinum group and often used on the tips of fountain pens, is the hardest pure metal known, recent tests have shown. Molybdenum is next and tungsten third. Of the common metals, nickel is the hardest, ranking fifth. The tests did not include alloys, such as those of steel with a high percentage of carbon, which rank higher


than any. The tests showed that thallium is the softest metal, being twenty-fourth on the scale, lead was twenty-third and tin twenty-second. Gold ranks as number eighteen, silver fifteen, copper eleven and iron ten.

Portable Electric Saw SAVES MUCH TIME AND WORK

With an electrically operated crosscut saw now on the market, two men are said to be able to do the work of seven or eight with handsaws, and the outfit is adaptable to a wide range of tasks. A

feature of the saw is the arrangement of the teeth. These are made in links and their action is the same as that of a rigid saw. On the cutting side, they travel toward the motor so that they keep the saw against the work, eliminating the need of "dogging" or fastening. Control is afforded through a foot switch,

and the cutting direction of the teeth can be reversed to equalize wear and reduce the frequency of filing. The saw operates on 220-volt alternating current from a power circuit or from a portable motor generator. It is especially adapted to trimming timber, cutting posts and mine props, notching railway ties, cutting piling and similar work. The outfit is made in



Link Saw in Action, Showing How It Can Be Used for Cuts at Angles; the Teeth Travel toward Motor on Cutting Side

three sizes, weighing from sixty-four to 104 pounds.

Reed-Prentice
Corp. Worcester
Mass.

Made by A. Mallory
Announced in Nature

2059

Aluminum fourth

Motor Cops of the Sea

By H. H. DUNN

2722 Prince
St. Berkeley
Calif

OUT where the west ends, and one state pulls \$25,000,000 worth of food out of the sea every year, modern inshore piracy, parasitic on this large industry, is being checked by policemen mounted in motor-boats. Just as deep-water fishing is one of the most picturesque of all industries—to the landlubber, at least—so life on the boats of the fish patrol of the California state fish and game commission compares for dash and danger with the life of a Texas ranger or the business of being a prohibition patrolman along the Canadian border.

There is a romance about the sea and its men, some of which has been passed on to the deputies of the fish patrol in the more than a quarter of a century of the existence of this water police force. They deal with pirates in fast boats who



Captain Bouton, Seventeen Years in the Fish Patrol, at the Helm of His Modern Pirate Chaser

seek to rob the commercial fishermen; with outlaw fishers who use seines with meshes smaller than the law allows, and who fish during closed seasons; with fishermen who take in nets fish whose capture is permitted only with hook and line; with hunters who shoot ducks and geese for market, and with game-law violators of all kinds.

The "beat" of the fish patrol is the whole state of California, wherever there is water deep enough to float their motorboats. Jack London wrote a book about them, away back at the beginning of the twentieth century, called "Tales of the Fish Patrol," and while few of the old-timers mentioned in that book are still on the patrol, the modern pirates of San Francisco bay and its tributary waters have so increased that the patrol is larger, stronger and busier today than it ever has been. Those who seek to prey on the fishing industry of California, and to loot its wild life, are increasing in numbers, in spite of the greater number of law violators captured every year.

These are some of the facts Charles Bouton and Bert Laws,



With This Specially Designed Grappling Hook, the Game Wardens Defeat Poachers Who Sink Their Illegal Nets to the Bottom

captain and crew, respectively, of the forty-foot motor patrol boat "Quinnat," told me as we pulled away from Fishermen's wharf and its 500 fishing boats, one warm morning. Crossing the channel that leads out through the Golden Gate, I learned that "Quinnat" had been in service for seventeen years, "without having so much as a shim removed from her bearings," according to Laws.

Forward, in "Quinnat's" heavy but capacious hull, were quarters for six men, but most of the space aft was taken up with the large and powerful motor, cooking accommodations, and the racks of rifles and shotguns—for not infrequently a fight with armed poachers is thrust upon the members of the patrol. Ability to shoot being one of the qualifications demanded of the deputy commissioners, however, most of the poachers, if cornered, surrender, and the battles of ten or fifteen years ago are becoming memories to most of the patrolmen.

North by east, across San Francisco and San Pablo bays, and into the flat, shallow, reaches of Suisun bay, we held, until we were in a maze of islands, overgrown with wild rice, concealing the mouths of sloughs—the retreats of the poachers, illegal sein-

ers and game-law violators. Presently, we heard what sounded like machine-gun fire, and out of the fog came a low, gray, almost invisible craft, spreading the water in a wide wake of foam on either side as she rounded to and lay alongside "Quinnat," which Laws had brought to a stop. In the newcomer was a middle-aged man, William H. Armstrong, veteran deputy commissioner, member of the fish patrol since 1901, and master of the thirty-miler "Hunter," recently added to the fleet.

Armstrong and Bouton conferred for a moment; "Quinnat" moved ahead at her maximum of twelve miles an hour, while "Hunter" lagged behind. We rounded one island, passed between two others, and heard the yammering of a fleeing motorboat, the foam of whose wake marked the still waters of the bay. Bouton pulled three sharp blasts out of "Quinnat's" air whistle, and we held on, to where wide ripples yet marked the place where something had been dropped into the sea.

We came to a stop. Laws stepped out on the bow of the patrol boat, an odd, five-pronged, weighted hook, rove with a chain leader into eight or ten fathoms of line, in his hand. This he dropped overboard, sinking it to the bottom, some fifteen feet



Foe of the Fish and Game Poachers, the "Quinnat" Scouts the 400 Miles of San Francisco Bay Shores on the Lookout for the Bay Pirates Who Seek to Elude the Game Laws



Fishermen's Wharf at San Francisco, Before All the Fleet Had Been Motorized; the Plans for the Double-Ended Boats, with Their Queer Lateen Sails, Were Brought from Naples and Corsica

down, and dragging it back and forth with experienced hand until he found what he sought, then lifting it inboard. As the hook came up, a brown seine came with it, nearly 2,000 feet of expensive netting, sunk to the bottom with blocks of cement, whose writing of ripples on the surface had been read instantly and clearly by both the patrolmen.

Out came gauges, and the meshes, measured, were found to be nearly an inch under the legal limit, and thus capable of taking small fish protected by the commission. Meanwhile, the whistle calls had been answered. A long, wide-beamed but fast fishing boat, half filled with striped bass, illegally taken, came round one of the islands, and, immediately behind her, Deputy Armstrong in "Hunter." Leaning forward out of the cockpit, one hand on the wheel and the other well equipped with a heavy automatic, Armstrong was running his engine controls with his foot, the while the three men in the captured boat obeyed his orders.

Followed by the "Quinnat" alone, the

poachers would have escaped easily, but they were no match for the thirty-miler. Most of the bass were dumped back into the bay, where many of them swam off uninjured. A few were kept for evidence, as was the net, worth at least \$500, and probably actually costing twice this amount. The larger patrol boat took the poacher in tow, after transferring her crew to her own decks, and we started back for San Francisco. Armstrong, in his rightly named "Hunter," slipped back into the fog, to lie in wait among the islands for another pirate.

Later in the day, he came in driving a large power dory, with four men, whom he had caught shooting ducks from their boat—double violation of the law, since the duck season had closed, and there is a ban on hunting game birds from a power boat on any waters in California. During December and January, last winter, "Quinnat" and "Hunter," and the three men on duty with them, have taken illegal seines valued at more than \$3,000, all submerged by means of weights when their owners

fled, but picked up by the specially designed drag with rounded hooks, which do not catch on snags, but gather the meshes of the net.

By night, the patrol boats move through the sloughs and tributary bays, and around the mouths of streams emptying into the bay. All their lights are out, and they seem to "feel" their way, never going on the banks, or meeting with accident. The patrolmen watch for the reflection of the lights on the boats of the poachers, or the sounds of their motors, and, with muffled engines, try to creep upon the law violators, and to take them at work. According to M. S. Clark, captain-in-chief of the patrol, the men on the boats know every foot of the more than 400 miles of coast line of San Francisco bay, and are familiar with the sea for fifty miles outside the Golden Gate.

After the poachers are captured, or the market hunters taken, with their seines and fish or their decoys and ducks, the work of the fish patrolmen has just started. Then they must deliver the lawbreakers to the nearest judge, or, if far up the bay,

to some landside justice of the peace, and convince the court that the captives must be held in sufficient bond to insure their appearance at trial. Thereafter, when the trial comes along, they must present the evidence to judge or jury in such form and in such quantity that the guilt of the arrested men is established and conviction obtained—and it is only on rare occasions that they do fail in this.

More than 5,000 commercial fishermen, operating more than 3,500 boats, are licensed by the state of California, and there are some 12,500 persons employed in the industry. The patrolmen must be sufficiently familiar with these men and their boats not to mistake one of them for a poacher and not to interfere with the bona-fide licensed fisherman going about his legitimate business.

Without motorboats and other modern mechanical equipment, the fish patrol could not succeed, and this year two or three more speed boats are to be added to it. Then the buccaneers of the fishing industry of California will find the law closing still tighter upon them.

AUTO-TRUCK SERVICE RECORDER REDUCES DAILY WASTE

Few operators of motor trucks keep an accurate record of the actual time the vehicle is in service each day, idle time, waiting, and other data, upon which to base a close estimate of running costs. This information is supplied by a simple indicator which tells the story of the truck's movements every hour of the day. It is essentially a clock arrangement with a swinging pendulum actuated by the swaying of the vehicle. This action causes a sapphire point to scratch off a mark on a wax-coated card which bears the hours of the day printed in a circle

like a dial. The marker is set to correspond to the time of the day; the clock movement is wound, a chart is inserted and the gauge closed. It requires no other attention until the record is to be taken out.

Due to the swaying of the truck, the period of actual running is designated by a wider mark on the dial than the thin line which indicates stationary intervals. If the motor is left running while the truck is stopped, that is shown by a mark slightly narrower than the running line, yet wider than the stop tracing. The device may be utilized on

various machines, such as looms, knitters, locomotives, presses and many other units for keeping a record of their operations.



Attaching the Truck Service Recorder to the Cab, and, at Right, One of the Charts, Showing Time of Operation

The Service Recorder Co.
Hanna Bldg. Cleveland, O.

3124 W. 31st Ave. Chicago

STRUCTURE OF HAIR GIVES CLUE TO PERSON'S IDENTITY

In the discovery that hair is a certain mark of an individual's identity, scientists have an additional means of detecting the criminal. Examined under a microscope, a hair is seen to have fine, overlapping scales like those of a fish and a canal in the center, containing the coloring matter. No two persons have hair structure exactly the same, some of the chief points of identification being the size of the hair and the central canal, and the scales.

STEEL CABLE IN WINDY CANYON PROTECTS PEDESTRIANS

In one of the narrow passes on the island of Oahu, H. I., the wind blows with such force that a steel cable has been attached to the rocks to afford a handhold for tourists. Before it was installed, many pedestrians had been blown off their feet and one man killed. The portion where the wind attains its greatest velocity is short, scarcely more than fifty yards, and as the canyon widens out beyond that, the speed is much diminished. Winds at fifty and sixty miles an hour are recorded almost daily at the narrowest point. Automobiles traveling the motor road near by are frequently damaged by the gale, which is strong enough at times to tear tops off and break windshields.



Rounding the Windy Point Where Gales Blow Almost Constantly; Cable Gives Pedestrians Handhold



Cameo Portrait Cut in Sea Shell; Twenty-Five Tools of Various Sizes Were Needed

1469

PORTRAIT-CARVING ON SHELLS LATEST ART NOVELTY


Cameo portraits, cut on large sea shells, are produced by a Los Angeles craftsman who has found the work a pleasant although somewhat difficult hobby. The chief trouble is that the shell is very brittle, and a chip or a break at any time may ruin the entire carving.

SPORT OF CRICKET FIGHTING FAVORITE IN CHINA

Matches between specially bred and trained crickets arouse as much interest in China as boxing bouts do in other countries. The insects are weighed in on miniature scales before the battle, placed in an earthenware jar and, if slow to fight, are incited to the conflict by tickling them on the legs or head. Once started, the combat becomes fast and furious, and is often fought to a fatal conclusion. The name of the victor is inscribed in gold on an ivory tablet, which is presented to the proud owner. Cricket fanciers take elaborate care of their pets, providing them with cool jars, artistically fashioned, in summer and fitted with tiny porcelain feeding dishes and clay beds. In winter, they are housed in specially grown gourds and sleep on cotton pads.

Continental Edition
London Daily Mail

Edinburgh and Midlothian
 Moller Esymkhana
 Scotland



Rider Trying to Dodge the Flood When Tilting Bucket Is Capsized in New Scottish Novelty Race

TILTING BUCKET ADDS NOVELTY TO MOTORCYCLE RACE

Motorcycle meets in Scotland have a novelty in the form of a tilting bucket which drenches the luckless rider who springs the trap, the degree of drenching depending upon the speed with which he passes under and gets clear. The bucket of water is mounted on a revolving board, and is normally held upright by a weight slung underneath. When the motorcycle passes under it, springing the

trap, the position is reversed and a couple of gallons of water are poured on the rider.

MORE RISK IN PLAY THAN IN WORK

You are more liable to injury during your hours of recreation than in working periods, according to the findings of an official of an eastern insurance company. A steel worker straddling a girder high on a building runs less risk of being hurt than when hanging a picture at home from the top rung of a stepladder. The reason, this official explains, is that when a man is at his occupation, he is on the alert against danger. When at play, he relaxes, thinks of other things and is less careful when hazard is involved. From data extending over many years, insurance rates have been graded according to classifications based upon the likelihood of injury. The classes range from 1 to 5, the first being those in the least danger and the last, those exposed to the greatest hazards. In addition to these, there is the "FF" group or those in extra dangerous call-

ings. Baseball players are in this division as are soldiers during war time, aviators, circus performers, acid makers, balloonists and consuls to foreign countries. Policemen on beats are placed in class No. 4 and firemen in division No. 5. Insurance officials estimate that the automobile has increased accidents in America between thirty-five and forty per cent in the last ten years. With regard to health insurance, the doctor who is exposed to all sorts of infection during his daily work, is the most likely to contract disease. Dentists

1926

are also poor risks and so are ministers. The banker is comparatively safe. It has been found that, during times of business depression, susceptibility to disease soars regardless of occupation. The age at which the liability is greatest is between forty-five and sixty, when the vitality of youth is no longer present to throw off ailments.

BEETLES SEALED IN GIANT TREE TWELVE HUNDRED YEARS, 2085

That no appreciable changes have occurred in a species of wood-boring beetle in the last 1,200 years is indicated on comparison of live specimens with dead ones which were recently found hermetically sealed in a giant Sequoia tree. The insects apparently had entered the wood after it had been struck by lightning. Some failed to emerge and were imprisoned by the new growth that formed over the lightning scar. The time they entered the tree was computed by counting the annual rings that had grown outside of them. Naturalists are not surprised that the specimens were the same as those found alive today, for beetles are regarded as a "conservative lot," and 1,200 years is not a long time, geologically speaking. Species that were sacred to the Egyptians have shown no signs of change in thrice that time.

STREETS OF OLD ROME CLEANED BY MODERN SWEEPERS, 1905

Contrasts between the old and the new are plentiful in Rome, and one of the most noticeable is the modern, motor-driven street sweeper, cleaning up dust and dirt from pavements that were laid in the time of the emperors. One of the most popular types of brooms is mounted on an automobile chassis. It is of the rotary kind, similar to those used in this country.



Ancient and Modern Rome in Striking Contrast; Motor Street Sweeper on Historic Highway

21 cat



Comparing Smoke from Chimney with the Testing Chart, to Determine Density

DENSITY OF SMOKE IS TESTED WITH SHADED CHART

How much can a chimney smoke and stay within the law? Many cities have expert observers to answer the question, and one of the most efficient guides they employ is a test by which the density of the smoke is gauged. It is simply a series of black lines drawn at right angles on a white background and so arranged that the observer notes different percentages of blackness when the chart is placed at a distance of fifty feet. The tester is hung on a level with the eye and in line with

the chimney. By comparing the shade of the smoke with that suggested by the most closely corresponding section on the chart, the inspector is able to determine, with a fair degree of accuracy, if the anti-smoke ordinance is being observed. The areas on the card are plainly marked to indicate percentage of blackness.

Used by Bureau of Mines
Discovered by Dr. G. V. Van Dine,
Professor Entomology,
University of California

1785



Photo Diagram Showing How a Box Kite, an Oatmeal Box and a Fisherman's Reel Helped Solve the Problem of Spacing Left-Over Trees So Their Seeds May Be Blown About to Accomplish Natural Reforestation



Counting the Seeds in Sixteen Square Feet After They Have Been Released High in the Air from a Box-Kite-Carried Container; Some Seeds Were Blown Two-Thirds of a Mile Away

Kites Solve Problem of Tree Seeds' Flight

Forestry Tests Imitate Nature and Disclose Extent to Which the Wind Can Aid in Reforesting Logged-Off Land

WITH a box kite, a fishing reel and an ordinary pasteboard oatmeal carton, forestry officials in the west have solved the question of how much the wind can do toward reforesting cut-over land by spreading seed from standing trees. With the homemade apparatus, they sent half a million seeds of different species up in the air to the height of an average tree and then released them to be blown away, while gauges on the kite and ground gave accurate data on wind velocity.

After the seeds had settled, the forest experts picked up all those found in measured areas at different distances and computed the general distribution. To facilitate the recovery of the seeds, they worked in the snow on a wind-swept plateau with the thermometer well below zero. The seeds were plainly visible on the white ground, but the crew suffered considerably from the intense cold.

The tests, which were originated by

the Pacific Northwest forest-experiment station, at Portland, Oreg., were carried out by the U. S. forestry service in co-operation with forestry officials of the province of British Columbia, so that the results could be applied on both sides of the international line. They discovered that a single tree left standing could distribute its seed as far as 3,500 feet away in a twenty-three-mile wind.

The apparatus used included a big-winged box kite, capable of lifting fifty pounds in a fairly strong wind. The kite was let out from a reel of fine steel piano wire, and carried aloft, attached to its tail, a homemade weather vane to show the wind direction and a wind gauge to record its speed. An oatmeal carton, hung upside down beneath the kite, carried the seeds, the cover being fastened with fine thread. A stout fishing line was arranged to break the thread and release the seed, the line being payed out from an ordinary

W. M. Mungier, Director Forestry
Experiment Station
Portland, Ore.

fisherman's reel. Besides the seed, the box contained a lead weight, attached to a cloth streamer, so that it would drop



Six Types of Seed Used, Red Cedar, Douglas Fir, White Pine, Yellow Pine, Noble Fir and Western Hemlock

to the ground directly under the box at the moment the seeds were released, and furnish a marker from which to measure the distance to the finds.

In operation, the kite was let out, and the fishline, marked with tabs at twenty-five-foot intervals, was fed out at the same time. When the tabs indicated the seed box was 200 feet above ground, the height of an average tree, the reel brake was applied, the taut line broke the light thread on the box cover, and the seeds were whisked away by the wind.

Seed counts were made every hundred feet down wind from the point of release, all the seeds recovered in the space inclosed in a four-foot-square frame being counted. The tests revealed that the shape of the seed had more influence than either size or weight. Light western-hemlock seed and the comparatively heavy western white-pine seeds made the best distance records, about 4,000 feet. Besides these two varieties, seeds of the western red cedar, Douglas fir, western yellow pine, and the noble fir were used—six different varieties in all.

At the start of the tests, the forestry experts believed the wind might blow the seeds from 200 to 300 feet. In a six-and-a-half-mile wind, however, seeds were found as far as 1,800 feet away. None of the seed fell within 150 feet of the point of release, but it was discovered that the number that came down at the 150-foot mark, dropping out of the race at the start, was about the same as the number that flew 3,500 feet. Another peculiarity found was that the seeds, instead of covering a

fan-shaped area, as had been expected were distributed in an almost straight path. While the experiment showed that a kite might be used to reseed large areas, the real purpose was to obtain information to guide lumbermen in leaving occasional trees to accomplish natural reforestation. As the prevailing winds at seed-dropping time are known, it will be possible to space the trees left so that their seeds may be expected to cover the entire area.

SOUTH SEA MYSTERY SOLVED

137² IN FINDING LOST IDOL

Sought for several years, the wooden image of the "shark goddess" of the Gilbert islands, the only one in existence, has been found and is now in the possession of Frank Burnett, explorer and collector of South sea relics. Discovery of the figure reveals a fascinating story that goes back into the centuries and has high lights of adventure and mystery like those

associated with the history of lost jewels and other treasure. Briefly, the story is this: Centuries before the white man came, the shark was a god to the natives of the islands in the south Pacific. Altars were built to it and food offerings made, some of the creatures becoming so tame that they thronged the beaches. There lived a powerful chief whose daughter was believed to be immune from the sharks and who could impart the



same gift to others. Shortly worship of her supplanted the old gods. At her death, her likeness was carved in a block of rare wood brought from the east. The idol was placed in a special house and was known as the "Shark Woman." In

1892, a British captain found it enthroned in the "House of Skulls" on the island of Apamama, a temple that was used by a chief as a receptacle for the heads of rival chieftains whom he had slain. Before the House of Skulls was destroyed by official order, the priest who had attended the idol, learned of the forthcoming destruction by secret means, revealed the hiding place to a white man who had done him a favor and told him the foregoing story of its origin. The white man was traced to Australia and there Burnett found him and secured the idol. The story is substantiated by the peculiar wood of which the idol is made and by the rough carvings which indicate that it was fashioned with crude tools made from giant clam shells, the only material the natives had for such purposes before the Europeans arrived.

HAND STRAP HOLDS GOLF CLUB TO IMPROVE STROKE 1773

To help correct the tendency to over-swing, slice or hook the golf ball, a hand socket strap for the club has been designed. Its function is to relieve the strain incident to stopping the club on the upward movement, so that the fingers will not relax their grip and allow the club-head to drop below the left shoulder. The strap is said to insure the proper start on the downward swing, reduce soreness of hands and add distance to drives, as it improves timing.



Golf-Club Strap in Use, Showing How It Corrects the Tendency to Make an Over-Swing

Blake Mfg Co

2008 9 46th St Cleveland



To Be Conquered by Rails? Castle of Lichtenstein in Southern Germany, Objective of Train Line

RAILWAY TO FAMOUS CASTLE TO SERVE TOURISTS

Plans are on foot to construct a railway to the top of the cliff on which is perched the famous castle of Lichtenstein in southern Germany. The place is visited by hundreds of tourists yearly.

WILD-LIFE REFUGE IN ALASKA TO PROTECT BEAVER 1922

Sanctuaries for wild animals have been established at Curry, Alaska, and at other points in the territory, to preserve beaver, muskrat and other creatures that are becoming scarce. Bears, wolves and wolverines may be hunted within the reservations, which are placed under the jurisdiction of the department of agriculture.

Christian Science Monitor
2/25/27

SPEEDBOAT SETS NEW RECORD OF SIXTY MILES AN HOUR

1564 Previous speed records for motorboats in the 151-class were broken recently when

British birds and beasts, and a section devoted to native English plants and flowers. The animals on exhibit in London will be relieved every few months and sent down to the country to get a taste of near-wild life, others, which have rested and recuperated, being sent up to take their places in the city cages. The site chosen is in a bit of "wild" country, where deer roam



Warming into a Mile-a-Minute Pace, the Motorboat "Angeles," Champion of the 151-Class, Roaring down the Test Course; It Broke Previous Speed Records by Thirteen Miles

the hydroplane "Angeles" was driven at the rate of 60.11 miles an hour over the test course on Newport bay near Los Angeles. The mark bettered by more than thirteen miles one which had been made shortly before by another craft of the same type. At the end of its spectacular performance, the "Angeles" skidded and was wrecked, but the pilot was unhurt.

"JUNGLE" FOR ZOO ANIMALS 2070 PLANNED IN ENGLAND

A 400-acre "jungle," where lions, tigers, elephants and other animals will roam at will through inclosures bordered by concealed fences and moats, is to be built by the London zoo, at a cost of \$1,000,000, in southern England. The scheme of development is to cover forty years, and provision is to be made for airplane-landing fields so that zoo visitors of the future can fly to the spot in their own planes. Planned primarily as a country home and "resting ground" for inmates of the London zoo, the scheme also contemplates a bird and animal sanctuary to preserve

the forests, where cottages are lighted by oil lamps, and with the nearest railroad ten miles away.

SHOOTING AT MOVING PICTURES LATEST RIFLE PRACTICE 1829

Hunting game through the medium of the movies and receiving excellent practice in skill with the rifle thereby, is one of the latest indoor sports introduced in Berlin. As the pictures flash across the screen, the marksman takes aim and fires. The instant the bullet strikes, the film is stopped so that the results of the shot may be observed. The equivalent of many ranges and a wide variety of other factors are realized with this apparatus, which is gaining rapid favor in shooting galleries.



Big-Game Shooting in the Rifle Gallery; Firing at Pictures of Animals on Screen; Camera Stops as Hits Are Made

ready to press
3/3/29

Krupp, Ernmann -
Schiers - Kins

**CAT PATROL KEEPS CAPITOL
FREE FROM MICE**

Not the least important among the many employes that keep the government machinery running, are "Mary" and "Dirty," two cats that patrol the basement and other parts of the capitol in Washington to keep it free from mice. Both waifs, and befriended by attaches of the building, the cats have proved their usefulness and are now enrolled on the capitol watch. "Mary" starts her day about four o'clock in the afternoon by strolling forth from the basement room where she sleeps. Her movements are unknown from then until about five o'clock in the morning, when she appears for her breakfast of liver. Mice that "Dirty" catches are proudly laid at the feet of G. R. King, assistant manager of the senate restaurant. Her first assignment was to guard the potato bins, where she is locked up each night. Not long ago, a cat got jammed in a ventilator shaft while following a fleeing rat. For some time, there was opposition to further use of the animals, but when rats took possession of some valuable records stored in the basement, it was decided to again enlist their services against the pests.

**CARBON PAPER IN CUSHION BACK
SAVES TIME AND WASTE**



To save the stenographer time, improve the quality of work and prolong the life of the carbon paper, a binder arrangement with a cushion back has been devised. One or more sheets are stitched to it at the top, and at the

bottom, they are uncoated so that the fingers will not be soiled in handling them. There is a thumb hole at the right-hand bottom edge for removing all the copies at once. The cushion insures more even impressions, the copy paper is kept smooth and in place, and the operator need not spend time in alining the separate sheets by jogging them, as this is already done with the carbons.

*Phillips Ribbon & Carbon Co., Inc.
6 Halstead St. N.Y.*



© Keystone View Co.

Putting On a Roof with Hose; Cement Is Sprayed on Wire Netting Attached to Steel Framework

**CEMENT GUN AIDS IN BUILDING
SEMICIRCULAR ROOF**

Uses for cement have been greatly increased through the method of applying it with compressed air from spray nozzles, and one of the newer developments is the hemispherical roof for dwellings and other structures. A framework of steel sheets and wire netting is first arranged, and the cement "fired" upon the mesh. When it has set, the steel forms are removed.

**DOLL'S HEAD THAT LIGHTS UP
LATEST BATTERY NOVELTY**

Attached to the end of a small electric battery, a doll's face glows when a wire at the base is pulled. The action completes the circuit, lighting a tiny electric lamp inside the doll's head. The colors are shaded to appear more realistic when the light is on.



*L. Keweenaw
8 E. Randolph St. Chicago*

*Used at West Laving
Middlesex
England 959
1258*

2062

2010

1339



To Guard Her Ears While Having a Haircut; Metal Shield That Prevents Injuries from Scissors

EAR GUARD PREVENTS INJURIES WHILE HAVING HAIR BOBBED

For women and children, an ear protector has been devised to be worn while in the barber's chair. It guards against cuts and burns and is perforated to admit air and sound.

MEMORY TESTS FOR SQUIRRELS SHOW HOW FOOD IS FOUND

Are squirrels able to remember where they hide nuts; are they guided by the sense of smell or do they just chance to find food that they or other squirrels have hidden? Naturalists are puzzled over the question, but tests performed with a squirrel by Dr. A. Brooker Klugh, of Cornell university, indicate that memory plays no small part in the animal's remarkable skill at locating food it has secreted. A red squirrel buried nine nuts in the snow on a house balcony. The next day it came and dug them up one by one, although a new fall of snow had complicated the problem. Dr. Klugh concluded that the performance showed the squirrel's strong memory for location. Others were frequently observed taking the shortest route to something that had been stored.

Another naturalist reports that a fox squirrel, fed in a shallow box on a house porch, was unable to find nuts that were completely buried in the sand, although it had no trouble in locating those that were partly exposed. This was taken to indicate that the sense of smell played only a small part in the process and that the squirrel was at a loss to find food it had not hidden itself.

SPRAY WATERING OUTFIT HELPS 1592 LAWNS AND GARDENS

Sprinkling newly planted gardens with an ordinary hose requires care, as too strong a stream of water may tear the soil. A sprinkler outfit now on the market is arranged to direct a fine, evenly distributed mist over tender plants or can be used in geyser-fashion, shooting several jets of water and covering a wide area. In a length of special hose are screwed a number of sprays which form outlets for the water and can be set at different angles. The hose is closed at one end and is held in place by brass anchor pins. The outfit may be had in short or long units, depending upon the area it is intended to serve.



Unit of Hose and Nozzle, Showing How It Is Attached, and Group of Sprinklers in Action

Bi. Lateral Fire Hose Co., 230 W. Randolph



A Glimpse of the Iron Age as It Is Expressed in the African Wilds; a Group of Natives "Cooking" Ore in Crude Clay Furnace; Charcoal Is Used for Fuel

IRON-MAKING IN AFRICAN WILD — REFLECTS EARLY PROCESS

How more highly civilized peoples have developed methods for transforming ore into metal is seen in one of the processes used by certain tribes in South Africa. The natives first fashion a plate of clay pierced with holes and bake it until it is extremely hard. Iron ore and charcoal are then placed upon the plate, a charcoal fire kindled underneath and kept burning with bellows. As the ore melts and trickles down through the holes, it passes into another clay container, where fire is blown upon it until the smelting process is complete. After this, the metal is hammered into crude tools and weapons.

WEATHER WHEEL TESTS PAINTS TO DETERMINE WEAR 2048

Qualities of paints are determined in a relatively short time on an electrical testing arrangement somewhat like a small Ferris wheel. Panels painted with samples to be examined are attached to the circumference of the wheel which makes a complete revolution in forty-five minutes. As it turns, the surfaces pass through a spray of water and then under a mercury-vapor lamp which radiates ul-

traviolet rays akin to sunlight. The panel then travels in front of a bank of electric lights, where it is heated, and dipped into a tank of ice-cold water. This cycle of conditions corresponds to those which the paint would meet under actual weather changes and, in less than an hour, it is subjected to wear equivalent to long service.

LOCATOR FOR ELECTRIC WIRING SAVES TIME AND LABOR 1917

To insure a higher quality of work with less expenditure of time and effort in installing electric



boxes for outlets at the baseboard, an accurate and easily operated guide has been devised. It is attached to the top of the board by a curved lip, then tapped lightly with hammer or pliers

to score the face of the wood and indicate the area which must be cut out. It is quickly adjustable to different dimensions, eliminates all guesswork and prevents cutting too large or too small apertures at wrong angles.

N.Y. Utility Bulletin
island Central Terminal
3/14/27

W.B. McGeorge & Co.
River Road, Cal. Cal. Conn.



Airing Bag Being Attached to the Cleaner; the Drawing Shows How It Is Placed for Operation, Closed and as Moth-Proof Container

THINGS EASILY AIRED INDOORS WITH VACUUM CLEANER

Pillows, blankets, woolens, infants' clothing and many other articles can be given a thorough airing and renovating through the use of a patented attachment for the vacuum cleaner. It is simply a sanitary bag, with a hose attachment at one end and air holes and draw-strings at the other. The articles to be aired are tucked into it, then the bag is connected to the vacuum cleaner, the airing end placed at an open window and in fifteen or twenty minutes,

with the cleaner running, an effective treatment has been given the contents of the sack. This is said to be more thorough than eight hours of exposure in the usual way, and there is no risk of theft, little work and much less hazard of soiling. The bag can be connected to any vacuum cleaner provided with attachments and, when not used, makes a storage sack for various articles, protecting them against moths, dampness and dust.

OFFICE BUILT OF CEMENT PIPE

Constructed almost entirely of concrete pipe, an office building of a California company has proved such a success that use of the material is suggested for other one-story houses, such as milk-cooling quarters, storage sheds and like buildings for farms. The pipe affords protection against dampness, heat

and cold, and the thick walls exclude almost all sounds. Concrete irrigation pipe, eight inches in inside diameter, was used for the sides, with ten-inch pipe at the corners. Center and corner columns were strengthened by filling them entirely with concrete and inserting reinforced steel. The first row was set six inches below the surface of the ground, eliminating a separate foundation.


Roof timbers were made fast by stud-ding them with nails, bent over and covered with cement. Joints were sealed with a rich mixture, and the spaces under the peak were boarded and stuccoed.



Office of Concrete Pipe; Shortly After Photo Was Taken, Cement Roof Was Constructed

Emb. L. Schotten Secy.
Concrete Pressure Pipe
+ Construction Co. Inc.

San Francisco, Calif.



How Father of Waters Is Coming Back to Life

LAST year a single line of barges carried more freight up and down the Mississippi than did all the hundreds of steamboats in the old days, when small colored boys sat on the safety valves of racing "floating palaces," out to set new records for the run from New Orleans to St. Louis.

As river navigation had been practically dead and gone for half a century, the performance of the federal barge line, in competition with highly organized railroad service, is all the more surprising. But the "Father of Waters" has come back as a transportation factor, and not only that, but his reawakening has hardly started, and within a few years the record may be doubled or tripled.

The Civil war hastened the death of the old-time river boats, and the World war brought steamboating back. During the

Old-Time Plantation-Landing Scene on the Big River
When the Floating Palace Paused to Deliver Freight

latter war, the government built fleets of barges and tugs to relieve the overburdened railroads in getting steel from Birmingham down the Warrior river to Mobile, and in handling cargo on the Mississippi. With the war over, and a fleet of barges on its hands, the war department conceived the idea of organizing a freight corporation and going into the business of showing that the river could compete with railroads even in times of peace.

The barge lines of the Mississippi and Warrior rivers are the result. The one plies



Modern Steamboating with Huge Steel Barges of 2,000 Tons' Capacity Each and a Single Powerful Tug to Push the Fleet

from St. Louis to the gulf, and the other from New Orleans around to Mobile and up the river to Birmingham. This year, a fleet of smaller craft is opening a feeder service on the upper river from St. Louis to St. Paul and Minneapolis, and other lines are to branch out up the Missouri and Arkansas, while the Ohio and the Cumberland are already organized by private companies.

The modern river boats, though, bear no relation to the old-time river palaces, with their high tiers of decks, splashing side or stern paddle wheels, their brave show of white paint and gold leaf, and their crews of rollicking, chanting negro roustabouts, singing as they loaded a few bales of cotton or a drove of hogs at some plantation landing.

Instead there is a fleet of as many as nine huge steel barges, each of 2,000 tons' capacity, all roped together with huge steel hawsers, and the whole lot pushed up or down the river by a single highly efficient tug. The pusher—"propellers" they call them on the river to distinguish them from the side and stern-wheelers—is a shallow-draft vessel, so shallow that its propeller turns in a tunnel in the bottom of the hull, the tunnel protecting it from snags and sand bars. When the propellers

first appeared on the river, the old-time rivermen scoffed, for even with the tunnel arrangement the draft was deeper than that of the paddle steamers. They expected the new-fangled boats to be piled up on sand bars and lost before the summer was over—but that was five years ago, and they are still going strong.


A typical tow down the river from St. Louis averages as much as 16,000 tons of freight. The average railroad car carries from forty to fifty tons, so it is easy to figure how many trainloads such a barge tow would make. Most of the freight is destined for trans-shipment to ocean-going boats at

New Orleans, and a single load is more than enough for any seagoing freighter, for even a 10,000-ton ship at sea is a big one. Ten to twelve thousand tons is a load even for the biggest of the great lakes ore freighters, which are the most efficient big ships known.

Yet the Mississippi barges regularly handle enough freight in a single tow to fill two or three average-size tramp steamers, and carry it down a channel where the water depth is frequently nine feet or under and where one of the most treacherous streams in the world is constantly piling up new sand bars and snags and shifting the old ones. They get stuck quite frequently, for three rows of barges, lashed three abreast, make a tow some 600 feet long and 100 feet or so in width, all propelled and maneuvered by a single tug puffing along behind. But when they do hit a sand bar, the crew unlashes the barges and one by one the tug pulls them off, then re-forms its covey and plods away again.

The crews that handle such a dead weight must be skilled men and quick thinkers. Many of them have good educations and plan to stay with the river boats until they can qualify as pilots. Anyone who has read Mark Twain's story of his train-

65-4



Five Giant Barges Lashed Side by Side, and Four More Ahead, Can Be Pushed 2,000 Miles against the Current in Twelve to Fifteen Days, Including Stops at Numerous Landings and, Sometimes, on an Uncharted Sand Bar; at the Right Are the Cranes on the St. Louis Municipal Docks, Where Freight Is Sorted and Dropped into the Waiting Compartments of One of the 2,000-Ton Government Barges; Below, an Express Barge, Self-Propelled, on the Warrior River Division, Plying between Birmingham, Mobile and New Orleans



315 Dan Antwerp Bldg
Mobile Ala

ing as a pilot, in his "Life on the Mississippi," has some idea of what the men who guide the ships down the Father of Waters must know.

The barge service is not limited to the big tows. To supplement it, there is a faster express service, handled by self-propelled barges, and carrying any sort of small-lot shipments. In a typical manifest, for example, there are groceries from Milwaukee, shipped by rail to St. Louis, reshipped by barge there for New Orleans, where they are transferred to a steamer for passage through the Panama canal and around to Los Angeles for final delivery—at less cost than a rail trip all the way across the continent.

The privately operated ships on the Ohio, Cumberland and Monongahela bring much freight down to Cairo to be trans-shipped to the government-owned barges. The Ohio also carries big steel and coal shipments down the river. Under government plans, some fifty dams have been built in that river to maintain fixed depths all the way to Pittsburgh, the pool behind one dam backing up to the foot of the next. In times of high water, the dams, which are built in sections, are laid flat on the bottom, so that boats may have an unobstructed passage, and when

the river falls, they are raised to retain the water, and ships pass through the locks.


Illinois is working on a new barge canal to connect the Illinois river with the Chicago drainage canal, and so with Lake Michigan. Locks as big as those at Panama are being built, and the federal government has been authorized by congress to dredge the Illinois river itself to open a nine-foot channel from the great lakes to the Mississippi. The locks built by the state at Starved Rock, Marseilles, Brandon Road and Lockport will be big enough to accommodate a nine-barge tow at one time, and at least one will have a higher lift than any lock in the Panama canal.

PINS KILL MORE CHILDREN 7982 THAN GUNS

The safety pin has claimed more children's lives than have guns, in the opinion of an eastern physician, who declares that the bad example, set by the mother in holding pins in her mouth while dressing the child, is responsible for many of the disastrous results of babies swallowing things. He has devised a special apparatus for the removal of safety pins from the child's stomach. With the aid of a small tube, electric lighted at one end and

W. Chevalier Jackson

*Pennsylvania Univ
Medical Faculty*



The Type of River Boat Made Famous by the Race of the "Robert E. Lee" against the "Natchez," in the Days When Pine Faggots Fed the Furnace, While Small Boys Sat on the Safety Valves

with holes for breathing. he can look into the organ and with the help of forceps, safety-pin closers or other instruments, shut the pin and so simplify its extraction. Such a tube, of the size that can be used for a baby, is hardly larger than a straw.

WHERE WAX IS MINED

In various parts of the world there are mines for obtaining a curious resinous substance, a mineral wax which is used as a base, with other materials, in the manufacture of wax candles, phonograph records and like articles. Deposits are often found in conjunction with rock, salt and coal, and while traces are discovered in Austria, Russia, Roumania, Egypt, Canada and Mexico, it has so far been profitably mined only from an island off the west coast of the Caspian sea. One of the hazards of the work is that the soft wax is sometimes forced into the shafts where men are engaged, due to the great pressure to which it is exposed.

GUARD DROPPED OVER WHEELS PROTECTS PEDESTRIAN

So that the wheels may not pass over a person or animal struck by the automobile, a guard is attached under the front fender on both sides of the car. It can be dropped by a driver's control or made to fall automatically in case the mudguard is struck by a person or inanimate object.



Guards Lowered to Prevent Running over a Person



Pasting Maps on the Globe, a Pleasant Geography Lesson; When Not in Use, the Sphere Is Drawn Up to the Ceiling

PUPILS MAKE THEIR OWN GLOBE AS GEOGRAPHY AID

To help pupils of a Cincinnati school gain a clear idea of the location of the different countries, their geography teacher has them fashion their own globe on a wire frame covered with cloth. The sphere is suspended from the ceiling of the classroom by a rope and pulley. After maps have been drawn and studied, those of the right scale are pasted upon the globe and in a few weeks, the entire world is there.

Names and addresses of manufacturers of articles described in this magazine will be furnished free by our Bureau of Information.

Chas. W. H. Kitchell
London Engineer

1305



Demonstrating the Lighting Equipment Which "Plays Tricks" on the Eyes, Causing Things to Disappear

APES' FAILURE TO LEARN WORDS
SHOWS IMITATION LIMIT

2134

Apes have a strong tendency to imitate what they see, but apparently little urge to duplicate what they hear, and in this lies one of the chief reasons why scientists have been unable to teach the animals how to talk, Dr. Robert M. Yerkes, of Yale university, believes. A chimpanzee might be instructed to talk with its fingers, after the manner of deaf persons, more easily than it could be made to imitate the sounds of human speech. Dr. Yerkes holds that the

sounds made by apes are not a language at all, but, primarily, emotional expressions of fear, anger or other emotions, which are not learned by imitation.

THINGS ARE MADE INVISIBLE
BY COLORED RAYS

W. H. Chandler


By the use of cleverly controlled rays of colored lights and a refraction screen, a Washington artist is able to make things invisible. At a demonstration, a person sitting in a chair was suddenly "dissolved from sight" while the chair remained. According to reports, the late Houdini was to have employed this system in causing an entire audience to disappear. The "magic" of the stunt is based on certain laws of light and vision, and emphasizes the fact that our eyes are dependent upon light rays for what they see.

EYE-REST GREEN AIDS SURGERY

Color as an aid to surgery has been given additional recognition as the result of research work by an eastern physician who has found that a shade of bluish-green for the operating room is best where subdued illumination is important to prevent glare and protect the eyes of the surgeon. The particular shade has been called "eye-rest green" and already has been prepared by chemists. One reason why it was chosen is that it proved to be the correct complement to the color of blood when exposed to air. In the opinion of the physician, table, gowns, towel and draperies used in the room should be of the deepest tint of the special green.

GATE OPENED BY AUTO BUMPER
CLOSES ITSELF

Mounted on weighted pivots, a farm gate devised by a western inventor is easily pushed open by the automobile and closes of its own accord, when the vehicle has passed. An extension in the center holds the gate down, until the car



Self-Closing Gate in Use; It Swings Back Upright After Auto Has Passed


has proceeded far enough to prevent scraping the rear when the gate rises.

H. C. Truncheon
1475 W. Alameda Ave

Produced by Chemists of C. S. du Pont de Nemours & Co., Wilmington, Del

UNUSUAL HOME IS BUILT OF CONCRETE AND GLASS

An unusual home has just been completed at Newport Beach, in southern California. The massive



Barren of Ornament and Designed for Utility, Odd Concrete Dwelling in California



reinforced-concrete columns were constructed first, while the interlacing of concrete walls, floors, and great glass windows served to connect the whole structure into a single unit. All the walls are of solid concrete, nearly four inches thick, and there is no exterior or interior finish aside from the usual cement surfacing. Huge plate-glass windows afford an abundance of light as well as beauty. In planning this building, the architect endeavored to use his materials in as natural a way as possible. All ornamentations, curved forms, and decorations were carefully avoided, and an entirely different con-

ception in building has been the result. The structure as a whole will be perfectly balanced. The furniture, lighting fixtures, doors, fireplace, and other parts of the interior, are carried out in the same angular construction. One piece of furniture includes several cloak closets, a long lounge with book and magazine racks on one side and on the other a place for the dinner table and cupboard shelves for use when serving. Every corner is utilized for some specific purpose.

AIR CHAMBER IN SURFBOARD MAKES IT UNSINKABLE

2123

A surfboard that cannot be sunk, because its upper and lower decks inclose an air chamber, offers new thrills for swimmers. As the board will support 150 pounds when at rest and considerably more when

under way, even an ordinary outboard-motor boat is sufficient to tow it with a rider. The upper deck is concave and the lower one convex. A brass drain valve is provided to keep the air chamber dry. Although nearly seven feet long and over two feet wide, the board does not weigh more than forty pounds.

Boyd Martin Boat Co
Seattle Wash

marshall kid
the hair.



Painting and Labeling Golf Balls; the Paint Is Put On by Rolling the Ball in Hands Which Have Been Smeared with the White Preparation, No Brushes Being Used in the Process

Where Millions of Golf Balls Go

United States, Which Furnished the Modern Rubber-Core Ball and Newest Type Clubs, Leads World in Playing Golf

FROM the day in 1491 (the year before Columbus put America on the map) when an angry Scottish king issued a ban against "golfe or uther sik unprofitabill sportis," to the recent announcement that a few of the larger American cities alone would use a million golf balls a week this summer, is a far cry. But in the last dozen or so years of those five and a fraction centuries the "Royal and Ancient" game has become as Americanized as the second generation flapper daughter of a European immigrant.

To use up a million balls a week requires an army of golfers, for the modern rubber-core ball, which is a distinctly American contribution to the pastime, is good for about five games—if not sliced into the rough and never recovered. New York, manufacturers estimate, will need 200,000 balls weekly, Chicago, Boston and Philadelphia 150,000 each and Detroit will take

another 100,000—a total of three-quarters of a million for those five cities alone.

Not all of the million will be a total loss when their short life is lived, for the business of making balls has reached such proportions and uses such a vast amount of raw material that a profitable industry has sprung up to rebuild the worn-out spheres. The heart of pure rubber may be knocked out of shape, but it is as good when the ball is discarded as when new, and can always be remolded to form a new core.

Besides furnishing the rubber-cored ball, America has also contributed the steel-shafted club, improved heads, and, of course, a number of winners of the British Open and British Amateur. The core ball, which replaced balls of solid rubber, was the most important, however, for it not only lasts longer, thereby lessening the expense of golfing, but it is easier on the club heads.




Golf-Ball Covers. Before They Are Applied, Look like Pancakes; Two Are Placed on Each Ball, Which Then Goes into a Mold to Be Compressed for the Baking Process



The Test of a Ball's Value Is the Rebound

Racks of New Balls Going into the Oven



The Winding Machine Covers the Inner Core with Fine Rubber Thread to Build the Ball Up to Size for the Final Covering

Chicago

2005



Tractor Rigged to Run Small Sorghum Mill; Wheels Were Adjusted to Describe the Right-Sized Circle about the Press, and After Motor Was Started, Tractor Needed No Attention

USE TRACTOR AS POWER PLANT AT SORGHUM MILL

Where only small amounts of sorghum are raised for home use, large mills and refineries are not practical, so many growers have constructed horse-drawn units to crush the cane. An effective substitute for this plan was employed by an Iowa farmer, who made use of his tractor during its idle season. He adjusted the front wheels to describe a circle of the right diameter about the mill, fixed the steering wheel in place with a chain and let the tractor pull the crusher instead of horses. A driver was not necessary.

MAY LENGTHEN LIFE SPAN

Use of a new mercury compound may result in lengthening the span of human life twenty-five years or more, an eastern physician believes. It is said to be the most powerful substance of its kind known to chemistry, and may be developed as a possible cure for tuberculosis, influenza and blood poisoning. Its efficiency lies in its power to kill bacteria, and, at present, it is too strong for the blood system of a human being. Great strides have been

made in the last few years in developing gold, mercury and arsenic compounds for the prevention and cure of diseases, and while some are in the experimental stage, remarkable results have been obtained.

CRACKER FOR BLACK WALNUTS PREVENTS CRUSHING KERNEL

One person can crack from 500 to 700 black walnuts an hour, it is said, with a strong cracker that produces the kernels



in large, easily removed pieces instead of crushing them. It also keeps bits of shell and dirt from the meat and will yield a pound more kernels to the bushel of nuts than an ordinary cracker, the manufacturers declare. It may be used for other nuts, but is specially adapted to the tough walnut and is intended to stimulate interest in raising and gathering this crop.

*Dr. H. Clark, 524, Harrisburg, Pa.
Clark nut Cracker
ad. Oct 1938 - Classified
mf-*

2124

\$7.50

*Dr. George Benjamin Craigie,
University of Pennsylvania*

GLASS AGE TO FOLLOW STEEL SCIENTISTS PREDICT 2126

From the stone age, civilization has passed through various "ages" down to the present, which is marked by the predominance of steel. In the opinion of some investigators, another substance is threatening the position of the metal. That is glass, one of the most fragile of all and, until recently, used chiefly for decoration and illumination. Modern research has developed new qualities in glass, making it far more useful. A kind prepared at Sheffield university has enormous heat-resisting powers so that water may be boiled in a heavy glass pot over a gas burner without danger of breaking the container. In making tea, for instance, this would be a great convenience as no other kettle would have to be employed. Another grade is so hard that it can be struck tremendous blows with a hammer and will not break; while still another variety can be plunged alternately into cold and boiling water without any sign of a crack appearing. The material has already been suggested for building purposes.

PAD WALLS WITH PAPER DISKS TO STOP ECHOES 2015

Wire-covered paper "sound traps" have been devised by an eastern inventor as a means of ridding building interiors of echoes that mar the acoustics. They can be applied to walls while the structure is being erected or to those already built. The disks are hollow and covered with wires so that they will not lose shape.



Preparing the Sound-Absorbing Disks for Improving Acoustics; They Are Paper Pads Covered with Wire



Steeple Minus Its Church; Landmark near Delsbo, Sweden, Illustrates Type of Native Architecture

OLD STEEPLE WITHOUT CHURCH UNIQUE SWEDISH LANDMARK


Churches with steeples are common enough but one of the interesting sights tourists are shown near Delsbo, Sweden, is an old-fashioned steeple minus the rest of the structure and set in a field as a landmark. It is well preserved in spite of the storms of many years and is considered a typical example of the characteristic belfry of the country-church architecture peculiar to Sweden.

LIGHT FLOATS IN MERCURY 2120

To keep it steadier during the boat's movements, a signal lamp on a lightship at the port of Havre is floated in a mercury bath, held in the usual compass-type support. It illuminates the whole horizon.

Makers - American Acoustic Co.
 1464 Columbia Road Washington, D.C.

Emile Berliner
 1458 Columbia Road
 Cont. Edison Jarvie
 The Farragut



Courtesy Gaumont Co., from the New Zealand film, "The Romance of Hina-Moa"

Before the Days of "Luxurious" Shaves; a Maori Barber and Victim, Demonstrating How Sharp Flints Were Used to Remove Beards

SHARP FLINTS USED FOR RAZOR AS IN STONE AGE

Maori barbers in New Zealand demonstrated their skill at an ancient shaving custom for a motion-picture film recently. For a razor, two sharp pieces of flint were used, while the "customer" plainly registered the fact that the operation was more of an ordeal than a pleasure. The practice of shaving with flints is said to have had its origin in the Stone age, more than 20,000 years ago, and was popular, even if painful, for many centuries and among various peoples. In the British museum are specimens of flints with which the Romans shaved in the classical age.

AVERAGE BOY IS TALLER TODAY THAN FIFTY YEARS AGO

According to research and measurements prepared by a Chicago physician, the average American boy of today is more than three inches taller than the lad of corresponding age fifty years ago. Figures obtained for the present generation were compared with those gathered from school

and other data, and the boys considered were from six to sixteen years old. Today, the average sixteen-year boy is forty-seven inches tall as against forty-three and six-tenth inches fifty years ago. The average eighteen-year-old boy today measures about seventy inches as compared with the sixty-seven-inch height of the boy of five decades ago. The factors responsible for the difference, in the opinion of the doctor, are better means of preventing diseases, knowledge of vitamins and the value of sunlight.

VALUE OF HUMAN LIFE

Every person in the United States has a value of \$17,500, according to estimates by the American statistical association. The total valuation of human life in this country is placed at \$2,000,000,000,000, on the basis of

the population, present national wealth and the probable earning power of individuals. The wealth-producing capacity of the average American is set at twenty to twenty-five times his annual income, and it is believed five times the aggregate of the country's wealth at the present time will be produced in the estimated period during which now effective human energies will continue to be applied.

ADDING PENCIL IS ACCURATE AND SAVES TIME



Double service is afforded from a refillable pencil that has an adding device at the upper end. It is easy to operate, and accurate and rapid when the few simple instructions have been learned. The adding mechanism is made of metal.

The Add. O. Graph Pencil Co.

Mr. Horace Gray.

in Journal of American

St. Louis, Mo.

1865

Rescue Work Saves Fish



Gathering Fish from Stagnant Pools in Arkansas, Where Millions Are Saved by Moving Them to Fresh Water; Spring Floods Wash the Fish into Sloughs, Which Later Become Dry

By TOM SHIRAS

Mountain Home, Ark

UNTIL rescue work was started several years ago by the Arkansas fish and game commission, hundreds of thousands of fish died annually in the summer, when the shallow lakes and slashes in the timbered lowlands of the state went dry.

A scorching-hot sun, water lines of every slough and shallow lake receding; water hot, brackish, with a thick green scum on the surface, and thousands of fish milling around seeking living water, then dying—these were the conditions the commission found.

During periods of high water, the rivers that flow out of the Ozark mountains, in the north part of the state, through the bottoms, overflow and when the water recedes, every depression is left full. The fish go in with the flood, spawn, and both the adults and fingerlings are trapped when the hot days of summer come.


The gear used in fish-rescue work consists of seines, ten-gallon cans in which to transport the fish, and hardening plants.

The latter are used to restore vitality, and harden the flesh which has been made soft by the stagnant hot water.

The hardening process is necessary. Without going through the treatment, the fish would die in a short time. The equipment in these plants is very simple, consisting of a small gasoline engine, a pumping jack, four wooden barrels, eighteen tubs, and two pieces of ordinary one-inch pipe, with one-eighth inch spray holes bored every two feet. The plant is set up under temporary shelter, at a good well of fresh water as close as possible to the area in which the work is being carried on.

The barrels are connected with short pieces of hose, are set on a platform, about five feet high, at the front end of the plant, and the water from the well is pumped directly into them. The two pieces of one-inch pipe with the spray holes are connected to the barrels and laid on a rack down the center of the plant, the tubs being lined up beneath them, nine on

1865
976



Fish-Hardening Plant in Operation; the Tubs Are Started with Warm Water, Which Is Gradually Lowered in Temperature Until the Fish Are Restored to Full Vitality

each side and each tub directly under one of the spray holes in the pipe. The overflow from each tub passes out through a screened hole in the side near the top, and runs off on the ground. When the fish become lively, screened frames are put over the tops of the tubs to hold them.

In preparing the plant to handle a batch of fish, the barrels and tubs are filled with water and allowed to stand until the temperature is raised to the same degree as that of the hot, stagnant water from which the fish were rescued. The water has to be tempered to avoid gill congestion, which is caused when fish with low vitality are plunged into water colder than that from which they were taken.


When everything is ready, the seines are put to work, and the fish are rushed to the plant and placed in the tubs. The pump is started and the flow of water through the plant starts, continuing very slowly, so that the temperature of the water is lowered gradually. As soon as the proper temperature is reached, the full flow of the water is turned on, and is kept running constantly for from twenty-four to thirty-six hours.

Water used in hardening fish must be pure, and, particularly, free from iron. The commission has had some sad experience in using water containing this mineral, and every well now is tested before a plant is set up. As fast as the fish are

hardened, they are placed in cans, and either hauled by truck or shipped by express to different points in the state where they are planted in living streams.

CHIMNEY-FED INCINERATOR HAS 1733 MANY ADVANTAGES

Dump your rubbish down a chimney and forget it. Such a convenience, with the additional requirement of an occasional match set



to the pile and removal of unconsumed materials every few months, is now possible in a built-in incinerator that replaces the unsanitary garbage can and is much simpler to use than other burners which require a special trip to the basement whenever refuse is to be deposited. The chimney is constructed at the time the

house is erected and is so arranged that there is said to be a minimum of smoke and gases during burnings, and thorough

Kernerator
Kerner Incinerator Co.
641 E. Water St.
Milwaukee Wis.
612 N. Michigan Ave.

combustion is assured. As the fire is at the top of the material, the heat liberates gases from below and these pass up through the flames where there is a plentiful supply of oxygen. No commercial fuel is necessary to operate the incinerator. By destroying stuff that often is allowed to accumulate in the basement, it is a great aid to cleanliness and safety.

HEAVIEST STAR IN UNIVERSE WEIGHED AT OBSERVATORY²⁰³

What astronomers believe to be the mightiest mass of matter known to man has just been weighed at the Yerkes observatory. It is star "27" of the Great Dog constellation and weighs 300 times as much as the sun. Its gravitational force is so great that if Babe Ruth attempted to hit a home run there with an ordinary bat, the ball would be pulled to the ground before it had traveled a foot. Ruth himself, standing on the surface of the star, would weigh sixty tons and, with merely human muscles, he would be unable to lift a bat or his own right hand.

GIANT MAGNET EASILY RAISES SEVENTY-FIVE TONS¹⁴³⁵

Work that would require many men is performed quickly and easily with a huge magnet in the Krupp works at Essen. It is nearly five feet in diameter and is capable of lifting seventy-five tons.



Lifting a Huge Steel Unit with Five-Foot Magnet, Seen in Center: It Saves Time of Adjusting Cables

FOREST-FIRE EXTINGUISHER

WORN LIKE KNAPSACK¹⁸³⁵

Indian Fire Pump



Knapsack Fire-Fighting Outfit for Forest Rangers; It Throws a Stream Nearly Thirty Feet

Putting out the forest fire while it is in the early stages is the object of alert rangers, and one of the special units to aid in this is an extinguisher which is strapped on the back like a knapsack. It is said to be capable of throwing a small stream from twenty to thirty feet, the galvanized-iron tank holds five gallons, and the hose is six feet long. The force pump attached is operated by the person carrying the extinguisher.

The outfit is considered especially suited to the needs of the rangers who often discover small fires started by careless campers and picnickers. Most of these fires occur near small streams, so that a water supply is usually available for operating the extinguisher.

☐ Whenever you find that you wish to know more about any article in this magazine, write our Bureau of Information. Send no stamps: the service is entirely free.



"Big Bertha," the Long-Range Gun That Shelled Paris from a Distance of Seventy-Five Miles, and a Gunner beside One of the Sharply Pointed Mammoth Shells Used in the Cannon

By HAROLD T. WILKINS

Road, Osney me, S.W. 9 4 Crookhurst London Eng.

THIS is the story of the tin fish and its brother, the metal tadpole; of the rubber eel and the porpoise ears, the sea buoy that concealed a cannon and its crew, the panic parties of the strange Q-boats, and some of the other secrets of the great war which now can be told.

Although it is more than eight years since the conflict ended, the carefully guarded secrets are just emerging, particularly that of "Big Bertha," the long-range gun that shelled Paris. When the advancing allied armies reached the forest of St. Gobain, where "Big Bertha" had her lair, they found only the wreckage left by the Germans, who destroyed the cannon when they found it was too big to move. Photographs of the wreck were taken, but until several pictures were smuggled out of Germany recently, the rest of the world did not know what the gun looked like in action.

Big Bertha was designed to break down the morale of the defenders of Paris. When the German drive on the French capital started and pushed forward toward the Marne, only forty miles from the city,

the long-range gun opened fire. The German idea was that the French would think the enemy had broken through the front and was almost at the city's gates, therefore the defenders were supposed to abandon everything and flee the city.

The upset to the German calculations came when the first shell dropped out of the sky and plunged through the roof of a church. The French were sure the line had not broken, and no one could conceive of a gun firing on Paris from behind the German lines; so, it was assumed the explosion was caused by a bomb dropped from an airplane, and before the truth was learned Paris had become injured to being shelled.

The big gun was an enormously costly failure, interesting in an abstract way because of the problems its operation involved, but of no practical value. The pictures recently obtained show the gun was fired at an elevation of forty-five degrees, so that the shell, rising in an enormous arc, quickly would pass through the layer of five or six miles of denser air at the earth's surface and emerge into the

Revealed

rarefied atmosphere where it would meet with less resistance in its flight. Experts calculate that to hit in the neighborhood of a chosen mark it was necessary to aim the gun, in the latitude in which it was used, about a mile to one side to compensate for the rotation of the earth.

The German engineers were exceptionally clever in developing their weapons, from big guns to airships and submarines, but the defensive measures produced by allied inventors were equally shrewd. Fortunes were spent in developing U-boats which could slip along under the surface and release mines that automatically rose to a certain distance from the surface while anchor cables dropped to the bottom. But a British

naval officer countered with the "tin fish" that sought out the mines, snapped the anchor cables and let them come to the surface, to be blown up by gun fire.

The tin fish, as the sailors called it, was officially named the paravane. Like its companion, the metal tadpole and the rubber eel, it was based on the principles applied in making the fancifully painted little tin fish used as artificial fishing bait, and it was from that resemblance that it got its name. The inventor had trolled for fish on Swiss lakes and got the idea from the tin lures he used. In operation, a pair of paravanes, towed at the end of long cables from either side of a mine sweeper, plowed along well under the surface until the leading cable met the anchor line of a mine. The anchor wire

British Naval Commander



A Rare Photograph of "Big Bertha" Being Fired; Note the High Angle to Send the Shell Miles above the Earth

slipped along the cable until it reached the paravane, when, if it had not already been exploded by contact, a powerful cutter snipped it through and let the mine come to the surface.

The tadpole was an added improvement. Towed from the bow of the mine sweeper, the paravane cable led back in a long slant, so that much of it was above the level of the hidden mines. The tadpole then was attached near the ship, and was so designed that, when it was pulled forward, it automatically descended to a certain depth and remained there.

More brains were concentrated on beating the submarine menace than any single problem of the war, and time and again they were aided by the carelessness of the U-boat commanders themselves. The safe



German Field Radio with Power Developed by a Tandem - Bicycle - Driven Generator, and, at Right, an Electrical Device for Locating Buried Shells

landing of the American army in France was largely due to the habit of the submarine commanders of coming to the surface at night to run up their wireless aerials and talk with each other, report to wireless stations at home, and josh the French land-station operators. What the Germans did not know was that the allies had perfected radio direction-finding stations, working with loop aerials, and were able to determine the exact direction from which any radio signal heard was coming. A half dozen of these stations scattered around the British and Irish coasts and in France insured getting bearings from at least two on every German radio report—and only two are needed to fix not only the direction, but, from the point where the two lines cross on the chart, the exact position of the sending set.

Night after night every submarine lurking in the area between Ireland and France and Spain, where all the ship lanes of the world converge to enter the English channel, would give itself away to the listening allied operators, its posi-

tion would be charted and the information rushed to the American naval headquarters at Brest, where Admiral Wilson was in command. Plotted on the charts, the reports quickly showed that the U-boats lurked in a rectangle about 400 miles off shore, with gaps to the eastward along the French coast and to the south off the coast of Spain. They never went outside that area except when en route to the Azores or to enter the Mediterranean.

One of the puzzles of the war, from the


German side, was how the allies knew so much about their submarine movements and also their mine fields. Frequently, within a few hours after a mine field had been laid, English sweepers would be on the scene busy clearing it away, and all shipping would be warned of its exact limits. The answer to the mystery was the work of a single British naval diver, who was rushed to the scene whenever a U-boat was



"Big Bertha" with Barrel Lowered and Covered with Camouflage, to Deceive Prying Airmen; from Above the Seemingly Carelessly Placed Strings Blend Completely into the Surroundings

reported destroyed. He would descend to the wreck, enter and not only recover the submarine's log, giving an accurate report on what it had been doing, particularly if it had been laying mines, but also salvage the latest German naval-code books from each wreck, so that the allies were constantly posted on enemy codes and could intercept and interpret the radio messages between submarines and land.

The diver, whose work was shrouded in the greatest secrecy, also kept the admiralty posted on new things in U-boat design and furnished tips that could be in-



A Paravane and a Ship Towing a Pair of Them, Showing the White Streaks They Made as They Plowed Along under the Water

"Titanic" disaster, and was conceived to enable liners traveling the North Atlantic to locate icebergs by reflected sound, or underwater echoes. For war use, the idea was improved by sending out vibrations of such a high frequency that they were inaudible to the Germans, while the reflected sound

was transformed down to an audible pitch for the listener. The rubber eel and the porpoise were sound detectors towed astern, to keep them away from engine rumble in the ship. They worked on a different principle, with delicate microphones that picked up the engine vibrations of distant submarines.

When the armistice came, the allies were ready to open up a whole bag of tricks. For one thing the American army had Lewisite, more deadly than any gas used in the war, and the British had a somewhat similar compound invented by Prof. Harold Maxwell Lefroy—a gas insidious that if it were dropped on the inhabitants would be unable to breathe it until they dropped dying with it.


Prof. W. L. Lewis, Northwestern

up lungs. Nothing but a house fly has been found that can resist it. Also American inventors had developed the radio-controlled submarine, a practical aerial torpedo, to be launched from flying machines, diphenylchlorasine, a sneezing gas worse than anything used in the war, an armored triplane mounting eight machine guns, a small cannon, and dropping 3,000-pound bombs; illuminating projectiles that would light up vast areas, and a liquid poison, three drops of which were fatal.


Great Britain was ready to introduce her new poison gas, which was so heavy that it could be projected against the wind without rolling back; an electric apparatus to explode ammunition dumps behind the enemy lines, flying warships, literally torpedo boats with wings, and was experimenting with death rays which showed promise of being able to bring down enemy airplanes by stopping their engines. France had a rocket to set fire to airplanes by spraying them with liquid fire, a 20.4-inch howitzer that was a bit more frightful than anything Germany produced in the way of portable big guns, and several other inventions.

One of the war-time mysteries that puzzled the Germans, was England's Q-boats, the famous "hush-hush" ships. The exploits of the German raider "Moewe," a converted merchantman which still looked innocent while carrying concealed batteries, suggested the idea. The Q-boats were built from the slowest, most dilapidated old tramps available; too old to run or put up a fight, and easy picking, apparently, for a U-boat.

Besides their innocent appearance these ships were manned by men who were real actors, the "panic parties" specially chosen for their task. When the submarine shoved its periscope above the surface to take a look at one of the waddling old tramps, the panic party got busy going through all the emotions of a mob scared to death preparing to abandon ship without waiting for its destruction. They rushed around lowering boats while the submarine came to the surface and drew near, ready to send off a boat to plant a bomb or fire a well-placed shell from its deck gun. Then, when the Germans were almost alongside, huge false bulwarks dropped down exposing a row of five-



"Blisters" on a Ship Hull as Protection against Torpedoes; the Big Bulges Exploded the War Head Before It Could Touch the Real Hull and Cause a Fatal Rent in the Steel Plates



An American Invention That Came Too Late for War Use, a Radio-Controlled Submarine Which Could Attack without Risking Anyone's Life, Since It Was Operated by a Distant Ship

inch guns. Many a submarine was sunk in this way.

If the enemy did succeed in getting in a torpedo, it was not enough to sink the Q-boat, which had been specially reinforced with timber and cork to keep it afloat and in action until it burned almost to the water's edge. The cork protection suggested another war-time invention, the "blister," which was applied to many ships. It was simply a streamlined bulge all along the hull to explode the torpedo before it came in contact with the real hull. The blisters slowed up the ships somewhat, but that defect has been corrected in newer American battleships by building the blister inside the hull instead of outside.

One of the queerest stories of war-time strategy, though it was never put to practical test, was the gun buoy invented by the Italians. They observed that the Austrian submarines operating in the Mediterranean for some reason had a habit of coming to the surface near a navigation buoy just at dawn. The habit became so regular that the Italians quietly built a

slightly larger buoy, with a small cannon and gun crew concealed inside, and moored it in place of the regular one. The buoy was arranged like a Q-boat, so that its sides could be dropped to permit the gun to fire. One of the jealously guarded French war secrets was an invention to eliminate the telltale flash by which batteries in action could be located at night. Research disclosed that the flash of flame from the gun muzzle was due to a second violent explosion when the released carbon monoxide and methane gases came into contact with the oxygen in the air. M. Delpech, a French scientist, found that a little vaseline added to the powder charge would stop the flash, the loss of heat being compensated for by an increase in the firing charge.

Another problem of night fighting, which Italy had some success in solving, arose when Italian aviators attempted to bomb Austrian towns after dark. The planes were invisible, but their motors were so noisy that the enemy searchlights quickly located them. To install mufflers

to drown the sound would have decreased the efficiency of the engines too much, so scientists were called in. A device that met with considerable success resulted, the work of a professor of acoustics in a small Italian college. Instead of tackling the problem from the engineering standpoint he considered it as one in acoustics and worked out a system of reflectors that made the sound apparently come from a spot several hundred feet away from its true source.

AIR POLICE FORCE IN GERMANY 1522. PROTECTS FLYERS

Aerial traffic has become so heavy in Germany that a special police squad is maintained at one of the landing fields to



help direct the aviators on arrival and departure. By means of signal devices, messages are relayed to the pilots and, at night, rockets and searchlights are employed to guide the flyers. The corps has established headquarters near Berlin.

CHIEF CAUSE OF AUTO MISHAPS 1980 IS "HUMAN ELEMENT"

More than eighty out of every 100 automobile accidents are due to human carelessness or lack of skill, according to a recent survey of motor mishaps in England. The investigation gave added proof that man's ability to anticipate danger and protect himself has not developed so rapidly as science has developed machinery. Of 443 cases involving death, less than six per cent were due to faults in the vehicles, seven and one-half per cent to the condition of the roads, three per cent to weather conditions, fires and similar circumstances, while the rest were attributable to causes within the control of some person or persons. The survey emphasized the need for further instruction of the public—both drivers and pedestrians—as to the proper use of the streets.



Copyright, Henry Miller

Upper View, Airplane-Traffic Police with One of the Signal Flags; Firing a Rocket and One of the Searchlights That Relays Directing Word to Pilots


Vernon Newton, M.D., Architect: John E. Cherson 985
Corps Surgeon
St. John Ambulance 1455.

RADIO CODE FOR MEDICAL AID AT SEA

For some time, radio has been used to great advantage in obtaining medical aid for persons suddenly taken ill while at sea, and to increase the effectiveness of this service, a British surgeon has devised a code report form. It contains twenty-nine items relating to the patient and his illness. In case of a radio call for aid, information could be broadcast according to this standardized list, entered accordingly, and an accurate record kept both at the sending and receiving ships or stations. It includes the most important points of a diagnosis, would insure a complete summary and prevent useless detail.

MOVIE FILMS MADE LARGER WITHOUT CUTTING REEL

Enlargements up to post-card size are quickly made from a motion-picture reel, without cutting or damaging the film in any way, with the aid of a simple magnifier lighted from an electric socket. The negative reels furnish enlargements directly on bromide paper, while an enlarged negative may be taken from a positive film for duplicate prints or still greater enlargements. The outfit consists of focusing mount, paper holder, adjustable in all directions, lamp and wire connection. No screws or gears are used in the assembly. It is small and easily packed in photographic kit.



Sketch of Proposed Labor Temple for Chicago: Seventy Stories High, It Would Cost \$75,000,000 and Be the World's Trade-Union Center

SEVENTY-STORY LABOR TEMPLE TO COST MILLIONS

One of the latest skyscrapers proposed for Chicago is a seventy-story temple of labor under consideration by the Chicago federation of labor as a world center of trade-union activities. It would contain offices and meeting halls and would cost approximately \$75,000,000, according to present plans.


The cactus plant is of American origin.



Making an Enlargement Directly from Movie Film without Cutting the Strip

Herem Products Corporation

152 W. 42nd St. New York



Double-Cantilever Spans of the Carquinez Bridge Waiting for the Connecting Links to Be Assembled and Lifted into Place above the Deep Ship Channel of San Francisco Bay

International

Sand Boxes Lift Giant Bridge into Place

Seven Hundred and Fifty Tons of Steel to Complete World's Longest Highway Bridge Raised High in Air by Sand

LIFTING an enormous steel bridge span, 125 feet in length and weighing 750 tons, to a height of 135 feet above the water with only four boxes of wet sand as a counterweight is an unusual feat recently successfully performed by the engineers erecting the Carquinez highway bridge across the upper end of San Francisco bay. The bridge is the longest highway structure in the world, though its two 1,100-foot spans are not as long as the suspension spans of the Quebec and Firth of Forth cantilever bridges, or the main suspension spans of several other similar bridges elsewhere.

The final gap in the California bridge was the center section of one of the 1,100-foot cantilever spans. To close it, the 125-foot section was assembled on barges and towed to place beneath the bridge. Steel cables, rigged over enormous steel blocks suspended at the ends of the two cantilever arms, were attached to the section, and the task of filling the boxes hung

from the cables began. The sand method was chosen not only because it furnished a cheap form of power, but because the gradual loading of the boxes added bit by bit to the weight carried by the cantilever arms, instead of forcing them to take up the entire 750-ton load at once, enabling the engineers to check the bending stresses as the weight was applied.

Once the span swung free of the barge, however, it gave a good test of the extra safety allowance, for each cantilever then supported 1,500 tons, or twice the weight it will be required to carry. The balance between bridge span and sand was so carefully adjusted that the engineers regulated the lift to one foot a minute, taking 135 minutes to raise the great steel weight the same number of feet.

When opened to the public, the new \$8,000,000 bridge will form a link in the Pacific highway and avoid the necessity of crossing the bay by ferryboat from Vallejo to Crocker.


*running from Mexico
along the coast to Canada.
also Pacific Highway*

Steel work superstructure
 U.S. Steel Product Co. and its 1961
 POPULAR MECHANICS
 Subsidiary American Bridge Co.
 UNIQUE ENGINEERING FEAT COMPLETES BRIDGE
 Concrete floor system - Harnsman
 + Harnsman Co.

987



Four Boxes of Wet Sand Lifting the Final Span of California's New Highway Bridge into Place; Slightly More than 750 Tons of Sand Were Used to Raise the Huge Steel Bridge Section at the Rate of One Foot a Minute for Two Hours and a Quarter



Comparative Sizes of the World's Greatest Bridges: Quebec Has the Largest in the Cantilever Class and the Delaware River at Philadelphia the Greatest Suspension Bridge, But the Carquinez Structure Leads in Over-All Length

Foundation Work - Missouri Valley
 Bridge + Iron Co, Leavenworth, Kansas

Preliminary Harnsman work. Diamond steel tower and all heavy
 and foundation work by Harnsman + Harnsman Co. of
 St. Louis

923

New York Herald Trib
3/12/27


Huge Wine Cask, the Famous Heidelberg Tun during Recent Celebration;
Size Is Apparent from Human Figures

ANCIENT WINE CASK HOLDS FIFTY THOUSAND GALLONS

Probably the only barrel in the world that is honored with a birthday party is the celebrated Heidelberg tun in Germany, a huge wine cask now 475 years old. It is thirty-six feet long and twenty-four feet high and holds more than 50,000 gallons. It rests in a cellar under Heidelberg castle and is the central feature of a jubilee celebrated each year.

wire screen, which is said to keep out eighty per cent of the dust, a window ventilator made of heavy sheet steel has a series of hooded openings that break up the direct air currents to exclude drafts,

World's best.



Window Ventilator Which Permits Closing or Opening
Sash While in Position and Breaks Up Direct Draft


GOLD RECOVERED FROM AIR

Picking gold out of the air suggests a fairy tale, but that is exactly what is done at the New York assay office in Wall street. Tests have shown that the method is saving the government thousands of dollars that otherwise would be wasted. The minute particles, of the metal are taken from the fumes in the smelting furnaces. High-pressure forced draft drives the gases up the stack to "settling chambers," where the gold is taken out by a special electrical process before the residue fumes are released. Since the mechanism was installed, it is estimated that gold to the amount of not less than \$12,000 has been recovered.

NOVEL VENTILATOR IS PROOF AGAINST DRAFT AND DUST

Adjusted outside the sash and equipped with closely woven copper-rain and snow. A particular advantage is that the window can be opened or closed without removing the ventilator. The unit is supplied in various sizes to fit different requirements, and is finished in a color that blends with almost any scheme of decoration.

Chicago. W. A. Preston
All-Weather Ventilator Co.
2508 Island Central Terminal



Immense Turbine for the Shannon River Power Plant; Entire Unit Will Develop 240,000 Horsepower

SHANNON RIVER POWER PLANT TO HAVE SIX TURBINES

When completed, the power plant being installed on the Shannon river near Limerick, Ireland, will be larger than any unit under one supervision at Niagara. It is said. The six huge turbines will develop 240,000 horsepower. The size of the plant may be gauged by the enormous tubes, one of which is shown here. It is nearly sixty-six feet long and the intake is almost seventeen feet in diameter.

RADIO "MAGIC" LOCATES RICHES BURIED CENTURIES AGO

With the aid of a radio detector, treasure hunters in Panama City already have found gold ornaments, chains, emeralds, rubies, diamonds and other riches which were buried in the latter part of the seventeenth century by Sir Henry Morgan. Search is being made for other caches which are believed to have been hidden in various parts of the city. The find was made in tunnels beneath an old church. The radio apparatus is similar to those which have been in use for some time by prospectors and others in searching for ore and oil deposits. The presence of

metals beneath the surface is revealed by variations in signals from the detector as the radio waves strike substances offering different degrees of resistance.

CHALK LINE WITH PLUMB BOB SAVES TIME AND WORK

A serviceable tool for the kit is a combination chalk line and plumb bob, operated like a tape measure and so compact

that it may be carried in the pocket. The chalk is carried in a water-proof chamber and the line, which can be locked at any required length, is wound on a reel turned by a handle that folds out of the way. The bob is easily attached or taken off, being secured to the line with an eye. The chalk chamber is big enough to hold a sufficient supply for six months' use.



Chp.
Refer to May issue 754

Always Ready
Chalk Line Co.

1484
1.00. with
plumb 625
no Chicago
525 W Willow St
Williamsport, Pa.

1485 Nov


TIME and MONEY for a



Sink and Electric Dishwasher in One; the Washer Is at Left; Water Is Forced Up by Motor Below and Sprayed over Dishes in Rack



Insulated Cover for Milk Bottle Prevents Freezing and Souring, and Keeps Flies Away




Soap Clamp Holds Cake and Spares the Hands in All Kinds of Scrubbing; Below, a Combination Measuring Glass and Fruit Squeezer That Catches the Juice in a Cup



To Keep the Heels of the Stockings from Wearing Out, Adjustable Rubber Strip Fits inside the Shoe and Is Quickly Glued On to Stay in Position

SAVING THINGS your Home



Clamped to Table or Other Surface, Vegetable Peeler Can Be Set to Cut Different Thicknesses



For Storing Various Supplies a Set of Rust-Proof Metal Bins Save Space and Are Ventilated at the Rear; Easily Lifted Out with One Movement When Cleaning Is Needed



Double Vacuum Cup for Laundering Delicate Fabrics Is Made of Aluminum and Has Detachable Stick for Packing



Why Bend Over to Use Shoe Horn? This One Has a Long Handle for Sitting Upright and Affords Powerful Leverage without Hurting the Fingers



Seven-Bladed Wire Chopper and Pie-Crust Flaker Improves Pastry and Is Easily Cleaned

obtain it by addressing Bureau of Information, Popular Mechanics, Chicago

What the Siberian
"Doctor" Wears to
Frighten Spirits:
Queer Costume with
Its Collection of
Charms



MAGIC DOCTOR WEARS ODD GARB TO FRIGHTEN SPIRITS

The costume worn by the "medicine man" in northern Siberia suggests that of a junk dealer rather than a healer, for it consists of a weird collection of metals, brass bells, dangling bars of copper and other articles, attached to his back. Rattling and shaking these things as he performs his rites is supposed to help frighten away the evil "spirits" causing sickness.

WHITE CARDS PROTECT HIKERS ON ROADS AT NIGHT

Pedestrians are in more or less danger on automobile roads at all times and particularly at night. An effective guard has

been found in a piece of white cardboard, worn or carried so that the light from approaching cars will strike it and attract the attention of the drivers. Small electric lights, white belts and illuminated hats are also available for the night hiker.

COSMETICS MADE HERE TOTAL OVER HUNDRED MILLION

In the last ten years, the amount of perfumes and toilet preparations manufactured in the United States has multiplied six times, according to reports from the American chemical society. The development of this industry here is shown by the fact that exports are steadily increasing, large quantities of goods of this kind being sent to China, Japan, England, and other countries. The annual output is valued at more than \$140,000,000. Creams, rouges and similar commodities rank first, their production aggregating \$34,000,000, dentifrices are second to the amount of more than \$25,000,000, and talcum and toilet powders next with a total of more than \$21,000,000. The increased popularity of many kinds of cosmetics since the war is said to be the main cause of the rapid growth of the business.


PUMP FOR BOTTLES SIMPLIFIES OILING AND SPRAYING

For applying a wide variety of liquids directly from the bottle, a small force pump prevents waste and reduces work and trouble. Inserted in the container, it is held by the finger through a loop, and is operated by moving the bottle down and up. The liquid is forced through a nozzle which may be regulated to pass a solid stream or a spray. Applying paint and varnish removers, treating plants, oiling auto and stationary machinery parts, are a few of the pump's many uses.



The Larver Corp.,
Atlas Pump Division
250 Park Ave. New York

LOFTY FIRE TOWERS GUARD CANADA'S FORESTS




Types of Observation Towers Used in the Canadian Forests, to Guard against Fires; the One Illustrated in the Center Is of the Demountable-Ladder Kind for Portability

Tens of thousands of dollars are being spent every year in Canada to save forests. Keen-eyed men have their lookout stations on lofty towers throughout the heavily-wooded regions and are always on the alert to discover any signs of smoke. The towers are built high above the surrounding trees and afford the watchers a clear view in every direction. Some of the installations are of the inclosed-cabin type of steel tower, offering protection from strong winds and making it possible for the men to live right in the tower. In order to select these tower sites to the best advantage, demountable observation ladders are used, which were originally devised for military purposes. This outfit can be readily loaded on a small truck and

can be erected at any desired spot by three men in a very short time, thus doing away with unsatisfactory and costly "hit-and-miss" methods of picking the sites.

HAMMER MAKES ITS OWN POWER FROM GASOLINE 1137


Electric motors, compressed-air apparatus and other equipment are not needed in operating a portable drill hammer, just introduced, for it is provided with its own power plant. This consists of a simple mechanism moved by exploding gasoline. The entire unit is contained in a chamber just above the drill, and it is said that the hammer will run four to five hours on a single gallon of fuel.



Drill Hammer with Its Own Power Plant, a Gasoline Unit in Chamber Just above the Drill

*Portable Power Co.,
68 Hudson Place,*

Wichawhen, N.Y.



Narrow End of the Wedge House,
 Floor Plan, and a Side View
 Showing Pleasing Appearance

If you had a lot less than six feet wide at one end and sixteen feet at the other, with a total length of only sixty-five feet, you probably would not consider building a dwelling house on it. But architects in Seattle, Wash., designed a residence to fit a plot of those proportions with pleasing and practical results. The entrance to the dwelling at the narrow end is but five feet nine inches wide.

SEEK TO PROLONG FISHES' LIFE WHILE IN CAPTIVITY

How certain kinds of fish that normally endure captivity only for a brief time, can be induced to live longer, is the subject of research by directors of the proposed Shedd aquarium in Chicago. Swordfish

cannot be kept in tanks, for the small ones are too nervous to thrive in confinement and the grown fish are too large. Goosefish, salt-water herring, kingfish, mackerel, anchovies and other kinds of rapidly moving fish seldom live more than a week or so in captivity. Fish that habitually live in darkness are also difficult to keep, for they injure each other in seeking to hide. So far as possible, the natural surroundings in which these nervous fish normally live, will be reproduced in the aquarium, in an effort to keep them longer. Water at constant temperature, natural food, protection against disease and efficient meth-



ods of aerating the tanks are among the measures proposed for making the fish comfortable. The task of keeping the slow-moving fish is relatively simple, so far as insuring their living to a mature age is concerned. In Europe, some species of carp have been known to live 100 years in their native habitat, and eight or nine years in captivity is not unusual. Bass, salmon, pike, big catfish, trout and the common goldfish live four to seven years. Some become so accustomed to their particular tank that they die if placed in another, while others thrive until strangers

1964
Walter A. Chute
 Associate Director

are introduced into the community, in which case it is not uncommon that all die.


HEATING ALFALFA SEED

Farmers have experienced considerable difficulty in raising alfalfa for the reason that many of the seeds are so hard that they will not absorb moisture and, consequently, will not sprout. Miss Anna M. Lute, of the Colorado experiment station, is reported to have overcome this trouble by subjecting the seed to heat. From many tests, she has found that a temperature of 167 degrees Fahrenheit gives the best results.

ELECTRIC RIVET HEATER SAVES EXPENSE IN BUILDING


Economy, through a saving in labor and faster operation, is claimed for an electric rivet heater to replace oil or coal-burning forges and furnaces. It is made in various sizes and affords, in two types, nine steps of heat control. With the larger sizes, a good operator can handle 600 rivets an hour and still larger numbers of the smaller rivets, it is said. The outfit uses alternating current and is adjusted to give a thorough heating without causing scale, burning, or the likelihood of heads popping off.

Electric Rivet Heater in Operation; It Has Nine Stages of Heat Control



American Hoe & Derrick Co.,
San Francisco, Calif.

A Castle in Trees; Elaborate Garden Design Achieved by Training Shrubs and Vines



MODEL CASTLE OF LIVE TREES NOVEL GARDEN DECORATION


Pine, cypress and yew trees in a French garden have been trained into fantastic shapes resembling a small castle and other forms. Some of the pieces are grown about a framework, but others are shaped simply by careful and constant trimming.

SMOKESTACKS OF OLD VESSELS PROTECT RAILWAY ROADBED

Sections of smokestacks from salvaged ships are used on a mid-western railroad to protect the roadbed from steam when the locomotives are blown off at watering places. They are placed in such a way that the tops are flush with the track, and as steam is blown from the engine boiler close to the rails, it passes into these receptacles, where it cannot dislodge the ballast or scald persons near by. A drain is provided to carry off hot water and impurities, while the steam itself escapes through the top of the stacks. An additional feature of the plan is that it eliminates discoloring of the ballast.

Electric, Toledo, Dronten

1590 Is E Hendrickson
sell instructions Argyle, Wis



The Evolution of the Professor from One of His Problems; a Simple Chalk-Talk Problem When Hidden Perforations, Visible Only to the Artist, Guide His Crayon

Invisible Pattern Makes Chalk Talk Easy

No Artistic Skill Needed to Make Rapid Drawings When the Lines Are All Shown by Minute Perforations

CHALK-TALK entertainments as given by professional performers require months of careful training and preparation, for even a skilled artist cannot always sketch amusing cartoons off-hand with the bold sweeping lines which hold the attention of a crowd. But with a little preparation anyone, even without drawing ability, can present a satisfactory parlor or social entertainment.

The secret lies in having all the drawings done in advance and transferred to clean white sheets as rows of minute perforations, perfectly visible to the artist, but so fine they cannot be detected by spectators seated half a dozen feet away. The perforating is done quickly with an ordinary tracing wheel, such as used by dressmakers in making patterns.

Cartoons of any kind, especially favorite characters from the newspaper comic sheets, make excellent material for parlor amusement, but the most interesting drawings, and the ones that lend them-

selves best to the "patter" with which the artist keeps the audience's attention while he draws, are the "evolution sketches" in which a face is constructed from letters, figures or other material.


A program can start with the artist printing the letters Y, O and U on the big white sheet on his easel, and then, while he entertains the audience with some bright talk, explaining that evolution of man was from letters instead of monkeys, he deftly sketches in a face, which, he says, will represent his composite audience, and when the sketch is done the letters have become the nose, mouth and line of a double chin.

The sheet is torn off, and the letters M and E drawn on the next one, while the artist explains that, as further proof of his evolution theory, he will demonstrate his own case. A few strokes and the letters again are part of a cartoon representing the entertainer's features.


Frequently individuals in the audience



Another Drawing, Showing How "Figures" Mold the Face of a Business Man, and, Below, the Evolution of "You and Me and Dobbin"



INVISIBLE PATTERNS FOR AMATEUR ARTIST ENTERTAINERS



War in China Is Another Clever Evolution Drawing; the Center Sketch Shows How the Letters of "Oats" Become First a Bag of Food and Then the Horse That Consumed It



Using a Pantograph to Enlarge a Small Comic-Section Drawing

can be singled out to fit in with the ready-prepared sheets, and the patter that goes with them. The evolution idea can be carried a step further by remarking that a man's occupation is brought about through processes of evolution, that a man whose family tree is made up of accountants, bankers, bookkeepers, mathematicians and men of similar professions, will have a face made up of figures.

As he talks the artist jots down, seemingly at random, a series of figures, 0, 1, 2, 3, 4 and 6, then rapidly fills in the connecting lines to complete the drawing.

Another interesting evolution sketch can be presented with an alleged reminiscence of school days, when problems were transformed into the professor's features. As he talks, the artist writes $0-0 \times 1-1$, and then transforms it into the professor's face.

Some of the chalk-talk drawings are even more complicated in their final evolution, keeping the audience guessing. The letters O, A, T and S, set down at random, spell oats, and then they can be placed in a bag, but with a few more deft strokes the bag becomes a horse's head—the evolution from oats to horses.

Some of the drawings can be presented

in various ways. One that lends itself to two developments is the map of China. Announcing he can draw a map of the country from memory, the artist sketches a china teapot, pauses to comment on present



Transferring an Original Drawing to a Blank Sheet, Underneath, by Piercing the Lines with an Ordinary Dressmakers' Tracing Wheel

disturbed conditions in that country, and adds the letters W, A and R, when a few more quick strokes will complete the picture of the man who started the trouble. Or, reversing the process, the word "war" can be drawn first, and the words "in China" added at the bottom of the sheet. While the audience watches breathlessly to see what is going to be done with the word, the china bowl is drawn around it, inclosing the "war" within "china," and then the face is completed.

And now for the process by which any amateur with no previous drawing experience can present the entertainment.

Obtain a supply of large sheets of plain white paper—ordinary newsprint from the left-over rolls at the newspaper office will do. Also get a large sheet of wallboard

Dewitt + Herby
239 Fourth Ave
New York
 990

or a large drawing board, build an easel to support the board and obtain a dress-makers' tracing wheel and a number of thumbtacks.

First work out the drawings in full size on sheets of paper, enlarging them from the sketches shown here, or taking cartoons from the newspapers. When a drawing is completed, place it over a blank sheet of paper, and with the tracing wheel, run over each line, perforating it into the blank sheet beneath. The original drawing, or master sheet, is then saved for future use, as it can be traced over and over again for successive talks.

When all the tracings have been completed, assemble them in the order in which you wish to present them, place a plain blank sheet on top of the pile, and pin all of them to the wallboard or drawing board with large thumbtacks. The plain top sheet hides the perforations if anyone should come close enough to inspect the board before you start.

When you are ready for the talk, make a few lines on the plain sheet, then tear it off as though spoiled. That exposes the first of the tracings, which, under artificial light, will be visible only to you, and not to your audience.

Use a large and very soft, black drawing crayon, or piece of charcoal, which will make wide and very black lines.

Exact enlargements of cartoons from the newspaper comics can be made by using a pantograph, which can be obtained from a dealer in drawing instruments, or made at home from a few strips of wood. One end of the pantograph is fastened to the table, a stylus is traced over the lines of the drawing to be copied, and a pencil fastened at the outer corner traces an exact enlargement on another sheet of paper.

Virginia is said to rank next to California in the amount of sunshine received annually.

ELECTRIC FLASHLIGHT IN CANE SAVES POCKET SPACE




Cane Light Turned On, Showing Its Usefulness in Helping Select Right Key

Concealed in the handle of a cane, a powerful little flashlight is useful in emergencies. The batteries are hidden in the stick. The cane lamp saves carrying a flash in the pocket, an objectionable procedure to those who do not like to burden themselves with too many articles.

TRAIN LIGHTS CROSSING SIGN RINGS BELL AND SETS FLAG

Trains give warning of their approach on a crossing sign which is fitted with a bell, lights and a stop flag, moved automatically into a clear position when the train is coming, but remaining hidden when the crossing is safe. A yellow light burns to give the signal for the railroad, and, when the train enters the block, this light is replaced by a flashing red one, while the stop sign, a large yellow reflecting disk, appears. The bell continues to ring until the train is past.




"Proceed" and "Stop" Positions of the Crossing Signal, Which Is Operated Automatically by Trains

Blueprint on file in Library
National Safety Council

Minnesota Ry.
& Warehouse Commission

**STOOL HAS ADJUSTABLE SEAT
LOCKED WITH STEEL BALLS**



Adjusting the Stool Seat, and Diagram Showing Balls That Wedge against Bar, to Hold Stool in Position

Gravity and steel balls simplify adjustment of a new stool to various heights. When the stool is in an upright position, the balls wedge between a round steel bar and a tapered chamber wall to keep it in place. To elevate it, a pull is all that is necessary, and to lower the seat, the stool is turned upside down, the legs pulled up slightly and then pushed down. It is said that the seat will hold a person of any size or weight and that it will not easily get out of order.


**GROUND WIRE LEADS AIRPLANES
TO SAFETY IN FOG**

Experiments with an electric leader cable to guide airplanes to their landing field have been successfully carried out by the British air corps. The cable idea is based on the submarine cable, laid in New York harbor several years ago, to guide ships in and out, delicate apparatus on the vessel picking up signals sent through the cable on the sea bottom, and telling whether the ship was over or to the right or left of the leader. For aerial use a five-mile cable was laid in a very elongated oval, so that both ends would be at the same place, getting away from the difficulty of returning the current without disturbing

the magnetic field. The cable is intended to supplement neon-tube lights used to pierce the dense English fogs. The neon glow will penetrate 300 feet of fog when the airplane is well above it, but as the ship descends, the light disappears for some time, and then reappears when the plane is about 150 feet above the ground. Coils on the airplane wings are used to pick up the current from the leader cable, and an instrument in the cockpit not only shows the whereabouts of the craft, but likewise indicates the distance above the ground at which it is flying.

**TRUCK TO CENTER-LINE ROADS
SAVES TIME AND COST**

Hundreds of miles of automobile roads were marked with a center traffic line at a minimum of expense and time with the aid of a special truck, equipped with a fifth wheel for applying the safety guide. Paint was carried in barrels on the auto and supplied to the marker through a valve. To insure keeping in the middle of the pavement, a wheel, taken from a motorcycle, was placed on an extension frame in front of the bumper and run just off the roadway. While painting, the truck makes about two miles an hour.



Marking Auto Highway with Truck Outfit That Paints Line from Supply Contained in Barrels

*Built in Shop of
Iowa Highway Commission*

*Royal Aircraft Establishment - Basingstoke area
Working*

*Ditch Mfg. Co.,
Amalia, Neb.*

Patd March 6, 1926.

1591 Emmet Dougherty, 514
Woodward Bldg, Washington, D.C.

Weather for Radio Distance



How to Forecast Reception

- ¶ Local static forecasts coming better reception from the west.
- ¶ Southern stations come in best after a widespread snowstorm.
- ¶ Big drop in temperature indicates good weather to last several days.
- ¶ Face the wind. Stations to right and left will come in better than those in front of or behind you.

DAILY radio-reception forecasts may soon become a part of the weather reports given by the newspapers, as a result of experiments that have shown the close connection between weather and wireless distance.

Professional operators have known for a long time that the direction from which static came always indicated a storm center, but it is only recently that rules have begun to be worked out by which the proposition can be reversed in order to obtain from the weather map the location of stations which will come in with good volume over long distances.


The problem is considerably simplified because of the fact that generally storms move across the United States in an easterly or northeasterly direction. If a storm center is shown on the weather map between Omaha and Denver today, it will probably be in the vicinity of Chicago tomorrow, and move on toward New York and New England the next day. So, when static blots out stations to the west, it indicates a coming storm.

In that way it is possible to tell something about coming weather by listening to the loud speaker grumble and howl, but the radio fan who likes to pull in the

distant stations can put the knowledge to much more use by taking the daily weather map and figuring out what stations he has a good chance of bringing in.

The weather map is covered with a series of lines, called isobars, amid which are printed such descriptive words as rain, snow, warm, cold, low and high. If the smaller and inner circle is marked "low," it is a storm center, to which winds from other places are moving, and if it is marked "high," it indicates the place from which winds are coming to equalize pressures elsewhere.

When you sit down at your receiver and take a look at your barometer, it may show a high reading of around thirty inches, with clear, good weather outside. But when you pick up the daily weather map and start selecting stations to go after, you will find a situation something like this, pictured from an actual map issued one day recently: Over southern Iowa, northern Missouri and a small slice of eastern Kansas and southeastern Nebraska, as well as western Illinois, there was a "low" or storm center. Therefore there was static originating in the neighborhood of the broadcasting stations in St. Louis, Kansas City, Davenport and



Radio Compass and Map Recorder, Left, and, Above, Graphs of the Miami-Hurricane Static, Normal Static and Wireless Code; Chart Shows Vessel's Position and Static Picture during the Hurricane, with Storms All around Her

Des Moines, Iowa, Omaha, Nebr., and neighboring cities; hence not much chance of a distant listener, say in New York, picking them up.

But go a step further, and out on the western coast there was nothing but high in California, with a low up north in Washington. And between San Francisco and New York all the isobars of the Missouri storm crossed the path between coast and coast at virtually right angles. Under such conditions the east coast would get the west coast with good volume, and on the night in question did.

Not everybody has access to the daily weather map, however, particularly those living in rural districts. But with a barometer and a bit of practice it is possible, from one night's reception, plus local weather conditions, to forecast rather accurately what the next night will bring.

If the barometer is falling rapidly, in-

dicating an approaching storm, it will show that much of the static heard is of local origin, under which circumstances few or none of the distant stations can be heard. But when the storm passes and moves on to the east, it should be followed by good reception, first from the north and later from the west. A steady and gentle rain, lasting for a day or more and not accompanied by lightning, frequently is followed by improved reception from southern stations. When both north and south stations come in good, there will usually be good reception from the west, and rather poor to the east.

A set with a tickler dial makes a good weather forecaster, for, when a storm approaches, it is necessary to turn the tickler higher to get the added regeneration necessary to bring up signals which have become muffled by static. Conversely, good weather requires less regeneration.

The navy recently has turned static to practical account by making it take a picture of itself to show storm centers at sea. Hooking a radio-map machine, designed to pick up weather maps transmit-

ted from Arlington, to a direction finder, and then revolving the loop aerial, the navy wireless engineers get a perfect picture of the static at every point.

Homemade Decorative Loop

An attractive loop can be made from odds and ends about the average home, as shown in the illustration. The parts required are inexpensive: An ordinary lamp standard, which, if not already on hand, can be obtained from the local furniture dealer; a picture or piece of framed tapestry, a length of dowel stock and two wood sticks, cut and shaped as shown and as long as the picture or tapestry is wide. Remove all electric fittings from the standard, and cut it to a length that will mount the loop at the required height. Replace the metal tube in the standard, and drill a hole in the dowel pin so that it will make a snug fit when slipped down over the tube. Drill a hole the size of the dowel through the center of one of the wood strips and screw this to the back of the picture near the bottom. Another hole is drilled part way through the center of the upper strip to take the top end of the dowel and allow the finished loop to revolve. This strip is then screwed on in the position shown. Any loop of the pancake type may be used and is fastened to the back of the picture by means of string and small screweyes. For the average set, this loop should consist of about 86 ft. of stranded loop wire with the turns spaced about $\frac{1}{4}$ in. apart.





Photo Shows Loop in Use, Harmonizing with Other Furniture; Right, Details of Loop and Mounting

*Selling & See
Greensway Works
Ponder's Eng. 868R*



Below, Enlarged View of the Winding Showing Separation of Turns; Above, Finished Coil

New Wire Provides Air-Spaced Winding

A new wire providing space-wound coils automatically, has been introduced by an English manufacturer. The wire is not completely covered but has two strands of insulating material wound spirally around the wire core. The insulating strands not only separate the turns but also lift the entire winding clear of the tube form. This makes possible good low-loss coils without bakelite tubing, or skeleton forms, cardboard tubing taking the place of the more expensive forms. The wire is made in various gauges, and in both solid and stranded patterns. In the latter, the strands are not twisted around each other in the usual manner, but lie parallel, being held together by the insulating winding. Wire of this kind is excellent for use in loops.

Use Old Tubes for Testing

Keep on hand one or two old tubes that will light although they will not do for the set. These tubes are useful in testing the wiring in a newly completed set and will often save a good tube if there is some mistake. Keep them in a handy junk box where they will be out of the way and still be accessible. The old tubes are placed in the sockets of the new set, and if they do not blow out, it is safe to put in good ones.

Wm. Anderson Co.
2 Middlesex Road
Stonham Mass.
 Radio World-Time Clock




This clock tells correct time in all parts of the world from London (Greenwich), around the globe to Berlin, and is now available for radio long-distance fans who wish to compute the time in various parts of

the world quickly. It is also of interest in the handling of radiograms.

Binding Frayed Insulation

The ends of fabric-covered telephone cords or flexible leads often fray out so as to make the terminals unsightly. This may be prevented by using stout, waxed cord, or twine, as shown in the illustration. A loop is made in the cord as at the left, and the free end wrapped around the phone cord and loop as in the center, leaving a small bight of the loop exposed. Then the free end is passed through the bight, and the upper end pulled until the loop disappears below the winding. The ends of the cord and frayed ends of the insulation are then clipped off, as shown at the right, making a neat binding with no external knots showing.



How to Mount Panel on Baseboard

When screwing the panel to a wooden baseboard, space the holes in the lower edge of the panel correctly, so that they will come in the center of the edge of the wood subpanel and not split out. Drill small holes for the wood screws before


trying to screw them in place; a drill about half the size of the wood screw should be used. This will give a good tight fit and prevent splitting.

Improved Method of Shielding Radio Receiver

It is a tedious and difficult job to shield a radio receiver with thin metal sheets. Owing to the tendency of thin metal to bulge and the difficulty of handling, it is hard work to turn out a neat-appearing job. To accomplish this in a simple manner, use the following method: Solder a wire to a small piece of metal, fasten this with a wood screw to the inside of the cabinet near the ground post, and connect the wire to the latter. Paint the interior of the cabinet, and the inside surface of the panel with any of the well-known metallic paints, such as aluminum or gold-bronze. Be sure to have all the painted surfaces join, but do not let the paint come in contact with any of the instruments, painting around them instead. Also paint over the metal piece that connects to the ground. Metallic paints are good conductors of electricity when dry. They are easy to apply, and if the work is carefully done, the finished job will be neat and attractive. I have been using this method for some time, and find it very efficient.—Prof. William Hoppie, Los Angeles, Calif.

Adjustable Gridleak Employs No Sliding or Pressure Contacts

A new adjustable gridleak, by which, it is claimed, all microphonic noises which accompany the use of carbon or graphite are eliminated, has been placed on the market. There are no sliding or pressure contacts.




The glass cylinder which is hermetically sealed, contains a high-resistance liquid. As the thumbnut of the

leak is turned for adjustment, the electrodes enter this liquid more or less, giving a range of exact values for the tube circuit and signal. It can be slipped into any standard fixed-condenser clips.—L. H. Georger, Buffalo, N. Y.

490 Broadway

POWER UNIT ELIMINATES ALL BATTERIES

By FRANK L. BRITTIN



REPLACING A, B and C-batteries with one compact unit and supplying all the necessary voltages to the receiver, the instrument described here is a real eliminator, in the full sense of the word. It has been thoroughly tested in Popular Mechanics radio laboratory and found to supply sufficient humless A-power to operate up to nine tubes of the 201-A type with their filaments wired in series, in addition to providing sufficient B and C-power for these tubes. The series wiring of the tube filaments, shown in the diagram on page 1008, reduces the current demand to that required for one tube, although the voltage, of course, must be increased with any addition to the number of tubes, and this is easily managed. Another advantage of series wiring is that the "drop,"


or slight loss of voltage across the filament of one tube can be used as a C-bias for the grid of some other tube in the circuit, and this is pointed out in the diagram. Without going into further details, the simple wiring diagram on page 1008 shows the reader how he can change his present set to use the new unit. Note carefully the sequence of the tubes in the filament circuit, and the necessary 1-mfd. condensers across the detector and r. f. tubes, as these points are important. The upper circuit diagram shows a much simpler arrangement, which is the one advised if a new set is built especially for use with the unit. Such a set, of the 4-tube type, will be described in the coming July issue, and will be combined with the unit in one cabinet.

The unit is designed for 60-cycle alternating current, 110 volts, and cannot be used on any other supply. This prologue to the actual building of the unit is given so that the reader may understand the conditions under which the unit can be used before attempting to build it.

The detailed layout and wiring diagram on page 1006 will immediately impress the



Installing Device in Console, Showing Comparatively Small Space Required for the Complete A, B and C-Power Unit



reader with the simplicity of the unit. It is easy to build, and the cost, including the rectifier tubes, is about the same as that of a storage battery, charger, and a good B-eliminator. Much advantage rests with the ABC-unit in that it requires no attention whatever and may be very simply controlled by a snap switch at the wall socket, which also controls the operation of the receiver.

The various parts are mounted on a 1 by 10 by 13-in. baseboard, which easily fits in the battery compartment of the average console, as shown in the photo on page 1005. It is even possible to install it in an ordinary cabinet with the set, as will be shown in the July issue. The simple arrangement of the various parts on the baseboard is clearly shown in the sketch. The condensers are stacked and held in place by means of two brass rods, threaded No. 6-32; these are pushed up through the holes drilled in the baseboard, and the condensers held firmly in place by means of washers and brass nuts. Two heavy-duty resistors are connected across the A-positive, B-45 and B-amplifier terminals, and the resistor marked "X" may

Layout of Power Unit, Showing All Instruments in Position and Detailed Wiring Diagram of Connections

be replaced by a universal-range Clarostat if the builder wishes to vary the detector-plate voltage. The 1-mfd. condenser mounted back of the resistors is a safety device, and should be of the 400-volt type, as it must carry the entire output of the power supply, which is about 600 volts, if the line current is turned on without the receiver filaments being connected to it. Remember this caution, and never turn on the house current, unless the receiver, with all tubes in place, is connected to the power unit. The 1-mfd. condenser might carry the load, but damage may result. The rear view, in the insert above the detailed sketch, shows the 110-volt 60-cycle supply connected to both sections of the power unit, and terminating in the usual wall plug. A snap switch can be connected in this line, or the unit disconnected by removing the plug from the wall socket, as desired.

The device is really two distinct eliminator units, as may be seen in the schematic diagram at the upper left on page 1008, each unit being an exact duplicate of the other. These units each use two

CX316-B rectifier tubes in conjunction with a transformer, chokes and the necessary heavy-duty condensers. In all there are four rectifier tubes, two transformers and two filter systems. If your set employs tubes of the 199 or similar 3-volt type only half of this double unit is required. The dotted line dividing the two units in the upper drawing, page 1008, shows how the section at the right may be cut away without disturbing the resistors, terminals and control lamp which must be retained. At this point it becomes necessary to explain what this control lamp is, and why it is used. The power output of the two units is in the neighborhood of 160 volts at 250 milliamp. when the tubes are connected, and, in order to reduce this to a suitable value for the receiver-tube filaments, a common 25 or 40-watt Mazda lamp is placed in series with the filaments and the power supply. If only one section of the power unit is used, two 10-watt lamps should be placed in series to reduce the filament supply to the low rate required for the small


tubes in the set. If the set employs five or more of the small tubes, it may only be necessary to use one 10-watt lamp. In other words, the lamp acts as a resistance that can be varied by the size of the lamp employed.

For example, in a five-tube set using 201-A tubes and the double power unit, all tubes in series will draw about 25 volts at $\frac{1}{4}$ amp., and the 25-watt lamp will draw about 120 volts at $\frac{1}{4}$ amp., thus making 145 volts at $\frac{1}{4}$ amp. The plate circuits of the tubes will take 20 milliamp. more and this will account for the drop in voltage of the power supply from 160 volts to 145 or 150 volts in actual practice. The simplest way to determine the correct lamp to use for




Left. Assembling Condenser Pack;
Above. Completed Unit Ready
for Installation

a six, seven or eight-tube set would be to connect the tubes, in series with the lamp, to the power supply, and try, first, a 25-watt, 120-volt lamp; then a 25-watt, 110-volt




Above, Schematic Diagram of Double Unit; Dotted Line Shows Section to Be Removed If 3-Volt Tubes Are Used



lamp; then a 40-watt, 120-volt lamp, and finally a 40-watt, 110-volt lamp. With one of these lamps, the builder will be able to obtain the proper filament voltage which can be measured by a common d. c. voltmeter of the type used for checking B-batteries, connected across the filament of any tube in the set; the reading should be between $4\frac{1}{2}$ and 5 volts. Obviously, when connecting tubes in series, the tubes on which the greatest voltage is desired should always be hooked nearest the negative end of the eliminator. These will be the audio-amplifier tubes. The detector, which requires the least plate voltage, is placed nearest the positive end. Of course, you cannot hook the second audio amplifier tube directly at the negative end for then you would not be able to get the necessary C-bias; therefore the first

DROP ACROSS 1ST A.F. FILAMENT PROVIDES C-BIAS ON 2ND A.F. TUBE



audio-amplifier tube is hooked in below the second audio, which will give 5-volt grid bias, or "negative-C," on the grid of the last audio tube. If 10-volt C-bias were required, it would be necessary to utilize the drop across two tube filaments instead of one.

However, for all practical purposes, the 5-volt drop across one tube appears to be satisfactory. In connection with the alter-

MATERIAL LIST

- 1 baseboard, 1 by 10 by 13 in.
- 8 Sangamo wound condensers, series B, 2-mfd.
- 1 Sangamo condenser, series A, 1-mfd., for 400 volts d.c.
- 2 Silver-Marshall power transformers, type 330.
- 2 Silver-Marshall unichokes, type 331.
- 4 standard X-type sockets.
- 1 common porcelain socket.
- 4 UX216-B, or CX316-B rectifying tubes.

- 2 Lynch, Ward-Leonard, or similar type, heavy-duty resistors, 5,000 ohms.
- 4 Fahnestock clips.
- 6 ft. lamcord, with plug.
- Wood screws, flexible, rubber-covered fixture wire (well insulated, stranded type).
- 2 brass rods, 5 in. long, No. 6-32 thread, $1\frac{1}{4}$ in. long, on each end.
- 4 No. 6-32 brass nuts and washers.

ation of standard receivers to series filament wiring, there is only one precaution to be observed, and that is, to bypass all r. f. and detector-tube filaments with 1-mfd. condensers, as shown in the filament wiring diagram.


A large detailed blueprint may be obtained from the Popular Mechanics radio department, 200 E. Ontario st., Chicago, for 25 cents, to cover postage and packing. Specify blueprint No. 119.

Repairing Loud-Speaker Diaphragm

Loud-speaker diaphragms of the mica type, while very efficient, are not as rugged as some others. Having one that was cracked, I tried various materials for replacing this diaphragm, and at last found that a disk of hard maple, cut to proper size and sandpapered to a uniform thickness of $\frac{1}{2}$ in., served very well. The tone quality was improved.—Malen W. Clark, Flint, Mich.

Homemade Low-Loss Coils


By using a short length of cardboard tubing and gluing six lengths of wood, bakelite or hard rubber on the outside, at equal distances apart, efficient low-loss coils can be made at home. The strips are planed or filed so that they have a triangular cross section and, if made of wood, should be coated with collodion or shellac, to prevent absorption of moisture. Bakelite or hard rubber is, however, the better material. To separate the turns of the coil evenly, a silk cord is run over and under them as indicated, or if desired, equally spaced nicks are cut along the edge of the strips with a knife file.



Cardboard Tube and Narrow Strips of Wood or Bakelite Make Good Form for Low-Loss Coil

Shock-Absorbing Tube Mounting

When tube sockets are rigidly mounted on the subpanel of a receiver, vibrations are readily transmitted to the tube ele-



Strip of Wide Rubber Band Makes a Shock-Absorbing Base for Tubes


ments, causing howls, which increase in intensity. These howls are called "microphonics" and can usually be eliminated by providing a shock-absorbing cushion under the sockets. The same result can be obtained by mounting them on a wide strip of rubber, which is fastened at both ends as shown in the illustration. Flexible wires should be used for making connection with the sockets instead of rigid busbar wire, which permits vibrations to be transmitted to the tubes even if they are mounted on a shock-absorbing base. The sockets should be held securely while inserting the tubes, to prevent tearing the rubber or pulling the wires loose.—H. R. Wallin, Brooklyn, N. Y.

Keep Aerial Away from Power Lines

When installing the aerial, be careful that no part of it runs over or under any electric wires or cables that may be on or near the building. Do not place the aerial near such wires, as they may be carrying high-voltage currents and, if the aerial should fall or come in contact with such wires, the high voltage would be conducted into the set—a very dangerous possibility. Always place the aerial at right angles to any power line in the vicinity; this will prevent the picking up of any interference from such lines.

Simplifying Battery Connections

Most radio owners have their individual ways of handling dry-cell batteries, but the method shown in the illustration, used



by one experimenter, is very simple and efficient. This consists in a compact assembly where the cells, placed one above the other, make connections in the same manner as in large flashlights. To make the negative contact a circular disk is cut

from the base of each cardboard container so that the positive terminal of the cell below makes contact at this point. Two pieces of 1-in. quarter-round molding are nailed to the wall, in a corner of a closet, or at any other convenient point, to hold the batteries in an upright position. A small brass terminal on the floor, at the base, provides a negative terminal of the assembly, and the positive connection is taken from the center post on the top battery.—G. A. Luers, Washington, D. C.

New High MU-Tube Increases Volume

A new "high MU" amplifier tube, known as the CX-340, has lately made its appearance on the market. It has been developed especially for resistance-coupled and impedance-coupled a. f. amplification circuits. The filament voltage required is 5; filament current, .25 amp., and the recommended B-voltage is from 135 to 180. The amplification factor is 30 instead of 20, as claimed for former tubes of this type. The requirement of amplifier tubes for resistance and impedance coupling is identical, but entirely different from the tube requirement for transformer coupling. This being the case, many radio owners who have been using resistance or impedance-


coupled amplifiers with the standard A-tubes have not been obtaining the best possible results from their receivers.

Fishing Poles for Aerial Masts

The auto camper will find a fishing pole handy for an aerial mast, as poles are usually a part of the camper's outfit and can be put to double use where it is difficult to erect a temporary aerial. The aerial wire, if sufficiently flexible and of small size, can be wound on an old reel. It is then easily unwound and will not become tangled. The pole may be lashed upright to the car and the wire stretched to some tree.

Homemade R. F. Choke Coils

Radio-frequency choke coils are used more and more, especially in short-wave receivers, and sets where it is difficult to keep the r. f. current out of the audio stages. Experimental r. f. choke coils are usually wound on empty sewing-cotton spools. Such chokes, however, have a large distributed capacity, as the layers of wire are very close together. The capacity may be considerably reduced by breaking up the winding into sections, or "slabs," and connecting these in series. The forms may be turned from wood or hard-rubber rod of suitable diameter, but as this necessitates the use of a lathe, the common



wood spool may also be used. The sketch shows how three sectional windings may be separated by two sets of wood or hard-rubber dowel pins driven into holes drilled through the spool. The pins are about $\frac{1}{8}$ in. in diameter, and their ends should be tapered to prevent splitting when they are forced into the holes. The lower illustration shows a cross section of the spool, giving the position of the dowel pins in the completed form. The winding of the

E. J. Cunningham, ham, d me. 1234-A 20 Church St. New York City

choke coil is carried out as usual, a total of about 300 turns of No. 30 gauge wire being required for the broadcast range. Wind 100 turns into the first "slot," then fill the next with another 100 turns, and finally the last slot. The wire is carried over from one section to the other without a break.—C. A. Oldroyd, Barrow-in-Furness, England.

Receiver Resembles Cash Register

Resembling a cash register, the radio receiver shown in the photo consists of three units, a base for holding the batteries, the receiving unit, which is a five-tube r. f. circuit, and a loud speaker. Tuning is done by means of levers connected to the condenser shafts, and extending through the casing of the set. They should be held in frictional engagement with each other, so that, when the main lever is moved, the others move with it, but either of them, of course, can be moved independently for balancing the different circuits over the entire wave band. A pointer on the main tuning lever registers with long sheets on either side. One of these sheets is printed with a list of high-power stations and, as individual receivers vary slightly in tuning, it is only necessary to carry a pencil line from the station name to the point where it comes in on the scales. The other sheet is left blank for logging. The chassis is one unit and, by removing the tube cover and taking out four screws, the set is bared for inspections or adjustment. The cabinet is of metal and effectively shields the wiring so the tuning is sharp.



Radio Receiver Resembling a Cash Register Has Levers for Tuning the Condensers

Directional Effects from Outdoor Aerials

Many radio fans have noticed that long outdoor aerials have slight directional



Getting the Benefit from the Directional Quality of Outdoor Aerials

tendencies. The signal from a long-distant station seems to come in better if it is directly in line with the aerial and the end of the aerial farthest away from the lead-in points toward it. With this in view, four separate aerials, at right angles to each other, and having separate lead-in wires, may be erected as shown in the drawing. The lead-ins are attached to the points of an induction switch as shown. The switch lever is connected with the aerial post on the receiver, and then, by merely moving the lever, any one of the four aerials can be used. By running a jumper wire across the points, any pair or all aerials can be connected to the set.

Simple Lead-In Arrangement

Bringing the lead-in through the window to the set, often puzzles the radio fan and seems to be the hardest problem to solve. There are several methods in use, such as drilling a hole in the glass, or through the sash or window casing, but each defaces the building and entails quite a bit of hard work. A simple method is to provide a strip of wood the width of the window and two or three inches high; this is drilled to take a porcelain insulator and is then set on the sill under the sash.

Blum's note
Base - 5.00
Receiver - 40.00
Speaker - 15.00
Blum Mfg Co, Clearwater, Iowa.




Orchestras in Japan Have Many Unusual Instruments and the Players Are Seated on the Floor; the Microphone of JOCK Being Specially Located for These Performers

Japan's Largest Broadcasting Studio

Station JOCK at Nagoya is Japan's largest and most popular broadcasting station. It has a 6-kw. transmitter and can be heard regularly on the western coast of the United States. The studio is equipped and arranged in both European and Japanese style.

Combining Phonograph with Radio Amplifier

Bringing the old phonograph up to date by combining it with a standard radio



Above, Front and Side Views of Tonearm with Button in Position; Below, Wiring Diagram

amplifier unit costs little and is well worth while. The newer phonograph records are electrically cut and have fuller tone and greater depth than the old type, but in order that the full tonal values be reproduced, a means of amplifying without distortion is necessary. A three-stage resistance-coupled amplifier unit is ideal for this purpose. Two MU-20 or high-amplification tubes should be employed for the first two stages, and a MU-6, or power tube, for the last stage, with proper C-battery. Such a unit, relatively inexpensive, will provide faithful amplification and volume sufficient for the largest living room, in conjunction with a good cone speaker. The pick-up device for converting the needle vibration into electrical variations consists of a small microphone known as the Skinderviken button. The diagram shows the connections for the button and how it is mounted on the tonearm of the phonograph.


How to Check R. F. Tubes

Of late many builders of radio sets are eliminating the detector jack because of the importance of using less wiring. This, of course, is an advantage, but has one drawback in that no provision is made for checking the r. f. tubes under operating conditions. Tubes, as they are turned

out today, are faulty in many cases and detection of these faults is difficult unless some means is provided for determining the quality of the signal as delivered by the detector tube. It is also a fact that many tubes do not make good r. f. amplifiers, and if distorted or weak signals are supplied by these tubes to the detector, poor results are sure to follow in the a. f. stages, no matter how good these stages may be. Experience has shown that, out of a dozen tubes picked at random, only two or possibly three will be good r. f. tubes. If no detector jack is provided, in the set, the operator may check the tubes by connecting a double-circuit jack in the detector output, or, for temporary checking, the phone-cord tips may be placed under the plate post of the detector tube and detector B-battery terminal, thus cutting out the audio stages.—L. H. Georger, Buffalo, N. Y.

Convenient Coil Form

For making spiderweb coils the form shown in the illustration will be found useful. It consists of two circular wooden



blocks, about 2 in. in diameter, although they may be larger or smaller to suit the coil you wish to wind. Cut a groove in one side of each block to accommodate the heads of nails, and fasten the blocks

together with screws or bolts so that the grooves are on the inside. Drill holes from the edge to the center of the blocks for nail shanks and be sure to space them apart equally. Then take the blocks apart, insert the nails, screw the blocks together again, and drill a hole in the center of the blocks, which completes the form. The construction may be simplified by using short lengths of brass rod instead of nails, and in this case it is not necessary to cut grooves in the blocks.—Arnim F. Reeves, Groton, N. Y.

Dull Finish for Panels

A novel satin finish on radio panels, which shows traces of circular rubbing,


Simple Homemade Tool for Giving Radio Panels a Dull Finish




can be had by using the tool shown in the drawing. It consists of a hardwood disk with a shank that will fit a carpenter's brace. A leather disk of the same size is glued on with waterproof glue and its surface is roughened with a file or fine sandpaper. Powdered pumicestone, moistened with water or oil, is used as an abrasive, the leather face of the tool being dipped in it and the tool then applied to the surface of the panel, rotating it evenly. The dull circles made in this way give the panel a very attractive appearance. 1121-2

Booster Charger Has High and Low Rate

The combined trickle and fast-rate charger shown in the illustration supplies a much needed means of quickly bringing back the A-battery to full charge, if the trickle charger should fail to meet an unusual drain on the battery. The toggle switch shown in the detail permits a quick change from a charging rate of $\frac{1}{2}$ to $2\frac{1}{2}$ amp., as required.



Antarctic Electric Co.,
4339 Sheena
New York



Radio Apparatus, Coupled to an Oscillograph, Is Used to Locate Noises in Automobile Motors

Radio Detects Automobile Noises


Visitors at an automobile demonstration in Detroit saw, projected on a screen, the shape that sound waves assume. It showed in popular form the more delicate and elaborate apparatus used for locating automobile noises. To study them it is necessary to reproduce the sound waves faithfully on a photographic film, where they are measured. The data are used to trace the noise to its source. The apparatus in the testing laboratory consists of three distinct units: the microphone, the amplifier and the oscillograph. The microphone picks up the noise vibrations in the air and changes them into pulsating electric currents. The vacuum-tube amplifier magnifies these currents until they become strong enough to actuate the delicate element of an oscil-

lograph. During this step, the current must not be distorted in the slightest degree. In the oscillograph, a tiny spot of light reflected from the moving element vibrates back and forth across the photographic film, which is placed on a drum. After development, the film shows a trace representing the wave form, intensity and pitch of the sound picked up by the microphone. Ordinary radio equipment is not accurate enough for this work, and each of these devices must be specially built for the purpose. Noise hunting in cars is difficult because vibrations may be "telegraphed" from one member to another, and thus there is always the danger that the wrong member will be accused of making the noise. It often happens, too, that, when the real source is found, the changes necessary to eliminate the noise, cannot be made. In such cases, one or more of the members through which the noise is being telegraphed are changed so that they will no longer respond to the vibrations.

Reproducing Phonograph Records

~~1186-2~~ Through Radio Set

The tone quality of phonograph music can be improved by fitting an earphone to the tonearm, connecting it with the audio amplifier of a radio set, across the primary winding of the first a. f. transformer, as shown in the diagram. This arrangement gives much more volume than the phonograph alone, which makes it especially suitable for use in halls. The loud speaker can also be located a considerable distance from the phonograph, which may be convenient on many occasions.



Arrangement for Reproducing Phonograph Records through a Radio Receiver

*General Motors Corp
Detroit, Mich*




How to Make a Camp Baker

By C. P. FORDYCE


ONE mark of the efficient camp craftsman is that he be able to make good meals from scanty food supplies. Perhaps nothing is so trying as to attempt to make good breads with the limited utensils at hand. In the north woods the reflecting baker of aluminum or light tin is the most popular style for all kinds of baking and roasting. It consists of two flat metal surfaces set at an angle with ends closed to hold the heat, and with

the flare or open front before the leaping flames of a camp fire; in the center of this angular unit is set the bake tin with its batter or dough. The heat from the camp fire hits the polished flat upper surface and is thrown down upon the top of the breadstuff and from the lower up against the bottom of the bake tin. Being of thin-gauge sheet metal and folding flat, the reflecting baker weighs but a few ounces and is easily carried in the pack.



How the Reflecting Baker Is Used; Note the High Fire and the Back-Log Reflector, and How the Baker Is Supported to Throw the Heat against Both Sides of the Pan

You can make one of these bakers at home and for this you will need a piece



Details of Construction of the Reflecting Camp Baker and the Baking Pan

of tin, 12 in. wide and 33 in. long; half a dozen small hinges, a pair of tinner's shears and a punch, two dozen tinner's rivets and a hammer. Cut the tin into three rectangles, 12 by 11 in. on the side, and use two to make the top and bottom of the reflector. They are hinged together so that they will fold like the covers of a book. The sides are made by cutting the third piece of tin diagonally across, producing two triangular sections, which are both hinged to the bottom piece of the baker. Lugs are formed on these, and on the top piece, as shown, to take a piece of wire that locks the baker when open. Near the center of the sides punch holes for inserting the ends of the wire pan rest. When you wish to use the baker, drive two small stakes into the ground and rest the rear edge of the baker on them. The bake pan can be made of another piece of tin if not purchased; the dimensions are from 8 by 10 in. to 8 by 11 1/4 in.

The special points about the fire for the reflector are that it must be built high and preferably with a back log reflector. A low fire burns the lower side of the biscuits before the upper side browns. The best woods to use are hickory, hard maple, oak and birch. Later these will

burn down to a fine set of coals which can be utilized for another cooking. The regulation of the heat is done by moving the baker to or from the fire and by laying a green log on the ground before the tops of the biscuits are done. The secret of success of the camp baker is the envelope of hot air, which must not be too hot and which must be kept even. Practically all of the commoner recipes in baking and roasting can be used.

"Digging" Worms with Electricity

On a recent fishing trip, I found it difficult to get worms, so I took two electric-lighting wires of opposite polarity and connected each one to a screwdriver to make good contact with the shank. These I stuck into the ground about 4 or 6 ft. apart and then turned the current on. In a short time, the worms came to the surface so that they could be picked up.—E. W. Carroll, Portland, Oreg.

Combination Lamp and Picture Frame

Novelty lamps of various designs are quite popular nowadays, and the one shown in the photo will perhaps strike your fancy. It is a dresser lamp and serves the additional purpose of holding a photo. It consists of a base and two standards, on the end of which miniature sockets are mounted for lamps of the design indicated. The standards are drilled lengthwise to accommodate the lampcord, which leads to each socket, these being connected in parallel in the base, which is drilled for that purpose. The connections should be well soldered and taped. The picture frame is pivoted between the standards.—B. J. Jakaitis, Chicago, Ill.




Lock for Ford Coupe


To prevent thieves from stealing things from the rear end of his Ford coupe, one owner put on a latch which could only be opened from the inside of the car. After the latch is closed and the doors are locked, the rear end cannot be opened unless pried. A small wire leads from the latch to the left side of the cushion and fastens to a ring, which prevents it from slipping back and also serves as a handle. When the wire is pulled the latch is released. To make it work automatically, a spring in the latch pushes it back again and locks the rear end as soon as the wire is let go.—R. E. McNatt, Beaumont, Tex.

Locating Knots on Quilts

In making comforters, the work of locating the various equidistant points where knots are sewed on, can be simplified by using string as shown in the illustration. The length and width of the quilt are divided into equal spaces along the supporting frame and tacks inserted at each mark. Twine or yarn is strung across the quilt from tack to tack to weave a sort of lattice and pins are inserted through the quilt at each intersection. The string and tacks are then removed and the work of tying may be accomplished in a short time.—G. E. Hendrickson, Argyle, Wis.



Simple Method of Locating Correct Position of Knots on Quilts or Comforters




Four-Wheel Brake on Boy's Coaster

Boys who make their own coasters will find it useful and interesting to provide a four-wheel equalizing brake as shown in the drawing. It consists of two crosspieces attached to a specially made wooden frame by means of steel bolts. Small coil springs are slipped over the bolts, between the crosspieces and the frame, to keep the former from touching the wheels when the brake is not applied. Both the front and the rear crosspiece are provided with a length of sash cord, one being run through pulleys and attached to a foot lever and the other fastened to the eye of the central pulley, as shown clearly in the details of the illustration. By forward pressure on the lever, which is pivoted to the underside of the car, the brakes are applied.—Hi Sibley, Los Angeles, Calif.

Two shotgun shells, one of 12-gauge and the other of the 16-gauge size, make a neat and useful matchbox for the huntsman; the larger shell fits snugly over the smaller one, making the box practically waterproof.

Side Guards Improve Tonneau Seat

Tonneau seats, which are used on a large number of roadsters, can be improved by the provision of side guards. These are



Triangular Pieces of Upholstering Material Fitted with Snap Fasteners Improve Tonneau Seat

simply triangular pieces of top covering, or upholstering material, edged and provided with eyelets to fit snap or turn-type fasteners which are driven into the seat. Besides helping to keep out dust and draft, they add to the appearance of the tonneau seat.—G. A. Luers, Washington, D. C.

How to Calk a Small Boat


Wooden boats are prevented from excessive leaking by calking between the planking. This consists in driving in some suitable material between the planks so that it will be held firmly by the swelling wood and will close the seam to make it water-tight. The paint later applied also acts as a binder. In calking, the first operation is to smooth off the outside of the hull with the plane and sandpaper; then prepare the calking material, either oakum or spun cotton. Pull out and lightly twist enough of the material to lay in a few feet of the seam. Then, with a calking tool, drive in the material by placing the edge of the tool on the material and tapping the handle with a hammer. Drive it in well but not hard enough to spring the planking or split it on the inside. If the seam is narrow, it may be necessary to lubricate the calking material slightly with graphite. If the seam is too


tight, open it with a chisel. One seam should be finished before commencing the next, and no calking material left projecting above the surface of the hull. When the calking is done, the hull should again be gone over with a small block plane to remove all the rough spots and then sandpapered. For boats that are to be painted, the sandpaper can be rubbed crossways of as well as with the grain, but for boats that are to receive a varnish finish the sandpaper should be rubbed only with the grain. First use the rough grade and then the fine. The priming coat of paint should be applied well into the seams to bind the calking material to the wood and prevent it from "spitting" out. When the final coats are applied, the seams will be well covered so that they are invisible. In calking old boats, be careful not to start the planking by too severe use of the calking iron and do not chip off the soft edges of the wood. Cotton soaked in linseed oil makes a slightly better job as the oil fills the pores of the wood and binds the cotton to it. An old hull should be dried out for several hours before calking it.

Simply Constructed Lawn Sprayer

A simple and practical lawn sprayer, consisting of a gaspipe tee, two plugs and a carriage bolt, can be made in a few minutes. One of the plugs is drilled to receive a $\frac{1}{4}$ -in. carriage bolt, 10 in. long, and from this bolt the head is clipped and the shank filed to a sharp point, as indicated. A rubber or lead washer is used in assembling the bolt and plug to make a watertight joint. The plugs are screwed into the tee after an angular slot has been sawed in the latter, as shown.

With the hose attached and the sharpened bolt inserted into the ground, the sprayer is ready for use and, in operation, will provide the wide mistlike spray so desired for the watering of lawns and gardens.





Novel Aerial Trolley for Diving into Small Streams Where Shallow Water Prevents the Practice of Diving from the Banks

Trolley for Bathers

If you go swimming in a narrow river where it is impossible to dive from the banks, rig up a trolley over the stream, as shown in the illustration. A strong rope is securely tied to a tree on each bank, one end higher than the other. The trolley consists of a piece of 2 by 4-in. stock to which two wooden pulleys are attached by means of U-shaped hangers. An ordinary bolt is slipped through holes

drilled in the end of these and washers are placed between the sides of the hangers and the pulleys. A rope handle is provided for the rider, being fastened to the trolley as shown, and a long rope is tied to the latter so that it can be pulled back to the starting position. The rope should be coiled to prevent it from being tangled when the trolley takes off.—Dale R. Van Horn, Lincoln, Nebr.

Simple Repair for Leaky Drain Pipe

Many small repair jobs around the house can be done with cement. A leaky drain pipe from a kitchen sink was fixed by this means. In this instance the lead pipe, which ran down through the floor, had broken loose where it was joined to the cast-iron pipe and also had a hole, about $\frac{1}{4}$ in. in diameter. Narrow strips of cloth, soaked in a thin mixture of cement and water, were wound around the joint. A

few turns of some light wire around the cloth served to reinforce it, and another layer of cloth and wire was applied for good measure. This repair has lasted for over two years and it still remains in perfect condition.—J. H. Edwards, Huntington, W. Va.

☛ To remove a cork from a bottle drive a screw-eye into it, and if the bottle has to be uncorked frequently, leave the screw-eye in the cork.



Homemade Ejector Attached to Water System Lightens Labor on Wash Days

Ejector for Emptying Washtubs

Carrying tubs of water is a difficult task and emptying them by buckets takes time. This work can be eliminated by using the ejector shown in the drawing, which acts as a siphon. Run a length of $\frac{3}{4}$ -in. pipe from the water main down the wall, vertically, and fit a valve on the end. A short nipple is screwed into the valve, a Y-fitting is added and then another length of pipe, which leads to the drain. A short nipple is screwed into the Y-fitting and a length of hose is attached as shown. The Y-fittings should be lower than the bottom of the tub when standing on a bench, in order to make the ejector work effectively. When a tub is to be emptied, place the end of the hose in the tub near the bottom and turn on the valve. The rush

of water through the pipe will suck the water out of the tub. After the siphon action has started, the valve can be closed.

Reclaiming Old Paint


Many amateur painters have wondered why paint that has stood for a time in a can, more or less exposed to the air, creeps and cracks in spite of the best efforts in brushing it over the surface painted. This action, though troublesome, is not due to the method of handling the brush, but is due to too much exposure to the air.

What should be done is to mix the paint with benzine or gasoline and allow it to stand, after being well stirred, for a day or more. Then pour off the benzine or gasoline with the oil and add a fresh supply of linseed oil and a little more drier than would ordinarily be used.

Sand Box for Children Built of Concrete

Children's sand boxes are usually made of wood, but concrete gives a better appearance and is, of course, more durable. The box should be large enough to accommodate several children. In building one, a trench is dug to a depth of about 18 in. and wide enough to receive wooden forms made of $\frac{3}{4}$ -in. material. The stakes, which are lengths of 2 by 4-in. wood, should not be over 3 ft. apart. Care should be taken that the top of the form is level and that the inner surface is as smooth as possible. The form should be drenched before it is filled. About $1\frac{1}{4}$ cu. ft. of concrete will

be required for each running foot. A box 15 ft. long and 5 ft. wide will require $48\frac{3}{4}$ cu. ft. of concrete. The mixture is made in the proportion of 1 sack, or 1 cu. ft., of cement to $2\frac{1}{2}$ of sand and 4 of pebbles, ranging from $\frac{1}{4}$ in. to 1 in. in diameter. All told, about 10 sacks of cement, 25 cu. ft. of sand and 40 cu. ft. of pebbles will be required. The next



Concrete Sand Box for the Children Is Neat-Looking and Durable

day after the form is filled it may be removed and the surface of the wall troweled with a small amount of cement and sand in the proportion of 1 to 2. Before the mortar has hardened, the entire surface should be painted with a well-stirred mixture of cement and water of a creamy consistency, which may be applied with an old paintbrush. The wall should be kept damp for several days and may be covered with wet burlap, straw or building paper to protect it from the sun. The sand box is filled, to a depth of 9 to 18 in., with clean, white sand in which children will enjoy playing. A concrete floor is not necessary, but if desired, provision should be made for draining it.—A. J. R. Curtis, Chicago, Ill.

Auto Radiator Automatically Blanketed

A Wisconsin merchant who keeps several delivery cars in a small, unheated garage at the rear of his store, found that, while the blanketing of the radiators between trips preserved the heat of the engines so that the starting was made easier and required less fuel, the crowded park-




Blankets Hanging in Garage Automatically Drop Down and Cover Auto Hoods

ing space in the building made the task rather difficult, and the drivers often neglected it. To overcome the trouble, blankets are hung from the ceiling, so that, when a car is driven into its space, they automatically cover the radiator and front.

Making Deadeyes for Ship Models

One of the jobs that daunts the amateur ship modeler is the making of the numer-




ous deadeyes required for the standing rigging. With a couple of simple tools, however, this job can be robbed of its terrors, and enough deadeyes for the average ship can be made in a single evening.

The first tool is made of a short length of $\frac{1}{4}$ -in. drill rod; a $\frac{3}{16}$ -in. hole is drilled along the axis, as shown in Fig. 1, and the end is then ground to the shape shown, and sharpened to a good edge on the oil-stone. The deadeyes are made of boxwood, old scales or rules providing the material, and they are marked on the wood, as indicated in Fig. 2, using a light hammer to outline the circles with the tool. The next step is to drill the holes for the lanyards, and, in doing this, be sure to lay out and drill the holes as shown in Fig. 4. The tool is now mounted in the brace or hand drill and the deadeyes cut out.

The next tool is a short length of $\frac{3}{16}$ -in. dowel stock, Fig. 3, into the end of which has been driven three bank pins, spaced so as to fit the holes in the deadeyes, and cut off so that they do not project through the latter. With a deadeye mounted on the end of this tool it is easy to sand the curve on the face and to cut the groove around the edge, using a rat-tail or a triangular file for the latter operation.—L. E. Davis, Syracuse, N. Y.

☞ Scorch marks on linen may be removed by rubbing with a freshly cut onion and afterward soaking in cold water.

How to Pick



TO the inexperienced canoeist all canoes look pretty much alike, but there are on the market a wide variety of models, many of which are made for special purposes; so it behooves the beginner in canoeing to "watch his step" when he strolls into a sporting-goods store to buy his first canoe.

Shape, length, breadth and weight are the four factors that must be kept in mind when selecting your canoe for lake or river use. I have found that the best way to get these four factors impressed in one's mind is to stand in front of several racks holding canoes and then check on these factors by an inspection of each model. For example, you may see a short, compact, speedy-looking little craft that looks "cute"—so attractive, in fact, that you want to buy it at once. That is the way I felt when I first saw a 12-ft. one-man "boat." But it is not adapted for general canoeing, for you and your guide to go fishing in. It is a one-man outfit, a specialized craft limited in carrying capacity and stability. In this manner you learn that flat-bottomed, wide canoes are more stable, but not so speedy as narrow round-bottomed craft.

Most canoeists, and especially those who pack up their duffle and make fairly long




trips on a river or through a lake region, want carrying capacity and stability, with speed a third consideration. In other words, when one turns explorer by water and takes along a complete camping outfit, the craft must be steady, have ample storage room and at the same time paddle with ease. Length and width are the two most important factors in deciding seaworthiness and carrying capacity. So, if you are looking for a cruising canoe, you must not buy or use a short narrow craft.

To illustrate this basic rule of canoe use, consider the 15 or 16-ft. boat of narrow beam alongside of the 16 or 17-ft. craft of wider beam. You'll find that the shorter boat is relatively unstable and pretty tricky when you try to pack anything in it, or fish from it. On an average, a 16-ft. canoe weighs in the neighborhood of 65 lb. It is apt to run closer to 70, although last summer I used an all-wood seventeen-footer that weighed (when dry) but 65 lb. All canoes take on poundage when wet. You can figure on each additional foot of length weighing about 5 lb., but

700 La Salle St
Chicago

Your Canoe *by* Bob Becker



that extra foot makes it possible to chuck in another duffle bag, as, generally speaking, it adds anywhere from 65 to 75 or 80 lb. of carrying capacity, depending on the model. When in doubt, get the extra foot of length, as it's an investment in comfort and safety. The average man has no hankering to cruise for days with the gun-wales of his canoe too close to the water, when, by adding a foot in length, he can rest easy.

After an arduous canoe trip through a virgin wilderness lake region last summer, where there were many portages and fairly heavy loads to consider, I am ready to advise the 17-ft. flat-bottomed, all-wood canoe as an ideal "buy" for the man who wishes a cruising canoe that is light, steady and able to carry a good load. Here was a trip with rapids to be run, which introduces the possibility of an occasional collision with a boulder, and a lot of duffle to be transported. To meet these requirements I found a canoe that was broad-beamed and steady, with ends that were not too high, so that windage was cut

down, and yet the craft had high enough gun-wales and rode so easily that one could stow away an exceptionally heavy load. Another feature of this canoe, one which you may want to consider if you are going to put your outfit through a pretty rough trip, was the all-wood construction. Made of three-ply birch, it surprised me to see how it would run on a sharp rock without a puncture. Instead of a jagged hole resulting from such an encounter, the pliable birch would give, and, barring the removal of varnish from a spot on the bottom, the canoe would be undamaged. For fishing, this seventeen-footer was ideal because it had short covered decks at each end. As you look at a canoe in a sporting-goods store, you may not give this feature a second glance. But here is how I found these two compartments useful. There was just enough room in the covered space at the prow to keep my fly book, reel, rain-shirt and tobacco pouch, and when it rained, I could reach for the shirt without worrying about the rest of the outfit, as it had protection.

The seventeen-footer I used for cruising and wilderness travel last season had



Two Views of a Good Wood-and-Canvas Cruising Canoe; It Has a Shallow Draft and Is Easy to Handle

no keel. This was a disadvantage when fishing in a wind, as it was almost impossible to hold the canoe against the breeze. The combination of flat bottom and shallow draft gives you no purchase on the water, especially without a keel. To get deeper draft, so that the canoe will keep its course more readily in a wind, you will find experienced lake canoeists turning to a different type. Lake work means wide stretches of open water upon which a wind has an unobstructed sweep, and in this situation you will find the round-floored canoe quite popular. Thousands of round-




bottom wood-and-canvas canoes have been bought and are being used on lakes, because they are the most efficient paddling "Injun-style" boats to be had. But my tip, after rocking around in many canoes of this type, is to get plenty of length

and a broad beam in your lake canoe, together with the round bottom. There is a decided tendency to roll in this type of craft, as you would expect in any with a round bottom. To counteract this, you again need length and width, those two faithful allies of stability. In the case of a lake canoe, there is apt to be little portaging, and hence you do not have to figure on weight so closely as you do in choosing an exploring ca-



One of the "Two-Man" Nipigon Canoes of Canada, an Ideal Craft for Use on Heavy Trips in Swift Waters



Above, 18-Ft. American Canoe for Lake Work; Note the Flat Bottom of the 17-Ft. Birch Canoe at Left

which air chambers have been added on both sides, at the gunwales. These chambers run from bow to stern and give the canoe a bulging appearance, which, however, you soon forget when you see how it performs.

This type of canoe is ideal for the summer camp, for family use, and as I have indicated, for sailing, as it doesn't tip you over on the slightest provocation. It will teeter to one side, if you don't sit straight or if you shift your weight, but the sponsons prevent it from going clear over. You will find that a canoe of this type weighs considerably more than an ordinary canvas or all-wood canoe of the same length, and because of this fact it is not suitable for a trip requiring many portages. It's a family canoe; the last word in safety for camp and lake purposes.


Now let us see what to buy for a more

noe. So buy an eighteen-footer for lake work and avoid those that have ends so high that they look like Venetian gondolas. On a windy day, those high ends act like sails, and add enormously to the difficulty of steering.

If you want a "family" canoe, one for sailing, or one in which you don't have to watch your step every minute, don't overlook the sponson canoe, which is the safest craft in the whole canoe family. Every outdoor fan who likes the water is ready to call the average canoe temperamental—and that's just what it is. Some are more so than others, but all have to be handled with care and none will brook many liberties. But the sponson is different, and this is the reason why: It is a canvas canoe to



Here Is a Good Cruiser Type for Two Men, Especially Where Many Portages Are Encountered



Drawings Show a Sponson Canoe and a 16-Ft. River Model; Below Are Shown Another Cruiser, a Lake Type, and One Method of Transporting a Canoe

intimate kind of paddling and exploring — that found on the small stream or river.

Although a 17-ft. flat-bottomed wood, or canvas-and-wood, canoe will serve very well, as such a craft is at home in almost any kind of water, the very best type of canoe for winding, twisting streams that are comparatively narrow is the one that is short and of fairly narrow beam.

I have had this fact driven home on a trout stream in the north woods. This stream flows out of a big spring hole tucked away back in the timber about a mile from a lake into which it flows. The stream winds and twists through the timber, broadening here into a pool and there rushing over rocks to make a riffle. To make quick turns, to get around the "corners" of that stream, you need a rather short, narrow canoe, one that obeys a flick of the paddle and responds instantly. Wind-

age need not be considered, as on a small stream hemmed in by dense forest, the breezes get little or no sweep. Nor is carrying capacity important, for one does not ascend the stream for a day's fishing with heavy tents and duffle, such as are carried on a long cruising trip. You will find that outdoorsmen naturally turn to a 16-ft. canoe for small-stream work. Sometimes they pick a canoe that is 31 in. wide, sometimes a 36-in. beam is chosen. But always the bottom should be flat for this work, as the idea is to get a craft that draws as little water as possible.

If you want a canoe that will do for lake work as well as small-stream work, one of the above-described type is not suitable, for it is not adapted for open-water work. Most outdoorsmen, facing the problem of a so-called all-around boat, will select a

17-ft. flat-bottomed canoe. Such a craft is not unwieldy on a small stream.

Occasionally the outdoorsman has need for a large, two-man canoe with exceptional carrying capacity—a boat for freighting or long-distance traveling on pretty good-sized rivers. This demand has brought into use one of the most unusual and serviceable canoes to be found anywhere. It is the giant wood-and-canvas canoe widely used on the Nipigon river in Canada, where swift water requires two paddlers and the trip involves large loads. On a long river trip in the north, where two men would be on the water for several months, with few portages, this type of canoe is ideal, and every outdoorsman should know about it. The boat is so wide of beam that two small persons can sit side by side. It is such a carry-all, that two passengers, two paddlers and hundreds of pounds of baggage can be transported without trouble. Moreover, it takes the rough water like a bird. We have shot swift long rapids in this "taxicab" of the canoe family without trouble and without getting wet.


Sooner or later, the beginner in canoe-craft must face the question: Which should I buy, a canvas or all-wood canoe? These are the two general classes of canoes on the market today. In the case of the former, you have a boat made by covering a framework of wood with canvas. It is not an all-fabric boat as the name would imply. If you want speed in your craft, better stick to an all-wood canoe, as they are, generally speaking, faster than the wood-and-canvas models. Yet, in spite of the all-wood type's speed and general practicability, the wood-and-canvas craft is more popular with Americans.

If you like the sport of sailing and want a canoe for this exhilarating fun, turn to the wood canoe and get acquainted with the most individual and highly specialized of all canoe models. Although you can turn an ordinary open canoe into a sailing craft, the special canoe is an all-wood boat, which, with the exception of a cockpit for the boss of the outfit, is entirely decked. But this is not its only distinctive feature. It is provided with water-tight compartments so that it will not sink, and it has a centerboard and a sliding seat. The need for the latter—a novelty in most

boats—comes when the sailer hauls close to the wind so that his craft heels over. To keep it from going clear over, he slides out beyond the boat's side where his weight offsets the dip.

Concrete Poultry Nests


Poultry nests made of concrete will not harbor lice, if disinfected occasionally, and a poultry man who wishes to make a number of these can do so readily. The forms are made of metal, as shown, and must be oiled so that the concrete will not adhere. The mixture used is 1 part of cement to $2\frac{1}{2}$ or 3 parts of sand. When the molds are arranged in position to receive the concrete, the front or open end is up and the concrete is rammed in with a $\frac{1}{4}$ -in. wooden rod. A piece of $\frac{1}{4}$ -in. wire mesh, or similar material, may be put in for reinforcement. After the nests are removed from the forms, they are covered with wet burlap for a few hours and then are immersed in a tank or trough for at least three days, with a moderate or warm temperature. Nests made of concrete can be easily cleaned and even burned, if desired.



Concrete Poultry Nests Are Practically Lice-Proof if Disinfected Occasionally

Office on Wheels

As manager of a new hotel, I have to travel between it and my old hotel ten blocks away. The new building is under construction and, the temporary office be-



Using a Sedan as an Office Which Is Fitted with an Improved Desk

ing dusty and dirty, I found it more convenient to use my sedan as an office when prospective tenants arrived at the new hotel. To facilitate writing, I arranged a sort of desk as shown in the drawing. It consists of a smooth board, hooked across the sides in front of the rear seat, special fittings being provided for this purpose. In the evening the lights are turned on and meals can be served if desired.—John F. Daschner, New York City.

Pointers for the New Auto Driver

Never, under any circumstances, race your engine, especially when new. More engines are ruined by racing than are worn out by proper driving. Besides, there is no sensible reason for racing the engine, even to warm it up, as many

drivers do. The engine will warm just as fast if run for a few minutes at a moderate speed as by racing it. If it is absolutely necessary to warm the engine up in a hurry, hang a sheet of paper over the radiator to shut off the air circulation.

Don't move the steering wheel while the car is stopped. This puts a very great strain on the entire steering mechanism, and it is scarcely ever necessary. There is usually room to move the car under power a few inches at least, and the steering wheel can be moved much more easily and with less strain on the mechanism when the car is moving even slightly.

Don't rush up to the place where you are going to stop and then slam on the brakes; save them for the time when you will need them more. It is just as easy, and much more pleasant for the passengers, to coast to the point where you are going to stop, and then apply the brakes gently, if they are needed at all. Gentle stopping is the mark of a good driver; "grand-slam" stops the mark of a very poor one.

If the car skids, leave the clutch engaged, and steer the car in the direction the car is skidding. That is, if the rear wheels skid to the right, turn the front wheels to the right side also. Turning them

to the left will only aggravate the skid. On slippery surfaces, if it is necessary to apply the brakes, apply them gently and intermittently, and leave the clutch in while the brakes are used. This will reduce the tendency to skid.

Use the motor as a brake when going downhill. That is, leave the clutch in, and keep the throttle closed. Keep the switch on. Apply the hand and foot brakes alternately if the hill is a long one, to keep the brake linings cool and reduce wear. If the hill is a very steep one, stop at the top, change down into second gear and go down using the motor as a brake.

Don't try to pass another car on a curve, on a hill, at a street intersection, or anywhere else where the view of the road ahead is obstructed in any way. There might be another car coming in

the other direction, and if there is, you might not have room to avoid him.

Use the best oil you can buy for your engine, remembering that it is the cheapest in the long run. Follow the maker's instructions about lubricating the car faithfully; if you lubricate every part of the car twice as often as he recommends, it is all to your own advantage.


Keep your foot off the clutch pedal except when you want to throw it out. "Riding the clutch" will only result in a repair bill sooner or later.

Fill in all cuts on tires with "tire dough," to prevent moisture reaching the interior of the casing and rotting the fabric.

You will find many nuts and bolt heads on the car unpainted. Paint these at once with a quick-drying enamel to prevent rust and subsequent bad appearance. Get underneath the car and paint all the unpainted spots you can see, and while you are there, oil all the brake connections, using steam-cylinder oil, not engine oil. The heavy oil stays on and lubricates these connections better.

Tighten the body bolts after the first 500 miles and go over them every 1,000 miles after that. Examine all screws and bolts about the body periodically and keep them tight, to prevent squeaks and rattles as long as possible. Tighten up spring clips after the first 500 miles also, and after that see that they are kept tight.

Holding the Teakettle Bail



Many teakettles are made with no provision for holding the handle in an upright position, and burned fingers often result. A simple remedy for this is to file notches in each ear of the kettle, as shown in the illustration. A small round file is used for this purpose. This allows the upper and lower sides of the bail loops to enter the slots, so that the handle will be supported perpendicularly.—G. E. Hendrickson, Argyle, Wis.

To Keep a Tent Warm Overnight

To keep a tent warm all day or night several methods can be used. One is to dig a hole in the ground inside the tent,



Heating the Campers' Tent during Cold Weather Increases Comfort

fill it with hot coals from the campfire and then cover it with an inverted bucket. If desired, the next day's ration of beans can be cooked by burying the can in the hot coals and letting it lie there overnight. To keep a slow-burning fire in a sheet-iron stove requires the use of a minimum of draft. First build a hot fire in the stove, to get a good bed of red-hot coals. Then fill the stove with pieces of logs as large as it will hold, give it a small draft, and the fire will burn for a long time.—Claude P. Fordyce, Falls City, Nebr.

Method of Saving Gas-Tank Gasket on Late-Model Ford Autos

The late-model Ford gasoline-tank caps are supplied with a loose cork gasket sealing the joint between the cap and the tank, to prevent loss of gasoline. The gasket is easily broken or lost, and at most service stations both cap and gasket would have to be purchased as the latter is not sold separately. The loose gasket should be cemented to the cap with shellac and the exposed side should be dusted with graphite or tire mica to give a smooth surface and avoid tearing it.—E. T. Gunderson, Humboldt, Iowa.

A Square-Rigger for the Boy


By HI SIBLEY, 1954 *Bridge Blvd. Pasadena, Calif.*

THE vogue for model craft which has launched ten thousand ships has left the youngsters somewhat unenthusiastic, for the reason that these picturesque little masterpieces cannot be tried out in the bathtub. "Gee, that's keen!" they say when shown a new model, and then ask, "Will it float?"


After the model shipbuilder has pa-

tiently worked for weeks on the intricate rigging and delicate trim of the "Santa Maria" or the "Half Moon," he is ready to go to the other extreme and make a simple ship.

The "Southern Cross," here illustrated, combines extreme simplicity with great seaworthiness. There is not a single unnecessary item in its entire construction.



Here Is an Easily Made Model of a Square-Rigger That Will Really Sail, and That Will Provide Endless Amusement for Any Boy



Details of the Model "Southern Cross"; While Extremely Simple, It Is Very Realistic, and Satisfies the Boy's Desire for "One That Will Float"

yet it is a very fair model of an old-time square-rigger and rides like a swan. It can be pulled over onto its beam ends, until half the sails are wet, and will right itself at once. Old salts may be somewhat amused at its queer rigging, but it must be borne in mind that the "Southern Cross" was designed for easy construction and sturdiness to stand rough usage in the hands of a hard-riding young skipper.

The hull is roughed out with a coping saw, which also is used to cut away the inside of the central block. Attach the bottom piece and deck to the central block, using glue and nails. Then round off bottom corners and stern overhang with a plane, chisel or drawknife. Next put on the wedge-shaped bow and stern pieces to give the deck the proper sheer or curve fore and aft.

The masts are made from $\frac{1}{2}$ -in. dowel sticks, tapered with a plane, and the bowsprit from $\frac{3}{8}$ -in. dowels. Bore holes for these but do not set them until after the keelboard is fitted.

The proper amount of ballast is important. This size model will take about $\frac{1}{2}$ lb. of lead on each side of the keel, that is, 1 lb. altogether. Make your own mold. Two pieces of board, nailed at right angles, with wood blocks or putty at the ends for

stops, will do nicely. Set three or four nails upright in the mold in order to make holes in the ballast pieces to fasten them to hull. The wood mold must be absolutely level when pouring from the ladle. When cold, cut the lead into two equal pieces and finish the rough edges with a file. Nail on both sides of keel, just a little back of center, in order to keep the bow higher than the stern.

For the rudder post, use about $\frac{5}{16}$ -in. dowel, and bore a $\frac{3}{8}$ -in., or larger, hole to receive it, so that it will still be loose enough when the dampness swells it. An extra item, though not necessary, is the wood cowl over the top of the rudder post, carrying a small clock gear as a dummy steering wheel. This, of course, can be left off entirely.

Yards should be cut from $\frac{1}{4}$ -in. dowel sticks, and tapered to each end with the

plane; each yard should be $\frac{1}{2}$ in. shorter than the one directly below it. Yards, masts, bowsprit and deck should be given a coat of orange shellac.

Paint the hull a bright vermilion below the water line, and green or black above. Give two coats of these colors, ground in japan, then one coat of spar varnish.

The dimensions of the sails given allow for $\frac{1}{4}$ -in. hem all around. When the sails are set and the yards slung to the masts, go over the strings with a coat of shellac to keep them in place.

Novel Method of Growing Strawberries

It would seem impossible to grow 1,500 strawberry plants properly on a plot of ground 12 by 26 ft. in dimensions. A glance at the photo shows how this has been done, however. A number of concrete blocks, 3 ft. long, 2 ft. high and 15 in. wide at the bottom, were cast, the forms being made from old dry-goods boxes. The blocks were made hollow, with a solid base. Muffin tins were attached to the outside to make the holes in the sides. The making and fitting of the forms, which were collapsible, was the most difficult part of the work, especially the inner one. When finished, the blocks were filled with dirt and the strawberry plants inserted, one in each hole. The roots were watered by pushing a broom handle down into the dirt and pouring water or fertilizer into the holes thus made. With this arrangement much more area is obtained for growing the berries, no dirt gets on them, there is no weeding to be done, and it is easy to clip the runners. To prevent birds



Growing 1,500 Strawberry Plants in a Small Backyard, in Hollow Concrete Blocks

from visiting the patch, it is an easy matter to cover the block with netting.

Grinding Juicy Substances with Food Chopper

If an ordinary food chopper is used to grind juicy substances, trouble is often ex-




perienced with the juice leaking out at the crank. Screwing the chopper in an inclined position, as indicated, causes all the drainage to take place at the other end. This can be done by providing a triangular strip on the chopper and cutting a nick in the edge of the bench, or by clamping on a board which is inclined. Both alternatives are shown in the illustration.—A. Stenson, Gardena, Calif.

Filling the Auto Gas Tank

Many motorists blame gasoline for being poor when the trouble lies in the gasoline hose at the service station. The hose is often hung onto the tank with the nozzle up. Immediately after a rain the water will get into the hose and when the gasoline is poured into the auto tank the water also gets in. Many times the hose is nearly half full of rain water and the motorist is always anxious to get the amount of gas in the hose, not knowing that some of it is water. Therefore it is a good idea, when purchasing gas, to make sure that the water is run out of the hose before putting the gas into the tank.—Charles Latour, Jr., Plattsburg, N. Y.

Lee McCrae
1707 N. Hill Ave.



A Rack on the Inside of the Pantry Door Will Increase Storage Possibilities Considerably

Making More Room in the Pantry


In small apartments or houses where space is limited, the inside of pantry doors and closets offers storage possibilities. The photo shows a homemade rack accommodating about twenty kitchen utensils. It is a three-sided affair, the door itself forming the fourth side. Screweyes are driven into the two ends and front side to hold a number of utensils. Holes are drilled in a wooden strip nailed to the front on the inside, to hold a pair of scissors, pliers and similarly shaped devices. A hole is also drilled in the top of one of the ends to hold a funnel. The front is made of slats so that one can see the storage space behind, which is used for egg beaters, etc., piled in loosely. Just below the main rack a carving set is supported at its ends by two vertical blocks, having holes drilled for this purpose. A third block, with a slit in it, serves as a guard to protect the point of the carving knife. A pencil sharpener is mounted below, where it is within easy reach of the children. The arrangement shown is suggestive only and may be modified.—L. I. Thomas, Oak Park, Ill.

Old Films Start Fires

If you intend camping out this year, be sure to include in your equipment as many old camera films as you think you will need, for although they won't take pictures for you, they will often enable you to get a good dinner in a hurry. You will find them particularly useful for starting a fire on damp and dull days. While a match will splutter and go out, the film is highly inflammable, so after getting the wood all piled to start the fire, stick a piece of film in among the starting twigs and light that instead of the twigs themselves. You will be rewarded with a hot blaze that burns long enough to give the average fire a start. You can easily carry all the films you need in an envelope, and should they get damp, a handkerchief will wipe them off so that a match will light them.—H. A. White, Cedar Rapids, Iowa.

Fastener for Wire Gate

Stretched wire gates, so much used, are greatly improved and made more secure against being opened by the stock by using an S-shaped piece of strap iron, about 1 ft. long, as shown. This enables one to open and close the gate with one hand, which is often handy when carrying something. For a light gate a piece of old buggy tire or similar flat iron will do. Drill two holes near one end to receive nails, which hold it in place on the post, as shown in the illustration.—J. S. Ward, Alamo, Tex.



Salvaging Stained Chamois Skin

Chamois skin that is heavily stained with paint and oil may be salvaged in a very simple manner. Soak the skin in a pail of rain water, to which has been added a gill of strong ammonia, for a period of


about 12 hours, after which it should be washed out in tepid water (not hot) with pure soap. This puts the skin in better condition than when it is new, for the lint has been removed, and better work can be done with it than before.

Adjusting Carburetor for Altitude Driving

The first thought of the autoist on driving in high mountains is that, on account of the lowered air pressure, he must increase the flow of gas to the carburetor. This, however, will be found to choke the carburetor and slow down the speed. The correct way is to admit less gas to the carburetor to make the gas mixture of the same proportions as at sea level. As the altitude increases above the mile limit you should gradually close down the gas supply to keep the motor running evenly and the carburetor from choking and smoking.

Wire Rack Holds Doors and Windows

To keep doors and hinged windows open and prevent them from being closed by the wind, either of the simple holders shown in the drawing will be found effective. One consists of a length of heavy galvanized-iron wire, bent as indicated and attached to the lintel above the door so that it will hold the door at any point. A window or door catch made of spring wire, such as bicycle or motorcycle wheel spokes, is shown in the lower detail.—V. Hodruss, Port of Spain, Trinidad, B. W. I.




Wire Holders and Catches Hold Doors and Windows Securely against the Wind

Handy Manuscript Holder for Speakers

Many speakers use small notebooks in which to write speeches, but the manuscript holder shown in the drawing has

Handy Manuscript Holder
Is Made from Film Spools,
Lengths of Wire and Rub-
ber Bands



been found much handier. It consists of a frame, made of two lengths of No. 12 galvanized-iron wire, and two rubber bands arranged to hold two camera film spools. A roll of paper, the same width as the spools, is obtained and the lecture or speech written on it. The ends are cut to a tapered point so that they can readily be inserted in the film holders and the strip of paper is then rolled on one of the spools. It is an easy matter to wind up the strip on the empty spool, and, when finished, a rubber band can be snapped around the spool and the lecture can be filed for future use.—R. M. Thomas, Denver, Colo.

Preventing Putty Marks on Ground Glass

Objectionable marks on ground glass, when glazing a window frame, are made by the oil in putty, and are very difficult to remove. The best and simplest way to prevent them is to rub soap on the edges of the glass before the putty is applied, so that the film will keep all stains from the glass.

Changing Balloon Tires

Anyone who has undertaken to change a balloon tire on the road has found the job troublesome with the use of the ordi-



Lessening the Usual Difficulty Experienced with a Jack When Changing Balloon Tires

nary jack furnished with the car. Much of this is due to the difficulty of placing the jack under the axle with the little clearance available when a balloon tire is flat. It is also due to the long lift that is necessary to raise the car high enough to remove the flat tire. The method illustrated overcomes these troubles. The spare tire is first removed from the carrier and placed directly ahead of the flat tire which is to be changed. The car is then driven slowly forward so that the flat tire rides on the spare. In this position, it is easy to place the jack under the axle, and only a little effort is required to raise the wheel so that the flat tire can be removed. The spare is then lifted up and placed into position for service.

Softener for Paintbrushes

Keeping paintbrushes soft between jobs is one of the bugbears of the home painter. Those that have become rock-hard will probably have to be thrown away, but as long as one shows any pliability, it can be brought back to normal as follows: Mix equal portions of raw linseed oil and gasoline and place in a can deeper than the


total length of the brush. Immerse the brush part and put cover on can. In 24 hours, the bristles will be sufficiently softened to allow the gum to be worked out with the hand, whereupon the brush is finally cleaned by washing in pure gasoline.

Preserving Battery Carriers

The band of some battery carriers, under the center of the battery, is usually covered with red, rough rust which is likely to wear into the bottom of the battery case. If the battery is in a metal box, this does not occur, but there are many rubber-cased batteries in use which are not placed in a box, and also many wood-cased batteries. The battery-carrier band should be wrapped with one or two layers of friction tape; this will wear through in time, of course, and also rot if acid reaches it, but will prevent wear on the bottom.

Homemade Renewable Fuse Plug

A renewable fuse plug can be made from a two-piece attachment plug, as shown. Obtain a spool of fuse wire of sufficient strength to take care of the local 110-volt 60-cycle supply, and place a short length across the prong terminals of the plug unit. The screw part of the plug is then turned into the socket and the prong unit pushed in place. If the fuse blows, it is easily renewed.



Cleaning Phonograph Turntables

After considerable use the green-felt covering of a phonograph will become soiled with grease from the hands and from dirt picked up from the records themselves. One of the best cleansers for this is ether. Buy a few cents worth at the drug store and, moistening a clean rag with just a little of the fluid, rub the felt briskly, and the dirt will disappear as if by magic. Ether leaves no stain, the odor soon disappears and the felt looks like new.




All Shop Notes published in 1926, in book form—Fifty Cents—from our Book Department

A Hot-Flame Blowpipe for the Shop

By H. W. PHILLIPS

IT frequently happens that a very hot flame is needed for a short time in the experimental shop for melting small quantities of metal, welding, etc. In such cases the apparatus described in this article will furnish intense heat at once. It is simple and the expense of making and using it is slight. It is merely the old-time chemical-laboratory gas generator adapted for use

turning it into an oxy-hydrocarbon flame. The outer container may be any sort of vessel that will hold water; a mason jar or a tin can of any sort. Tin friction-top containers are excellent. The top of this is closed with a plug, of wood, cork, or even plaster of paris. This stopper has a hole in the center to admit the inner tube or container, which holds the "oxygen cubes" commercially called "oxone." This tube may also be of any suitable material, even



A Couple of Small Containers, a Length of Tubing with a Blow-pipe Tip, an Alcohol Lamp and a Supply of Oxone Provide the Experimenter with an Intensely Hot Flame

in supplying a stream of oxygen to the ordinary blowpipe frame, thus



*inner + Amend
3rd Ave
18th St
New York
2 lb.
cans
at \$1.60
per
can
plus
shipping
charge*

*not available
must be sent by
express*

paper that has been waterproofed by soaking in paraffin, if nothing else is at hand.

About 1 in. from the lower end of the inner tube is placed a disk cut from screen wire, slightly larger than the inside diameter of the tube, so that the edge may be bent over, holding the disk in position by pressure. This disk keeps the lumps of oxone out of reach of the water in the outer container until the gas is needed.

A piece of metal tubing to run through the plug of the inner container, a length of rubber tubing and a stop clip, such as used on fountain syringes and obtainable in any drug store, and a common, so-called jewelers' blowpipe, costing a few cents, complete the list of material.

If the plugs for the tubes are to be made of plaster, the easiest procedure is to first pour the mixed plaster in a paper box, larger than the diameter of the outer tube. When the plaster has become a little firm, but before it has set hard, grease the edge of the tube, and cut the plug as you would a biscuit. Then shake the plug out, and cut another for the inner tube. Next, push the center tube through the inner-container plug. The plugs must fit snugly, but yet be easily removable.

In operation, the outer container is filled about halfway with water, and the plug replaced. The plug of the inner tube is removed, and some lumps of oxone dropped on the wire screen. Then, first making sure that the spring clip on the rubber tube is closed, so that no air can pass through, the inner tube is put in position. Atmospheric pressure prevents the water from reaching the oxone until the spring clip is opened. When it is opened, water flows up into the inner tube, reaches the oxone and generates oxygen with sufficient pressure to be used as a blowpipe stream.

Any sort of flame may be used; candle, alcohol or plain kerosene. A lamp with flat wick is preferable, the flame being blown the long way of the wick. As you are now dealing with straight oxygen, the heat obtained will surprise you; it is quite comparable to the oxyacetylene or hydrogen flame.

Oxone may be obtained from large chemical dealers, and costs about \$1.60 for a 2-lb. can. It keeps very well, if the lid of the can is tightly replaced. I have

had a can for five months and the material shows no deterioration.

Oxone is sodium peroxide. The water, after use, is a strong solution of caustic soda, so do not get it on your hands or clothes. I saved some of the solution in a tightly stoppered bottle, as a strong alkaline solution often comes in handy for getting rid of grease.

Iron in small form, either cast or wrought, melts easily in the flame. By proper manipulation, and in a closed furnace, small castings can be made. Even platinum (of course in very small quantity) will yield.

All the interesting oxygen experiments can be performed, by using a fruit jar, in the bottom of which is put about $\frac{1}{2}$ in. of sand or ashes, and then pour in a couple of inches of water. Drop a lump of oxone in, and there's your oxygen.

Phosphorus burns in oxygen with a light like the sun. A watch spring or other high-carbon steel will also burn; to demonstrate this, first draw the temper of the spring by heating it, straighten it, wire a match to the end, strike the match, plunge into your jar of oxygen, and the spring burns with a brilliant light, small globules of melted steel and oxide falling to the bottom of the jar. There is nothing dangerous about a little oxygen.

Substitute for Focusing Cloth

Most photographers know how unhandy it is to use a focusing cloth, espe-



Old Bellows Is an Excellent Substitute for Focusing Cloth and Gives Good Results

cially when taking outdoor photos in the wind. By using an extra bellows from a discarded camera and attaching an eyeshade to it, as shown in the illustration, the focusing cloth can be dispensed


with. The small bellows on the front end serves as a lens shade, preventing light from falling on the lens.—Leonard Eilers, Burbank, Calif.

Substitute for Frosted Glass

The breaking of a very large frosted-glass window found us unable to get another in town because of its size. An immediate replacement was imperative, for the glass was a part of the partition of a doctor's private rooms. We finally hit upon an idea that solved the problem easily. A new clear glass was fitted in place and wiped to remove grease and dirt. Then, with a clean brush, the glass was given a coat of white spar varnish on one side. After allowing it to stand half an hour, we applied flour, finely sifted and free from lumps. The flour was dusted on and the surplus wiped off with a light sweeping movement. The result was as good in appearance as the other frosted glasses in the partition. When the varnish had dried, another coat was applied to waterproof it.—H. E. Walker, Herkimer, N. Y.

Conveyor Loads Lumber on Flat Cars

Considerable space and time are saved in a lumber mill by the installation of a double-track overhead-conveyor system, for loading lumber on flat cars, as shown in the photo. While one conveyor is being unloaded on one side of the flat car, the other is loaded, and is then brought in position for unloading while the empty one leaves. Both tracks converge to a single track outside of the loading space.



Adjustable Creeper Headrest, Supported on a Coil Spring, Provides Comfort for the Auto Mechanic

Spring Headrest Makes Creeper More Comfortable

When using a rolling creeper for any length of time there is considerable strain on the muscles of the neck and shoulders, as the worker must often raise his head, unsupported, to see how to manipulate the tools. The spring headrest shown in the illustration will be found an effective remedy for this. The center board is fitted with a padded headrest on one end, is hinged in the middle, and a discarded auto-cushion spring is fastened between the headrest and the crosspiece. When reclining upon this creeper, the workman can force the headrest down, or by relaxing, allow it to support his head.



Western Sawmill Uses Overhead-Conveyor System to Load Flat Cars Quickly



Flexible Shaft for Doing Light Drilling, Grinding and Buffing by Motor Drive

Flexible Shaft for Small Tools

For the home workshop, a flexible shaft for driving small tools electrically from a stationary motor will be found of considerable utility. It consists of a speedometer shaft, a drill chuck and a $\frac{1}{8}$ -hp. motor. Cut off the square end of a shank and rivet the latter to the endpiece of the speedometer-shaft chain, the lugs on the latter fitting holes that are drilled in the shank. File a slot in the end of the motor shaft, to receive the lug on the fitting at the other end of the chain, and drill a hole through both for a cotter pin. Also drill a hole in the shank of the chuck for a pin to hold the chuck while tools are inserted.—J. Augustus Prendiville, Southboro, Mass.

Convenient Opening in a Fence


In places along a fence where a farmer or rancher often goes through, but where he does not wish to place a gate, a simple device may be installed. Buy some round-eye swivel snaps, or use old ones that have been discarded around the barn, one for each wire in the fence. If the opening is made at a wooden post the snap is nailed on with a staple, but if a steel post is in use a wire is used in attaching the snap. In each case the snap should be stationary,

and should replace the staple originally used to hold the wire to the post.

When one wishes to pass this place all that is necessary to do is to open the snap, withdraw the wire and hold the wire down while the horse or vehicle passes. It is very easy to snap the wire back, and this saves much time, as otherwise it would be necessary to pull out the staples to loosen the fence.

Robbins & Myers, Springfield, Ohio.
Fire Extinguisher Operated Automatically

A western manufacturer of electric-motor coils had to keep constant guard against fires in the varnish rooms and arranged extinguishers as shown, which would tip over automatically and sprinkle their contents out through a length of perforated pipe. Each of the extinguishers is supported by two lengths of strap iron, which are screwed or bolted to an overhead beam and drilled through the lower end. A circular strap-iron band is clamped securely around the extinguisher well below the center. Pins, riveted through each side of the band, serve to pivot in the holes drilled in the strap-iron supports. When thus arranged, the extinguisher is top-heavy, but it is held in a nearly vertical position by means of a wire, soldered to the bottom and attached to the beam, as shown. This is cut in half and a length of fusible wire inserted, which, when



Ordinary Fire Extinguisher Tips Over Automatically When Heat Becomes Excessive

J. B. Robbins, Harwich, Mass.

*S. S. White Dental Supply Co.
152 W. 42nd St. New York
Chicago Flexible
Shaft Co. 1124 S. Central Chicago*

*Process Extinguishers for the purpose
of preventing fire
Chicago Flexible
Shaft Co. 1124 S. Central Chicago
E. 45th St. New York
H. 11th St. New York*


melted, allows the extinguisher to tip over. The rubber hose is connected to a sprinkler pipe running through the drying troughs. Should a fire start, the heat will melt the fusible wire. This releases the overhead extinguisher, which tips over, thus breaking the acid container and creating the pressure to force the contents out of the sprinkler pipes and quench the fire at the start.

Placing Brush Cover Bands


The brush cover bands on Ford starters and generators are clamped in place by a screw drawing the two ears together, one on each end of the cover band. There is a $\frac{1}{2}$ -in. gap between the ends of the band when clamped in place. If this gap happens to be placed over one of the openings in the generator or starter yoke, dust and dirt will be admitted. Therefore, the cover band must be placed with the gap over the metal of the yoke, and between the openings giving access to the commutator. The first models of the Ford starting system have a solid cover band, which cannot be placed wrongly.—E. T. Gunderson, Jr., Humboldt, Iowa.

Repairing Lawn Mower

To repair a pawl housing in the wheel of a lawn mower, I drilled a $\frac{3}{8}$ -in. hole in the pawl and a $\frac{1}{16}$ -in. hole in the casting, threaded the latter hole with a $\frac{3}{8}$ -in. tap and then screwed in a $\frac{3}{8}$ -in. bolt from the inside so that the pawl pivoted on the bolt. Two nuts are used instead of one to lock them on the bolt without binding against the casting. The writer used a mower with four of the six pawls fitted in this way for a whole season.—Oscar Boding, Crosby, N. Dak.



Barbed-Wire Rack Prevents Cattle from Breaking Wooden Farm Gate



Farm-Gate Protector Prevents Cattle from Breaking It

Wooden gates used between fields are likely to be broken down by cattle trying to reach over them to get at fodder in the next field. This trouble can be prevented by hooking a barbed-wire protector over the gate, as shown in the illustration. It consists of a wooden frame, with the wire applied as indicated in the lower detail, and two pieces of flat iron bent to form hooks, which are slipped over the gate. It is placed on the gate so that the barbed-wire section is on the side where the cattle are, and will effectively prevent them from reaching over. In the drawing, however, the protector is set on the wrong side to make the arrangement plainly visible.

Removing Scratches from Plate Glass

Scratches in plate glass can be polished out easily in the following manner: Mix powdered chalk, 60 parts; tripoli, 30 parts, and ~~hole~~ 15 parts, to a fine powder. Dip a wet, soft cloth in the above preparation, and rub the scratched spot until it has disappeared. The method is, of course, not applicable to very deep scratches.

from Aluminum Reduction plant - Aluminum Company

Dry red clay Pulverized as fine as possible

2444 Oliver Blvd
Cittisburg, Pa.

Device Paints Boards Quickly

At a western woodworking plant it was necessary to prime a large quantity of pine siding. In order to do this as quickly as possible, the painting device shown in




the photo was made. It enabled two men to paint 1,000 pieces of 6-in. siding, 8 ft. long, in five hours. A sheet-metal trough, about 3 ft. long, 1 ft. wide and 1 ft. deep, is mounted on strong metal legs and two sets of rollers, between which the boards are passed, are arranged in and above it, as indicated. Three of the rollers are of metal, while the fourth is wood with a covering of carpet tacked on. This rolls in the paint and applies it to the underside of the board as it is pushed through. A large brush near the other end, also on the underside of the board and inside of the trough, removes surplus paint and assures a neat, smooth job. Besides the timesaving feature, all waste of paint is avoided by using this device.—Jos. C. Coyle, Denver, Colo.

How to Protect Your Trees against Mice and Rabbits

Here is a kink that costs nothing and is worth many dollars to orchard men. Go to a railway siding where cedar ties have been peeled, gather up a quantity of the bark and cut it into 18-in. lengths. Drive strips of bark into the soil around

the tree trunks and tie a cord around their tops. As the bark is light, a large quantity can easily be carried in a bushel basket. It will be partly curled by the sun, if the ties or poles have been peeled sometime previously, and this curvature will make it fit the tree trunks. I have tried tar paper, wire screen, etc., for the same purpose, but this suits me best and costs the least. Leave the bark in place summer and winter. Bugs will not hibernate in it. The growth of the tree will stretch the twine for two or three years until it breaks. The bark, if it is stuck well into the soil, will still stand as long as the tree needs it—five or six years, until the



Machine Used by Western Woodworking Plant for Painting Large Quantities of Siding; It Does the Work Quickly and Wastes No Paint

danger from mice and rabbits is past. If I were located where cedar bark was not available, I would use cedar stakes, split from old telephone poles, railroad ties or fence posts, in the same way. Cedar shingles would also answer the purpose, set with the thick end down.—J. H. Deniston, Bayfield, Wis.

Crude Oil as Wood Stain


A wood stain with many practical uses in the laboratory or workshop can be made from crude petroleum. Mixtures of it with gasoline in varying proportions will give stains for the softer woods in good imitation of practically anything from light, golden oak to a dark walnut. Oils from different districts have different characteristics, and the right proportions will have to be found by experiment. The gasoline evaporates quickly and leaves the

wood with a dull finish. Polished effects can be obtained with the usual methods for other stains, but a cheap and durable polish is realized by applying hot beeswax with a brush and rubbing off the excess with a soft muslin cloth. Such stains are useful for shop or other furniture that is subject to hard usage, as they are cheap, have high penetration, keep the wood-work neat, and act as a preservative.

For laboratory tables or storage-battery workbenches, where an acid and waterproof coating is desired, the following can be used: Apply a generous coat of boiling-hot unmixed crude oil with a brush. If the wood is well seasoned and porous, apply a second coat. A finishing coat of a hot half-and-half mixture of crude oil and beeswax should be applied, and the excess oil and wax rubbed off with rags or waste. A blowtorch or Bunsen flame played over the surface of the wood to keep it hot will assist this rubbing operation. The resistance of this coating even to hot concentrated acids as encountered in chemical analyses is surprising. Care must be taken, however, as hot crude oil is inflammable and therefore large quantities should not be heated over a flame.


Wrench for Bending Small Pipe

When no pipe-bending table or wheel is available, the work can be done by means of an ordinary large-size monkey wrench, with a hole drilled through the jaws as shown in the illustration. The outer edges of the hole are chamfered off with a file. Usually it will be found best to hold the pipe in a vise, but



sometimes the handle of the wrench may be gripped in it to better advantage.

Bends of different radii are made by regulating the distance between the jaws of the vise and the wrench. A 1-in. hole will accommodate pipe up to $\frac{3}{4}$ -in. iron size, the largest to which this method can practically be applied.—O. S. Sprout, Lancaster, Pa.



Air Pressure Applied to Auto Cylinder Locates Compression Losses Quickly

Compression Loss Detected by Air Test

Compression leakage in an auto engine is sometimes difficult to locate. Contributory causes, as warped valves, worn or stuck piston rings and broken gaskets, are not easily detected by inspection of the parts. The drawing shows a method of determining accurately the loss of compression in a cylinder, by means of a special plug made from the shell of a spark plug and a valve stem from an inner tube. The piston is placed at the bottom of the compression stroke, air pressure is applied and the mechanic listens for the hiss of leaking air. If this is audible at the breather pipe, the piston rings are at fault; if it occurs through the carburetor, the intake valve is leaking, and if it can be heard through the muffler, the exhaust valve is the offending member.—G. A. Luers, Washington, D. C.

□ A type cleaner for typewriters which has proved entirely satisfactory consists of carbon tetrachloride, 95 parts, and ammonia, 5 parts; it is applied with a brush, and the type should be rubbed with it until it is clean.



EASY WAYS to

stone, floor and a dash of colorful design on the ceiling beams, which lends life to the whole.

When Oskar J. W. Hansen, a sculptor, wanted to convert an old barn into a studio of real distinction, he found a simple way by which the costly method of European construction could be reproduced. The accompanying pictures show the results obtained, and the method is amazingly simple. All it requires is a careful attention to the details described.

The first thing is the "stone" work: After you have removed the old wall paper or calcimine from the walls and ceiling they are ready for the work to begin. As you will see from the photograph the stone work can be varied in height and design to fit around the doors and win-

Applying the Stain for the "Parquet" Floor; Note How the Glass Is Held So the Stain Will Not "Blot"

TO possess a Castle in Spain may seem a very unattainable dream; but when the plain, drab four-square walls of any room may be made to reflect the variety, dignity and charm of an old-world interior by a small expenditure and effort on your part, you lend substance to the stuff of your dreams.

The buildings of Europe seem to have grown out of the ages. They have that livable feeling which is the real mark of a home. This charm is produced by the successful combination of a great variety of building materials. There is the picturesque strength of stone masonry, the intricate designs of wrought-iron hinges and lock plates, the mellow rough texture of aged woods, the infinite variety of rough plastered walls, the parqueted, or perhaps,

dows. The rest of the walls and ceiling should be in a fairly simple rough plaster texture. This gives a solid feeling of balance to the room and at the same time provides a wall of interesting variety.

The plaster material used as a foundation for this stone mixture is called marb-l-cote B. To a gallon of boiling water add enough of this powder to make a mixture the consistency of cream. Then mix in, slowly, enough plaster of paris to make a thick paste. Stir this paste until it is free from lumps, and it is then ready to be applied to the wall. This should be done at once, while it is still soft and warm.

With a pencil, draw a rough outline on the wall to show the height and shape of your stone work, and then with a small square plasterers' trowel spread on the


may
3617 S. Wall

Mr. Teller

Marb-L. Cote. Inc.

25 400 N. Michigan Ave.
Chicago, Ill.

BEAUTIFY *your* HOME



View of Corner Studio, Showing the Effect of the Floor, the "Stone Work," the Rough Door Texture and the "Wrought-Iron" Hinges and Latch on the Door

paste fairly evenly and about $\frac{1}{4}$ in. thick. After it has hardened for about fifteen minutes, take a stiff small brush or a whisk-broom and, with a sidewise motion of the hand, make scratches all over the surface of the plaster. Ever so often, pound the brush in straight and then pull it away. Some of the material will follow the brush and leave rough holes and marks on the wall. In this way you can produce any kind of stone effect you wish. The softer

the paste, the rougher the texture. For a sandstone effect, let the mix get quite hard on the wall before brushing.

The next step is to mark off the joints between the stones. It is better to make the stones of varying sizes and shapes, and this is done by simply dragging a small modeling tool along a straight guiding stick. A modeling tool for this purpose can be made out of a round stick, 6 in. long and $\frac{1}{4}$ in. thick. Make one end



Another Door, with Simpler Hinges and Ornamental Frieze on the Lintel; Below, Close-Up of Door

flat and pointed and the other end oval and rounded. With this tool you can model anything you wish. While the plaster is still soft, you may even want to model into the center of some of the stones some simple design of a flower or a rosette. When the plaster gets dry, these designs look like stone carvings. In the same manner you may model an ornamental lintel for the top of door openings or an ornamental shelf for the fireplace. You do not need to do all this in one day, as the material joins easily to itself. When all the stone work is done, let it dry for at least two days. Then do the coloring.

While the walls are drying, you can get on in your work by making the imitation wrought-iron hardware. Leave your old hardware on and model over it. The mixture for this work is the same as for the walls except that you put in more marb-l-cote and but a small quantity of plaster of paris. This will give you a mixture which will withstand the constant vibrations of opening and shutting the doors. The mixture should also be made a little stiffer than for the walls. For the design of your hinges, you may either use those



of the accompanying illustration, design some yourself, or consult illustrated books on ancient buildings at the public libraries. You will find a wealth of designs to choose from. First draw the designs on tracing paper and then transfer them to the doors.



View Showing How the Stone-Work Design Is Carried around Window Openings in Irregular Yet Unified and Highly Artistic Style

If the door is heavily varnished, the surface should be scratched with a coarse sandpaper so as to give a "tooth" for the plaster. After transferring the design onto the door, drive a few small large-headed nails into the wood and let the heads stick out about $\frac{1}{4}$ in. Now spread the warm plaster mixture onto your design, to the thickness you want your hinge, and let it set for a while. When it begins to get hard, fasten your tracing paper over the plaster and cut through to the wood with a small penknife. In this way you will get a sharp outline of your work. Then you can imitate hammered-iron effects by using the rounded end of your modeling tool and squeezing dents into the plaster, and with some softer material put in the rough "nail heads" in their appropriate places. Do not do this work of modeling too carefully; leave it a little rough and crude—it looks more genuine that way. The hinges should now dry for at least two days. During this time you may antique

the woodwork and rough-coat the upper walls and ceiling.

The mixture for the woodwork is the same as for the hardware except that you add enough water to make it very thin—thinner than for the walls—and apply it to the wood with a medium-sized paintbrush. By stippling it on the wood you will get a nice rough texture of even roughness which you may vary with a twist or turn of the brush now and then to suit your fancy. The same thing can be done with the upper walls and the ceiling. They can be made a little rougher than the walls but not too much so; it is better to keep them fairly plain so as to make a contrast with the stone. The whole room is now allowed to dry and then you can proceed with the coloring.

To color the stone work, apply first one coat of a light cream-colored flat enamel. When this is dry, make a thin mixture of turpentine, burnt umber in oil, and add just a little raw sienna and lemon-yellow.



A Glimpse of the Plasterboard Ceiling Beams; the Windows Here Formerly Lighted the Horse Stalls in the Barn

Put the colors into the turpentine very slowly and a small quantity at a time. Stir until they are thoroughly dissolved. Try on a small sample until you have the correct shade. Now begin to color each stone in the wall by itself. Rub into the texture a quantity of the color mixture with a small paintbrush and, while it is still wet, rub off enough with a soft rag to leave the stone of the desired color. In this way you can vary the tones of the individual stones according to how much color you allow to remain. It is also a good idea to save some of the cream-colored enamel and from time to time stick your brush into it and then into the umber mixture. In this way you will give some of the stones a sort of warm gray, dusty finish that is very agreeable.

For the woodwork of a Spanish or Italian interior, pistachio green makes a very pleasing color contrast. Pistachio green

is made by painting your woodwork with two coats of flat enamel colored a light blue. Cobalt blue into white makes the right color. When this is dry, brush on the same kind of color mixture that you used for the finish of the stones and wipe off with a soft cloth. The umber mixture will turn the blue into a soft mysterious shade of green, and the slight roughness produced by the marbl-cote finish retains enough of the darker coloring to give the wood an aged, mellow appearance. This finish grows more beautiful with age.

You can now make the hardware a dark dusty brown by allowing the umber mixture to dry on without wiping. Then, after it is dry, add a few touches of raw sienna to give a rusty effect and a few touches of red to the nail heads for the purpose of color accents.

The upper parts of the walls and ceiling should be done in a soft grayish shade of tan, to harmonize with the stone work. They can be given added interest by making a thin mixture of orange and then dipping the points of a sponge into the color and touching the sponge very lightly to the wall. A faint touch of color like that gives the wall a deep vibrant feeling, while at the same time it is apparently very plain and severe. If the ceiling has beams, they can be stenciled in some quaint old pattern, but it is equally satisfactory to leave them plain.


The room is now all finished except the floor. A very distinguished-looking floor can be made by staining an ordinary oak floor with dark squares. The size of the squares should vary with the size of the room, 12 to 18 in. being the average size. After the floor is finished in the ordinary manner (do not attempt this finish over varnish), the squares are measured off

and marked on the wood in pencil. Care should be taken to have them come out as even as possible on all sides of the room. For the light squares the wood is left in the natural color, while every other square is stained dark in checkerboard fashion. The effect is a floor almost equal to the finest parquet. The handling of the penetrating stain so as to get sharp lines without blotting into the light squares requires careful attention to the method used. A piece of glass, a few inches longer than the square, and a new 1½-in. rubber-set flat brush are used to apply the stain. The glass is held at an angle of 45°, as shown in the illustration. The brush is dipped in the stain and wiped almost dry in the center of the square to be stained; then, with a steady motion of the hand, a line is made along the glass on each of the four sides of the square. The secret is to keep the brush almost dry. The center of the square is then carefully brushed in.

The cost of such a floor is just about one-tenth of a real parquet floor, and the appearance is about the same. After the stain is dry the floor is either varnished or waxed the same as any ordinary floor. A few small Oriental rugs will complete the picture. The room will look spacious and elegant and will always seem inviting for dances and entertainments. With the fine reproductions of period furniture which are now so cheaply and easily obtained, you can carry out the rest of the ensemble and become the proud possessor of an honest-to-goodness Castle in Spain.

Remedy for Slipping Tractor Belt

Tractors travel so slowly in comparison with the speed of the engine, that a slipping fan belt will invariably cause an overheated engine. To prevent slipping, wrap several turns of tape around the center of the fan pulley and the pulley on the engine crankshaft. This provides friction and causes the belt to ride in the center.



Brakes on Railway-Station Trucks Prevent Them from Moving When Not in Use

Coin or Washer Stacker

A useful tool for stacking piles of similar coins or washers can be made of sheet metal, bent as shown in the drawing. The stacker is pulled through a pile of coins or washers and will pile up several at each pull. By pushing the tool backward, the pile thus collected will be left standing by itself. To stack without counting the pieces, the pile picked up at each movement can be left as it is. If it is desired to count as well as stack, the tool should be made the proper height to hold a certain number of pieces. If the stacker is not filled by pulling it through the pile, a few extra coins or washers can be quickly added with the fingers.



Brakes Make Hand Trucks Safe to Handle

A large eastern railroad has applied a pair of brake shoes to all of its platform baggage trucks to prevent them from being moved when the handle is raised and hooked. The brake shoes are a pair of wooden blocks bolted to the cross-piece on the handle. Besides preventing movement of the truck when it is not in use, the brakes also will control the movement of a truck under a heavy load on an inclined surface.

being moved when the handle is raised and hooked. The brake shoes are a pair of wooden blocks bolted to the cross-piece on the handle. Besides preventing movement of the truck when it is not in use, the brakes also will control the movement of a truck under a heavy load on an inclined surface.



Simple Tool Made of $\frac{1}{2}$ -In. Wire Mesh, to Give Rough Finish to Plaster

Stipple Trowel for Rough-Surfacing Walls

During the construction of a new house I watched the interior finishers give the plaster a rough finish. The tool used for this purpose was made by folding over a piece of wire mesh and attaching it to a wooden handle. By twisting, patting or stroking the tool over the plaster attractive finishes were produced. The tool was of the very simplest construction. It was found that $\frac{1}{2}$ -in. wire mesh, 6 in. wide and 24 in. long, was best suited to the purpose. The ends were tapered to fit the handle, and then the strip of wire was doubled over lengthwise so that the ends could be tacked to the handle, as shown in the illustration and details.—L. B. Robbins, Harwich, Mass.

Painting over Keene's Cement


To paint or enamel over Keene's cement successfully, the painting must be done at the latest within 24 hours after the plasterers have finished their work. The reason for this is that this cement is very sensitive to moisture and, though apparently dry, will absorb all of it present in the atmosphere. When the cement has absorbed moisture, it is impossible to keep the paint from running when it is applied. This is quite enough to prevent any chance of doing a perfect job.

Effect of Temperature on Steel Tapes

The United States temperature standard for steel measuring tapes is 68° F. The standard tension for a steel tape, 50 ft. long, supported throughout on a horizontal flat surface, is 10 lb. The coefficient of expansion of steel tapes, as determined by the bureau of standards, is .00000645 in. per degree Fahrenheit. This means that steel tapes change by that fraction of their length for each degree rise or fall in temperature. This figures out, for a 50-ft. tape, to an increase in length of .00387 in. for 1° rise in temperature, and the tape is shorter by the same amount for 1° drop.

Wheel Sign for Delivery Cars

The wheel disk shown in the drawing does not revolve with the wheel, but stands still, and the wheels appear as if they were sliding along. The disk is made of medium-gauge tin, and is cut the size of the wheel without the tire. A $\frac{1}{8}$ -in. hole is drilled in the end of the hub cap, a 1-in. stove bolt is inserted through the hole from the inside, a nut is screwed on it at the outside, and the disk is then put in place. Two nuts are screwed onto the end of the bolt to secure the disk. The first nut is not screwed up tight and the second nut locks the first. A piece of strap iron



Signs on Automobile Wheels Remain Stationary While the Wheels Rotate


is riveted to the lower side of the disk, on the inside, and acts as a ballast to keep the disk from turning with the wheel. This makes an attractive sign, which can be read whether the car is moving or standing still.—Thos. F. Johnson, Cuero, Tex.

Sand Blast Removes Paint from Wicker Furniture

When it is necessary to repaint reed or cane furniture, it is nearly impossible to remove the old paint. An Indiana bus company experiencing this trouble, solved the problem by means of sand blasting. The sand was applied at a 45-lb. pressure, to prevent cutting the reeds, and care was taken not to keep the blast on one spot too long. The same method was used to remove paint from canvas roofs.

Emergency Repair for Stripped Valve-Stem Thread

Due to excess pressure and hard usage, a steam-valve connection in a small paper-making plant was stripped, resulting in continued escape of steam. It was impossible to cut out the line, and to make a quick emergency repair, the method shown in the illustration was used. A rough clamp was formed from a piece of heavy flat iron to fit the valve, and a hole was drilled and tapped through it for a threaded screw, which was made from an iron rod and bent. Obviously the same repair is applicable to screw-down faucets or valves in water lines.



Air-Pressure Test on Radiators


A good method of testing a repaired radiator consists in immersing it in a vat of water and then pumping air into it. An ordinary tire pump is attached to a special filler cap, which screws onto the



filling opening. To eliminate the danger of damaging the radiator by too high pressure, one repair shop has adopted the safety measure shown in the illustration. An inner tube is used as a reservoir for the air and also acts as a gauge to show the amount of pressure. The top opening or inlet is closed with a rubber gasket, the overflow pipe is corked, a gasket is used in the filler-pipe cap and the tube reservoir is connected to the bottom radiator outlet, as indicated. In this way the radiator is fully protected.


Holding Ink Bottle on Drawing Board

About the simplest way in which the ink bottle can be held on a tilted drawing board is that shown in the illustration. One end of a string is tied around the neck of the bottle and the other end is fastened to the upper edge of the board with a thumbtack. The bottle will not slip even though the board is set at a steep angle.



Portable Air Compressor Made from Junk-Pile Parts

When digging up asphalt road for repairs on the street-car tracks, it was found



Air Compressor Made from Electric Motor, Compressor, Tank and Automatic Switch Taken from a Discarded Street-Car Truck

that, although the air drills were not very costly, the price of an air compressor exceeded the sum available. The road-maintenance mechanic studied the problem for a time and then went to the junk pile, where he found a discarded street-car truck and enough other parts to make a compressor. The motor is electrically driven, connection being made with the trolley wire by means of a hooked conductor. The air pump is controlled by means of an automatic switch, which stops the pump motor when the air in the tanks reaches the maximum pressure. Lengths of regulation-size air hose lead to the drills, which have interchangeable bits for either breaking up the roadbed or tamping up cross ties. The compressor was mounted on an old auto chassis so that it could easily be towed from place to place. The designer claims that the device cost much less than the manufactured air compressors. The ground connection for the

machine is made from a short length of flexible conductor clamped to an old-fashioned smoothing iron. This is set, face down, on the track rail. It can be seen in the photo under the truck on the ground.


The conductor pole is along the top and the drills rest on the side.

Sill as Guide for Car Doors

Some of the older Ford closed cars were not fitted with rollers on the door frame nor was there a projection on it to prevent the door from sagging slightly and striking on the sill beneath the door when closing. The hinges on doors of this kind will

bend after long use because of the weight. Doors to which this has happened can be improved, after straightening the hinges, by cutting a little wood from under the metal plate on the sill. This is done at the outer edge only and causes the plate to incline downward where the corner of the door would strike it, tending to lift and guide the door when being closed. The wood is removed for about 2 in. at the point where the sill curves upward at the catch side of the door.

Substitute for Draftsman's Quill



Ball-Pointed Pen Eliminates Trouble Experienced from Curled Quills

When the cork is left out of the drawing-ink bottle, the quill will invariably curl, so that it does not reach the ink and then it is necessary to shake the bottle in order to load the quill. A good remedy against this trouble is to cut off the quill and replace it with a ball-pointed pen, as shown, which will always reach the bottom of the bottle.

Keeping Battery Cable in Place

When the battery cable loses its grip on the post and jumps off, trouble may result, due to the intermittent connection as the car vibrates. To overcome this, drill and tap a small hole in the center of the post. Then lay a washer, large enough to cover both post and cable ring, over this hole and fasten it with a machine screw threaded down into the tapped hole. This will prevent the cable from jumping off, but it can be removed by taking out the screw and slipping off the washer.


Gasoline-Pump Extension

In order to comply with the regulations of a small city where the location of gasoline pumps on the curb is prohibited, one garage owner installed the pump next to his garage and provided an extension, as shown in the drawing. A swinging joint was attached to the top of the pump and a suitable length of pipe was fitted to the joint to extend horizontally to a position just above the curb. A guy wire was used to support the pipe so that it



Overhead Extension on Gasoline Pump Where Curb Location Was Prohibited

could be extended over the curb when required and swung against the side of the garage after use. An elbow was fitted at the end of the pipe and the hose was attached as indicated in the drawing.—J. S. Hagans, Chicago, Ill.



How to Turn Small Wooden Plugs

Making little round wooden plugs for boiler flues was a tedious task when ordinary hand methods were employed, but with the simple device shown in the drawing, they can be turned out very quickly. A small circular saw, on an 8-in. section of brass mandrel, is screwed onto the shaft of the high-speed motor which runs the lathe. A tapering hole, 4 in. long, with a slot in one side, is drilled into the end of the mandrel, and a cutting blade is screwed to the edge of the slot at the same angle as the taper. The device works like a small pencil sharpener. After the plugs are turned, they are pushed against a small spring gauge attached to the side of the motor and severed with the saw. A chute guides the plugs into a barrel.—Jos. C. Coyle, Denver, Colo.

Release for Milk-Can Cover

When putting a cover on a filled milk can, it is often found that it goes down hard and with a tendency to spring up, especially if the can is well filled. This is due to the compressed air under the cover. To remedy this, drill a small hole in the cover, conveniently near the handle, and fit it with a cork. Then remove the cork when putting on the cover and replace it when the air has escaped.



Preventing Plaster from Cracking along Floor Joists near Top of Stairway

To Prevent Plaster from Cracking

Plaster often cracks where it covers the floor joist that runs along the top of the stairway, because it will not anchor securely on the joist. To prevent this, nail short lengths of lath on the joist vertically and then apply a strip of metal lath. This provides some space for the plaster to work behind the metal lath, and it will never crack. Another weak spot is in corners, especially under stairways. This trouble can also be remedied by applying a strip of metal lath, bent to conform to the corner, as shown in the illustration.—Robert Page Lincoln, Minneapolis, Minn.


Overhead Bracket for Ignition Wiring

Special battery-ignition systems for Ford cars have a bracket held under one of the cylinder-head capscrews, for spark-plug wires. These brackets are rather short, and the wires are held close to the top of the motor, where they are exposed to the heat, and are in the way when spark plugs must be removed. The bracket should be hung from the radiator stay rod, leaving plenty of space for work on the plugs, and holding the wires farther from the heat. A steel strip, 1 in. wide, $\frac{1}{8}$ in. thick and of a length depending on the model of the car and the make of the ignition system, and two clamps like those

of the gas-feed pipe are used for this purpose. A hole is drilled in one end of the strip and the two feed-pipe clamps are bolted to it and clamped to the stay rod. The bracket for the wires is inverted, the wiring put through it, and the bracket set at the proper height to take up the slack in the wires. The steel strip is then bent at right angles and a hole is drilled for the bracket, which is bolted to it. The strip is again bent to extend down to a cylinder-head capscrew on the left-hand side, and finally a hole drilled through the strip for the screw.—E. T. Gunderson, Jr., Humboldt, Iowa.

Uses for Old Auto Plates

Old auto plate numbers can be used to good advantage as shown in the drawing. Cut the plates with a hacksaw or heavy tin shears and use the numbers for rural mail boxes, for sprinkler systems or for house numbers. They are large and plain, which makes them especially suitable for these purposes. To attach them, it may be necessary to punch holes and wire them in place, as around pipes, or



Old Automobile Numbers Can Be Put to Many New Uses, Such as Illustrated Here

they can be riveted to thin metal surfaces such as a mail box, while, if they are to be used on a wooden surface, such as a porch post, nailing will do.—Truman R. Hart, Ashtabula, Ohio.

Cane Tube for Fly-Rod Tips


Ordinarily the tips of a fly rod are carried with the rest of the sections of the rod in a cloth case. While they are not often broken, they must nevertheless receive special attention while being carried about. A special tube that can be made at home and that will protect the tips from being broken consists of a piece of ordinary cane pole cut long enough to accommodate the sections of the rod. The inside of the tube should be at least $\frac{1}{2}$ in. in diameter and the obstructions at the joints can be removed with a $\frac{1}{4}$ -in. chisel or gouge attached to the end of a hardwood stick. After the obstructions have been removed, the inside surface of the tube should be smoothed down, which can be done by means of some emery cloth tacked to the end of the stick. A wooden plug is glued in one end of the cane and a cork is inserted at the other end. If desired, the threaded section of a narrow-neck can may be cut off and tacked on the end so that a screwcap can be used instead of the cork, and this is less likely to be accidentally lost. The tube is slipped into the cloth case along with the thicker sections of the rod.

Rails as Guides for Endless Chain


At a large southern sawmill using a heavy endless chain to pull logs from the pond up into the mill house,

a guide or track for the returning chain was made of railway rails. Any number of rails can be coupled together, laying them side by side as shown in the drawing. The lags of the chain slide on the rails beside

them, while the vertical links pass between the rails and prevent the chain from twisting.—L. M. Jordan, Vredenburgh, Ala.



Chute Attached to Bench Makes Disposal of Bench Litter Easy, and Helps Prevent Loss of Small Parts




Trash Box under Bench Is Aid in Small Shop

The open can or box generally used for sweepings from the bench in a small shop has one great disadvantage: that small tools and parts may easily drop into it unnoticed. A box and chute that has all the advantages of the open-top box and none of its disadvantages is shown in the illustration. The construction of the chute itself is simple and is quite plain from the drawing. It is hinged to one of the crosspieces of the bench, as indicated, and is normally held under the bench by means of a strong spring attached to the rear edge. To use, the upper edge of the chute is pulled out and the trash swept into it. It will be noticed that the chute is not attached to the box, and consequently the trash can be thrown out without disturbing the former.

Sidetracking Engine Gases

When an automobile engine becomes worn from much use, some of the gas leaks by the rings and is discharged through the breather pipe, thus finding its way into the car body, making the air foul. To stop this, one autoist attached a flexible metal conduit to the breather-pipe opening and a short piece of rubber hose to the other end of the conduit. This hose was led outside under the engine hood and discharges all the gases into the air.

Is This Your Home?



Copyright, Architects' Small House Service Bureau

Plan No. 5A23

QUESTIONS regarding home building addressed to this magazine will be answered by The Architects' Small House Service Bureau of the United States, Inc., controlled by the American Institute of Architects and endorsed by the United States department of commerce. Inclose 10c and self-addressed envelope. Blueprints, specifications and material list for the house shown here may be obtained at nominal cost. Inclose self-addressed stamped envelope for reply. If further information is desired, send 5c and stamped envelope for a 24-page booklet explaining how the Small House Service Bureau functions and showing 12 sample plans. A new booklet, entitled "Fifty Ways to Lower Home Building Costs," illustrated by ten bureau houses actually lived in, and showing how as much as \$1,000 can be saved on a home, may be obtained for 20 cents.

THE home illustrated above will gladden the hearts of home builders because of its spacious, comfortable, conveniently arranged plan. It is designed on simple, effective lines, that insure its being moderate in building cost and pleasing in appearance.

The fireplace in the living room and the combination built-in dining-room buffet and kitchen cabinet are features that will increase value and convenience beyond the money they cost. It is a well-known fact also that a fireplace adds considerably to the selling value of a house.

The kitchen is arranged after that of a design chosen from a national competition. However expertly this may have been designed to eliminate extra steps, many persons prefer to have the sink under the outside wall. The plans therefore provide an alternative drawing for such an arrangement of the fixtures.


There is a built-in buffet in the dining room. Graceful plaster arches between the dining room and vestibule and the living room and vestibule lend an unusual charm to these rooms as well as give them the spacious open effect so much desired.

The working drawings call for frame construction, brick front steps, shingle or composition roof, and exterior finish of stucco, although siding or shingles may be used with good effect.

Home Builders' Questions

Q. What makes a fireplace smoke? How do you fix it? **A.** The flue may be too small, or crooked, or it may be filled with soot. Also, the throat may be too small or the fireplace may be too high for its depth. Clean the flue; put in a mechanical throat; build up the back hearth one course of brick—get a contractor to tell you which.

Q. We wish to buy some property in our city. How far back is it necessary to trace the title? **A.** The abstract of title should be carried back to the original grant of the land from the government. Make sure that every transaction has been closed and that all claims against the property have been satisfied legally.



The Live Spring in the Handle makes "Yankee" No. 130-A the Quick-Return Spiral Screw-driver.



Up or Down

is the same to

"YANKEE" No. 130-A

In either direction driving (or drawing) screws is surprisingly easy and speedy with this world-famous Quick-Return Spiral Ratchet Screw-driver.

The live spring in handle keeps blade in screw slot, and brings handle back ready for the next push—without a second's loss.

Great for working one-handed.

Just push! The Spring and "Yankee" Spiral do the work for you, and save your time.

Right-hand Ratchet, Left-hand Ratchet and Rigid. Three sizes of bits: No. 130-A, Standard

Size. No. 131-A, Heavy Pattern. No. 135, Light Pattern.

"Yankee" Spiral Ratchet Screw-drivers, without the Quick-Return feature, No. 30-A, No. 31-A, No. 35.

Some Other "Yankee" Tools

Ratchet Bit Braces.
Ratchet Breast and Hand Drills.
Automatic Feed Bench Drills.
Automatic Push Drills.
Plain Screw-drivers.
Ratchet Tap Wrenches.
Vises—removable base.

Dealers Everywhere Sell "Yankee" Tools

*"Yankee" on the tool you buy
means the utmost in quality,
efficiency and durability.*

NORTH BROS. MFG. CO., Philadelphia, U. S. A.

"YANKEE" TOOLS

Make Better mechanics



FREE

"Yankee" Tool Book for all lovers of fine tools. Write for it.



AN ADVERTISEMENT OF THE AMERICAN TELEPHONE AND TELEGRAPH COMPANY

THERE are twenty-five Bell Companies, but there is but one Bell System—and but one Bell aim and ideal:

A telephone service for this nation so far as humanly possible free from imperfections, errors and delays, and enabling anyone anywhere at any time to pick up a telephone and talk to anyone else anywhere else in this country, clearly, quickly and at a reasonable cost.

WALTER S. GIFFORD
President

ETHYL GASOLINE

knocks out that "knock"..

..turns carbon into power



What Ethyl Gasoline will do in your own automobile

- 1 It will end all carbon trouble and make carbon formation an asset.
As carbon forms, both temperature and compression (pressure) are increased. Ethyl Gasoline neutralizes the higher temperature and the increased compression becomes increased power.
- 2 It will give you more power, particularly on hills and heavy roads.
- 3 It will make your engine operate more smoothly.
- 4 It will reduce gearshifting.
- 5 It will increase acceleration, making your car easier to handle in traffic.
- 6 It will eliminate "knocking" under all driving conditions.
- 7 It will reduce vibration and engine wear and tear.
- 8 It will save the expense of carbon removal.
- 9 It will give you more power from each gallon of fuel that you use.

IN SHORT, the advantages of Ethyl Gasoline over regular gasoline are so marked as to make the small premium it costs a real economy.

IT is important that you differentiate between Ethyl Gasoline and other "anti-knock" gasolines. Ethyl Gasoline is the *only* fuel which eliminates "knocking" under *all* conditions, thereby making present day automobiles perform more efficiently.


It was developed by General Motors Research Laboratories after 8 years of scientific research which resulted in these two important discoveries.

- 1 That "knocking" is an inherent characteristic of *all* gasolines. What had previously been called a "carbon knock" or "ignition knock" or "engine knock" is in reality a *fuel knock*, due to the too rapid combustion of gasoline in the cylinders.
- 2 That "knocking" could be completely eliminated in gasoline by the addition of *Ethyl Brand of Anti-Knock Compound*. This ingredient was discovered by General Motors research engineers after experimenting with more than 33,000 chemical compounds.

SO SUPERIOR is Ethyl Gasoline to other so-called "anti-knock" fuels that it has been adopted wherever unusual performance by a gasoline engine is required. That is why the United States Navy uses Ethyl Gasoline in its latest types of airplanes. That is why Ethyl Gasoline is used by the racing car drivers who are setting up new records.

Ethyl Gasoline is available throughout the United States and Canada through leading oil companies and responsible jobbers. It is sold at pumps which display the "ETHYL" trade mark shown at the left.

ETHYL GASOLINE CORPORATION, 25 Broadway, N. Y.





Millions of Men Buying Dollar Topkis



Topkis Flatlock Seam
Nine threads, instead of one, sew the materials together at the waistline, forming a seam that is the strongest part of the garment.

You men have come back for the Topkis Dollar Union Suit until now it must be made by the millions!

In Topkis you get quality and variety of fabrics (plain and fancy patterns) like high-priced underwear. And Topkis is cut full and tailored to give fit, comfort, freedom all the time.

Biggest money's worth a dollar buys. Ask dealer for Topkis. Look for label.

Write us for free illustrated booklet

TOPKIS BROTHERS COMPANY, Wilmington, Del.
General Sales Offices: 93 Worth Street, at Broadway, New York

Fancy madras, plain madras, white or color stripe, silk stripes, mercerized crepe, pajama check.

Men's Union Suits, \$1. Shirts and Drawers, 75c each. Boys' Union Suits, 75c. Children's Waist Union Suits, 50 and 75c. In Canada, Men's Union Suits, \$1.50.

AT THE TOP OF UNDERWEAR FAME STANDS THE TOPKIS NAME

Before you start shopping around —send for this **FREE BOOK**



Pledge to the Public on Used Car Sales

- 1 Every used car is conspicuously marked with its price in plain figures, and that price, just as the price of our new cars, is rigidly maintained.
- 2 All Studebaker automobiles which are sold as **CERTIFIED CARS** have been properly reconditioned, and carry a 30-day guarantee for replacement of defective parts and free service on adjustments.
- 3 Every purchaser of a used car may drive it for five days, and then, if not satisfied for any reason, turn it back and apply the money paid as a credit on the purchase of any other car in stock—new or used. (It is assumed that the car has not been damaged in the meantime.)

To the Public: We pledge adherence to the above policy in selling used cars.

Your Studebaker Dealer

If your dealer lives up to this PLEDGE you can safely buy a used car from him without reading the book. But before you start shopping around you had better send in the coupon

YOU can travel in Pullman comfort at day-coach cost by investing wisely in a good used car. But before you start looking around, send for your copy of "How to Judge a Used Car." This valuable guide, written by experts who have bought and sold hundreds of used cars, will save you time and money—tell you exactly what to look for and exactly what to avoid.

If you read and heed this helpful, simply written book you will know how to protect yourself when buying a used car from a friend, how to avoid "orphans," what code prices mean, whether to depend on speedometer figures, and the important check-ups to make in examining any used car—everything the buyer of a used car should know.

Studebaker has prepared this free book for your guidance, just as Studebaker dealers have adopted, for your protection, the famous Pledge shown above. Wherever you see it displayed you can buy with assurance of absolute satisfaction.

Mail this coupon **TODAY!**

THE STUDEBAKER CORPORATION OF AMERICA
Department F72, South Bend, Indiana

Please send my copy of valuable free booklet,
"How to Judge a Used Car."


Name.....

Street.....

Town..... State.....

STUDEBAKER

Seventy-five years young



Buy separately or
in assortments

Your work bench...

Make it yourself from Stanley Plan SD-72

EVERY tool-user needs a work bench. Here is how to get one at very little cost. Stanley Plan No. SD-72 shows plainly what materials to order, how to prepare them, and how to "carry through" to the finishing touch. Thousands of men have work benches where they do repairing and original construction.



A good work bench and good tools go hand-in-hand. Using the best tools brings a personal satisfaction that you should not deny yourself. Most carpenters and manual training instructors prefer Stanley Tools because they know from experience that the Stanley name assures durability, correct design, and right "feel."

You can buy Stanley Tools separately

and so collect your own set. For your convenience in buying there are also complete sets of Stanley Tools in chests at a wide variety of prices from \$15 to \$95. Or there are assortments in strong cardboard boxes containing directions for making your own tool chest. Priced from \$5 to \$20.



Your hardware dealer has Plan No. SD-72 as well as other Stanley Plans for making useful articles, or he can get them for you. The plans cost only 10c each. Ask him also for small Catalog No. SD-50 which shows the most complete line of woodworking tools on the market. It is free. If he cannot supply you, write to The Stanley Works, New Britain, Conn.

The best tools are the cheapest to use
Ask your hardware dealer



STANLEY TOOLS

Sport in every mile!




HIT the trail to joyland! Slip away from crowded streets and stifling heat. Spend never-to-be-forgotten hours at the lake, on the beach, in the breeze cooled country. Short spins. Long trips. Picnics — outings — vacation tours. All yours with the powerful, dependable

Harley-Davidson Twin. Upkeep is only a fraction the cost of a car — 2¢ per mile for gas, oil, tires and all. Plenty of room in the sidecar for a friend and your outfit. Prices as low as \$310 f. o. b. factory — on easy Pay-As-You-Ride terms. See your dealer—send coupon for catalog.

HARLEY-DAVIDSON MOTOR COMPANY
Department P Milwaukee, Wis.

HARLEY-DAVIDSON Motorcycles



The Single

—our famous solo mount that travels "80 miles per gallon" and is priced at only \$235, complete, f. o. b., factory.

Twin and Single-cylinder models in a wide range of prices. Get our catalog.

*Mail
this
Coupon*

HARLEY-DAVIDSON MOTOR COMPANY
Department P, Milwaukee, Wisconsin
Interested in ☐ Twin ☐ Single
Send illustrated catalog.

Name

Address

Always strong at the finish



ON THE next to the top step of Bill Gettner's brand-new hand-made ladder lies the plane he should be using. It's the Sargent Steel Block Plane—the one for just such small jobs as rounding off the last sharp edges or for use in close quarters. But Bill simply couldn't resist showing how the big Sargent Auto-Set Bench Plane can be used for even such a close cut as this. It's a versatile

plane—the Auto-Set—great for coarse or fine cutting and so much lighter than ordinary planes of the same size that you can use it for hours without tiring.

Both these Sargent Planes should be on every school and home work-bench. They are very moderate in cost and long-lasting. See them at your hardware dealer's and write us for descriptive booklet today.

SARGENT & COMPANY, *Manufacturers*, 49 Water St., New Haven, Conn.

SARGENT PLANES

*Sargent Steel Block
Plane No. 5206*



*Sargent Auto-Set
Bench Plane
No. 714*

"I look for 'em in the Starrett Catalog"




"When I hit on some job that seems hard t' do just right, I find it's usually a case of not having the right tools. I gen'ally find the answer in my Starrett Catalog."

Starrett Catalog No. 23"AP" is a mighty good book to have handy. It illustrates and describes 2500 and more fine tools. Simply by looking through it you'll discover a lot of valuable suggestions for doing your work better, quicker, easier.


It's free. Write for your copy, today.

THE L. S. STARRETT CO.

*World's Greatest Toolmakers
Manufacturers of Hacksaws Unexcelled
Steel Tapes—Standard for Accuracy
ATHOL, MASS.*



No. 181



No. 87



No. 620


No. 439



No. 108




No. 119




No. 169



No. 101



No. 94



No. 265



No. 470



No. 429



Use Starrett Tools

No. 1042

1/4" Heavy Duty — 110 Volt A. C.
or D. C. No-load speed 1800 R. P. M.
Weight, 6 pounds. **Costs only \$36.00**



Goes through *cold rolled steel*

Just as your Hand Drill goes through soft pine

TRY this 1/4-inch Heavy Duty electric drill on those long, hard jobs you've always tackled with a hand or breast drill. You'll open your eyes with sheer delight to see it bite its way through metal. And wood? Well, oak and hickory are a joke to it.

Expensive? Not at all. You probably never dreamed you could own a really fine electric drill for the price of this one. **No. 1042 costs only \$36.00**



Adapted as Bench Drill

As a BENCH Drill

With **No. 1005** Stand pictured at left, No. 1042 can be changed from portable to bench drill in a couple of minutes. This stand is firm and solid, and affords perfect leverage control.

It stands 25" high. Lever arm is 18" long. Base measures 8 1/2" x 12" and serves as work-rest. **Price only \$12.**

No. 1042 is one of a complete line of electric drills in eight types from 1/4-inch Heavy Duty to 3/8-inch Standard — made by Goodell-Pratt, and sold by hardware dealers, mill supply and automotive supply stores. Write us for literature covering interesting details, and name of a nearby dealer who can supply you.

Universal Motor Runs on 110 Volts A. C. or D. C. Also made for 220 Volts.

Lubrication. Self-oiling bearings need attention only at long intervals.

Every part quickly accessible. Can be taken apart in five minutes. Standard screws used in assembly.

C-l-e-a-n. Tightly sealed lubrication keeps commutator, armature and field from becoming oil-soaked and foul.

Fine for close drilling. Almost straight line from handle to drill point. You can drill close up to wall, floor or ceiling, etc.

GOODELL-PRATT COMPANY, GREENFIELD, MASS., U. S. A.

MAKERS OF *Toolsmiths*, MR. PUNCH

GOODELL-PRATT

1500 GOOD TOOLS

Now!

New Indian SCOUT 45

Now for the fun! Now for the thrills! Now for the big "kick" of outdoor sport at its best! Here it is—the new Scout 45—inviting you out to a real world of adventure!

The Scout 45 has a super-powerful motor, snappy acceleration, large oversize brake, classy sport handle bars. Holds boundless power for the veteran rider, easy handling features for the novice. Takes you anywhere—any time—and brings you back safely. Ride the 45 a mile—and see what a champion sport solo it really is!

DEALERS: A few territories still open for agency of Indian Motorcycles. Wonderful opportunity for ambitious, energetic men. Write today for particulars. Address:

Indian Motorcycle Co.

Dept. P-6, Springfield, Mass.



*The
Police Special
and Sport Solo*

Easy to Own a
Scout "45"

Call on your nearest Indian dealer and find how easily you can own a Scout 45 under our generous pay-as-you-ride plan. Or mail coupon below for the complete interesting story of this popular model.

*Ride
the 45
a mile!*

Indian Motorcycle Co., Dept. P-6
Springfield, Mass.

Send me FREE descriptive circular on the new Indian Scout 45. This places me under no obligation.

Name _____

Address _____

City _____

State _____

"Stronger, Clearer, Better Binoculars



than those costing double."

—E. F. D., Annapolis, Md.

"Didn't need 10 days' trial—10 minutes was enough."

—L. H. K., Kaliispell, Mont.

8 Power Prisms

French and German makes: 8-POWER magnification, genuine prisms, famous PREMIERE QUALITE, brilliant illumination, exquisite definition, WIDER field of vision. Individual eye-strength and width adjustments. Leather case, neck and shoulder straps.

Tested by the
GOVERNMENT

TESTED by Bureau of Standards at Washington. See miles away! Conquer distance! Bring people, ships, game, scenes—right to your feet! Explore vistas of nature! Double the thrill of dashing sports! You'll find these Binoculars a never-ending pleasure—a life-time treasure! Usually sell from \$40.00 to \$50.00. As Importers, selling "Direct-to-You," our price represents BIG savings. We are selling thousands to Army, Navy Officers, Explorers, Motorists, Tourists, Yachtmen, Big Game Hunters, Globe Trotters, Naturalists, Men and Women all over the World at this Bargain Price. **\$23.50**

10 Days' Trial Absolutely FREE

Our Plan
is Different!

It is the talk of the Country! We ask for NO money in advance! NOTHING on Delivery. BINOCULARS are sent to responsible persons for 10-Days' Trial ABSOLUTELY FREE. If pleased you may pay on Budget Plan: **\$5.00 MONTHLY**

or if you prefer to pay cash at end of 10 DAYS, deduct \$1.35 and send Check or Money Order for \$21.75 in FULL SETTLEMENT. Otherwise return them. Order NOW at this Special Price! Send NO Money! Pay NOTHING on Delivery! **\$21.75**

SEAEVER-WILLIAMS CO.

Importers, Exporters, International Mail Order House

365 WASHINGTON ST., BOSTON, MASS.

Largest Retailers of Binoculars in America

Gentlemen:—Send me the 8-POWER BINOCULARS for 10 days' FREE Trial on the above plan.

Name.....

Address.....

If a new customer please tell us something about yourself. (We will appreciate and respect the information. THANK YOU. Pop. M. 4-47)

Many Agents Make \$200.00 to \$500.00 per month

New Patented Instant Plug Inserting Instrument. Best, Easiest and Quickest Plug Inserting Instrument known. That's why every Garage, Vulcanizer and Tire Man is easily sold. Mr. Pim writes: "Sold 26 out of 30 demonstrations. Easiest seller and best profit maker I've ever seen. Demonstrate and they buy. Write today for exclusive territory proposition and watch your bank account grow."

TOURISTS PRIDE MFG. CO. Dept. 5-F Minneapolis, Minn.

AGENTS! NEW!



Lights Gas Without Flame!

Sells quick to every user of gas. Lights instantly, manifies gas stoves, jet heaters, Ammazing! Mysterious! No flame or spark. Lighter is held over flow of gas—flame appears. Harmless. Lasts years. Protector cap free with every lighter.

MAKE \$10.00 DAILY! Housewives eager to buy. Retail at 25c. Your profit 12c. Rush \$10.00 for gross, or \$1.00 for sample dozen, with sure fire self selling plans. Money back if not delighted. Masterlite Mfg. Co., Desk RF-23, 110 E. 23rd Street, New York City

Extra Income

Spare time-Part time-Full time profits

200 to 500% Profit

\$1,334.00 Profit on Side Line

Mr. A. LeDoux is one of hundreds cashing in BIG, making ornamental concrete products.

He invested \$89.00 in a mold that cleared \$1,334.00 profit in short time. Other molds brought his extra income over \$5,000.00.

Catalog shows hundreds of opportunities for success.



WIN INDEPENDENCE

manufacturing Brick, Block and Tile in your community.

Write for machinery catalog—it's free.

CONCRETE EQUIPMENT CO.
570 Ottawa Ave., Holland, Mich.



Send for Catalog

\$5.00 an Hour! GREATEST

\$2.95 Slicker line in the field. Brilliant New Colors for Men, Women and Children. Knocks all competition cold. Men are making \$5 an hour. Experienced men can make more. Quick action important. Write now. Selling outfit absolutely FREE.

443 So. Dearborn St. Dept. L CHICAGO

LIGHTING FIXTURES

Ready to hang



Direct from the manufacturer. Completely wired, including glassware. Send for new catalogue No. 28. Just Reduced Prices. Special Proposition to Dealers.

Erie Fixture Supply Company, Inc.
Station A ERIE, PA.



STOP FORD CRANKSHAFT END-PLAY!

C-A ADJUSTABLE BEARING corrects and prevents end-play without removing motor. Eliminates many troubles. Easy to install—simply drop pan. Only \$3.75. Ask your dealer or send prepaid by ADJUSTABLE BEARING CO., Dept. F, 405 Virginia Ave., Indianapolis, Ind.

MEN DOUBLE YOUR INCOME

Cash paid Daily

SELL PIONEER \$23.50 TAILORING FULL OR PART TIME

Make \$12 a day from start—part time men \$5 an hour selling famous Pioneer tailored-to-measure, all-wool suits at \$23.50.

Commissions paid in advance. Striking leather brief case containing 100 large swatch samples furnished—other equally remarkable values at \$29.50 and \$34.50. We train the inexperienced Men with determination and willingness to work for success write for this big money-making opportunity—today!

PIONEER TAILORING CO., 150 W. Harrison St., Dept. F1116, CHICAGO

In Great Britain they say:

**“England’s wars
are won or lost
on the athletic
fields of her schools”**

How TRUE this is was proven in America during the great war.

For in the West—land of husky outdoor men, apparently natural soldiers—as high as one out of four men was found imperfect for military service because of one mistake made in boyhood: heavy, ill-fitting shoes had injured and deformed the feet.

But in the South, where going barefoot or wearing light, easy-fitting shoes is more generally the custom, very few men had this trouble.

Keds give almost perfect barefoot freedom without barefoot dangers. In them you are ideally shod for games and sports on turf, cinder track or floor; and at the same time you are giving your feet the chance to develop which means continued athletic success and health.

KEDS—the shoe of Champions

Thirteen National Tennis Championships were won on Keds in 1926.

No other shoe has all the advantages of Keds. They are made only by the

United States Rubber Company



The great war showed that if during your school years you wear light, well fitting shoes, you will have little foot trouble of the kind that caused thousands of young Americans to be rated physically defective

The “ROYAL TREAD”

An unusually rugged Keds model with tough moulded sole for indoor or outdoor wear. Great anti-slip-ping qualities. In white or brown



The “SPORTSTER”

A sturdy athletic-trim Keds model—built for hard wear. Comes in lace-to-toe style—white or brown—both models with gray soles



They are not **Keds**

Trademark Reg. U. S. Pat. Off.

unless the name Keds is on the shoe



LUMINOUS PAINT

Make Your Watches, Clocks, Etc., Visible by Night

The very latest discovery in the scientific world. Hitherto, practically unobtainable LUMINOUS PAINT, which, applied to the surface of any article, emits rays of white light, rendering it perfectly visible in the dark. THE DARKER THE NIGHT, THE MORE BRIGHTLY IT SHINES. Quite simple to use. Anyone—you can do it. A little applied to the dial of your watch or clock will enable you to tell the time by night. You can coat a push button or switch plate of your electric light, match boxes, and innumerable other articles; make your own Luminous Crucifixes, Luminous Rosaries, etc. Small bottle, price 25c. Larger sizes, 50c and \$1 postpaid. **JOHNSON SMITH & CO., Dept. 810 RACINE, WIS.**

Serpent's Eggs

Box contains 12 eggs. When lit with a match, each one gradually becomes itself into a snake several feet long, which curls and twines about in a most life-like manner.

Price per box, 10c postpaid, 3 for 25c.

CIGARETTE MAKER



Roll your own and save money. Makes them better and quicker besides saving more than half. Use your favorite brand of tobacco. Neat, useful and handy. Pocket size, weighs 1/2 lb. Made entirely of metal, nickel-plated. Price 25c postpaid.

MIDGET BIBLE

GREAT CURIOSITY
Smallest Bible in the World.
Size of a postage stamp.
200 Pages.
Said to bring good luck to the owner. A genuine work of art. Must be seen to be appreciated. Makes good money selling them to friends, church acquaintances, etc.


PRICE 15c each, 3 for 40c, 12 for \$1.35, 100 for \$7.50. Also obtainable in Leather Binding, with gold edges. Price 50c each, 3 for \$1.25, \$4.50 per doz. Magnifying Glass for use with Midget Bible, 15c.

STAGE MONEY



With a bunch of these bills, it is easy for each person of limited means to appear prosperous by flashing a roll of these bills at the proper time and peeling off a genuine bill or two from the outside of the roll. The effect created will be found to be all that can be desired. Prices, postpaid: 40 Bills 20c, 120 for 50c, or \$3.50 thousand postpaid.

Wonderful X-Ray Tube



A wonderful little instrument producing optical illusions both surprising and startling. With it you can see what is apparently the bones of your fingers, the lead in a lead pencil, the interior opening in a pipe stem, and many other similar illusions. A mystery that no one has been able to explain. Price 10c, 3 for 25c 1 dozen 75c. **Johnson Smith & Co.**



Good Luck Ring

Quaint and Novel Design

A VERY striking and uncommon ring. Silver filled, skull and crossbones design, with two brilliant, flashing gems sparkling out of the eyes. Said by many to bring Good Luck to the wearer, hence its name, Good Luck Ring. Very unique ring that you will take a pride in wearing. **ONLY 25 CENTS.**

JOHNSON SMITH & CO.

Dept. 810

RACINE, WIS.



A De Luxe Edition of our new 1927 CATALOG mailed on receipt of 25c. Handsome binding. Bigger and better than ever. Only book of its kind in existence. 550 pages of all the latest tricks in magic, the newest novelties, puzzles, games, sporting goods, rubber stamps, unusual and interesting books, curiosities in seeds and plants, etc., unobtainable elsewhere. Send by Stamp, Coin, Money Order, Check, etc. Unused U. S., Canadian and Foreign Stamps also accepted.

Exploding Cigarettes



JUST LIKE ORDINARY CIGARETTES, BUT SUCH REAL STARTLERS! The box contains ten genuine cigarettes of excellent quality. They appear so real, but when each cigarette is about one-third smoked, the victim gets a very great surprise as it goes off with a loud BANG! A great mirth provoker yet entirely harmless. Price 25c per box.

Popular Watch Charms



ONLY 15c
1 for 40c; \$1.35 doz.

Very pretty little curiosities and decidedly novel. Fitted with Magnifying Lenses that enlarge the picture to a very surprising degree; in fact, it seems almost incredible that a clear picture could be possible in such a small compass, and how sharp and distinct they show up when you look through. Come in assorted views—Actresses, views of Panama Canal, Lord's Prayer in type, etc.

Mystic Skeleton

A jointed figure of a skeleton 14 in. in height, will dance to music and perform various gyrations and movements while the operator may be some distance from it.



10c + pd.

Novelty Badges



Kissing Permit 10c

Garter Inspector 10c

Two very novel metal badges, nickel plated, that you can wear, giving you fun out of all proportion to their trifling cost. 10c, each badge, 3 for 25c, or 75c per doz. postpaid anywhere.

MAGIC FLUTE

Wonderfully Sweet Toned and Musical



Post Paid 15c

The Magic Flute, or Harmonium, is a unique and novel musical instrument that is played with nose and mouth combined. There is just a little trouble in playing it which, when once acquired after a little practice, will enable you to produce very sweet music that somewhat resembles a flute. There is no fingering, and once you have mastered it you can play all kinds of music with facility and ease. When played as an accompaniment to a piece of any other musical instrument, the effect is as charming as it is surprising.

Blank Cartridge Pistol


REVOLVER STYLE

PRICES

50c &

\$1.00

Post-Paid



Well made and effective Pistol modeled on the pattern of the latest type of Revolver; appearance alone is enough to scare a burglar. When loaded it may prove just as effective as a real revolver without danger to life. Takes standard .22 Calibre Blank Cartridges obtainable everywhere. Even the most timid person can use it with perfect safety. A Great Protection Against Burglars, Tramps and Dogs. You can have it lying about without the danger attached to other revolvers. **PRICE ONLY 50c** Better make and superior quality for \$1.00, Postpaid. Blank Cartridges .22 Calibre, (by express) 50c per 100. Revolver Holster and Strap (Cowboy type) for Blank Cartridge Pistol, 50 cents extra.

BOYS! BOYS! BOYS! THROW YOUR VOICE



Into a trunk, under the bed or anywhere. Lots of fun fooling the teacher, policeman or friends.



THE VENTRILLO

a little instrument, fits in the mouth out of sight, used with above for Bird Calls, etc. Anyone can use it.

Never Fails. A 16 page course on ventriloquism, the Ventrillo, ALL FOR 10 CENTS



Everything about the Ku Klux Klan told in a clear, fearless manner. Book tells all—How it started and was oppressed in 1871—The New Ku Klux Klan—How Organized—How Members are Enrolled—Oath of the Klan—Questions for Candidates—Creed—Objects of the Order—Obedience—Fidelity—Pledge of Loyalty—Ku Klux Klan and the Masons—The Jews—The Masons—Steel K. of C. G. A.—The Negro Ku Klux Klan, etc., etc. Largest and most complete book on the Klan published. Price 25c, Postpaid. **Stamps or Cash**



Female

SEX

Indicator

25c



Male Sex Indicator

Hold the MAGIC INDICATOR over a man's head—instantly it reveals in a straight line, backward and forward, hold it over a woman's head and it describes a complete and continuous circle.

The same action can be obtained over a letter written by a man or woman, etc. It is fascinating business. We have never been able to figure out how it's done, but we've never seen it fail. Many novel and entertaining facts may be performed with the Sex Indicator. For example, whether results can be obtained with animals, cats, dogs, rabbits, mice, birds, chickens, etc., etc. Also used to predetermine the sex of chickens and birds, etc. In fact it is sold as a patented egg tester in Europe. Price 25c, or 3 for 65c, postpaid.



LOOK 35c Look

Wonderful instrument. Great test thing yet nice to have articles in one.

Everybody delighted with it. Odd, curious and interesting. Lots of pleasure as well as very useful. It is a double Microscope for examining the wonders of nature. It is also an Opera Glass, a Stereoscope, a Burning Lens, a Reading Glass, a Telescope, a Compass, a Pocket Mirror, and a Laryngoscope—for examining eye, ear, nose and throat. It is worth all the cost to locate even one painful clinder in the eye. Folds flat and fits the pocket. Something great—you need one. Don't miss it. Send by mail, postpaid. **Price only 35c or 3 for \$1.00.** **JOHNSON SMITH & CO., Dept. 810, RACINE, WIS.**

4 out of 5 Have Razor Pains

But not the folks who shave with Barbasol. No, sir; all slick and swift and cool for them. No brush. No rub-in. Use Barbasol—3 times—according to directions. "Mister, you're next!"



Barbasol

For Modern Shaving

The Barbasol Company
Indianapolis, Ind.


I enclose 10c. Please send trial tube.

Name.....

Address.....

P-M-6-17

NEW VEST POCKET ADDING MACHINE



ADDS, SUBTRACTS, MULTIPLIES, DIVIDES
Does work of \$300 machine. Guaranteed 5 years NOT A TOY.

Made of steel and indestructible. Million dollar capacity. Fits in pocket. Will not make mistakes. So simple child can operate it. Instructions furnished. Everybody should carry one for figuring.

FREE TRIAL

\$2.50
Total Cost

SEND NO MONEY—Just name and address. We will ship Calculator immediately. On delivery pay postman \$2.50 (Plus few cents postage). (If outside U. S. send cash). If not satisfied after 10 day trial you get your money back. **THOUSANDS OF SATISFIED USERS.** This is lowest priced practical calculator made. "Why pay more for inferior imitations?" Order from this ad.

Guaranteed

Mail Coupon Today

BABY CALCULATOR SALES COMPANY

Dept. 41, P. O. Box 1118, CHICAGO, ILL., U. S. A.

- ☐ I am enclosing \$2.50—send adding machine prepaid.
☐ Send Adding Machine C. O. D. \$2.50 plus postage.

Name.....

Address.....

City.....

State.....

AGENTS

Write for big commission and territory proposition.

How Does He Do It?


—Always has extra money for pleasures and things he wants, yet he doesn't draw any more pay than you do. Hundreds are making from \$3.00 to \$8.00 an evening with the

FOLEY Automatic SAW FILER

The only machine that automatically files and joints all kinds of saws in one operation. Big demand for its speedy, perfect work. Often sets a man up in business for himself. You'll make extra money easily—write today.

FOLEY SAW TOOL CO., Inc.

216 Foley Bldg., 27 Main St. N. E.
MINNEAPOLIS, MINN.



Model F-3

Hand drive
Also made in
power drive
models.

MOTORCYCLES



Price \$10 and up purchased through our Co-Operative Plan for as low as \$1.00 down and \$1.00 per week Indians Harley-Davidsons Ace Henderson and Clevelands

Send ten cents for Bulletin A.

Motorcycles shipped all parts of the world

WALKER-INDIAN CO., 188 Mass. Ave., BOSTON



Your Coat and Vest Can Be Matched with New Trousers

24 of the price of your suit is in the coat and vest. Why not get full value out of them by replacing the worn out pants with a new pair.

Send us sample (small piece from seam or the vest) and we will show you how close we can match it. All tailored to measure. Prices range from \$9.00 to \$15.00 according to quality.

ACME PANTS MATCHERS

Dept. BF 14, 20 W. Jackson, Chicago



I'll Pay You \$40 A DAY!

To Show My Mystery New Cigarette Lighter to Men



Quick, easy profit for you with this amazing invention. Lights cigarettes and cigars in strongest wind. Does work of expensive lighters but sells for only 50c. Guaranteed for 10 years.

Men Making Big Money

Elmers sold 48 in one day. Only one day's sales to dealers easily nets you \$38. Enormous steady repeat business. No experience necessary. Work full or spare time. Smokers and dealers buy on sight. Send 5c and name for special sample and sure fire selling plan. Satisfaction guaranteed.

No
wind can
blow it out!

How does
it work?



MASTERLITE MFG. CO., Desk CF-23
110 E. 23rd Street NEW YORK CITY

\$3500

IN SIX MONTHS FROM \$500!

washing houses with the

NIELCO Lightning Washer

(Patents Pending)



From an unretouched photo taken of the NIELCO LIGHTNING WASHER, in action and just before rinsing.

The only machine of its kind, to wash any painted surface, tile, terra cotta, and glazed brick.

Painters say that 90% of the houses painted each year are painted because they are dirty and NOT because they need paint.

We find that 44% of the home owners are interested in having this work done.

NIELCO Cleansing Compound used exclusively with the NIELCO LIGHTNING WASHER IS GUARANTEED to be harmless to the hands, paint or lawn.

Exclusive Territory

Available to men who want to get into a profitable business. Two men with one machine can make \$20.00 per day profit, in addition to paying themselves regular wages. We help you get the business!

Write or wire for your territory and proposition

NIELSEN INDUSTRIES, Inc.

Maccabee Building

DETROIT

MICHIGAN

Industrial Users: A NIELCO LIGHTNING WASHER and cleansing compounds for every purpose

LIVE DISTRIBUTORS WANTED!



Wood In A Can Holds Screws and Nails without splitting!

PLASTIC WOOD handles like putty and hardens into real wood on exposure to air. It may be worked with tools, holds nails and takes paint, stain, lacquer and varnish like any wood. PLASTIC WOOD is a great help in any construction or repair work. Try it to mend broken corners of screens and to fill old screw holes in window and door frames.

Sold by Hardware and Paint dealers— $\frac{1}{4}$ lb., 35c; one pound, \$1.00. Send coupon if they cannot supply you.

Addison-Leslie Company,
40 Bolivar Street, Canton, Mass.

Please send me a trial quantity of PLASTIC WOOD for which I enclose 35c.

Name.....

Address.....

Name and address of Hardware Dealer.....



The Handy Tool
for the Handy Man

TORIT No. 23
Acetylene Torch

PAT. JAN. 5, 1926



Uses Acetylene Only. No oxygen or air pressure required. Tips suck in air. Simply connect to Presto auto tank, light gas, and the outfit is put to work. Gives Heat Instantly! Beats anything you ever tried for soldering, radiator repairing, melting, lead burning, tempering, heating, light brazing, etc. Consists of torch, 4 tips for different kinds of work, soldering copper, 5 feet rubber tubing, tank connection, and full instructions. All ready to use. Quickly \$7.50 pays for itself. PRICE, complete, without tank,

ST. PAUL WELDING & MFG. CO.
177 West Third Street Saint Paul, Minnesota

PARKS

WOODWORKING MACHINES

Cabinet
Shop
Special

\$290

with Motor



You ought to have this handy Parks in your shop. It is a compact, complete machine designed just like a big production outfit at one-fifth the cost. Includes 8-inch circular rip and cross cut saw with polished cast-steel saw table, 16-inch band saw with tilting table for bevel-sawing, 6-inch jointer, and motor operating from any light socket. Just plug in and go to work! Fits in a corner of your basement. Does any kind of cabinet and joinery work. Add lathe, shaper and other attachments any time at small cost. For the man who does "odd jobs" in his off time this Parks is a big money maker. Turn out as much as a four-man shop working by yourself.

Write for circular and Parks complete catalog of handy woodworking machinery.

The Parks Ball Bearing Machine Co.

1500-1540 Knowlton St.


Cincinnati, Ohio

Canadian Factory: 208 Notre Dame East, Montreal, Can.

BURN YOUR NAME ON TOOLS

WITH THE
ARKOGRAP

PROTECT YOUR TOOLS FROM THEFT
Write with electricity any name or design on the hardest and finest tools and instruments, or any metal, like writing on paper with pen or pencil. Complete Outfit \$3.50—Prepaid Anywhere. Interesting illustrated circular free. Write today. Agents wanted.
ARKOGRAP PEN CO., 1171 E. Clark St., Portland, Oregon



Measure Hard-to-Reach Places with
"Interlox" THE SPEEDY RULE

Indispensable for accurate inside and outside measurements. Slides—no folding. Any length, 2 to 8 ft., 20 ft. No. 1 ft. If not at dealers, sent postpaid.

Dealers and Agents: Write for attractive proposition.

MASTER RULE MFG. CO., 813 E. 136th Street, NEW YORK



If you want to be free from worry about your tools, keep them safely in a

GERSTNER Tool Chest

There's one you can use and one you will want. Write for free catalog.

Gerstner & Sons

442 Columbia St., Dayton, Ohio



A Genuine \$2 Knife for \$1.18 Postpaid

Handy shaped Blade makes this knife best for mechanics, sportsmen and farmers: light but strong; re-sharpened easily. Stagh handle. German silver finish; blades file tested, hand forged from razor steel and warranted.

Direct at Factory Prices

Sample \$1.18 3 for \$3.00 Postpaid

Hand Forged Razor Steel Blades

Send for our 100-page FREE List and "HOW TO USE A RAZOR."

Maher & Grosh Co.

106 A St., Toledo, Ohio



**TEMPERED
FOR TOUGH
TIMBER**

The tougher the job,
the greater the need for
a saw made of special steel
—a Simonds World-Famous
Crescent-Ground Cross-Cut Saw.
Ask your Hardware Dealer.

SIMONDS SAW AND STEEL CO.

"The Saw Makers"
Established 1832

Fitchburg, Massachusetts

SIMONDS

Pronounced SI-MONDS

SAWS FILES KNIVES STEEL

Branches and Service Stations in Principal Cities

\$25 to \$45



**GET THE NEW IDEA
BATES MOTOR SAW
— 6 SAWS IN 1 —**

Does the work of band-saw, rip-saw, cross-cut, miter, bevel and scroll-saw. A wonder worker for the home shop. Direct drive! Can't stick! Cuts 2" wood. Most amazing variety saw ever invented. Does more, costs less! Not a toy. Write for circular.

BATES MOTORCRAFT COMPANY
Dept. M 28 N. Clinton CHICAGO, ILL.



CALCULATIONS

In Office, School, Store and Shop can be instantly made with the Gilson Slide Rule. It gives the answer to any problem involving fractions, mixed numbers, decimals, whole numbers, roots, powers, Logs, and Trig. Functions. Thousands of these rules are used by Accountants, Engineers, Clerks, Students, etc. It is the most versatile calculator ever invented. If you have any figuring to do, order a Gilson Slide Rule on trial. Made of aluminum with figures on white celluloid. Size 4".

Price with Instruction Book, \$1.50. Leather Case, 50c extra. Catalogue Free. Sent C. O. D. if desired.

Your money back if you are not satisfied.

GILSON SLIDE RULE CO., Stuart, Florida.

**Tight Handles—Send for booklet
"HOW to KEEP TOOL HANDLES TIGHT"**
Fayette R. Plumb, Inc., 4857 James St., Philadelphia

**LE PAGE'S
GLUE**

Handiest tool in your
workshop.

In bottles, tubes and cans.



The CRESCENT

20" band saw, 4" and 6" bench jointers, No. 12 saw table are adapted for use wherever there is wood work to be done. These machines are small but are substantially built. Ask for circulars.

In the larger sizes we can supply band saws, saw tables, jointers, shapers, variety wood worker, planers, planers and matchers, disk grinders, cut off table, swing saws, borers, hollow chisel mortisers, tenoners, self feed rip saw, universal wood workers.

THE CRESCENT MACHINE CO.
93 Columbia Street, Leetonia, Ohio, U. S. A.

**Put These
TOOLS
to Any Test
We Stand Behind Them**

Tools of phenomenal strength and wearing qualities. . . . You can drive rivet punch through auto frame. . . . Cut shaving off axle shaft with bearing scraper. . . . Lock our wrench with any other wrench and bring pressure until one breaks. . . . Drive 3/4" chisel through 1 1/2" machinery steel. . . . Your money back if tools fail to meet these tests.

**CORNWELL
Quality Tools**

Hand made of finest Swedish Charcoal Process Molybdenum Steel manufactured to our famous Cornwell formula. . . . Forged, heat treated, hardened and tempered in oil. . . . NOT drop forged and case hardened.

Free Booklet—Mail the Coupon

Booklet describing amazing tests of these tools will be sent upon request. Our Money Back Guarantee is your assurance that these tools will do everything we claim.

The Cornwell
Quality Tools Co.,
Dept. L,
Cuyahoga Falls, Ohio

Send me new illustrated booklet with prices on full line of Cornwell Hand-Made Tools.

.....Where Employed
Name
Address
City State



Keep forever
the thrill of today!

Pathex catches all the life and action of the moment so easily, simply, and inexpensively. Just a few seconds to load—then aim, and press the button!

Non-inflammable film, and free development of all you take, gives you the utmost in safety and low cost operation.

New complete Motor Driven outfit—lowest price of all. The projector shows your own pictures and a wonderful variety of films from the Pathex Library.

PATHEX, Inc.

35 W. 45th Street

New York, N. Y.



Demonstration at your dealer's or write direct to us for illustrated booklet.



Pathex

AUTOMATIC

**MOTION PICTURE
CAMERA AND PROJECTOR**



\$10.00

**DOWN
Brings
this Lathe
to You**

SYPER MANUFACTURING COMPANY
Dept. D Toledo, Ohio

Lathes \$6.00 to \$75.00. Largest line of small lathes in America. Send four cents for 24 page catalog of lathes, drill presses, bench saws, jig saws, hand saws, etc.

**4 1/2 Brake
H.P.**

SPEED
over 20 miles per hour

**MASTER
CAILLE** ⁵SPEED TWIN

SEND for FREE BOOK




The only outboard motor with neutral starting position—the only one with fast and slow speeds forward and reverse—the only one where the hand that steers controls all speeds by merely raising or lowering the steering handle. Other features—practically vibrationless—safety tilting—light weight—the famous Caille guarantee—easy payment plan.

THE CAILLE MOTOR COMPANY
6218 Second Blvd., Dept. E., Detroit, Mich.

Pay as You Play

\$32.00

puts a motor on your boat. The rest in easy payments.



Rider Agents Wanted

Select from the 44 Styles, colors and sizes of Mead Bicycles. Models for every age. Ride and exhibit sample and make money.

30 Days' Free Trial select On Approval for a month's trial. If not fully satisfied, return it at our expense. Prices from \$21.50 up.

Tires best quality, factory prices. Save big money on lamps, wheels and equipment, low prices. Send No Money, do business direct with makers.

MEAD CYCLE COMPANY
DEPT. 110 CHICAGO

Write today for free Catalog, factory prices and marvelous new offer.



Makes Old Ford a Tractor

Now you can convert that old Ford car into a useful farm tractor without altering any Ford parts. We furnish the traction wheels, drive gears and auxiliary axle and mountings, ready to clamp on to the Ford frame. Pulls 16" plow.

We supply a Belt Pulley also



Write for Free Particulars.
SHAW MFG. CO., Dept. S, Galesburg, Kan.

AGENTS! EXPERIENCE UNNECESSARY



Science has finally produced it. An instantaneous metal cleanser—neither sloppy liquid nor messy paste. Dry magic floss. Touch it to nickel, copper or brass. The metal shines bright and clean instantly. No hard rubbing! Lightning Silver Cloth does same for Silverware. Lightning Furniture Floss instantly cleans and puts high luster on Furniture. No liquid! Lightning Polishing Cloth is approved by Good Housekeeping Institute. Agents making up to \$50 a day!

**AMAZING
DISCOVERY
ABOLISHES
METAL AND FURNITURE
POLISH**

Imagine! Touch tarnished articles with a Lightning Polishing Cloth or Floss and you make them bright as new. Demonstrations positively astonishing! Every one a sale! Agents collect real money on every call.

Makes a Sensational Demonstration!

Everybody Buys These Products. Housewives buy the Lightning Silver Cloth and Furniture Floss. Autoists buy Lightning Polishing Floss. Sell all three to stores and offices in big quantities. Nothing else like them. Sure big, quick MONEY GETTERS.

Sample Free! Exclusive territory. Real cooperation. Triple profit. Answer this ad at once. Make big money. Easy! Quick! Don't delay. Write NOW! FREE test sample and proposition by return mail.
E. O. LIGHTNING PRODUCTS CORP., 1773 Greenleaf Ave., Chicago

\$542⁰⁰ Earned IN ONE MONTH

A BIG MONEY-MAKING BUSINESS

A BUSINESS TO ENTHUSE OVER—THE "IDEAL" LAWN MOWER SHARPENER

A wonderful invention that sharpens lawn mowers scientifically—quickly—perfectly; does the work as nothing else can.

W. T. Moore, Twin Falls, Idaho, writes: "The Ideal Grinder, as a side line, netted me a profit of \$1200.00 in 90 days."

W. F. Kendt, Buffalo, writes: "I sharpened 904 lawnmowers last season and the receipts were nearly \$2,100 which is not bad for a side line."

LAWN MOWERS SHARPENED TO RAZOR EDGE

People glad—owners delight in mowing lawn with mower sharpened on an "Ideal." Mower runs light—click-click-click and the grass is cut. Build permanent business for yourself. Start Now! No town too small.

Use Your Spare Time If you work at a trade, put an "Ideal" in your basement and earn \$4 to \$6 an hour evenings and Saturday afternoons.

WRITE TODAY for full information of this wonderful money-making machine. **FREE**

THE FATE-ROOT-HEATH MANUFACTURING COMPANY
Plymouth, Ohio

Zeno Brandon, Middletown, Ohio, writes: "I made \$520.70 in 55 days with my 'Ideal.' Have made as high as \$28.70 in one day."

USE THIS — MAIL IT TODAY

The Fate-Root-Heath Company
818-844 Bell Street, Plymouth, Ohio

Please mail free illustrated Catalog and booklet with scores of letters from "Ideal" owners and pictures of their shops.

Name _____

Address _____



Now, Only \$39

Let Me Send You the Greatest LOG SAW Offer

Put the OTTAWA Working For You

—I ever made. One man saws 15 cords a day—easy. Falls trees, saws limbs. Make big money. Use 4 H.P. Engine for other work. Saws faster than 10 men. Shipped from Factory or nearest of 10 Branch Houses. Cash—Easy Terms. Write for 30-Day Trial Offer and big FREE book.

OTTAWA MANUFACTURING COMPANY
1741-W Wood Street, Ottawa, Kan.
from 1741-W Magee Bldg., Pittsburgh, Pa.

SOLDERALL
METAL IN PASTE FORM

The only convenient metal solder

Every Electrical Connection needs Solderall for perfect reception

25¢

The SOLDERALL CO., NEWARK, N.J.

FREE TO BOYS

"THE SHOOTER'S ART" Tells how to hold, aim and handle rifles; helps you guide others in correct knowledge of guns. Gives facts that make crack shots. Contains safety and common sense instruction every parent and boy should have. Helps to make boys leaders. Your copy Free. Write at once.

The NEW BENJAMIN Air Rifle

America's Original Air Rifle

Outshoots All Others

\$5 at your dealer's or sent postpaid. Write! BENJAMIN Air Rifle & Mfg. Co., 645 N. Broadway, St. Louis, Mo.

The Shooter's Art

Make BIG Spare-Time MONEY

Have fun playing for dances, and get good pay for it. You can be ready in sixty days with a

BUESCHER

True Tone Saxophone

If you can whistle a tune you can learn to play a Buescher. 3 lessons given on request with each Buescher Sax' give you quick, easy start. Many learn scales first hour, play tunes first week, with their Bueschers.

Easy to Play — Easy to Pay

Take any Buescher Instrument home for six days' trial. See what you can do. If you decide to keep it, pay a little each month. Send for Beautiful Catalog and details of this liberal plan. No obligation. Mail the coupon today.

BUESCHER BAND INSTRUMENT CO.
Everything in Band and Orchestra Instruments
2011 Buescher Block Elkhart, Indiana

BUESCHER BAND INSTRUMENT CO. 2011 Buescher Block, Elkhart, Ind. 284
Gentlemen: Without obligating me in any way please send me your free literature. Mention instrument interested in.
Age?.....Name Instrument.....
Name.....
Address.....

SEND FOR FREE BOOK





for
vacation time

Pocket Ben

WHATEVER you do, wherever you go, you need a reliable watch that's sturdy enough for a vigorous outdoor life.

Pocket Ben is that kind. He'll help you plan your days and hours to get the most fun out of the shortest time.

Sold everywhere for \$1.50. With luminous day-and-night dial, \$2.25.

WESTERN CLOCK
COMPANY
LaSalle, Illinois



Glorious sport with this speedy square stern canoe


If you want a light, sturdy motor-boat, a boat of unusual speed and greatest economy, get one of these "Old Town" Square Stern Sponson Canoes and equip it with a portable motor. In this jaunty little craft you can fairly shoot across the surface of the water.

"Old Town" Square Stern Sponson Canoes are unsurpassed in durability too. Carefully constructed of the finest selected materials and thoroughly reinforced.

Free illustrated catalog gives prices and complete information about sailing canoes, square stern canoes for outboard motors, dinghies, etc. Write today. OLD TOWN CANOE Co., 1766 Middle St., Old Town, Maine.

"Old Town Canoes"

CATCH FISH EASY WAY!



Catch Fish, Lobsters, Eels, Crabs etc. in large numbers. Also Skunks, Weasel, Mink, Muskrats and many other fur-bearing animals, with my New Folding Galvanized **STEEL WIRE TRAPS**. They catch them like a fly-trap catches flies. Made in all sizes. Big money makers for trappers and fishermen. Write for Price List, **Free Trap Offer**, and my **Free Formula** for making best bait known for attracting fish and animals. **J. F. GREGORY, Dept. 131, Lebanon, Mo.**

Bodies of Rare Beauty for Fords

At Factory Prices!

Write for circular A-2
showing this De-Luxe
Model and others.

\$22.75 AND UP



Sport Factories AURORA, ILL.

100 SCALE PLANS



for building old and modern ship models. Send 6 cents for catalog of plans, books, prints, maps and other things that smack of the sea.

SEA ARTS GUILD, 405-A Eleventh Avenue, MILWAUKEE, WIS.

AGENTS 500% PROFIT GENUINE GOLD LEAF LETTERS



guaranteed to never tarnish. Anyone can put them on stores and office windows. Enormous demand, large profits. Paul Clark says: Smallest day \$28.70. R. L. Reel made \$920 in two months. Write today for free sample and liberal offer to general agents. **METALLIC LETTER CO., 433-B N. Clark St., CHICAGO**



TELLS ALL ABOUT THE 15 New Features

as well as the many other features of the wonderful Motor that thrilled the world in 1926 by its remarkable speed and power. You will want to know especially about "The Pilot"—a NEW device that steers your boat in any course you choose—straight or curved, without attention from anyone. Leaves you free to cast, or troll or rest. The New—

LOCKWOOD BOAT MOTOR

also offers you many other advantages—improvements in Power, in Speed, in Ease of Starting, in Stopping, in Convenience and Durability. Find out all about them before you choose any Motor. Get the facts now.

WRITE FOR FREE FOLDER

Just out—See how Lockwood is blazing the way by advanced engineering methods backed by 23 years of marine engine building experience. (24)

LOCKWOOD
MOTOR COMPANY
716 Jackson St. Jackson, Mich.

Own a CORONA

The portable typewriter built like an office machine. Has four-row keyboard and big-machine features throughout. Write to



LC Smith and Corona Typewriters, Inc.
612 E. Washington St., Syracuse, N. Y.

DRIES IN MINUTES!

Valspar Lacquer gives chairs, tables, cabinets, woodwork a beautiful satin finish in any color. Easy to apply—dries in minutes. Send 20c for sample! Red, Blue, Green, Yellow, Orange, Lilac, Brown, Ivory, Coral, Gray, Black, White, Valentine & Co., 450 Fourth Avenue, New York, N. Y.



VALSPAR BRUSHING LACQUER

Thompson
BEATS
the World
on BOATS

BETTER BOATS at Lower Prices



**The BEST that
Skill and Experience can Produce**
TWO BIG FACTORIES

Our complete line of 22 models offers you a variety to choose from. Prompt shipment from factory to you.
Catalog Free—Save Money—Order by Mail
Please state kind of boat in which you are interested.

THOMPSON BROS. BOAT MFG. CO. (20)
201 Ann St., PESHIGO, WISCONSIN (Write to either place) 101 Elm St., PORTLAND, ME. NEW YORK



We Studied Years

To correct the mistakes of old-type shaving preparations for you—now please accept a 10-day tube of Palmolive Shaving Cream to try

GENTLEMEN:

Palmolive Shaving Cream is a truly unique creation.

We made it up to meet the supreme desires of 1000 men whose ideals of a shaving cream we asked.

130 formulas were developed and discarded before we found the right one. All our 60 years of soap study, we put into this preparation.

The result was a business sensation. Palmolive Shaving Cream rose, almost instantly, to a leading position in its highly competitive field.

These 5 advantages

1. Multiplies itself in lather 250 times.
2. Softens the beard in one minute.
3. Maintains its creamy fullness for 10 minutes on the face.
4. Strong bubbles hold the hairs erect for cutting.
5. Fine after-effects due to palm and olive oil content.

Just send coupon

Your present method may suit you well. But still there may be a better one. This test may mean much to you in comfort. Send the coupon before you forget.

THE PALMOLIVE-PET COMPANY, CHICAGO, ILL.

3581

10 SHAVES FREE

and a can of Palmolive After Shaving Talc

Simply insert your name and address and mail to Dept. B-1335, Palmolive, 3702 Iron Street, Chicago, Ill.

Residents of Wisconsin should address Palmolive, Milwaukee, Wis.

(Please print your name and address)

The Old
Reliable
Credit
Jewelers

LOFTIS
BROS. & CO. EST'D 1888

Dept. A-894
108 N.
State Street
Chicago, Ill.

Genuine Diamonds Guaranteed
DIAMONDS
CASH OR CREDIT



Buy At Importer's Prices!

Save big money by buying from Loftis, the Direct Importer. Our Diamonds are world renowned for beauty and brilliance; all are blue white, carefully selected gems, set in mountings of solid 18-k white gold, exquisitely hand engraved.


Satisfaction guaranteed, or money back. Goods sent for your free examination on request. Credit terms: Pay one-tenth down; balance weekly, semi-monthly, or monthly at your convenience. All goods delivered on first payment.

SEND TODAY FOR OUR FREE CATALOG



Wedding Rings

No. 824—The "Elite" \$750
solid 18-k white gold
Set with 3 Diamonds, \$22.50;
5 Diamonds, \$32.50; 7 Diamonds,
\$42.50; 9 Diamonds, \$52.50;
12 Diamonds, \$67.50.



No. 857—Ladies' Wrist Watch,
solid 14-k white gold, 15 Jewels.
\$27.50—
\$2.75 down \$275 month week

19 Jewel Adjusted Wal-
tham No. 846—14-k white
gold filled; assorted pat-
terns, \$42.50, \$4.25
down and

\$100



Railroad Watches—Guaranteed to Pass Inspection

HAMILTON NO. 992, 21 Jewels, Adjusted to 5 Positions, Gold filled 25-Year Quality Case \$55
ELGIN'S LATEST RAYMOND, 21 Jewels, 8 Adjustments, Runs 40 hours one winding, Gold filled 25-Year Quality Case \$55
Credit at Cash Prices

BIASCOPE



AMERICAN
MADE
SIX-POWER
BINOCULAR

\$5

For all who hunt, fish, sail, motor, camp out or study bird life. Unexcelled for use in the movie and theatre or at outdoor games. Magnifies 6 times. Makes distant objects large and clear—brings the world to your feet. Precise optical qualities. Durable finish. Carrying case included. At your dealer or direct, postpaid.

PÖCKESCOPE

THE POCKET
TELESCOPE



\$2

A practical six power telescope. Made on the same formula as the Biastroscope, serving similar purposes. Neat leather case. At your dealer or direct, postpaid. Money back guarantee.

WOLLENSAK OPTICAL COMPANY

894 Hudson Avenue : : : : Rochester, N. Y.
Manufacturers of Binoculars, Telescopes, Microscopes,
Photographic Lenses of High Quality.

EDWARDS

WILL SAVE YOU
MONEY
ON
METAL ROOFS

We own our own steel mills, roll our own sheets, make them into high-grade REO METAL SHINGLES, Sidings, Cellings and Roofings of every type and style for every kind of building. We control every operation from the raw material to the finished roof and we sell direct from our factories to the user. Not a dollar to divide with anybody but the customer! You get better value for less money.

OUTLAST THREE ORDINARY ROOFS

EDWARDS METAL ROOFS are weather-proof, lightning-proof, fire-proof! The galvanizing bends with the metal. No tools required.



LOW-COST ALL-METAL GARAGES

Any size. Any style. Portable. Ready to erect. Complete with frames, doors, sash and hardware. Ornamental, durable, economical. Blue-prints and complete instructions FREE.

Write today. Get our low prices and Free Samples. Ask for Roofing Book No. 150 or for Garage Book No. 150

THE EDWARDS MFG. CO.
600-650 Butler St. Cincinnati, O.



Sport Bodies for Fords

AT FACTORY PRICES!



This Model in Grey Prime **\$39.50**

Write for Booklet A-2 Showing Other Models.

SPORT FACTORIES, AURORA, ILL.

SHAW MOTOR ATTACHMENT

MAKES YOUR BIKE A MOTORCYCLE!

A high grade 2 1/2 H. P. motor attachment quickly clamped on any bike frame. Speed 4 to 40 miles an hour. 90 to 125 miles per gallon of gas. Special Low Price Now! Write today for Complete Description and Special Low Prices on SHAW Motor Attachments and the SHAW Complete Motorcycle. SHAW MANUFACTURING COMPANY Dept. 37 Galveston, Kansas



RAISE BELGIAN HARES

NEW ZEALAND REDS—Chinchillas—Flemish Giants
MAKE BIG MONEY—We supply stock and pay you following prices for all you raise: Belgian Hares \$2 each—New Zealand \$3 each—Chinchillas \$4 each—Flemish Giants \$5 each. 25-page illustrated book, containing and contract, also copy of Fur Farming magazine, tells how to raise skunk, mink, fox, etc., for big profits, all for 10c. Address


OUTDOOR ENTERPRISE CO., Box 25, Holmes Park, Mo.

TYPEWRITER PRICES CUT

World's best makes—Underwood, Remington, Oliver—prices slashed to almost half.

\$2 and it's yours

All late models, completely rebuilt and re-branded new. GUARANTEED for ten YEARS. Send no money—big FREE catalog shows actual machines in full colors. Get our direct-to-you every payment plan and 10-day free trial offer. Limited time so write today. International Typewriter Co., 186 W. Lake St., Dept. 604, Chicago



A successful shave is
made up of three things—


a good brush,
a good lather,
and a good razor.

We will supply the first
requirement with a

**WHITING-
ADAMS**

Vulcan
Rubber-Cemented
Shaving Brush


The other two are up to you.
This famous name on a shaving
brush is a guarantee that
you are getting a good brush.




WHITING-ADAMS
BOSTON
BRUSH MAKERS FOR 118 YEARS

\$45 Buys This Motor Cycle

It's a Harley-Davidson, 16 H. P., twin chain drive, magneto and clutch. It has power and can get up and go on the open road at a speed which thrills. This is only one of hundreds of bargains in used motor cycles which you can get. Send for Free Catalog. It tells of big bargains and tremendous values in used motor cycles. Repairs quickly done. Motor cycles exchanged. Send us your machine to be overhauled.



Oliver Cycle & Motor Co., 1045 N. Grand Ave., St. Louis, Mo.



MOTORCYCLES

WE WILL TRUST YOU
Pay As Low As \$2.00 per Week
Hendersons, Harley-Davidsons, Indians

Slightly used and rebuilt. Hundreds to select from.

Send 10c for list today.

MYEROW BROS. CO., 15 Berkeley St., Boston, Mass., U. S. A.

HOW A BOY BUILT UP A GREAT SQUAB FARM



Started small in backyard when at school with no money, now has \$30,000 plant, ships to New York 150 bbls. squabs yearly, receiving \$75 to \$100 a barrel. You can do the same. Send for this book. Price is fifty cents but we will mail it to you for the names and addresses of four of your friends and your own name and address. Write today to

Plymouth Rock Squab Co., 634 A St., Melrose High., Mass.

DENINGER WILL TRUST YOU

\$40 SEND 20c IN STAMPS FOR CATALOGUES
BIG MONEY SAVING FOR YOU

Used and rebuilt motor cycles \$25 to \$100.
used bicycles \$9.50, tandems \$20.
All machines fully guaranteed.
New bicycles and motor cycles
at factory prices, save dealers'
profits. Motor cycles and auto-
mobiles from \$3. Complete line
frames, engines, supplies.

DENINGER PRICE CUTTER, ROCHESTER, N. Y.
PAY AS YOU RIDE



Even outdoors—hair never out of place!

STRIKE~ You're Out!

One, two, three—Out! He didn't have a chance.

Your unruly hair hasn't a chance, either, when you use—*Stacomb*! Go into action with this modern dressing and you can give those stubborn cowlicks the one-two-three every time they come to bat!

Stacomb is the hair dressing which more fellows rely on than any other. And here's the reason—

Stacomb really does keep your hair smoothly in place. There simply isn't any argument.

But more!—*Stacomb* brings out the natural lustre of your hair. Supplies the oils your hair needs. Never leaves it dried out, as frequent wetting with water does.

Stacomb never makes your hair look gummy either. It is actually beneficial—it helps prevent dandruff.

Stacomb comes as a combing cream,—in jars and tubes,—and now in the popular new liquid form as well. All drug stores.

FREE
OFFER

Stacomb

Standard Laboratories, Inc.,
Dept. BB-3, 113 W. 18th Street, New York.

Send me free sample of *Stacomb* as checked:—

Original, cream form ☐

New liquid form ☐

Name.....

Address.....



\$10⁰⁰ to \$25⁰⁰ a Day!

**Selling Freshly
Roasted Peanuts**

Wherever you find a crowd, hot, savory peanuts and crisp, sweet popcorn are in demand. Set up a Kingery Machine anywhere—in stores, at ball games, races, fairs. Profits 60% to 100%. Machines take little room; are easy and inexpensive to operate. Barbecue machines, too. Write now for Free Catalog.

The Kingery Mfg. Co. Dept. PM4, 410 E. Pearl St.
CINCINNATI, OHIO

Five Reasons Why Mechanics Prefer the Prest-O-Lite Blow Torch



Stand it on end, or hold it in any position—the Prest-O-Lite Torch excels in convenience as well as speed. Write for details, mentioning the class of work you do.

Prest-O-Lite is Quicker. No pumping, no generating, no pre-heating. Just turn on the gas and get busy.

It is Safer. No liquid fuel to spill and ignite. Fire-hazard reduced to a minimum.

It is Rugged. No delicate complicated parts requiring repairs or replacements.

It is Inexpensive. Simply exchange an empty tank for a full one (paying for the gas only) at any Prest-O-Lite Gas exchange station throughout the country. There are more than 15,000 of them.

Best for Every Blow-Torch Purpose. Gives you a wide range of heat under perfect, focused control.

THE PREST-O-LITE CO., Inc. - Indianapolis

New York - San Francisco

In Canada, Prest-O-Lite Company of Canada, Ltd., Toronto, Ontario
Unit of Carbide and Carbon Corporation

Prest-O-Lite

Gas

The Gas of a Thousand Uses



Big Pay!

"I MADE \$21.00 IN FIVE HOURS"

Writes Peter Werner, III. Sell Madison "Better-Made" Shirts for Large Manufacturer direct to wearer. No capital or experience needed. Spare or full time. Cash bonuses.

WRITE FOR FREE SAMPLES

MADISON SHIRT MILLS, 582 Broadway, New York

Diamonds Here at 60% of Market Price

Free Bulletin lists diamonds as low as \$60 per carat, also Gems of Finest Quality at higher per carat charges, but proportionately Low Bargain Prices. This 3/4 less 1-16 carat correctly cut diamond, a snappy blazing solitaire at \$68.50. This 75 year oldest largest Diamond Bunking Firm in all the world lends money on diamonds. Thousands of unpaid loans and other bargains. Many from big cash deals direct with European Diamond Cutters. Must sell NOW.

WHY PAY FULL PRICES

Costs Nothing to See

Any Diamond sent for absolutely free examination at our risk. No obligation. No cost to you. Latest Listings—Unpaid Loans. Sent Free. Describes Diamond Bargains in Detail, gives cash loan values guaranteed. Explains unlimited exchange privilege. Write today for your copy of Diamond Bargain List. Use blank below, clip ad and mail.


Name _____

Address _____

Tear out and mail today to—

Jos. De Roy & Sons,
Only Opposite Post Office

1957 De Roy Building
Pittsburgh, Pa.



If You Are A

MAN

worthy of the name and not afraid to work, I'll bet you \$50 that you can't work for us 30 days and earn less than \$200. Think I'm bluffing? Then answer this ad and show me up. Openings for Managers. The "Wonder Box" sells on sight.


TOM WALKER

DEPT. 25 - PITTSBURGH, PA.

MAKE YOUR FORD Into The "LARK"

\$500 Red-I-Kut life size patterns

Class—Snap



Famous sure-fit RED-I-KUT life-size patterns and picture instructions show how you can easily convert your Ford into this Fast, Sassy, Sport Car as thousands have done, with easily obtained materials. No need to lay up the car. Rear seat folds, making 4-passenger car. Send 10c coin for actual body photo

and new manual of other distinctive sport body patterns from \$5.50 up—"RKO" Steel "Swing-Lo" irons, Tops and Windshields. ORDER RIGHT NOW.

KUEMPEL COMPANY, 85 Kuempel Bldg., GUTTENBERG, IOWA


Information on any book free. Write Popular Mechanics Press, Chicago, Ill.

Women Simply Can't Resist This Fast-Selling Line

Just show women this exquisite display of dress goods, silks, wash fabrics and you can't keep them from buying. Men and women agents needed to devote full or spare time. Good commissions. Average \$40 to \$85 a week. 1,000 samples furnished. Write quickly.

THE NATIONAL IMPORTING CO.
Dept. T-6, 569-573 Broadway, N. Y. C. 1000 Beautiful Samples





TWELVE to 15 miles per hour with the Evinrude Fastwin gives the same thrill as 45 with your car. Carried in one hand—weighs only 49 pounds, develops 4 H. P., attaches to any boat in minute.

Three other models—S H. P. Speeditwin 75 lbs.; 2½ H. P. Sportwin 44 lbs.; and 2 H. P. Utility Single. Speeditwin, on hydroplane, delivers 15 to 27 miles per hour. Exclusive, copyrighted "Boat Speed Guide" tells at a glance which motor will give you the results you want. Standardized down-payment of only \$30 on any model. Standardized, low monthly terms—a long time to pay.

Free Trial Guarantee

—refunds money if not satisfied. That's the confidence we have in Evinrude superiority and in your liking this sport. Every outing a real vacation. No traffic rules, no way to be reckless. More room than in your car—new things to see, new places to go.

EVINRUDE MOTOR COMPANY
2404 27th St. Milwaukee, Wis.

FREE! New Evinrude Year Book

Motors in actual colors; 40 interesting pages showing beautiful waterways, speed records—complete! Send for free copy today.

Beautiful HOUSES \$900 and BUNGALOWS

CAN BE BUILT FOR AND UP

This and many others in my new book, Building Plans for Modern Homes, will save you hundreds of dollars. One of the most complete and comprehensive books of plans ever published by any architect. New edition just off the press. Nearly 600 floor plans and photographs of Colonial houses, bungalows, etc., costing from \$200 up; gives sizes and cost to build. Sent postpaid for \$3.00.



FREDERICK H. GOWING
ARCHITECT
101 Tremont St., BOSTON, MASS.

AGENTS AND SIGN MEN

Now Making \$50.00 to \$100.00 and Up Per Week Selling Our GOLD LEAF SIGN LETTERS

R

For store and office windows, board signs, trucks and glass signs. We also make to order script signs and business emblems singly or by the thousands. A permanent business. No capital or experience required. Big demand in every city. Samples and Literature Free.

CONSOLIDATED SIGN LETTER CO. 69X W. Van Buren CHICAGO, ILL.

Every muscle out of kilter

More muscles aching than you knew you had—scraped shin, scratched hand—sunburn.

Apply Absorbine, Jr. for relief—soothing, healing, cleansing, antiseptic. It is a powerful liniment.

\$1.25 at your druggist's.
W. F. YOUNG, Inc.
Springfield, Mass.



WURLITZER

REG. U.S. PAT. OFF.

"Bill Carola"
Landau's
Seranaders



Couldn't Play a Note—Now Makes

\$100 a week

"When I sent for your catalog, I didn't know a note of music. A few months after I bought my Wurlitzer instrument, I had taken my place in a professional orchestra. Now I am making \$100 a week, three times what I made as clerk. I wish everybody knew how easy it is—anyone who can whistle a tune can learn to play a musical instrument."

—Bill Carola

Free Trial Easy Payments

You may now have any Wurlitzer instrument for an ample free trial in your own home. Examine the instrument, note the fine workmanship, the full, rich tone value and especially how easy it is to play. No obligation to buy—no expense for the trial. We make this liberal offer because we want you to try for yourself a genuine Wurlitzer instrument, the result of 200 year's experience in musical instrument building.

Easy payments are arranged to suit your convenience. This is your opportunity to try a famous Wurlitzer instrument in your own home. Send for

Free Book

Illustrates and describes every known musical instrument—more than 3000 articles, many of them shown in full colors. All genuine Wurlitzer instruments—buy direct from Wurlitzer and save money. Special offers on complete outfits.

We also give you our Free Trial, Easy Payment Plan. No obligation.

Send Coupon Today!

The Rudolph Wurlitzer Co., Dept. A177

117 E. 4th St., Cincinnati 329 S. Wabash Ave., Chicago

120 W. 42nd St., New York 250 Stockton St., San Francisco

Send me your Free Book on musical instruments. Also your Free Trial, Easy Payment Plan. No obligation.

Name

Address

City State

Instrument

Copyright 1927, The Rudolph Wurlitzer Co.

PATENT

Protect Your Ideas

Take the First Step Today

If you have a useful, practical, novel idea for any new article or for an improvement on an old one, you should communicate with a competent Registered Patent Attorney AT ONCE. Every year thousands of applications for patents are filed in the U. S. Patent Office. Frequently two or more applications are made for the same or substantially the same idea (even though the inventors may live in different sections of the country and be entirely unknown to one another). In such a case, the burden of proof rests upon the last application filed. Delays of even a few days in filing the application sometimes mean the loss of a patent. So lose no time. Get in touch with me at once by mailing the coupon on the opposite page.

Prompt, Careful, Efficient Service

This large, experienced organization devotes its entire time and attention to patent and trade mark cases. Our offices are directly across the street from the U. S. Patent Office. We understand the technicalities of patent law. We know the rules and requirements of the Patent Office. We can proceed in the quickest, safest and best ways in preparing an application for a patent covering your idea. Our success has been built on the strength of careful, efficient, satisfactory service to inventors and trademark owners located in every state in the Union.

NO CHARGE for Information On How to Proceed

The booklet shown here contains valuable information relating to patent procedure that every inventor should have. And with it I will also send you my "Record of Invention" form on which you can sketch your idea and establish its date before a witness. Such evidence may later prove valuable to you. Simply mail the coupon and I will send you the booklet, and the "Record of Invention" form, together with detailed information on how to proceed and the costs involved. Do this NOW. No need to lose a minute's time. The coupon will bring you complete information entirely without charge or obligation.

My Patent Law Offices
Just Across
Street From
U.S. Pat. Office



Above is a view of my drafting and specification offices where a large staff of experienced experts are in my constant employ. All drawings and specifications are prepared under my personal supervision.

NEWS

Inventors Write for these Free Books


Strict Secrecy Preserved

All communications, sketches, drawings, etc., are held in strictest confidence in strong, steel, fireproof files, which are accessible only to authorized members of my staff. Feel free to write me fully and frankly. Your case will have my personal attention. It is probable that I can help you. Highest references. But FIRST—clip the coupon and get my free book. Do THAT right now.

Clarence A. O'Brien

Registered Patent Attorney

Member of Bar of: Supreme Court of the United States; Court of Appeals, District of Columbia; Supreme Court, District of Columbia; United States Court of Claims. Practice confined exclusively to Patents, Trade marks and Copyrights



Clip this Coupon and Mail it Now!


CLARENCE A. O'BRIEN, Registered Patent Attorney

70-Y Security Savings and Commercial Bank Bldg., Washington, D. C.

Please send me your free book, "How to Obtain a Patent," and your "Record of Invention" form without any cost or obligation on my part.

Name.....
(Important: Write or Print name clearly.)

Address.....



Our New York Office
Suite 1007 Woolworth Bldg.



Our Philadelphia Office
Suite 714-15 Liberty Bldg.



Our Washington Office
Victor Building

PATENTS TRADE-MARKS AND COPYRIGHTS

Have You An Idea?

Our Offer: FOR THE PROTECTION OF YOUR INVENTION YOUR FIRST STEP

Before disclosing an invention the inventor should write for our blank form

"RECORD OF INVENTION"

This should be signed and witnessed and returned to us together with model or sketch and description of the invention for **INSPECTION and INSTRUCTIONS**

No Charge for the Above Information

Our Four Books Mailed Free to Inventors

Our Illustrated Guide BOOK

How to Obtain a Patent

Contains full instructions regarding U. S. Patents. Our Methods, Terms, and 100 Mechanical Movements illustrated and described.

Our Trade Mark Book

Shows value and necessity of Trade Mark Protection. Information regarding *Trade Marks and unfair competition in trade.*

Our Foreign Book

We have Direct Agencies in Foreign Countries, and secure Foreign Patents in shortest time and lowest cost.

Progress of Invention

Description of World's Most Pressing Problems by Leading Scientists and Inventors.

We Regard a Satisfied Client as our best advertisement, and furnish anyone, upon request, lists of clients in any state for whom we have secured patents.

**Highest References—Prompt Attention
—Reasonable Terms**

VICTOR J. EVANS & CO.

PATENT ATTORNEYS

Main Offices: 956 9th St., N. W., Washington, D. C.

Opposite U. S. Patent Office

PATENTS TRADE-MARKS AND COPYRIGHTS

IMPORTANT

TO HAVE YOUR CASE MADE SPECIAL AND AVOID DELAY YOU SHOULD HAVE YOUR CASE MADE SPECIAL IN OUR OFFICE to secure protection, save correspondence and secure early filing date in Patent Office. To secure special preparation of your case send \$25.00 on account with model or sketch and description of invention.



MAIN OFFICE, VICTOR J. EVANS & CO.—VICTOR BUILDING, WASHINGTON, D. C.

Our Lawyers Practice in all U. S. Courts and defend Clients in Suits involving Patents, Trademarks and Copyrights

All Communications and
Data Strictly Confidential.
Interference and Infringe-
ment Suits Prosecuted

OUR ORGANIZATION OFFERS
PERSONAL SERVICE
By Experienced Patent Lawyers,
Solicitors and Draftsmen



Our Chicago Office
Suite 1114 Tacoma Building



Our Pittsburgh Office
Suite 514 Empire Building



Our San Francisco Office
Suite 1010 Hobart Building

**FREE
COUPON**

**VICTOR J. EVANS & CO.
PATENT ATTORNEYS**

NEW YORK OFFICES
1007 Woolworth Bldg.

CHICAGO OFFICES
1114 Tacoma Bldg.

PHILADELPHIA OFFICES
714-715 Liberty Bldg.

PITTSBURGH OFFICES
514 Empire Bldg.

SAN FRANCISCO OFFICES
Hobart Bldg.

MAIN OFFICES: 956 9th Street, N. W., WASHINGTON, D. C.

Gentlemen: Please send me *Free of Charge* your books as described on preceding page.

Name

Address

PATENTS

Just as it is important that you protect your idea with a patent, so it is imperative that your patent covers your invention completely. The one best way to assure this is to retain a reliable, experienced patent attorney.

MUNN & CO. PATENT ATTORNEYS

Associated for 81 years with the Scientific American

1572 SCIENTIFIC AMERICAN BLDG.
24 West 40th Street, New York

523 SCIENTIFIC AMERICAN BLDG.
Washington, D. C.

1312 TOWER BUILDING
Chicago, Ill.

520 VAN NUYS BUILDING
Los Angeles, Cal.

655 HOBART BUILDING
San Francisco, Cal.

Ask for free copy of "Patents—A Book of Facts Every Inventor Should Know" and for "Inventor's Diary." Send for them NOW.

PATENTS

Booklet Free

Promptness Assured

Highest References

Best Results

Send drawing or model for preliminary examination of Patent Office records.

ALL BUSINESS GIVEN PROMPT AND PROPER ATTENTION

Listed Patent Lawyer in the latest editions of the Rand-McNally Directory of Bankers and Attorneys, of Chicago, Ill.; The Baggott & Ryall Directory of Attorneys, New York City; The Lawyers Guaranteed Directory, Detroit, Michigan; The Lawyers and Bankers Quarterly, published by the Legal Directory Publishing Company of St. Louis, Mo.; the American Lawyers Annual, Cleveland, Ohio.

WATSON E. COLEMAN,
REGISTERED PATENT LAWYER

Victor Building, 724 Ninth Street, N. W.
WASHINGTON, D. C.

1000 NEEDED INVENTIONS!

Here is the most remarkable book ever offered to inventors. One Thousand needed inventions listed and described. Arranged as follows: General Problems; Automotive; Mechanical; Electrical; Chemical; Radio; Marine. Separate chapter on the Ten Most Needed Inventions. This book may give you one idea that will win you a fortune. Nothing else like it has ever been published. Compiled at enormous expense. Edited by Raymond Francis Yates, formerly Managing Editor of a leading scientific magazine. Over 100 pages, durably bound. Send no money. Pay postman only \$1.00 plus postage on arrival. Money back after 10 days' examination if desired. Limited edition. Write NOW.

BUREAU OF INVENTIVE SCIENCE

DEPT. 36

ROCHESTER, NEW YORK

Have You An Invention?

If so the WORLD PROGRESS will send you upon request sample copy Free containing SUGGESTIONS TO INVENTORS as to Inventions Needed. We invite manufacturers to address us regarding inventions they want.

Subscription for one year 60 cents

WORLD PROGRESS PUB. CO., Inc.
Room 203 Victor Bldg. WASHINGTON, D. C.



PATENTS

Send us sketch or model for advice and exact cost of patent. Our book "How to Obtain a Patent" sent free. It tells how to apply for Patents, Trade Marks, Foreign Patents, Copyrights, etc.; gives information on Patent Procedure; tells what every inventor should know. Thousands of inventors, who are our clients, are our reference.

CHANDLER & CHANDLER, 25 Years' Experience
473 7th St. Washington, D. C.

PATENTS

To the Man with an Idea

I offer a comprehensive, experienced, efficient service for his prompt, legal protection and the development of his proposition.

Send sketch, or model and description, for advice as to cost, search through prior United States patents, etc. Preliminary advice gladly furnished without charge.

My experience and familiarity with various arts frequently enable me to accurately advise clients as to probable patentability before they go to any expense.

Booklet of valuable information and form for properly disclosing your idea free on request. Write today.

Richard B. Owen, Patent Lawyer
9-303 Owen Bldg., Washington, D. C.
41-E Park Row, New York City

TRADE-MARKS
REGISTERED

INVENTORS PROTECT YOUR IDEAS

Send for our Guide Book, **HOW TO GET A PATENT**, and Evidence of Invention Blank, sent Free on request. Tells our terms, methods, etc. Send model or sketch and description of your invention for INSTRUCTIONS. No charge for the above information.

RANDOLPH & CO.
301 Victor Bldg., WASHINGTON, D. C.

NAME _____

STREET _____

CITY _____ STATE _____

Charge it



\$39.50

G-50 4 diamonds and 4 blue sapphires adorn this 14 karat solid white gold Wrist Watch with 15-jewel movement. \$3.85 a month.

G-51 5 blue-white diamonds in 18 karat white gold Wedding Ring. \$32.50. \$3.15 a month.

\$1 With Order 10 MONTHS TO PAY

Your choice of these exceptional bargains will be sent to you for approval and 15 day trial if you will simply send \$1 with your name and address. If satisfied, pay balance in 10 equal monthly payments, otherwise return and your dollar will be refunded.

Our charge System is simple, easy, convenient, prompt delivery, no red tape, everything confidential.

Other Big Bargains in Diamonds, Watches and Jewelry in this booklet. SEND FOR IT TODAY. IT'S FREE.



G-52 AAA blue-white diamond in Ladies' Engagement Ring. \$60. \$4.90 a month.



G-53 3 blue-white diamonds in 18 karat white gold Dinner Ring. \$39.95. \$3.89 a month.


L.W. SWEET Inc

BULOVA PATENTED DUSTPROOF
You pay the Nationally Advertised Cash Price
\$28.50



The man who studies gets ahead. Popular Mechanics Press will advise you what books to read to advance in your trade. 200 East Ontario Street, Chicago, Illinois.

THIS WONDERFUL INVENTION



converts any ordinary cook stove into a gas stove. OXO-GAS is made from kerosene and air. Cheaper, cleaner and more efficient than coal. Responsible distributors wanted.

GLORIA LIGHT CO.
111-6N. May St. Chicago, Ill.

Build and Fly Model Aeroplanes



Build your own Model Aeroplane; make trial flights and learn the principles of Aeronautics. IDEAL Scale Drawings and Building and Flying Instructions help you build exact 3-ft. duplicates of any of the following well-known Planes. Send 25c now for complete Plans for the one you want to build. **Fokker North Pole Plane; De Havilland Mail Plane; Curtiss JN-4 Training Plane; NC-4 Naval Seaplane; Curtiss Military Trainer; Blériot, Nieuport or Taube Monoplane; also Cecil Peel Racar.** 25 cents each, postpaid.

Everyboy's Airplane
All parts ready to put together without nails, wire or glue. 3 1/2 ft. wing spread; Monoplane type. Guaranteed to fly. Complete outfit, prepaid, \$6.00.

IDEAL AEROPLANE & SUPPLY CO., 408 West Broadway, corner Spring St., NEW YORK

PATENTS

Don't Lose Your Rights To Patent Protection

Before disclosing your invention to anyone send for blank form "EVIDENCE OF CONCEPTION" to be signed and witnessed. As registered patent attorneys we represent hundreds of inventors all over the United States and Canada in the advancement of inventions. The form "Evidence of Conception," sample, instructions relating to obtaining of patents and schedule of fees sent upon request.

LANCASTER & ALLWINE

480 Ouray Bldg.

WASHINGTON, D. C.

Originators of forms "Evidence of Conception."

Will Finance Patents

"Patents of commercial value financed on royalty basis without expense to inventor. Mail models and copies of patents or full details to

KAMSTONE HOLDING CORP.

41 East 42nd Street

N. Y. C.

PATENTS

Trade Marks, Copyrights, Patent Litigation Handbook with illustrations, 100 mechanical movements. Sent free on request.

ALBERT E. DIETERICH

formerly member examining corps U. S. Patent Office
PATENT LAWYER and SOLICITOR

621-A, Ouray Bldg.

27 Years' Experience

Washington, D. C.

Materials For Handy Men

Bearings, Belting, Blue Prints, Books on Mechanical and Scientific Subjects, Brass Castings, Compressors, Gears, Lathes, Motors, Saws, Shafting, and Supplies of every kind for **MODEL MAKERS and HANDY MEN.**

Complete Catalogue 25c which is allowed on first \$2 order.

Amalgamated Sales and Service Corporation
327A South La Salle St., Chicago, Ill., U. S. A.

PATENTS

As one of the oldest patent firms in America we give inventors at lowest consistent charge, a service noted for results, evidenced by many well known Patents of extraordinary value. *Book, Patent-Saves, free.* **Lacey & Lacey, 646 F St., Wash., D.C. Estab. 1869.**

BLUE BOOK ON PATENTS

AND PRIORITY RECORD BLANK GRATIS.

MONROE E. MILLER, PATENT LAWYER
411-2 Ouray Building, WASHINGTON, D. C.
ELECTRICAL AND MECHANICAL EXPERT



Inventors and Mechanics
Send 10 cents in stamps for **Material Catalog**

COLBURN GEAR & MFG. CO.
98 Holmes St., Quincy, Mass.



MAKE A MOTORCYCLE

OUT OF YOUR BICYCLE with a STEFFEY MOTOR ATTACHMENT. RELIABLE—ECONOMICAL—EFFICIENT.

Easy to attach. Fits any wheel. Send stamp for circulars.
STEFFEY MFG. CO., Dept. P, 3924 Fairmount Ave., Phila., Pa.

Great New Invention

for Seekers of Health—Power—Beauty
Elco Electric Health Generator

Generates High Frequency Violet Ray, Mechanical Vibration Medical Electricity, and Ozone. Four of Nature's Greatest Curative Agents. For Home Treatments at less than 50 cents per year.

FREE BOOK "Health, Power, Beauty" describing this Great New Invention. Re-vitalize yourself. Bring back energy. Be wholly alive. Write today. **Lindstrom & Co., 30 W. Lake St., Dept. A-135, Chicago**

WANTED AGENTS SALESMEN MANAGERS

Experience Unnecessary
SEND FOR FREE SAMPLE



This REVOLUTIONARY DISCOVERY in "Tube Repairs"—"Devils Grip"—this MASTER STROKE of Scientific accomplishment—this new, legitimate, simple, fast-moving motor car necessity of insignificant price, makes it possible for absolutely anyone to make Big Money steadily and permanently, as our representative, YOU SHOULD EASILY

EARN \$100 EACH WEEK UP

We want more agents, salesmen, managers to take part in the nationwide distribution of this outstanding revelation in the automotive accessory field. EXPERIENCE DOESN'T MATTER. Men from ALL WALKS OF LIFE may benefit by this remarkable opportunity. Anyone with ambition and a sincere desire to get ahead can accomplish abundant success. For we make it doubly easy with the most astounding selling arrangement the world has ever known. We allow you to sweeten each sale with


REX VISION FILTER FREE

(Ends terror of blinding headlights) as an introductory premium and thus present every customer with an irresistible bargain—double value—twice the money's worth. It is not a question of—"Can You Sell." It would fit much better to ask—"Can you give away to motorists a high grade necessary accessory which they want and will have the moment they see it." With this added inducement you are enabled to make A REMARKABLE SOLICITATION.

A SOLICITATION—A SALE AND A PROFIT EVERY 5 MINUTES We have a FREE SAMPLE waiting to send you postpaid by return mail. Let "Devils Grip" reveal its own positive worth and amazing revolutionary value. It satisfies an ever-existing, ever-repeating, tremendous demand. We want more men to supply car owners, filling stations, garages, auto accessory stores, etc. FULL OR SPARE TIME. Exclusive territory. If you want to earn Big Money and earn it Fast in a clean, dignified occupation, Write For Your Free Sample and full particulars today. Do It Now, while the opportunity is still open.

REX RUBBER MFG. CO., 102 Sears Bldg., Chicago, U. S. A.

PLUMBING - HEATING WATER SYSTEMS



SAVE UP TO 40%

Wonderful bargains—everything guaranteed. Full line of plumbing and heating supplies. Hot water, steam heating plants and fixtures and water systems at big savings.

Install Them Yourself

Finest materials all brand new and perfect. Tell us your wants and mail us a rough sketch of your rooms.

SEND FOR PRICE LIST

B. KAROL & SONS CO. 800 S. KEDZIE AVE. Dept. 20 CHICAGO

30 DAYS FREE TRIAL 7 Tube-Single Dial RADIO SET

Write TODAY for This Wonderful Offer Direct from Factory!

World's greatest radio. Perfect working, single dial control, 7-tube receiver, shipped to your home for 30 days' free trial. Test it for distance, volume and tonal quality—and if you are not convinced that it is the best single dial set you ever heard, return it to factory.

Metrodyne Super-Seven

Only one dial tunes in all stations. Get 1,000 to 3,000 miles on loud speaker. Easiest set to operate. Highest grade parts used. Magnificent Two-tone Walnut Cabinet.

Big Profits to Agents and Dealers selling Metrodyne radios. All or part time. Great money making opportunity. Demonstrating set on 30 days' free trial, WRITE FOR OUR OFFER.

METRO ELECTRIC CO.

2151 N. California Ave., Dept. 145

CHICAGO, ILLINOIS


Retail Price

\$75

Completely Assembled

I Want to Send You a Santa Fe Special Watch

for You
to see and
examine



~ Send No Money ~

Watch Sent on 30 Day Free Trial

Santa Fe Special Watches are today being shipped to every civilized country in the world, and are probably the best and most favorably known watch in both Army and Navy.

In addition to our NEW LOW PRICE, I will send for your approval one of these Standard Watches, guaranteed for a lifetime of satisfactory service, not only by the Santa Fe Watch Company, but by the Great Illinois Watch Factory. So accurate, Government officials carry them; so perfect and beautiful, jewelers say they are worth 1-3 to 1-2 more than we ask for them. I will send you one to see WITHOUT ONE PENNY DOWN—allow you to wear it 30 days FREE—then sell it to you on easy payments.

WHY NOT OWN A 21 JEWEL SANTA FE SPECIAL WATCH?

You will never miss the few cents a day that will make you own one of these watches—SEND FOR WATCH BOOK—illustrating in beautiful colors hundreds of designs and combinations in cases in the POCKET WATCH, MEN'S STRAP WATCH and LADIES' WRIST WATCH. You can have your name or monogram and any emblem you may desire engraved in the Case to suit your own ideas. Write today for Free Watch Book, and make your selection at once, while this offer lasts.

FREE A limited offer! With every Santa Fe Special, beautiful gold chain or strand of exquisite pearls. Write today. Mail coupon for both Watch and Diamond Catalog

SANTA FE WATCH COMPANY

66 Thomas Building

Topeka, Kans.

(Home of the Great Santa Fe Railway)

Mail
coupon
to-
day!

SANTA FE WATCH COMPANY

66 Thomas Building, Topeka, Kansas


Please send prepaid and without obligation your Watch Book Free, explaining your "No Money Down" Offer on the Santa Fe Special Watch.

Name

Address

City

State



BUILD and RACE THIS MODEL of the WORLD'S FAMOUS INTERNATIONAL STAR CLASS

Construction set consists of all wooden parts shaped, sails, keel, mast, deck, screws, glue, small plane, sandpaper and very complete instructions—28 inches over all.

Price of complete set.....\$8.00 F. O. B. New York

Our complete catalog (worth 25c) will be sent free with every order for a Star Construction Set. Contains useful information to all model makers, also complete line of engines, boilers, fittings, power boats, sail boats and ship plans.

BOUCHER, INC. 415 MADISON AVENUE
NEW YORK, N. Y.

Ingersoll
WRIST WATCH \$3.50



FOR MOTORING wear an Ingersoll Wrist Watch. The jolts and jars of driving don't affect its timing dependability the way they do the more delicate watches.

And in case of accident, you can get it repaired quickly and at a very low cost by sending it to the Ingersoll Service Department, Waterbury, Conn.

Wrist Radiolite, tells time in the dark, \$4.00. Dealers everywhere.

INGERSOLL WATCH CO., Inc.
New York • Chicago • San Francisco

AGENTS Big-Quick PROFITS

Tires Hammered Full of Nails, Leak no Air. GALACITE a new Viscous Pneumatic Cement (NOT A LIQUID)
Seals PUNCTURES Instantly—the very moment they occur. One application made in a minute without taking tire off wheel or rim does the work. Seals slow leaks and porous tubes. Galacite aids in preserving rubber often doubling Tire Mileage. Don't confuse with anything else intended for the same purpose. Galacite is new, different, clean and scientifically correct. Made by a long established, highly rated financially responsible concern.

FREE SAMPLE

AT OUR RISK, MAKE THIS TEST
Hammer as many nails into a tire as you wish—Pull them out. No air will escape. No pressure will be lost. If you are not delighted we will pay you for your time and trouble.
AGENTS It will pay you to get the facts and get them NOW. You can't get rich in an hour but you can make immediate, sure, steady profits that are amazing. No talking. Just drive nails in an old tire. We back our men with powerful advertising helps. Banners Posters, Newspaper Advertisements and circulars.
FREE SAMPLE Full particulars, big book and a free sample will be sent you postpaid, by return mail. Territory is going fast. Send no money, just your name, but **ACT NOW.**
JOHNSON & CO. 19 W. Jackson Blvd., Dept. 594, CHICAGO




BOW LEGS?

OUR GARTER (Pat'd)
Makes Trousers Hang Straight

If Legs Bend In or Out. Self Adjustable.
Free Booklet—Plain Sealed Envelope

THE T. GARTER CO. Dept. 2, New London, New Hampshire

Simply and
Clearly Written



All You Need for Balloon Tire Repairing

Write for New Free Booklet

If you are interested in adding to your vulcanizing equipment—planning to add a repair department or start a shop—take the first step NOW. Get this new book! All the essential information with equipment illustrated and clearly described.

Every day brings more tires on the road—more repair work necessary—more profits for you if you are ready. Write for this book—unless you are one of the many who wait and put things off to let others profit.

The Shaler Company, 2706 Fourth St., Waupun, Wis.

GOOD TUBES DESERVE

Nothing else will do—to insure self-adjusting filament control, utmost tube performance, longest tube life. Insist on Amperite. Eliminates hand rheostats. Simplifies wiring. Price \$1.10 complete. Sold everywhere. Write for Free Radiall Book giving season's popular hook-ups and construction data to Dept. P. M. 6.



RADIALL COMPANY
50 Franklin St.
New York

AMPERITE

REG. U.S. PAT. OFF.

The "SELF-ADJUSTING" Rheostat



THIS 100 PAGE
RADIO CATALOG
FREE

Contains "Hook Ups"
5 Radio Illustrations
500 Over 1,000 Articles

"Build your own with 'RASCO' Parts"

RADIO SPECIALTY CO., 98 E Park Place, New York, N. Y.

Turn 1 Dial—get programs everywhere: **30 Days FREE!**



MIRACO
Tune 5

Users report Miraco Radios get Coast to Coast, Canada to Mexico, loud and clear on speaker; outperform \$100 to \$200 sets. Some hear Europe. Marvellous bargain! Don't buy unless 30 Days Trial proves it Most Selective, Clearest and Most Powerful Distance-Getter among big, fine 6-tube radios. Solid walnut cabinet. Write for **Factory Prices—SAVE Up to 1/2**. Every set completely assembled, rigidly tested, fully guaranteed. Ultra-b, \$49.75 flat. Speakers, batteries, tubes, etc. at big savings. Literature, record testimony and BIG SPECIAL OFFER.

Free

MIRACO RADIO GETS 'EM COAST & COAST

Midwest Radio Corporation
Pioneer Builders of Sets

USER-AGENTS WANTED
Write for discounts

Send for Proof 407-E Miraco Bldg., Cincinnati, O.

A & B Battery \$2 Charger ONLY

SATISFACTION GUARANTEED



Charges any type of storage A or B battery, using a few cents worth of ordinary house current, either alternating or direct. Cannot injure battery. Complete directions enclosed. Anyone can operate. No expensive "extras" to buy. Why pay \$10.00 to \$15.00 for a charger when you can get this splendid GUARANTEED R. B. Charger by mailing us two dollars (bills, money order, check or stamps) plus ten cents in stamps or coin to pay mailing costs. Charger will be sent postpaid. If you are not satisfied, return within five days and we will refund your money. Order at once—TODAY.

R. B. SPECIALTY CO.
Dept. L-1 318 East Third St., Cincinnati, O.

I made my first week \$93

"Made \$93 my first week. Since then I have been earning over \$100 every week selling Stay-Prest—S. L. Patterson, Iowa."

MEN OR WOMEN

\$123 Very First Week

"I worked six days, six hours each day, and made \$123 quick cash profit my very first week. Have been going strong ever since—Stay-Prest is the best seller ever."—J. W. VARNER, Iowa.

\$54 First Two Days

R. E. Bendine, Kentucky, who had never had any selling experience, made \$54 his first two days with this big profit maker.

\$32 Very First Day

Mrs. Helen Rhodesby, Oklahoma, made \$32 the first day she tried selling Stay-Prest.

\$14

First Two Hours

S. D. Mathews, Minn., trying Stay-Prest as a side line made \$14 first two hours. Now sells full time.

\$39

Spare Time First Week

G. M. Stewart, W. Va., tried selling Stay-Prest in spare time and made \$39 first week. Now a full time success.

New! INVENTION Stay Prest Trouser Presser



Keeps pants always pressed. Puts in knife-edged creases, removes baggy knees, smooths out entire surface. Easy to use—takes only a few seconds. No steam nor heat. Saves nap of cloth. Lengthens life of clothes. Durably made of hardwood—lasts years. Finished in black leatherette. All metal parts heavily nickel-plated. Fits any size trousers. Folds to 15 inches to fit small hand bag. Over 500,000 in use.

Great Big Profits in Advance

No waiting—no uncertainty! Average sale takes less than 7 minutes! Then you have your big, generous, quick, cash profit in your hand—we deliver and collect—you just write orders given you! Stay-Prest is absolutely guaranteed—patented in all countries—exclusive territories now being allotted—no time to lose.

NEW—No Competition

Stay-Prest never had competition—and in its new and improved form it cannot have. Everyone who takes orders for Stay-Prest makes big money from the very first day. Many earn \$125 to \$165 the first week, \$500 or more the first month—\$45 to \$25 the first day. No experience necessary—just follow our tried, tested, and proven selling plan—we furnish everything—you risk nothing. Send now for FREE selling outfit offer.

THE GETGEY-JUNG COMPANY
G-121, G-J Building, Cincinnati, Ohio

THE GETGEY-JUNG COMPANY

G-121, G-J Building, Cincinnati, Ohio

Rush full information about Stay-Prest Trouser Presser and FREE Super-Selling Outfit Offer. Also consider my application for exclusive sale in my territory.

Name.....

Address.....

City.....State.....

SPECIAL Values
SEND ONLY
A FULL YEAR TO PAY

Values not found elsewhere. Pin only \$1 to your order and your choice comes to you parcel post prepaid on 10 Days Free Trial. Then pay postman only \$1 more on delivery, and after free trial period pay balance in 12 equal monthly payments. Satisfaction absolutely guaranteed or your money refunded—our policy for 32 years.

Free Royal Book of Gems
Thousands of special values in genuine diamonds, jewelry and watches. Copy sent at once on request. No Interest, No Extras.

WB1—Sensational Value!
New, elegant Lady's dinner ring, 18K white gold, with 9 genuine blue white diamonds, 2 French blue sapphires. **\$39.75** a month

WB2—Think of it! 3 genuine first quality blue white diamonds, popular design, Lady's ring, 18K white gold. **\$29.50** per month

WB3—Style Leader! Attractive Lady's wristwatch, 14K solid white gold case with ribbon band and white gold clasp. Highest grade, 15 jewel ruby and sapphire movement, lifetime guarantee. **\$22.00** per month

WB4—The Smartest thing in a lady's ring. Genuine blue white diamond, artistically engraved and pierced. 18K white gold. **\$56.75**

WB5—Master's gentleman's ring. 14K green gold, engraved, genuine radiant blue white diamond, white gold top. **\$47.50**

WB6—Remarkable gentlemen's strap watch sale. Nationally famous Elgin strap watch, in 30-year guaranteed green gold filled case, radium dial, accurate timekeeper. **\$24.50**

ROYAL DIAMOND & WATCH CO.
ESTABLISHED 1895
ADDRESS DEPT 1320 170 BROADWAY N.Y.

RADIO AT HALF USUAL COST

Now—we give 30 Days' Free Trial on newest 5-tube—ONE DIAL—Coast to Coast Radio. Buy direct from factory—save half and get 2 year guarantee. Full line table type, consoles or complete outfits at prices that will surprise you. Over 15,000 satisfied owners. Don't buy any Radio until you write us for FREE Catalog, low prices and 30 Day Trial offer.

Westingale Electric Co., 1757 Belmont Ave. CHICAGO

'B' BATTERY ELIMINATOR

Only **\$4.75**

MONEY-BACK GUARANTEE
No more worry with "B" Batteries! Hook up a Perfect "B" Battery Eliminator and forget battery troubles forever. This wonderful new invention means better reception, sharper tuning. Gives you more real pleasure from your set. **Completely Equipped—No "Extras" to Buy**
Operates perfectly on direct or alternating current, giving up to 90 volts current, and using the full wave of the power supply. Simple directions enclosed—anyone can plug it in to any kind of set up to six tubes. Constant voltage gives set more power. Costs no more than set of good "B" Batteries.

SEND YOUR ORDER NOW
Don't blame your set because run down "B" Batteries won't let it work right. Order your Eliminator NOW. Write name and address on a piece of paper, pin a dollar bill to it, and mail it TODAY. Pay postman balance (\$3.75 plus a few cents postage) when he delivers your Eliminator. Use it ten days. If not more than satisfied, return it and get your money back.

PERFECT ELIMINATOR CO.
W-2 National Theatre Bldg., Cincinnati, Ohio

SET BUILDERS!

Before you build get our special prices on the parts you are planning to use. We'll save you money. Largest and most complete stock in U. S. A.

CHICAGO SALVAGE STOCK STORE
Dept. P.M. 509 S. State St., Chicago, Ill.

BURGESS RADIO BATTERIES

RADIO DEALERS' CATALOG—FREE!

A most complete catalog of everything in Radio. All the latest hook-ups. Sets, Parts and Kits of every description. Live Dealers need this book. Write on your business stationery.

COLUMBIA RADIO CORP., 111 W. Lake St., Dept. 238, CHICAGO, ILL.


FREE RADIO MAP

Size 28 x 33 inches with rule for measuring distances. List of radio stations, with call letters, and wave length, FREE if you send us names and addresses of five friends who have radios and what kind.

A. A. VIKING, 124 W. Austin Ave., Chicago

Fansteel Products Company, Inc.
North Chicago, Illinois

For Better Filament Control on your radio set use the **NEW Lynch EQUALIZOR** in place of rheostats. \$1 complete with mounting. At your dealer's or post-paid. Money back if dissatisfied. In ordering, state number and types of tubes in your receiver. **ARTHUR H. LYNCH, Inc.,** Manufacturers of the **Lynch Metallized Resistor,** 250 West 57th Street, NEW YORK, N. Y.



Quick action on the odd jobs!

The deftness that has long been associated with the use of Crescent Wrenches applies equally now to the complete line of pliers, chisels, hacksaws and other tools. All are made under the supervision of and guaranteed by the originators of the Crescent Wrench. Hardware and accessory dealers have them.

CRESCENT TOOL COMPANY
210 Harrison St. Jamestown, N. Y.

CRESCENT and Smith & Hemenway TOOLS

RADIO PANELS OF GENUINE BAKELITE

Cut, drilled and engraved to order. Send rough sketch for estimate. Our complete Catalog on Panels, Tubes and Rods—all genuine Bakelite—mailed on request.

STARRETT MFG. CO. 524 S. Green St.
Chicago, Ill.

Simplified Radio Blueprints

Blueprints for the most popular sets described in Popular Mechanics Magazine can be obtained for a charge just sufficient to cover the cost of production and mailing. The sets for which blueprints are available are:


Simple One-Tube Receiver	April 1926	— 25c
Two-Tube, Loud Speaker Set	May 1926	— 25c
Three-Tube, Cockaday Receiver	April 1925	— 25c
Three-Tube, Low-Loss, Short-Wave Set	Oct. 1925	— 25c
Three-Tube, Loud Speaker, Loop Set	Dec. 1926	— 25c
Three-Tube, 15 to 550 Meter Set	Nov. 1926	— 25c
Four-Tube, Loop Set, for Car or Home	Aug. 1926	— 25c
Five-Tube, Browning-Drake Set	May 1926	— 25c
Six-Tube, Self-Contained Receiver	July 1925	— 25c
Six-Tube, Counterphase Receiver	Feb. 1926	— 25c
Six-Tube, Portable, Loop Set	June 1926	— 25c
Electrolytic B-Eliminator	Feb. 1927	— 25c
Eight-Tube, 1927 Model Superheterodyne; this set of blueprints includes drilling templates and extra photos.	Oct. 1926	— 75c
B-Battery Eliminator	Mar. 1926	— 25c
Non-Radiating Unit	May 1926	— 25c
Simple Tube Tester and Chart	July 1926	— 25c
New Perfect-Tone Six	Mar. 1927	— 25c

Address the RADIO DEPT.

Popular Mechanics Magazine
200 E. Ontario St., CHICAGO

Back numbers of the magazines describing the construction of the sets can be obtained from our Circulation Department, price 25 cents each.

THE NEW RED JACKET CRAFTSMAN'S LATHE



Makes Homework Easy Now

It's fun to make furniture, garden trellis, toys, improvements and repairs with a set of tools like this carefully designed by a master workman.

The complete equipment consists of the powerful Red Jacket Motor, with **direct drive to an accurate wood turning lathe** (capacity 9 in. x 34 in.); a **bench saw**, that has depth and side gauges; **scroll and jig saw**; and **all accessories for both portable and stationary power drilling, buffing, grinding and cleaning**. Attaches to any light socket and converts your work bench into a complete private tool and machine shop.

A Special CRAFTS COURSE

And **Blueprint Service** is free to Red Jacket Shop owners—all that there is to know about handcraft methods, raw materials, woods, carving, sawing, turning, designing, carpentering, decorating, is taught by special correspondence.

Buy On Your Own Terms

Only \$10.00 down. Liberal discounts for cash. Easy monthly payment plans. It is no hardship to own a Red Jacket.

Interesting Literature Free

Just send the coupon. You will be surprised with all it contains. Beautiful, instructive, fascinating, interesting. Everything explained in our literature.

**only
\$10.00
down**


***** MAIL COUPON TODAY *****

WACO TOOL WORKS, 2915 So. Wabash Ave.
Chicago, Ill.

Manager, Dept. 106. Please send me particulars about 10-day free trial, free blue-prints and \$10 down payment.

Name.....

Address.....



**Don't Be
a
Slave**

Be independent and
make big profits with the

BEISSER KEY MACHINE

You can start a business of your own, no experience necessary. Only machine that will cut ALL KINDS of keys perfectly. No hand filing required. Also first keys by number without need of taking locks apart. Write Today for Full Particulars.

BEISSER KEY MACHINE CO.
407 Fort Street, East Detroit, Michigan

CRUISE this summer

on
the

D&C

lake
lines

Mackinac Island..
The Summer Wonderland
Chicago... Detroit
Cleveland.. Buffalo
Niagara Falls

**Over-
Night
Service**

On business, pleasure, or vacation,
sail between the above points on the
luxurious D&C liners—the fast-
est ships on the Great Lakes.
Swift, restful, refreshing, dust-
less traveling. First class
accommodations exclusively.
Autos carried. Wireless
aboard. — Write for Free
Illustrated Booklet of D&C
Tours

between Cleveland and Detroit, Buf-
falo and Niagara Falls and Detroit, and
between Detroit or Chicago and Mackinac
Island. Also daylight trips between Cleve-
land and Detroit during July and August.

Round Trip Fares between

*CHICAGO and DETROIT.....\$60

*MACKINAC ISLAND and
CHICAGO or DETROIT.....\$30

*BUFFALO and CHICAGO.....\$79

One Way Round Trip
†CLEVELAND and DETROIT \$3.50 \$6.00

†BUFFALO and DETROIT.....\$6.00 \$11.00

*Berth and meals included. †Berth and meals extra

On the Detroit and Chicago Division
there is music, dancing, with hostess in
charge, bridge, afternoon tea, golf, horseshoe
pitching, radio, moving pictures, and other
entertainments. Passengers limited to sleep-
ing accommodations. Radio and moving pic-
tures also on Buffalo Division.
Yachting, golf, horseback riding,
fishing, etc., at Mackinac Island.
Liberal stopover privileges.

For Reservations or further infor-
mation, address E. H. McCracken,
Gen. Pass. Agt. at Detroit, Mich.



DETROIT AND CLEVELAND NAVIGATION CO.



Let It Bring New Summer Joys!

THE Elto not only brings you the splendid
new sport of outboard motor boating—
racing, cruising, exploring—but it multiplies
the pleasures of your favorite recreation. Do
you tour—fish—swim—camp? An Elto
puts fresh joy in every sport—instantly makes
a fast, reliable launch out of any rowboat
on any lake or stream.

The All-Use Motor!

Meets Every Need! The Super Elto combines boun-
tiful power, flashing speed, compact portability and
light weight. Starts instantly on the quarter turn
flip of the flywheel. Provides motor and boat control
from any part of the boat. Famous propello-pump.
Send for new catalog—full of facts you should know
before you buy a motor. Write today. ELTO
OUTBOARD MOTOR CO., Ole Evinrude,
President, Mason St., Dept. AA Milwaukee, Wis.

The Super Elto

Starts with a quarter turn

MOVIES AT HOME



Many models of genuine MOVIE MACHINES, some
as low as \$3.75, all using standard size big theatre films.
Our stock of films is the most complete and lowest in
price—with an exchange service. Films of leading stars
and religious subjects are available. DON'T DELAY.
WRITE FOR FREE INTERESTING CATALOGUE
NOW!

PARAMOUNT MFG. CO.

Dept. 1371

BOSTON, MASS.

The man who studies gets ahead. Popular Mechanics
Press will advise you what books to read to advance in
your trade. 200 East Ontario Street, Chicago, Illinois.

New 21 Jewel Burlington



Only \$100 Down

brings you the NEW Burlington Watch. Then small monthly
payments. The famous Burlington—always a masterpiece—is
now better than ever! Sent on approval. Rock bottom, direct-
to-you prices.

Write Quick! While this special offer lasts. Get
in colors all the latest styles and over 100 exquisite designs.
Tells how to avoid over priced watches. A postcard will do—
19th St. & Marshall Blvd.
BURLINGTON WATCH CO. Dept. A-135 CHICAGO



Why Don't You Play a Hohner Harmonica?

Anyone may quickly learn to play real music on a Hohner Harmonica with the aid of this Free Instruction Book.

See how easy it is! Read the simple directions, look at the charts and pictures, take your Harmonica, hold it as shown and *blow-draw, blow-draw*. In a short time you will master the scale; and when you can play the scale you will soon be playing favorite melodies to the delight of yourself and friends

Get your harmonica today and be sure it's a Hohner. And ask for the Free Instruction Book. If your dealer is out of copies, write M. Hohner, Inc., Dept. 181 114 East 16th St., New York.

The Hohner "Marine Band" is the World's Greatest Harmonica Value at 50c



NEW TIMER FOR FORDS
MARVELOUS INVENTION
FREE OFFER TO USERS
FORD DYNAMO
60,000 MILES WITHOUT TROUBLE
WRITE TODAY FOR FREE OFFER
Agents Wanted Everywhere
Eclipse Timer Co., 2925 Melnecke Av., Milwaukee, Wis.



AMAZING INVENTION
Appeals to every motorist. Gets any car out of mud or sand. Nothing like it.
GETS-OUT TIRE LUG
Special offer to agents. Ask for details and territory.
Chicago Tire Lug Co., 860-336 W. 47th St., Chicago



Auto Owners Wanted

To introduce and use **HYDRO Insured TIRES**. Hydro Agents make money selling the only Tires in the World insured for One Year against all road hazards regardless of mileage. **HYDRO TIRES** sell fast because they have no competition in price; no rival in quality; no limitation in appearance and no equal in the insured protection to the user. Insurance Policy with every tire. Are made by the only tire factory in America selling its own product through authorized Salesmen-Agents. We offer opportunity of lifetime to establish profitable tire business of your own. No capital required. Sales kit and advertising helps furnished. Exclusive territory granted. Write today for catalog and complete information about the Hydro Agency Plan. *The Most Beautiful Tire in America*

Dept. 59, **HYDRO-UNITED TIRE CORP.**
Pottstown, Pa. Millersburg, O. Chicago, Ill.

Every Handy Man needs SMOOTH-ON NO. 1

SMOOTH-ON
No. 1 hardens like iron and expands in doing so to make cracked, open or loose parts everlastingly tight.



With Smooth-On No. 1, you yourself can do a perfect job for a few cents, usually in a few minutes, and you can collect a handsome profit on every Smooth-On repair you make.

Get the Smooth-On habit and you will quickly find that it puts many dollars into your pocket. Try it on the following and see for yourself:

In construction work

Tightening loose screws, hooks, locks, door knobs, anchoring posts, bolts, hooks, etc., in brick or concrete, mending loose tool handles, stopping leaks in steam, water, gas, oil or stove pipes, mending cracks, breaks or leaks in furnaces and boilers, radiators, supply and flush tanks, sinks, pits, sealing open spaces where pipes go through walls, etc.

In the home

Mending leaky pots and pails, making loose handles tight on cutlery, brushes, umbrellas, drawers, setting loose casters, etc.



Write for FREE BOOK



On the Automobile

Making bursted water jackets and pumps good as new, stopping leaks in radiator, hose connections, gas tank and gas, oil and exhaust lines, making a fume-proof joint between exhaust pipe and tonneau heater, tightening loose headlight posts, keeping grease cups, hub caps and nuts from loosening and falling off, etc. To get perfect results, write to us and use the Smooth-On Repair Book. Free if you return the coupon.

Get Smooth-On No. 1 in 7-oz., 1-lb. or 5-lb. cans at any hardware store, or if you want us to send sample 7-oz. can, enclose 35 cents in stamps when returning coupon.

SMOOTH-ON MFG. CO.
Dept. 37, 574 Communipaw Ave.
JERSEY CITY, N. J.

Do it with SMOOTH-ON

SMOOTH-ON MFG. CO., Dept. 37,
574 Communipaw Ave., Jersey City, N. J.

Please send the free Smooth-On Repair Book.

Name.....

Address.....

\$148⁰⁰ Weekly & Up Riding Around & Demonstrating

NEW Moisture Humidifier Increases Mileage $\frac{1}{4}$ to $\frac{1}{2}$



Model "A-1" VIX Vapor Humidifier and Gas Saver.

5 Models to fit every auto, truck, tractor, bus, taxi, engine, etc., including NEW Ford with Holly Vaporizer. Not a toy. Retails \$4.00 to \$25.00, installed and guaranteed.

Gives added snap and pep. Faster pick-up. Higher top speed. More power on hills. Eliminates hard carbon deposit in engines.

The wonderful Vix Vapor Humidifier and Gas Saver is a Moisture device which makes autos run all the time with the same wonderful efficiency they do on a cool, moist night. Users report 43 to 75 miles per gallon—official tests show 30 to 43.2 miles. Vapor moisture does it! Automatically and permanently eliminates hard carbon deposit in engine; does away with frequent plug cleaning and valve grinding and gives added power, pep and pick-up. Five models for all autos, trucks, tractors, busses, taxis, engines, etc. Installation comparatively simple with pictured instructions—no adjustment or attention after attached.

1 VIX FREE OFFER

The inventor is offering 1 free to introduce. Every Salesman, Agent and Car Owner should write for one at once. Direct Factory Agencies wanted everywhere. Address

WALTER CRITCHLOW,

Inventor and Manufacturer
X2-305 St., Wheaton, Illinois, U.S.A.



Made by one man selling the VIX. Another made

\$1656.40 IN 58 DAYS

BIG, QUICK PROFITS for Salesmen, Agents, Dealers, who act quick for spare or full time, because this amazing new patent is a startling DEMONSTRATOR. Monthly earnings reported by "spare time" Agencies:

Frank Hanfelder \$107.00	H. P. Phelps... \$105.00
William Fraser... 189.00	H. C. Daniel... 107.00
Louis A. Carlin... 80.00	E. Schafer... 96.00
M. M. Werline... 143.00	W. M. Hardy... 132.00
P. R. Langel... 117.00	W. R. Moser... 81.00
R. Stefaneky... 189.00	James Paton... 125.00

Can you do as well? Do you want to build a business of YOUR OWN? Do you want to make money FASTER, take life EASIER, get more of the BETTER THINGS of life—and get AHEAD QUICKER? Write quick for the VIX proposition for your territory.

Reports from Users

75 MILES Cephas H. Brown, of Roseneath, Canada, says: "I went on a 225 mile trip in my Ford and made my best record of 75 miles to a gallon with the VIX. That's some, isn't it? I can get you the fellow that was with me to prove it."

66 MILES George B. Cousins, Illinois, "Last Sunday with the VIX on, we drove up to Nuttall, 33 miles, and back, a total of 66 miles, on a trifle over 1 gallon of gasoline."

48 MILES Chas. J. Jabouze, Texas: (SWORN AFFIDAVIT) "The VIX on my Ford is great. Got 48 miles per gallon on 138-mile trip with 14 miles in black mud and chainson. Previously averaged 18 to 20 miles."

SM

You'll find 'em where the best is demanded!



The selection of S-M parts for the Popular Mechanics batteryless receiver, as well as for over half the season's popular circuits, are

the best reasons why they will improve any set you have or intend to build.

A number of booklets can be had for the asking—

- How to Build the Silver Shielded Six.
- How to Build the 635 Short Wave Set.
- "Secrets of Quality"
- How to Build the 652 Reservoir B.

The 222 output transformer illustrated above, connected between any set and loud speaker is guaranteed to improve reproduction. Price \$8.00.

SILVER-MARSHALL, Inc.
840 W. Jackson Blvd., Chicago, U. S. A.

You-and This New Machine Can Earn \$500 a Month



Operate a Tire Repair Shop

90,000,000 Tires in use. America's greatest opportunity for men with small capital. We furnish everything—\$100 and up. Easy payments. We train you FREE right at home. Start making money at once. Write today for Free Book "Steps to Success."

Haywood Tire Equipment Co.
1334 South Oakley Chicago, Illinois

SPORTING GOODS BARGAINS



FIELD GLASSES

5 Power; lenses 1 1/2"; central wheel focusing. Genuine leather case \$6.95

and shoulder straps. Wonderful value

Marble's Woodcraft Knife... \$1.90

Full size, man's Professional model.

Fielder's Glove. Fine grade

Horsehide; leather lined, reg- \$1.90

ular \$3.00

Hunting Knives, Rifles, Air Rifles and Pistols;

Baseball, Boxing and Tennis Goods—everything

at bargain prices. Satisfaction guaranteed.

Write for Catalog "W"

HUDSON SPTG. GDS. CO. (Dept. W) 52 Warren St., New York

Let us recommend the best books to study on any subject. Popular Mechanics Press, Chicago, Illinois



BUILD YOUR OWN GRANDFATHER'S CLOCK

We furnish blue prints and instructions. Buy the works and dial from us at surprisingly low prices. Make fine profit building artistic clocks for your friends. Plain Works as low as \$5.00. Others with Chimes at all prices. Ask for attractive free offer.

AMERICAN CHIME CLOCK COMPANY
1670 RUFFNER STREET PHILADELPHIA

Get this book FREE

NEW & USED AUTO PARTS

30 TO 80% Saving!

THE largest, most complete book of its kind ever printed! Packed full of nationally advertised Auto Parts at lower-than-bedrock prices—less than regular wholesale! An 80 page Book of Bargains—Timken Axles and Bearings, Brown-Lipe Transmissions—Pistons—Rings—Hayes and Firestone wheels—Rims, Tires, Tubes and a complete line of Accessories—new, except where specified. Everything for the auto at the low prices made possible by quantity buying and big-volume selling.

Largest Stock in the World

of new and used replacement parts! Write us FIRST—we have many parts impossible to get elsewhere—and you save 30 to 80%.

Write for Your Catalog Today—FREE!

WARSHAWSKY & Co.

World's Largest Replacement Parts House

1915-35 S. State St. Dept. PM-6 CHICAGO, ILL.



FREE SAMPLE CASE OFFER

\$100 to \$125 Profits Weekly

New line of quality toilet goods sells like wildfire. No experience required. All you do is take orders from this beautiful sample case. Perfumes, soaps, creams, face powders—wonderful products at prices that appeal to all women. FREE CATALOG.

NATIONAL SOAP & PERFUME COMPANY

512 W. Huron St., Dept. C-7, Chicago

AMAZING NEW WAY TO Play TENOR BANJO

Play as You Pay

Guitar — Ukulele — Mandolin

NO music to learn—NO tiresome lessons. Play latest song hits by numbers instead of notes (or by notes, if you wish). Just press numbered keys of the E-Z Player, or the same easy principle as a typewriter, and you are playing tunes. So easy we guarantee your success—"no play, no pay."

PLAY A TUNE IN 10 MINUTES OR SEND IT BACK

Travis Frigano, famous mandolin star, wrote: "I played in five minutes and never touched a stringed instrument before." John A. Cruser: "I was skeptical about anyone playing tunes instantly but have changed my mind completely." W. B. Matthis: "Your advertisement didn't tell half." Mrs. A. Kason: "The more I play the better it gets."

FREE BOOK


You will be surprised how little the cost to own your favorite string instrument. Send for Free Book explaining everything and the E-Z Pay Plan. No obligation. Be more popular, have more fun. Write today.

FERRY & CO. Dept. 977A CHICAGO



\$500 Down

buys a WITTE Engine



Easy Payments

With my Liberal EASY Terms the Witte Engine pays for itself! I sell direct—save YOU 25% to 50%! I am an engine specialist—been building engines for over 45 years. Mail coupon below now for my big FREE book telling WHY the great Witte Engine is the best you can buy—for any job—ANYWHERE.

Increases Your Profits \$500 to \$1000 a Year

That's what the Witte Engine will do—absolutely! Yes, and I guarantee it to do the work of 3 to 5 hired hands. Used all over the world—because it runs on cheapest fuels anywhere, from the frozen wastes of Alaska to burning sands of Arabia—from below sea level to 20,000 feet above! Whether you have an engine now or not—investigate the great Witte Engine. Mail coupon now.

Life Time Guarantee!

Runs on

**Kerosene
Gasoline
Gas Oil
Distillate
or Gas**

My unheard of Lifetime Guarantee is the talk of the engine world. Send for it today. The Witte engine is THE cheapest to operate. Burns any fuel with surplus power. Starts right off, even when it's 40 degrees below zero. Parts INTERCHANGEABLE. Spare parts years from now. We are today supplying parts for 40 year old Witte engines. 4 cycle throttling governor type. Semi-steel cylinders, heads, pistons and carburetor. Comes completely equipped with Wico Magneto. Buy on your own terms. No interest.

Send for Free Book Even though you may not be ready to buy today get the facts now about this great GUARANTEED for Life Witte Engine. Ask about my 1 1/2 to 30 H. P. Engines, 3-in-1 Saw Rig and Pump Outfits. Learn all about my EASY Payments Plan. Get ALL the facts—mail coupon today SURE!

Witte Engine Works, Dept. A-174

Witte Bldg., Kansas City, Mo. Empire Bldg., Pittsburgh, Pa. Without cost or obligation please send me your FREE Witte Engine Catalog and details of "Small Easy Monthly Payment Plan."

Name

Address

State

R. F. D.

Specify Type Engine Wanted

Trade your hours for dollars

At once—No more trifling with an uncertain wage job.

There is a big demand for Floor Surfacing Contractors.

Our national advertising is helping to develop it—building still greater business for American Universal Floor Surfacing Machine operators.

More than \$50,000,000 of floor surfacing and resurfacing to be done every year.

Get your share of it.


No big capital required—No long period of training.

Just get your American Universal and start to work.

The American Universal Floor Surfacing Machine is electrically driven—

Easy to handle—
Does the work of six hand scrapers.

Work is pleasant—
Always inside—
And shows big profits.



American Universal FLOOR SURFACING MACHINE
523 South St. Clair Street, Toledo, O.

Turn Your Spare Hours Into Real Money

HAVE'N'T you often wished for a spare-time way of making more money than comes in the regular pay envelope? Of the various ways which present themselves none is more pleasant or profitable than playing engagements in a Band or Orchestra.

Send the Coupon

For particulars of our easy Payment Plan that tells how you can "Pay While You Play."

Free Trial—We want you to try out a King in your own home, without obligation and if you do not find the King the very best instrument you ever played—return it.

Trade-In Proposition—Turn in the instrument you now own as part payment on a new King. Our latest catalogs show many new model Kings and tell why they are the best instruments to learn on and play on.

Use the coupon to order your copy.

THE H. N. WHITE CO.
5211-88 Superior Ave., Cleveland, O.

Instrument

Name _____

Address _____

City _____ State _____



Save more than ever
This 6 Room Bungalow **\$1493**
NOW FREIGHT PAID
Price includes everything complete—lumber cut-to-fit, FREIGHT PAID to your station.

New Low Prices Our customers claim average savings of 47% over local prices. This year reduced prices make possible still greater savings.

We Loan You Money to Build

We ship you any home you select, ready to erect, and ADVANCE YOU CASH to help you build. You pay us in small amounts monthly, just as you pay your rent—and your rent money is saved instead of spent. Send 25c in coin today for beautiful Color Book of Sterling Home Plans and you can be living in a home of your own a month from now.

INTERNATIONAL MILL & TIMBER CO.
764 S. Wenona Ave. BAY CITY, MICH.



Do Your PRINTING

Cards, stationery, circulars, tag, labels, paper. Complete Outfits, \$3.85 up, Job Presses \$11 up, Rotary \$149. Card Cutters, \$3. Save money. Print for others, big profits. All easy rules sent. Write for catalog presses, type, paper, cards, ink etc. THE KELSEY CO., A-37, Meriden, Conn.

Oh Boy! See All!

Big 3 1/2 Ft. Telescope

Lend wings to your eyes! People and objects miles away seem close. Wonder telescope brings new pleasures to home, farm, camp, travel, sport. Study the mysterious Sun spots; see Moon and Stars as never before. See people on the beach, on the mountains, etc.

FREE Yes, absolutely free! A handsome leatherette Carrying Case and Shoulder Strap. Also Solar Eye Piece to view the sun—a special feature, found only on expensive instruments.

5 Sections 8 Power Lenses
Brass bound; measures 12 in. closed; powerful achromatic lenses protected by dust caps.
Thousands Pleased
F. Brush wrote: "Watched submarines three miles off coast." Ed. Foster: "Told time on clock five miles away." G. Scribner: "See light house 15 miles away." Mrs. Yarbrough: "Could tell color of aeroplane four miles away." S. M. Gearhart: "Can see men working seven miles away." A. R. Walker: "Would not take \$10 for it."

SEND NO MONEY

On delivery of Telescope, free Case, Strap and Eye Piece pay Postman only \$1.85, plus postage (2 complete outfits \$3.50.) Satisfaction guaranteed or money refunded. Send today, entertain your friends! Be first to have one.

FERRY & CO., Dept. 177A, Chicago, U.S.A.



Start an HB Equipt Shop Earns \$150 to \$300 Monthly

Established Garages-Battery Stations and mechanics are adding substantial profits without expense to them. Start in business yourself with HB One Day Battery Service—Paint Spray—or Starting, Lighting, Ignition Service Equipment. HB guarantees bigger profits and enables you to do far better work than the other fellows with less expense to yourself.

Only \$16 Monthly Easily paid by increased profits




ONE DAY BATTERY CHARGING

Gives you the edge on competitors. Saves 30 to 50% on electric bills over rectifier and turns out work in one-third the time. Recommended by leading car and battery makers.

FREE AIR SERVICE

With \$12 monthly you can have constant Automatic Air Service to bring customers to your doors. Beltless, Silent, Ball Bearing. Quantity production makes possible the low prices.




PAINT SPRAY

Does the work of five men with brushes. Paints cars, furniture, houses, barns, garages. You can earn bigger profits yet charge far less than any competitor.

HB TEST BENCH

The best paying line in Automotive Electrical work. Tests starting, lighting and ignition systems. Brings you business from other shops. Priced \$100 to \$150 below similar quality outfits.



HOBART  BROTHERS
Successful manufacturers ~since 1893~

BOX M67

TROY, OHIO

Tear off Coupon and Mail Today

HOBART BROTHERS CO.
Box M67, Troy, Ohio.

Send me complete information on the items I've checked with your 30 day trial offer, easy payment terms, and information on how HB equipment will increase my earnings.

- ☐ One Day Battery Service Profits
- ☐ Electrical Test Bench Opportunities
- ☐ Portable Paint Spray Business
- ☐ Better Automatic Air Compressor

Name.....

Address.....

Occupies
Floor Space
Only
3 ft. sq.



**8 Cold Tubes for
8 Different Flavors
The Right Flavor
always on Top—
and COLD**

Each tube holds 9 cold bottles—72 in all. 72 more in reserve rack so you can't run short. To serve any flavor asked for, take a warm bottle out of rack, push it in one end of tube, holding same flavor, and out comes a cold bottle on the other side.

"'Liquid' Cooler Doubled My Profits in Bottled Drinks"

—says A. CRUICKSHANK, Dallas, Tex.

**Many make up to \$675 a Month Serving
Bottled Drinks this New Way**

NOBODY ever dreamed that so much money could be made selling bottled drinks until the "Liquid" Bottle Cooler appeared two years ago.

Nobody ever imagined that bottled drinks could be served so fast, clean and cold.

Nobody ever conceived that the public would be so quick to pass up the old fashioned ice box or tub of ice water to buy from the new, sanitary, "Liquid" Bottle Cooler that they see advertised in Saturday Evening Post color pages.

But actual records tell their own amazing story. Read about them in the book "Liquid Profits"—sent free if you'll mail Coupon. Learn how more than 20,000 merchants in almost every line of business are ringing up unheard of profits with this new invention. Many who never sold bottled drinks before because of the mess and bother of old fashioned methods are now clearing \$10 to \$30 a day from a little waste floor space 3 feet square!

"Doubled Business and Profits"

A. Cruickshank of Dallas, Tex., writes, "My 'Liquid' Cooler has doubled my business and profits in drinks and quickly paid for itself." McGrain Motor Co. says, "Profits paid for 'Liquid' Cooler and left a nice margin." "Best investment I ever made. Doubled sales of soft drinks," reports F. J. Houser of N. Y. And a Schenectady dealer tells how two "Liquid" Coolers cleared \$90.00 profits in a single day!

Profits Pay for "Liquid" Cooler

Many guess the price of "Liquid" Cooler at \$200 to \$500. Yet it costs only \$100 on easy terms. One dealer paid entire purchase price out of first 5 days' profits. Others pay for it quickly out of savings in ice and clerk hire.

Send for Free Book

Get all the facts in new book, "Liquid Profits." Tells how others have increased sales of bottled drinks 100% to 400%—made up to \$675 a month in season—cut ice bills 33 1/3% to 66 2/3%—saved 60% or more floor space and up to 80% clerk hire. "Liquid Profits" sent free if you give name of local bottler. Mail coupon now.

FREE "Liquid Profits"

Liquid Carbonic Corp., Dept. P-6
3100 So. Kedzie Ave., Chicago, Ill.


Send Free Book "Liquid Profits" and Easy Terms on The "Liquid" Bottle Cooler.

Name.....

Street.....

City..... State.....

My Bottler is.....



Blue Ribbon **5 TUBE NEODYNE**
RADIO KIT - COMPLETE

Only \$16.95

FREE!
GENUINE 20 INCH
ERLA CONE
LOUD SPEAKER &
5 TUBES

Can be built in 2 hours

COAST TO COAST RECEPTION

Latest 5 tube circuit designed by one of the foremost radio engineers in the country. Clear and realistic reception guaranteed. Solid bakelite panel and sub-panel. Panel beautifully engraved. Sub-base marked for all connections. Dial control; Kurz-Kasch bakelite indicator knobs. New type UX sockets. Low ratio transformers for improved tone quality. All hook-up wire and colored battery cable included. Tubes are 201-A type, tested and matched. Value \$80, our price \$16.95.

MAKE MONEY IN YOUR SPARE TIME! Complete Set of Simple Plans and Directions to Build

Very easy to build this set with the plans and instruction we furnish. No complicated drawings. Can be built in 2 hours. Instructions for operation included. Make money by building these sets in your spare time and selling them to your friends.

SEND NO MONEY

Just write your name and address on a post card and ask us to send you this great kit together with the Erla Cone loud speaker and 5 tubes. We will ship them right away. When they arrive, pay only \$16.95, plus a small delivery charge. **RADIO EQUIPMENT CO., Dept. P, 549 S. Wells St., Chicago, Ill.**

FROST-RADIO

SMOOTH WORKING AND FINE LOOKING

Frost-Radio Metal Frame and Bakelite Rheostats are the smoothest working rheostats made. Perfect contact with absolutely no wear on windings. You'll like them. Bakelite pointer knob; genuine Nichrome wire cannot burn out; supplied in resistances from 25 to 75 ohms. Metal Frame, list, 50c. Bakelite, list, 75c. Secure them from your dealer.

HERBERT H. FROST, Inc.
Main Offices and Factory, **ELKHART, IND.**
Chicago Philadelphia St. Paul
New York Pittsburgh New Orleans
Boston Washington, D. C. Los Angeles
Buenos Aires, Argentina

Mail Coupon For Our Literature

HERBERT H. FROST, Inc., Elkhart, Ind.
Send me literature about your rheostats as advertised in Popular Mechanics.

Name _____
Address _____
City _____ State _____

Long-Eakins Co., 628 High St., Springfield, Ohio

Mail me at once your free catalog and full particulars about how to make big profits in the Crispette business.

Name _____
Address _____

Profit \$1,000 Month Easily Possible!

the heart of the Socket Power Unit

is the variable resistor. Which accounts for the fact that CLAROSTAT, the greatest variable resistor, is the choice of radio engineers, manufacturers and fans. Its current carrying capacity of 20 watts and its ability to cover the entire resistance range, assures quiet, uniform power and long life to your radio set or eliminator.

CAUTION! CLAROSTAT is being imitated. Don't be misled. Insist on seeing the name which is stamped on every genuine CLAROSTAT.

AMERICAN MECHANICAL LABS.
285 North 6th Street
Brooklyn, N. Y.

CLAROSTAT

OPE-N-SEAL
Fruit Jar Tool Kit

Opens and Seals Jars in a Jiffy

SAVES FRUIT from spoiling! Saves hands from injury! Use when canning and every jar will be sealed **SECURELY**. Use in opening each jar and eliminate danger of cutting hands or breaking jar. Simple as A-B-C. Jar Lifter prevents burning hands in hot water. Six piece set. Fits pint, quart and half gallon standard jars. Needed year 'round. Sold direct by Tyler representatives or by mail, \$1.00.

AGENTS Make \$8 to \$20 a day selling this outfit. Spare or full time. Write today: **THE TYLER MFG. CO. Dept. M-8 Muncie, Indiana**

PROTECT YOURSELF

From Burglars and sneak-thieves. Kee-lock is guaranteed to make any mortise lock **PICKPROOF**. Needed on every door equipped with mortise locks, stores, tool houses, sheds, clothes closets, furnished rooms, etc. Jimmy proof. As simple to apply as inserting key. Send 25 cents in coin today. Agents write for special money making proposition. Sells at sight.

KEELOCK MFG. CO. Dept. P. M., 415 W. 50th St. NEW YORK, N. Y.

When You Want a BLTORCH

That gives 400° more heat—
That's 100% safe—send for

TURNER MASTER No. 45
Only \$7.75, postpaid

TURNER BRASS WORKS, Industry Ave., Sycamore, Ill.

Make Things at Home with a Speedway Shop

Eight motor-driven tools, complete lathe, bench saw, big saw, portable electric handsaw, stationary power drill, buffer, grinder, scratch brush. Works from any lap socket. \$10.00 down, 10 days' free trial; free working blueprints furnished. Write for full information.

ELECTRO MAGNETIC TOOL CO.
Dept. 212, 1830 S. 52nd Avenue CINCINNATI, ILL. (Adjoining Chicago)

New Improved SPORS Fountain Pen. 60 Day Trial. Money back if not pleased

Agents' Sample **65c** Sells for \$1.25. Writes like a \$7 Pen
Make \$10 Daily Easily

LADIES' OR MEN'S STYLE
Comes in Red or Green
GUARANTEED 2 YEARS
Improved Point

MAKES \$8.40 IN TEN MINUTES

I sold my dozen pens in about 10 minutes. Will order another dozen soon. **TRACY KRENZ, Nebraska.**
Write for **FREE Wholesale Specialty Catalog.**
427 MAIN ST. LESUEUR CENTER, MINN.

F. SPORS CO.

Go-where the Fish are Striking

HOOKED! You bet he's hooked! Game little scrapper. He's given you a battle. Your heart pounds—your blood tingles—as you play him toward the net. Man! there's a real thrill.

Bass waters soon will open. Get more and better fishing this year with a Johnson portable boat motor. Attaches to any rowboat. Anyone can operate. Four new 1927 Johnson Motors offer speeds of 8, 13, 22 and 27 m. h. p.

Ask any Johnson dealer to let you try a Light Single or Light Twin. Ideal for fishermen and auto-tourists. Sold on payments by sport goods, hardware and marine supply dealers. Write for our 1927 catalog describing the new Johnsons.

JOHNSON MOTOR COMPANY

2436 Sample St., South Bend, Indiana

Export Division: 75 West Street
New York, U. S. A.

Canadian Distributor: Peterborough Canoe Co.
Peterborough, Ont., Canada

World's Largest Manufacturer of
Outboard Boat Motors.



Johnson

Outboard Motors

Catch Fish!

Eels, Mink, Muskrats with our new folding galvanized

STEEL WIRE TRAP. Write for our **FREE TRAP OFFER** and Bargain Catalog. \$1 Box of our famous Fish Bait **FREE** to introduce our traps.

WALTON SUPPLY CO., 3500 JUNIATA AVE., ST. LOUIS, MO.



REMINGTON

PORTABLE TYPEWRITER
Dealers and Branches Everywhere



"Independent" GOLD POINT
Lever, Self-Filler Stylopen
"Makes Writing a Pleasure"
Jumbo, \$3.50; Red, \$3.00; Black

\$2

I. C. ULLRICH & CO., 161 Washington St., N. Y. Est. 1894 Agents Wanted

30 Days' Free Trial

on all **MEAD Bicycles**

Select from 44 Styles, colors and sizes. You can easily save \$10 to \$25 on your bicycle. Prices \$21.50 and up.

Factory to Rider Do business direct with the makers. Wash upon approval.

Get a month's free trial. Rider Agents make big money. best quality, at factory prices. Lamps, wheels and equipment, low prices. **Send No Money.**

Mead CYCLE COMPANY
DEPT. H-110 CHICAGO



Write today for free Catalog, factory prices and marvelous new offer.



Will you wear these Shoes and Show them to your Friends?

Men! Women! Here's your chance to get your own shoes without cost, and to make the easiest money of your life. Take orders for genuine Tailor-Made Shoes from your friends and neighbors. Shoes Tailor-made to fit six actual foot measures. Choice of 70 different leathers—made in 70 styles in men's, women's and children's shoes. Unlimited market. Amazing value because sold direct from makers. Every pair guaranteed to fit perfectly and give comfort and satisfaction.

GET FREE OUTFIT No capital—no investment necessary. Big commissions for you in advance. I do the collecting and delivering. Send for FREE outfit immediately and get genuine Tailor-Made Sample shoes to wear without one penny of cost.
TAILOR-MADE SHOE SYSTEM, Dept. 291, 932 Wrightwood Ave., Chicago, Ill.
Act at once. Mail Name and Address—Today.



MODEL SHIP BUILDERS

Give your boat a true model appearance. Rig her up with true scale parts and have your efforts appreciated. Enclose stamp for booklet, containing parts, plans, etc.

Model Ship Supplies, Box 613, Dept. M, Minneapolis, N. Y.

MAKING IT EASY TO BUILD THINGS

You can perform every woodworking operation with greater speed, accuracy and economy on

Boice-Crane Bench Machines

Do ripping, mitering, grooving, rabbeting, sanding, grinding and band saw operations better, quicker and easier. Driven by $\frac{1}{4}$ to $\frac{1}{2}$ h. p. motor attached to light socket. Sold with or without motor. Send 10c today for 64-page booklet on Bench Saws, Drills, Jointers, Lathes, Band Saws, etc., also contains list of books which have over 250 working plans of furniture. **Send NOW!**

W. B. & J. E. BOICE, DEPT. P. M. 6-C, TOLEDO, OHIO



NEW, Simple, Automatic

easy
\$ **100**
cash
per week

FIRE PROTECTION
at a price that brings
VOLUME SALES

Nothing else can give you Fugo's BIG money-making advantages. Representatives "cleaning up" fast — \$15 and \$20 cash-in-pocket from just one day's work not unusual. Most sales made without demonstration. Fugo is the only **Instantaneous AUTOMATIC** home and life protection—using same chemical all Fire Departments use. America's biggest Fire Chiefs recommend it. It's your opportunity to make good in a BIG WAY.

65%—90% Cash Profit

No investment. No red tape. Full commission same day you take order. Biggest field. **Every** home, factory, church, store, theatre, truck, automobile, etc. wants FUGO! For FUGO outperforms, therefore outsells competition. Easy to make \$100 a week—many doing better. No experience needed—simply ambition and ability to follow instructions. Waiting profits all around you.—Act Quick! Write AT ONCE for full details.

THE NATIONAL FORMETAL CO.
6535 Metta Ave., N. E. — Cleveland, Ohio

2 sales instead of 1 at these low prices
1 qt. size \$5
2 qt. size \$7.50

Distributors! Write at once for State rights.

WE MATCH PANTS

To Any Suit!

Double the life of your coat and vest with perfectly matched pants. **100,000 patterns.** Every pair hand tailored to your measure; no "readymades." Our match sent **FREE** for your O. K. before pants are made. Fit guaranteed. Send piece of cloth or vest today.

©-27 **SUPERIOR MATCH PANTS COMPANY**
215 So. Dearborn Street, Dept. 62 Chicago

30 DAYS FREE TRIAL

\$5.00 Down
5 Years to Pay

\$275.00

Our Factory to Home selling plan actually saves you from \$150.00 to \$200.00. We pay the freight and deliver to your home anywhere in the United States any piano or player piano that you may select from our catalog.

Every instrument is guaranteed for 25 yrs. Fill out the coupon below. It will bring you full details of our liberal selling plan.

Est. 1859 Capital and Surplus \$2,000,000

Schmoller & Mueller Piano Company
Dept. 379 Omaha, Nebr.

Please send me your plan and catalog.

Name.....
Address.....

Send for this Book that spells P-R-O-F-I-T-S for You!

This book is "The Nestler Plan," a startling revelation of the profit-possibilities in a new tire-servicing business of your own. Any ambitious man with a modest capital can quickly build up a successful full-time or spare-time business with Nestler methods and equipment; no tire or garage experience required. Nestler operators make money because they furnish an exclusive service that every car-owner needs.

To Car-Owners Everywhere

Save money! Your old, worn tires are good for thousands of extra miles if you take them to a Nestler man and have them serviced by the exclusive Nestler Rubber-Fusing Process. Write for address of your nearest Nestler Station.

Write Today
for interesting book "The Nestler Plan"—it's FREE!

Dept. 36

NESTLER RUBBER FUSING CO., Inc.
245 W. 55th St., N.Y.



HOLLAND PRINTS

Wonderful new way of binding kodak pictures. Keep a photographic record. Sample Holland print from your negative for 10c.

FRANK SCOBIE, 43-B, SLEEPY EYE, MINN.



FOY'S BIG BOOK, in Colors

A complete guide to successful Poultry and Squab Raising. Low prices on CHICKS, Breeding Stock and PIGEONS.

Write Today! FREE!
FRANK FOY, Box 18, Clinton, Iowa



12,000,000 FORD OWNERS
Need This
NEW Timer!

Earn \$100. Weekly
Selling Them!

Automotive engineers claim that the average Ford may wear out from 8 to 10 ordinary Timers. Think of the sales possibilities when you offer the "Dynamo Timer" with a guarantee for the life of the car. You do not have to be a salesman. This amazing Timer sells itself on sight. You make \$80 per cent profit on every sale.



Makes Old Fords Run Like New

Once a Ford is equipped with the "Dynamo" the timer can be forgotten—the only thing that will prevent forgetting it will be the noticeable improvement in the running of the car. More power, more mileage, instant starting, amazing pickup, are a few of the features that will make any Ford owner a "Dynamo" booster after he once uses this new Timer.

Get Territory Quick


Our agents can easily make \$3,000, \$5,000, yes, even \$10,000 a year. Sparetime workers make \$50.00 and even \$300.00 a day.

John Cable made \$200 in less than 10 days. Many others report tremendous profits. You too can get into the big money class the same as John Cable and others.

DYNAMO TIMER CO.
426-1125 Eleventh St., Milwaukee, Wis.

FREE SAMPLE

To aid our agents we have arranged a plan that provides them with a Free Sample so they can equip their own car or carry it for demonstration purposes. The unique principles of this wonderful Timer will make themselves apparent to any Ford owner after a minute's examination. Send name and address for Free Sample Offer and particulars of our big money making proposition.



No. 22—9 in. swing
IMPROVED MODEL
SOUTH BEND JUNIOR
Back Geared Screw Cutting
Precision BENCH LATHE
 Complete with Countershaft and Equipment..... **\$160**
 and up

A Precision Lathe for Small Work

An improved model precision screw cutting lathe used by repairmen, mechanics and small parts manufacturers. Will cut screw threads 4 to 40 per inch, bore, drill, ream, turn, chuck, turn tapers, etc. Hollow spindle for Draw-in Collet Chuck work.

Can Be Fitted With Many Attachments

Milling and Keyway Cutting Attachment, Taper Attachment, Electric Grinder, Draw-in Collet Chuck, Electric Mica Undercutter, Turrets, Lathe and Drill Chucks, Tools, Etc.

Motor Drive from Ordinary Lamp Socket


Illustrated on the right is the Improved Model Self Contained Chain Drive Unit Motor Driven No. 22 Jr. Lathe complete with $\frac{1}{4}$ -H. P. Reversing motor and Reversing Switch. Driven from an ordinary lamp socket.

BOOKLET No. 22—Illustrates, describes and prices the Improved Model No. 22 Jr. Lathe. Write for it today.

South Bend Lathe Works

622 East Madison Street
 South Bend, Indiana

New York City Sales-
 room 183 Centre Street
 N. Y. Tel. Canal 9085



No. 22 Improved Model 9 in. x 3 ft. Lathe complete with Self Contained Unit Motor Drive with $\frac{1}{4}$ -H. P. Single Phase Reversing Motor, Reversing Switch and Equipment - **\$261**

Features

Of the No. 22 Jr. Lathe

Back Geared Head Stock
 Six Spindle Speeds
 Phosphor Bronze Bearings
 Power Feed to Carriage
 Set-over Tail Stock for Taper Turning
 Graduated Compound Rest
 Micrometer Graduated Collar on Cross Feed and Compound Rest Screws
 Built in 2½, 3, 3½, 4 and 4½ ft. bed lengths. Floor Legs if desired.

Time Payments if Desired.

Improved Model SOUTH BEND LATHE

The entire line of 96 types and sizes of South Bend Lathes has been completely redesigned in the last two years. The new lathes are heavier, stronger, and have greater belt power.

In 20 years, we have shipped 36,000 Lathes to 64 countries of the world. The most popular sizes listed below:

Size of Lathe	Quick Change	Standard Change
9 in. x 3 ft.	\$258	\$228
11 in. x 4 ft.	308	268
13 in. x 5 ft.	387	337
16 in. x 8 ft.	553	493
18 in. x 10 ft.	746	681

Specifications

Of the No. 22 Jr. Lathe

Swing over Bed.....9½ in.
 Length of Bed.....3 ft.
 Distance between Centers.....18 in.
 Size of Centers.....No. 2 Morse Taper
 Hole Thru Spindle.....½ in.
 Size of Spindle Nose, 1½ in. diameter
 8 Threads
 Precision Lead Screw ½ in. diameter
 8 Threads per in.
 Thread Cutting Range..4 to 40 per in.
 Weight, Lathe and C'shaft....375 lbs.

Time Payments if Desired.

DEVITT 8" COMBINATION SAW

13 TOOLS IN ONE

Saw table raised, showing Emery wheel, saw guard and drill attachment.



Planer attachment on saw table.

Showing Sanding disc attached.




Table tilted for beveling.

Dado head attached for grooving.



\$35
F. O. B. Phila.

YOU save a great deal of money, time and space by buying a Devitt 8" Combination Saw. Why buy special tools for beveling, grooving, buffing, etc.? The Devitt Combination Saw will rip, cross cut, bevel, miter, groove, mortise, tenon, drill, rabbet, grind, buff and polish. The attachments are easily and quickly adjusted. The saw and motor when set up ready for work occupy very little room. The $\frac{1}{4}$ H. P. 60 cycle 110 volt A. C. motor can be run from a light socket and provide power for other purposes when the saw is not in use. A cut up to $2\frac{1}{4}$ " can be made with the 8" Combination Saw without planing. The ideal machine for shop, factory or home, complete with attachments: 12"x16" table, 8" Combination Saw, iron pulley for saw table, 10" ripping fence, adjustable cut off miter gauge, motor-specifications as above, $1\frac{1}{4}$ " endless leather belt, wood pulley, 8 ft. cord and plug, 6" buffing wheel, $\frac{3}{4}$ " 3 jaw drill chuck, 5" emery wheel, 6" sander, saw guard, and 2" dado insert. \$35.00 F. O. B. Phila. Height $7\frac{1}{2}$ ", shipping weight, 100 lbs. (Planer attachment to fit on table top will smooth pieces up to 2 in. wide, \$12.00 extra F. O. B. Phila.)

Write for our beautifully illustrated 4 page circular.

PAUL J. DEVITT 1102 South 2nd Street
PHILADELPHIA, PA.




Men Women Wanted
Stunning RAINCOATS
AGENTS Special Price
Money Back **ONLY \$3.95**
GUARANTEE
AMAZING VALUE
A week paid to
\$75 Agents daily. We deliver

This Wonderful opportunity is offered to the first person in each locality to introduce our exceptional line of stylish, fine tailored, good quality Super-Built Raincoats-A Real Value. **Get Your Coat FREE**
WRITE FOR FREE OFFER
SUPER-BUILT GARMENT CO.
Box 453, Dept 12, Chicago, Ill.

Start to Play
Very First Day

Be the life of the party. Xylorimbists make \$5 to \$25 a night. No knowledge of music required. Wonderful for home, Free, easy lessons; five days' trial; a year to pay. Write for big FREE Book.

J. C. DEAGAN, Inc.
4-145 Deagan Building
CHICAGO



I Offer You
\$8.00 a Day
~and a

Write quick for new proposition. We offer \$8.00 a day and a new Chevrolet Coach, for demonstrating and taking orders for Comer All-Weather Topcoats and Raincoats. Spare time. No experience required. Sample Outfit Free. Write now.
COMER MFG. CO., Dept. W-5123, Dayton, Ohio



Stops Foot Pains In Five Minutes

An amazing new home method for permanently ending foot troubles with their aches and pains has recently been invented by Dr. F. H. Griffith, a successful foot and leg specialist. His method differs from others in that there are no arch supports, bandages, bands, cushions or other make-shift devices to be worn in the shoe or on the foot—no tiresome exercises, no discomfort or troubles. Yet foot and leg pains

are stopped almost instantly, weak or fallen arches raised and strengthened, the circulation invigorated, weak feet made strong, sturdy and self supporting and foot troubles permanently ended. If your feet are weak or flat, if they ache and pain, burn and itch, are tired, tender, puffed and swollen, write Dr. F. H. Griffith, 3157 Davidson Bldg., Kansas City, Mo., for his free book "Foot Health," which fully explains his method. As it points the way to foot health and comfort, and is sent without cost or obligation, every foot sufferer should have it.

THE MELODY SHIP



Mayflower, 1620
The Pilgrim's Vessel

\$12.50

Size:
Height 25"
Width 9"
Length 27"



Santa Maria, 1492
The Flagship of Columbus

Size:
Height 25"
Width 11"
Length 27"

Build a Ship Model Loudspeaker

Perfect Tone Plenty of Volume No Distortion

Do you want a loudspeaker that is different?

Do you want a beautiful Ship Model?

Do you want perfect tone?

Of course you do! All of these are to be found in the MELODY SHIP, and it will not cost you as much for both combined in one as the ordinary Ship Model or the ordinary loudspeaker alone would cost. The SHIP MODEL when complete is the most beautiful of its kind on the market today. The loudspeaker combination is unsurpassed for beauty of tone and undistorted volume that brings out all the low musical notes, faithfully reproducing the zoom of the bass viol, drums and tuba, as well as the soprano tones of violin and flute. There is nothing like it on the market anywhere today. It is absolutely new. This is not an experiment but a real proven device, sold on money-back guarantee to assure satisfaction.

THE WORLD'S LARGEST BUILDERS OF SHIP MODELS will supply you with all the parts to build a MELODY SHIP. You may choose either the Santa Maria or Mayflower Model. The parts for the Ship Models are made of wood. This is not a cheap cardboard imitation, but a real Ship Model. Putting it together is as simple as A B C. The instructions read like this: "Put No. 49 on top of No. 48, and tap lightly with a small hammer," etc. A school boy can put one together in a few hours.

The Loudspeaker Unit is of the Electro-Magnet type. Power amplification is not needed to force the low tones through. They come through with perfect ease and do not interfere with the higher notes, giving you faithful reproduction at all frequencies. The Unit is placed on the main mast, which is firmly seated two inches deep in the three-and-one-half-pound hull, making it impossible for counter-vibration to affect the perfect reproduction of the MELODY SAIL. The driving pin is attached to our specially prepared, super-vibrating MELODY SAIL. It does not change the appearance of the Ship Model. Instructions for installing come with each MELODY SHIP.

MINIATURE SHIP MODELS

3818-20-22-24 Baring St.

Philadelphia, Pennsylvania

If you own a Ship Model and wish to install the MELODY SAIL and Unit, forward us an outline drawing of your main-sail. We will then send you a MELODY SAIL and Unit to fit your Model, via Parcel Post, C.O.D., \$9.00 plus postage.

The unassembled parts for either the Santa Maria or Mayflower Model, without the Melody Sail attachment, can be had for \$4.98 plus postage. Full detailed diagram and instruction sheet showing and explaining every operation for completing the Model supplied with each.

If you want the unassembled parts for either the Santa Maria or Mayflower Ship Model, together with the MELODY SAIL attachment for making a MELODY SHIP complete, send us your order—NO MONEY—and pay postman \$12.50 plus postage.

CANADIAN AND FOREIGN ORDERS MUST BE ACCOMPANIED BY MONEY ORDER.

GUARANTEE: If, after assembling the MELODY SHIP, you do not think it worth many times the purchase price, return it to us in good condition and we will gladly refund your money. What can be fairer than this?

WRITE FOR CATALOG.

MINIATURE SHIP MODELS
3818-20-22-24 Baring Street
Philadelphia, Pennsylvania.

Dept. 112

Please send me the complete parts, cut to fit and ready to put together, as follows, for which I agree to pay postman the indicated price plus postage:

MELODY SHIPModel, \$12.50
SHIP MODEL only.....Model, 4.98
MELODY SAIL for.....Model, 9.00
(Be sure to indicate whether you want Santa Maria or Mayflower model!)


PLEASE PRINT NAME AND ADDRESS PLAINLY TO AVOID DELAY

Name

Street or R. F. D.....

City or Town.....

State



---to Less Than a Hair's Breadth


The measured thickness of a hair is about two thousandths of an inch—twice the tolerance allowed in grinding pistons for many fine automobiles.

Split hair accuracy is required in making the modern motor car. On the careful fitting of many

parts depends the proper performance of the complete machine.

Every working day, in the hands of practical mechanics all over the world, Brown & Sharpe Tools are used in doing accurate work—work where a variation of one thousandth of an inch or less is all that is allowed.

B.S.



These accurate tools are described in our Catalog No. 30 which will be sent to you on request.

DEPT. P.M.
BROWN & SHARPE MFG. CO.
Providence, R. I., U. S. A.

BROWN & SHARPE TOOLS

"World's Standard of Accuracy"


Wobbly Chairs?

LINX Fixes 'Em
for GOOD—

Not a wire makeshift but a sturdy brace of coppered chain that pulls the chair together with a 1000 lb. pull!

Used by big Hotels. Try for 10 days FREE. Eighty cents if you like LINX.

H. S. Reid Corporation
16 Exchange Place New York City



CAL. 30-40



KRAG CARBINE STYLE

The Choice of those who know. 5 shot, 22 inch Barrel. A few used, but service-able, for \$9.75. Shipping weight, 13 lbs. Shipping extra. \$15

Krag Rifle.....	\$12.50	Krag Sporting Rifle.....	\$14.00
Springfield 45 Shot Guns ...	4.75	Springfield 45 Carbine.....	4.50


Krag Bayonets 40 cents each. Postage Extra—Shipping Weight 2 1/2 lbs.
Terms Strictly Cash. No C. O. D. Shipments.
Catalogue Free on Request.

W. STOKES KIRK, 1627-P. M., North 10th St., Phila., Pa.

AGENTS

AMAZING NEW ADDING PENCIL

ADDS
MULTIPLIES
SUBTRACTS
DIVIDES



AGENTS Great money maker. Everybody interested. Reserve territory immediately.
HOUK ADDING PENCIL CO., Dept. 38 St. Louis, Mo.
\$16.00-\$24.00-\$32.00-\$40.00-\$48.00-\$56.00-\$64.00-\$72.00-\$80.00-\$88.00-\$96.00-\$104.00-\$112.00-\$120.00-\$128.00-\$136.00-\$144.00-\$152.00-\$160.00-\$168.00-\$176.00-\$184.00-\$192.00-\$200.00

WRITE!

THIS COUPON ^{is} VALUABLE

NOW IS THE TIME TO GET YOUR TYPEWRITER!

Be up-to-date—know the pleasure and convenience of having one in your home. You'll be amazed at the uses everyone in your household will find for this real Underwood typewriter. Every member of the family will use and enjoy it! Don't send a cent—but do get our big special offer—our valuable book on typewriters and typewriting—FREE.

Any One Can Learn to Operate a Typewriter!

You can learn to write on this standard-keyboard machine in one day; it's so simple that even a child can use it. A week after the expressman has brought it, you'd feel LOST without it. A trial will PROVE it—and doesn't cost you a penny!

SPECIAL FREE TRIAL OFFER

We don't want a penny now. Nor any money at all unless this proves the typewriter bargain of your life. The trial is FREE. If you buy, our easy terms make it a pleasure to pay. There's no excuse now, for not owning a typewriter—and the finest make! We include all tools, a cover, etc., all complete, all ready to write. Write us now. Deal direct; we are the largest factory of the kind.

Our plan gives you the opportunity of a thorough trial before you buy. You run no risk whatever. You start to pay for your typewriter AFTER you have found it the only machine for you! But get the facts before this lot of machines is all in use. Clip the information coupon before you turn the page. It will pay you! Note the very useful book you will receive free! Write for full particulars at once.

The Greatest Typewriter Offer Ever Made

If you know typewriters, you know the perfect work and the ease and speed of a Shipman Ward rebuilt Underwood typewriter. New machines are guaranteed for only one year; WE GUARANTEE EVERY ONE OF OUR MACHINES FOR FIVE YEARS! If you have never owned a typewriter, start with the finest! You can try this one at our risk. But, the time to act is NOW. Don't miss out on this present bargain offer whereby you can get this genuine Underwood at a big savings. Don't do longer without the convenience of a typewriter.

FREE! Get our catalog free; lowest prices and terms. A manual free, too; valuable instruction for learning rapid typing, useful pointers for all who use a typewriter, business forms, social correspondence, work for others, etc. Clip coupon **NOW!**

Mail Today!

Shipman Ward Manufacturing Co.,
A-212 Shipman Building, Chicago, Ill.

Please send me your Free Trial Plan and Typewriter Book, together with your special offer on prices, terms, free course in Touch Typewriting and also how I can make money with this typewriter, without obligation. This is not an order.

Name.....

Street or R F D.....

City.....


State.....

\$3⁰⁰
DOWN
and
its
yours

5
Year
Guar-
antee



THOUSANDS HAVE FOUND A WAY TO OWN TYPEWRITERS—and make Sparetime Cash too



LIGHTING MATCHES WILL MAKE YOU



Amazing Sure- Fire Demonstration

sells by thousands new automatic attachment that sworn public tests prove makes Fords run

43.8 Miles on 1 Gallon of Gas

Agents everywhere report astounding results. R. K. Waite ordered 1000 Blancke devices in one month. (Profit \$3000.00). Wires, "Get ready another 2000." Clyde B. Jones sold 63 devices in one day. (Profit \$189.00). You don't need experience.

What Is This Sensational Demonstration?

The instant heat touches the Blancke Thermostatic Carburetor Control, the needle valve on the carburetor slowly turns before the fascinated eyes of spectators. As it cools the needle valve turns back again. It is easy to understand why immensely superior results can be obtained with this accurately adjusted automatic instrument—to see why Blancke Thermostatic Carburetor Control in official public and private tests showed 43.8 per gallon of gas. 250,000 tests averaged 32 miles per gallon. *Guaranteed to give over 30 miles per gallon on Fords.*

Starts Coldest Motor Instantly

even on wintriest days without use of choke. Guaranteed results combined with amazing demonstration make Blancke Control greatest agent's selling success of recent years.

Get One Free to Introduce

Also Blancke Plan that starts you without capital in a real business that pays you \$300.00 to \$2500.00 and up each month. Exclusive Territory. Sales guaranteed. Start to make big money—beginning NOW! Send coupon today for sample Blancke Control and great Distributor's Plan.

BLANCHE AUTO DEVICES CO.

157 E. Erie St. Dept. 805-H Chicago, Ill.

Mail This Important Coupon Today!

Blancke Auto Devices Co.,
Dept. 805-H, 157 E. Erie St.,
Chicago, Ill.

Gentlemen: I should like to get a Blancke Control Free to introduce in my community. Also send details of amazing new Guarantee Plan by which I can make from \$300.00 to \$2,500.00 a month profit.

Name

Address

City State

Strongest Guarantee In Automotive History

backs sale of Blancke Controls. Guaranteed to give over 30 miles per gallon on Fords—to practically eliminate carbon formation and its troublesome consequences—to save half oil—to relieve battery strain—make motor run smoother—give better acceleration—allow lower speeds in high gear. Starts motor immediately in any weather without use of choke and saves half repair bills. Ford owners everywhere are delighted with it and their boosting promotes sales.

SALES Guaranteed

**\$15.00
a Day
Guaranteed
to Distributors**

Cadillac and Delco Light now use as standard equipment Thermostatic Carburetor Control under Blancke License. You can get no better proof of merit than this!

"Why-It's a Whole Machine Shop!"



This Amazing 17-Ounce Tool Conquers 60-Lb. Kit!

The most revolutionary hand tool ever invented. Does the work of other tools costing over \$50—truly a tool of 1000 uses. Just the "hand-grip" of a tiny rubber band holds a hard bearing ball—the hardest-to-hold thing known—against a 300 Pound Pull!

Grips with 1 Ton Direct—128 Tons Per Sq. In. Pressures through its 10-to-1 Leverage Power-Gear Transmission. In addition, the Grip LOCKS!

Among Thousands of Large Users are the MAKERS of Buick, Chevrolet, Nash, Packard, Reo, Studebaker, etc. Automobiles, Fisher Bodies, etc.; who with their employees have bought Kits in quantities of 500 to 1000! Studebaker has approved it for use in its Service Stations throughout the World. Thousands of housewives are using it too, because it does so many useful and amazing things so easily, so instantly. And even a woman's hand applies a HALF-TON Giant's Grip! Every Auto and Home Owner—every man who ever uses any tools needs it every day.

World Flight Equipment

It was standard equipment for the U. S. WORLD FLIGHT and the U. S. S. Shenandoah. Creates a sensation everywhere. Just its astounding 1-Ton Grip makes it worth ten times its cost.

The amazing EIFEL-FASH Pile-Rench is a true Ratchet WRENCH—Parallel Pliers—Speed VISE, and more. Instantly and automatically it LOCKS its death-grip Jaws on the most worn and chewed nuts in the tightest places—and T U R N S THEM!

AGENTS \$200 a Week

Pile-Rench representatives earn amazing incomes demonstrating this wonderful new tool. One man alone sold nearly 10,000 in just one state. Fastest seller known. Factories buy by hundreds. Every auto and home owner buys. We have wonderful special proposition to agents. Mail coupon for full details. Why not earn \$75 to \$200 and more a week, spare or full time?

Whole Kit in 1 Tool

You get in a Royal Blue Leatherette HOLSTER, the 8 1/2" Universal Pile-Rench with 2 EXTRA Jaws—a PIPE Jaw—and a WIRE Jaw—each giving undreamed of performance. Instantly (in 1/5 second) you insert the Jaw you need, and as quickly snap a One-Ton Grip on work of any possible kind, or shape, or size from 0-in. to 1 1/2-in. And—nothing Ever can get away from that grip! HAVE YOU EVER HEARD OF A TOOL THAT WORKS LIKE THIS—it actually out-grips a 40-lb. Vise, and applies a 1-TON grip at the very jaw-tips. Will remove broken studs, taps, drills, etc., with next-to-nothing to hold on. Yet its smooth grip will hold a hair and coil a spring of hair-fine piano wire!



The Universal Pile-Rench

For every kind of Pliers, Nut Wrench, Vice, Clamp, and Spring-making Work—Everywhere.



The Pipe Pile-Rench

For every kind of Pipe Wrench and Pliers Work; Chewed Nuts that no other tools can budge, etc.



The Wire Pile-Rench

For every kind of Wire, Tire Chain, Cable and Spring Work; and the Special work other Tools won't do.

Guaranteed

The Pile-Rench KIT is positively guaranteed.

It has stood the most trying tests of time and service. Of thousands—the First Commander of the U. S. World Flight said—"It should form part of the equipment of each and every Airplane and Automobile." One Engineer said—"I have used my Pile-Rench for 5 years and wouldn't be without it for \$100—and I mean it!"


Special Introductory

PRICE \$3.65 ONLY

Regular Price \$5.00

Thousands fortunate enough to be able to see the astonishing performance of this marvelous Pile-Rench KIT are glad to pay the regular price of \$5.00. You can TRY this amazing performance on your own work in your own way for 2 weeks, and if the Pile-Rench KIT has not EARNED FOR YOU in that time the value of its price—just return it, and your money will be refunded as fast as the mails can carry it. Also, with your Pile-Rench KIT you receive a valuable Manual of Mechanics that every man should have. It tells in 64 pages and 145 illustrations some of the marvels of "The Pile-Rench Way"—the quicker, better, and easier way to do every kind of mechanical work.

Make use of the Coupon below, get this incomparably better tool KIT for the price of just one ordinary tool—let the marvelous Pile-Rench with its versatile 3 Jaws SPEAK FOR ITSELF as no Steel Jaws ever spoke before!




MAIL TODAY!

THE FLASH SALES CORP'N

FP-4809 N. Ashland Ave., CHICAGO, ILLINOIS

The Flash Sales Corp'n, FP-4809 N. Ashland Ave., Chicago, Ill.
☐ 1. Rush your amazing new Eifel-Fash Pile-Rench KIT. I will pay \$2.00 a week and get my Money Back if it is undelivered. I may return Kit within 2 weeks and get my Money Back if it is undelivered.
☐ 2. Send me your literature.
☐ 3. Am interested in Salesman's Big Proposition.
 Name _____ R. F. D. _____
 State _____ City _____

Snap a switch



The 6-tube Console pictured above stands 40 inches high—contains skillfully engineered shielded circuit—single drum dial control. Musicones built in. Price, without tubes and power unit, \$95.

- No more batteries
- No battery charger to watch
- No batteries to water
- No failure of the power plant just as you sit down to a fine program
- No upsetting the house to have the radio serviced
- No apologies to make to callers that the batteries have just run down
- No batteries to recharge
- No batteries to renew

A B and C Power from the light socket for the latest model Crosley A C Radios

This power unit weighs 13 lbs., stands 9 inches high and is 4 inches wide and requires no more attention than a vacuum cleaner or an electric iron. It transforms mechanically ordinary 110-volt 60-cycle house current into smooth, quiet radio energy. No interfering hum!

Price \$50

Crosley radios especially designed to use this battery eliminator are the 6-tube AC-7, a neat table model of the famous Crosley single drum control receiver selling at \$70, and the 5-tube console model AC-7-C pictured above at \$95.

Prices slightly higher west of the Rocky Mountains.

Crosley Musicones \$9.75 and \$14.75

Write Dept. 15 for descriptive literature

THE CROSLEY RADIO CORPORATION
Powel Crosley, Jr., President CINCINNATI, OHIO

Crosley sets are licensed under Armstrong U. S. Patent, No. 1,113,149, or under patent applications of Radio Frequency Laboratories, Inc., and other patents issued and pending.



TO SET

CROSLEY


BETTER — COSTS LESS

RADIO



Radio Listeners!

Get Distance Loud and Clear ALL SUMMER



Works Like a Sieve

The static is filtered out and held back by the lead outer jacket. Only the music gets thru to the copper core which connects to your set.

SUBANTENNA

Filters Out So Much STATIC and Noise You Never Know they Exist

Imagine listening to beautiful music, thinking it is from a local station, then hearing the announcer clearly speak the call letters of a station a thousand miles away. Imagine the pleasure of getting real DX crystal clear on bad nights when STATIC is raging all around you. Imagine being able to bring in distant stations with tremendous volume on the same set which with an ordinary aerial gets only "air noises" and static crashes! Because the filtering action of SUBANTENNA delivers such a clean, clear signal to your set, you can turn the power full on when listening to DX. This means you can get bigger volume and more distance with your present set if you use a SUBANTENNA.

Read PROOF of the Amazing Performance of this Great, New Radio Improvement

"Subantenna you shipped me now working and results are good. Had WJZ, WLS, KDKA, WTAX, WSM and others during thunderstorm." Signed L. T. DONALDSON, M. D., Louisiana

"I have a six-tube set and after installing Subantenna I received greater distance than ever before. On January 18th, I received a program on my set broadcasted from Buenos Aires, South America, at 10:15 in the evening. I never could receive such distance on my outside antenna." Signed, W. C. FREYMUTH, River Forest, Ill.

"I am able to report that static which was a source of much annoyance before, has been entirely eliminated so far as I am able to observe. For clarity and for its contribution to selectivity I think the Subantenna is the best device I have ever had any experience with." Signed, REED L. PARKER, Chicago.

"I am glad to report to you the wonderful reception that I am receiving without interference or static of any kind. It is, indeed, a wonderful thing for radio and my opinion is that it will revolutionize the industry." Signed, CARL DESSAUER, Kansas.



Trial Offer!

Make this Convincing Test

Install SUBANTENNA. Leave your old aerial up. Select a bad night when DX is almost impossible with the ordinary aerial. Make a comparison station for station, connecting first your aerial, then SUBANTENNA. From stations that are just a mess of jumbled noise with the old aerial, you'll get reception that parallels local in sweetness and clarity. Send coupon at once for scientific explanation of SUBANTENNA and for particulars of GUARANTEE and FREE TRIAL OFFER. Send COUPON NOW!

CLIP AND MAIL AT ONCE!

Cloverleaf Mfg. Co., 2714-M Canal St., Chicago
Tell me all about SUBANTENNA and your FREE TRIAL OFFER.

Name.....

Address.....

Cloverleaf Mfg. Co.
2714-M Canal St., Chicago, Ill.



Just natural —



*Just the natural taste
of fine tobaccos put
together right - there's
nothing can beat that!*